

Risoluzione dei problemi relativi ai dispositivi non Cisco visualizzati in PCA 11

Sommario

[Introduzione](#)

[Prerequisiti](#)

[Requisiti](#)

[Componenti usati](#)

[Problema](#)

[Soluzione](#)

[Problema](#)

[Soluzione](#)

Introduzione

Questo documento descrive come risolvere i problemi di Prime Collaboration Assurance (PCA) di inventario durante l'aggiunta di Cisco Unified Communications Manager (CUCM) e Prime License Manager (PLM). L'inventario mostra il dispositivo come non Cisco mentre è un'applicazione CUCM o PLM.

Contributo di Michal Myszor e Andrea Cingolani, tecnici Cisco TAC.

Prerequisiti

Requisiti

Nessun requisito specifico previsto per questo documento.

Componenti usati

Questo documento si applica a:

- Modalità provider di servizi gestiti PCA 11.X (MSP)
- Hosted Collaboration Mediation Fulfillment (HCM-F) 10.6.X
- Cisco Unified Communications Manager (CUCM) 11.5.X
- Standalone PLM 11.5.X

Le informazioni discusse in questo documento fanno riferimento a dispositivi usati in uno specifico ambiente di emulazione. Su tutti i dispositivi menzionati nel documento la configurazione è stata ripristinata ai valori predefiniti. Se la rete è operativa, valutare attentamente eventuali conseguenze derivanti dall'uso dei comandi.

Problema


Il dispositivo CUCM viene visualizzato come Non Cisco nella pagina di inventario o nella visualizzazione del dispositivo quando l'autorità di certificazione non è in grado di determinare il tipo di dispositivo in base alle query SNMP.

Inventario PCA:

cucm-alfa.alfa.com NonCisco RTAC ciscoUCVir... 10.48.55.29 10.48.55.29

Lo stesso viene presentato nella visualizzazione di Device 360:

Device 360° View



 **CUCM-ALFA**

10.48.55.29 / 00:50:56:9e:01:9e

Not Configured / NAT Disabled
94 days, 8 hours, 52 minutes



NONCISCO

[View Details](#)

Private IP Address **10.48.55.29**
Model **ciscoUCVirtualMachine**
Customer **RTAC**

Il log di AccessLevelDiscovery mostra:

```
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|work() : Starting Access
Level Discovery for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|41| Later Error Index for
device 10.48.55.29 is 1022 Old Message
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|94| Error Index for device
10.48.55.29 is 1022 New Message Discovery in progress.
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Started
for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
Matching credentials for 10.48.55.29
12-Sep-2017|15:25:43.003|ERROR|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|getFinalDeviceCredenti
alsList|709| Ignoring the DEFAULT profile as the snmp community string is not provided.
12-Sep-2017|15:25:43.005|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|getFinalDeviceCredenti
alsList|760| probeAccessLevel() : CmDevice Credentials List size : 0
12-Sep-2017|15:25:43.006|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|231|
Before classificationOfDeviceType, device credential id is 6429244
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
isDeviceTypeReDiscoveryEnabled flag has set to true or mode is MSP - 10.48.55.29 device type
is re-initilize to Unknown.
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : *****
CmDevice Type Classification - STARTS [ 10.48.55.29 ]*****
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
DeviceType is null/Other/Unknown for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Running
device type classification for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-
```

```
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|167|
getDeviceType() : For device 10.48.55.29 - Find the device Type
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|169|
getDeviceType() : For device 10.48.55.29; DC PROFILE NAME : 10.48.55.29
12-Sep-2017|15:25:43.007|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|217| DC Id: 6429244
12-Sep-2017|15:25:43.008|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|759| DeviceUtil.getSysOID:Before invoking PAL
for SysOID10.48.55.29
12-Sep-2017|15:25:43.077|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|766| DeviceUtil.getSysOID:After involking PAL:
sysOID =1.3.6.1.4.1.9.1.1348 Ip Address 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|240|
getDeviceType(): SysOID and SysDescr are fetched from device 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|241|
getDeviceType(): SysOID : 1.3.6.1.4.1.9.1.1348
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|242|
getDeviceType(): SysDescr : Linux release:2.6.32-431.20.3.el6.x86_64 machine:x86_64
12-Sep-2017|15:25:43.108|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|268| Device type of
profile is null
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSwitchType|getDeviceType|17| Checking is Switch
Type check for 10.48.55.29
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceRouterType|getDeviceType|17| Checking is Router
Type for 10.48.55.29
(...)
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|19|
DeviceUC500SeriesType:getDeviceType
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|26| DeviceGroup-
Call Control : DeviceName - Cisco CallManager
12-Sep-2017|15:25:44.637|ERROR|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceESXType|checkifESX|65| Exception in
checkIfESXnull
12-Sep-2017|15:25:44.692|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceCIMType|checkIfCIM|61| checkIfCIM ()
12-Sep-2017|15:25:45.390|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|42| From
DeviceSOFTSWITCHType
12-Sep-2017|15:25:45.390|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|checkIfSoftSwitch|60|
checkIfSoftSwitch ()
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|51| Device
10.48.55.29 is not a SOFTSWITCH
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceNonCiscoType|getDeviceType|32|
DeviceNonCiscoType: device Type is Non Cisco
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|175|
probeAccessLevel() : Found DeviceType NONCISCO for device 10.48.55.29
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|classificationOfDevice
Type|339| probeAccessLevel() : ***** CmDevice Type Classification - ENDS *****
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|244|
After classificationOfDeviceType, device credential id is 6429244
```

```
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|251|After resetting to original id, device credential id is 6429244
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : DC
10.48.55.29 with type null NOT matched CmDevice 10.48.55.29 with type NONCISCO
```

Soluzione

Verificare se il servizio SNMP viene eseguito su un'applicazione UC.

Nota: Cisco CUCM dispone di due servizi SNMP.

```
SNMP Master Agent[STARTED]
(...)
Cisco CallManager SNMP Service[STOPPED] Service Not Activated
```

Il servizio SNMP Cisco CallManager è responsabile della risposta alle query MIB SNMP specifiche di Cisco

L'inattività del servizio SNMP è già stata risolta in PCA 11.6. Si consiglia di disattivare il servizio SNMP:

```
11-Sep-2017|12:56:52.752|DEBUG|AccessLevelDiscovery|pool-6-thread-10|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|109| Error Index for device 10.48.50.59 is 1003 New Message SNMP timed out. Probable reasons could be: 1. SNMP service not enabled in the device. 2. SNMP credentials do not match. 3. Firewall settings blocking the port. Refer the Install and Upgrade guide for the exact ports to be unblocked.
```

Problema

Il dispositivo PLM viene visualizzato come Non Cisco nella pagina di inventario.

Soluzione

1. Selezionare il **server PLM** nella pagina Inventario e sospendere il dispositivo.
2. Eliminare il dispositivo dall'inventario PCA.
3. Eliminare qualsiasi stringa della community aggiunta in PLM tramite l'interfaccia della riga di comando (CLI):
utilizza snmp config 1/2c community-string delete

4. Aggiungere nuovamente il dispositivo nell'APC utilizzando la CLI (Platform Platform) del sistema operativo nel campo delle credenziali del dispositivo PCA HTTP(s) come mostrato nell'immagine.

Add Device



*IP Address

Note: For multiple IP Addresses, use a unique delimiter: comma, pipe or blank space.
Example: 10.39.65.1|10.33.68.99

▶ General SNMP Options

▼ CLI

CLI Login Username

CLI Login Password

Re-enter CLI Login Password

CLI Enable Password

Re-enter CLI Enable Password

▼ HTTP(s)

HTTP(s) Username

HTTP(s) Password

Re-enter HTTP(s) Password

*Note: Please enter the domain name along with username for IICCF devices (ex

Discover

Close