

Probleemoplossing en controle van WAN-module in CGR 1000

Inhoud

[Inleiding](#)

[Voorwaarden](#)

[Vereisten](#)

[Gebruikte componenten](#)

[Methodologie voor probleemoplossing](#)

[Verifiëren scripts](#)

[Vaak voorkomende kwestie tijdens het uitvoeren van scripts](#)

[Synbelastingfout](#)

[IPSLA-laag \(Internet Protocol Service Level Agreement\)](#)

[Gerelateerde informatie](#)

Inleiding

Dit document beschrijft hoe u problemen kunt oplossen en het Taal van de Opdracht van de Gereedschap (TCL) script genaamd tm_wanmon.tcl die in de IOS beelden is ingesloten voor Cisco IOS 1000 Series Connected Grid Router (CGR). Dit script, indien ingeschakeld, fungeert als WAN-bewakingssoftware (Wide Area Network) voor WAN-interfaces en voert steeds intringender handelingen uit om te herstellen van een WAN-link of een tunnelstoring.

Wanneer WANMON op de router wordt geactiveerd, wordt het script afgeleid in het sys:/eem_policy/folder en het script kan worden bekeken met het gebruik van deze opdracht; Router#more.sys:eem_policy/tm_wanmon.tcl.

Voorwaarden

Vereisten

Cisco raadt u aan het TCL-script in te schakelen zoals uitgelegd in deze documentatie;

http://www.cisco.com/c/en/us/td/docs/routers/connectedgrid/cgr1000/ios/software/15_4_1_cg/WAN_Mon.html.

Minimale software: Cisco IOS-softwarerelease 15.4(1)CG

Gebruikte componenten

De informatie in dit document is gebaseerd op CGR1120/CGR1240.

De informatie in dit document is gebaseerd op de apparaten in een specifieke laboratoriumomgeving. Alle apparaten die in dit document worden beschreven, hadden een opgeschoonde (standaard)configuratie. Als uw netwerk live is, moet u de potentiële impact van elke opdracht begrijpen.

Methodologie voor probleemoplossing

Wanneer WANMON wordt gevormd en op een CGR loopt, kan het zuiveren voor het script worden geactiveerd wanneer u deze configuratie aan de configuratie van het apparaat toevoegt:

```
Router(config)#event manager environment wanmon_debug all
```

Verifiëren scripts

```
Router(config)#event manager policy tm_wanmon.tcl authorization bypass
Router(config)#event manager environment wanmon_if_list1 {GigabitEthernet2/1 {recovery {5 25}
{90 180} {600 100}} }
Router(config)#event manager environment wanmon_debug all

*Aug 8 21:24:14.555: %HA_EM-6-LOG: tm_wanmon.tcl: Command: enable      <----- WANMON is orienting
itself to privileged exec mode by sending the 'enable' command to IOS
*Aug 8 21:24:14.775: %HA_EM-6-LOG: tm_wanmon.tcl: Output:
*Aug 8 21:24:14.775: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#      <----- Output from IOS tells
WANMON that it is now at the privileged exec prompt
*Aug 8 21:24:14.789: %HA_EM-6-LOG: tm_wanmon.tcl: context_retrieve succeeded      <----- The
router was able to successfully retrieve WANMON polling data
*Aug 8 21:24:14.789: %HA_EM-6-LOG: tm_wanmon.tcl: last_run: 1249760980      <----- The event
identifier for the last time WANMON polled its enabled interfaces
*Aug 8 21:24:14.789: %HA_EM-6-LOG: tm_wanmon.tcl: exec_count: 5      <----- The number of times
WANMON has polled since it last started. The last operation (1249760980) was the 5th process in
a row
*Aug 8 21:24:14.791: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1,link_events: {1 {}
1249760380 {Sat Aug 08 19:39:40 UTC 2009}}      <----- Enabled interfaces and time stamp of first
execution
*Aug 8 21:24:14.791: %HA_EM-6-LOG: tm_wanmon.tcl: last_polled_run: 1249760980      <-----
last_run and last_polled_run are equal in this case but if recovery levels are active the last
polled run may be earlier than the last_run
*Aug 8 21:24:14.797: %HA_EM-6-LOG: tm_wanmon.tcl: Starting: Received event polltimer      <-----
A new polling process has started with a new polltimer
*Aug 8 21:24:14.799: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_name Value: {}
*Aug 8 21:24:14.799: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_sec Value: 1249766654      <-----
-- The new event identifier
*Aug 8 21:24:14.799: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_type Value: 21
*Aug 8 21:24:14.801: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain Value: 600.000      <-----
The polltimer has been reset and there are 600 seconds until the next polling event
*Aug 8 21:24:14.801: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_severity Value: severity-normal
<----- This message indicates that this is a regular poll and not caused by one of the alert
levels being triggered from a previous polling event
*Aug 8 21:24:14.803: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_id Value: 3
*Aug 8 21:24:14.803: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_type_string Value: timer watchdog
*Aug 8 21:24:14.803: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time_sec Value: 3458755454
*Aug 8 21:24:14.805: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_type Value: watchdog
*Aug 8 21:24:14.805: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain_msec Value: 0
*Aug 8 21:24:14.805: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain_sec Value: 600
*Aug 8 21:24:14.805: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time_msec Value: 46
*Aug 8 21:24:14.807: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_time Value: 1249766654.045
*Aug 8 21:24:14.807: %HA_EM-6-LOG: tm_wanmon.tcl: Name: job_id Value: 6
*Aug 8 21:24:14.807: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_msec Value: 45
*Aug 8 21:24:14.807: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time Value: 3458755454.046
*Aug 8 21:24:14.807: %HA_EM-6-LOG: tm_wanmon.tcl: Exec count: 6      <----- The exec_count has
incremented by 1 from the previous execution
*Aug 8 21:24:14.811: %HA_EM-6-LOG: tm_wanmon.tcl: All interface vars wanmon_if_list1      <-----
If multiple lists are present, they will all be included here separated by spaces (i.e.
wanmon_if_list1 wanmon_if_list2 wanmon_if_list3)
```

```

*Aug 8 21:24:14.813: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_interfaces: {GigabitEthernet2/1
{recovery {5 25} {90 180} {600 100}} }      <----- The bracketed configurations from all WANMON
statements will be included in this line
*Aug 8 21:24:14.821: %HA_EM-6-LOG: tm_wanmon.tcl: last_polled_run: 1249760980      <----- Event
identifier for exec_count 5
*Aug 8 21:24:14.821: %HA_EM-6-LOG: tm_wanmon.tcl: current_polled_run: 1249766654      <-----
Event identifier for exec_count 6 which is the current process
*Aug 8 21:24:14.823: %HA_EM-6-LOG: tm_wanmon.tcl: drift: 5074
*Aug 8 21:24:14.823: %HA_EM-6-LOG: tm_wanmon.tcl: abs_drift: 5074
*Aug 8 21:24:14.823: %HA_EM-6-LOG: tm_wanmon.tcl: drift_thres: 3600
*Aug 8 21:24:14.825: %HA_EM-4-LOG: tm_wanmon.tcl: Clock drift (5074 s), threshold exceeded,
resetting context
*Aug 8 21:24:14.827: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all interface name and states      <--
--- This output signifies that WANMON is now polling layer 1 and 2 status for all enabled
interfaces
*Aug 8 21:24:14.833: %HA_EM-6-LOG: tm_wanmon.tcl: Command: show interface GigabitEthernet2/1 |
include line protocol      <----- Command send to IOS
*Aug 8 21:24:15.047: %HA_EM-6-LOG: tm_wanmon.tcl: Output: GigabitEthernet2/1 is up, line
protocol is up      <----- Input received from IOS
*Aug 8 21:24:15.047: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 8 21:24:15.057: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1 admin_state:1,
line_state:1      <----- WANMON assigns a binary (0 or 1) value to admin_state and line_state tcl
variables
*Aug 8 21:24:15.061: %HA_EM-6-LOG: tm_wanmon.tcl: Processing all interface config
*Aug 8 21:24:15.087: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all IP addresses
*Aug 8 21:24:15.099: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all IPSLA      <----- As IP SLA is not
attached to this configuration, there is no IP SLA output
*Aug 8 21:24:15.105: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all traffic stats
*Aug 8 21:24:15.109: %HA_EM-6-LOG: tm_wanmon.tcl: Processing all interface statistics
*Aug 8 21:24:15.113: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/1:
*Aug 8 21:24:15.119: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1 lineproto=1 => 1      <-----
The script's logic is that if line_state is 1 or greater then consider the status as "up"
*Aug 8 21:24:15.131: %HA_EM-1-LOG: tm_wanmon.tcl: Detected GigabitEthernet2/1 link is up      <--
--- Up status confirmed
*Aug 8 21:24:15.137: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,admin_state) = 1
*Aug 8 21:24:15.137: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,causes) =
*Aug 8 21:24:15.137: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,checkip) = 0
*Aug 8 21:24:15.139: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,checklist) =
lineproto
*Aug 8 21:24:15.139: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,exists) = 1
*Aug 8 21:24:15.139: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,fullname) =
GigabitEthernet2/1      <----- This section is where the recovery level timers are shown as well
as whether or not the interface state is a 0 or 1.
*Aug 8 21:24:15.139: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,lineproto,state)
= 1
*Aug 8 21:24:15.139: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,recovery,0,max)
= 25
*Aug 8 21:24:15.141: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,0,thresh) = 5
*Aug 8 21:24:15.141: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,recovery,1,max)
= 180
*Aug 8 21:24:15.141: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,1,thresh) = 90
*Aug 8 21:24:15.143: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,recovery,2,max)
= 100
*Aug 8 21:24:15.143: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,2,thresh) = 600
*Aug 8 21:24:15.145: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,state) = 1
<----- Once the script has completed, the 'state' value is set to 1 and no recovery actions are
taken
*Aug 8 21:24:15.145: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(current_polled_run) = 1249766654
<----- This is the event identifier which correlates with exec_count 6
*Aug 8 21:24:15.145: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(if_list) = GigabitEthernet2/1
*Aug 8 21:24:15.147: %HA_EM-6-LOG: tm_wanmon.tcl:

```

```

wanmon_saved_ctx(GigabitEthernet2/1,link_events) = {1 {} 1249766655 {Sat Aug 08 21:24:15 UTC
2009}}      <----- exec_count 6 is finished and its historical polling data has been saved
*Aug 8 21:24:15.147: %HA_EM-6-LOG: tm_wanmon.tcl: Finished      <----- Regular polling has
finished
*Aug 8 21:24:15.159: %HA_EM-6-LOG: tm_wanmon.tcl: context_save succeeded      <----- The process
has been statefully ended without error

```

Vaak voorkomende kwestie tijdens het uitvoeren van scripts

Synbelastingfout

Een situatie kan zich voordoen waar je denkt dat WANMON werkt wanneer het wordt geconfigureerd, maar het heeft geen effect. In een omgeving waar het WANMON - script niet correct werkte, werd deze debug-uitvoer bijvoorbeeld waargenomen:

```

*Aug 8 21:44:14.487: %HA_EM-6-LOG: tm_wanmon.tcl: Command: enable
*Aug 8 21:44:14.601: %HA_EM-6-LOG: tm_wanmon.tcl: Output:
*Aug 8 21:44:14.601: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 8 21:44:14.617: %HA_EM-6-LOG: tm_wanmon.tcl: context_retrieve succeeded
*Aug 8 21:44:14.617: %HA_EM-6-LOG: tm_wanmon.tcl: last_run: 1249767255
*Aug 8 21:44:14.617: %HA_EM-6-LOG: tm_wanmon.tcl: exec_count: 1
*Aug 8 21:44:14.619: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1,link_events: {1 {}
1249766655 {Sat Aug 08 21:24:15 UTC 2009}}
*Aug 8 21:44:14.619: %HA_EM-6-LOG: tm_wanmon.tcl: last_polled_run: 1249767255
*Aug 8 21:44:14.627: %HA_EM-6-LOG: tm_wanmon.tcl: Starting: Received event polltimer
*Aug 8 21:44:14.627: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_name Value: {}
*Aug 8 21:44:14.629: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_sec Value: 1249767854
*Aug 8 21:44:14.629: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_type Value: 21
*Aug 8 21:44:14.629: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain Value: 600.000
*Aug 8 21:44:14.629: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_severity Value: severity-normal
*Aug 8 21:44:14.629: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_id Value: 3
*Aug 8 21:44:14.631: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_type_string Value: timer watchdog
*Aug 8 21:44:14.631: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time_sec Value: 3458756654
*Aug 8 21:44:14.631: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_type Value: watchdog
*Aug 8 21:44:14.633: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain_msec Value: 0
*Aug 8 21:44:14.633: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain_sec Value: 600
*Aug 8 21:44:14.633: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time_msec Value: 45
*Aug 8 21:44:14.635: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_time Value: 1249767854.045
*Aug 8 21:44:14.635: %HA_EM-6-LOG: tm_wanmon.tcl: Name: job_id Value: 8
*Aug 8 21:44:14.635: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_msec Value: 45
*Aug 8 21:44:14.635: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time Value: 3458756654.045
*Aug 8 21:44:14.635: %HA_EM-6-LOG: tm_wanmon.tcl: Exec count: 2
*Aug 8 21:44:14.639: %HA_EM-6-LOG: tm_wanmon.tcl: All interface vars wanmon_if_list1
*Aug 8 21:44:14.641: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_interfaces: {gig 2/1 {recovery {5 25}
{90 180} {400 100}} }
*Aug 8 21:44:14.649: %HA_EM-6-LOG: tm_wanmon.tcl: last_polled_run: 1249767255
*Aug 8 21:44:14.649: %HA_EM-6-LOG: tm_wanmon.tcl: current_polled_run: 1249767854
*Aug 8 21:44:14.651: %HA_EM-6-LOG: tm_wanmon.tcl: drift: -1
*Aug 8 21:44:14.651: %HA_EM-6-LOG: tm_wanmon.tcl: abs_drift: 1
*Aug 8 21:44:14.651: %HA_EM-6-LOG: tm_wanmon.tcl: drift_thres: 3600
*Aug 8 21:44:14.655: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all interface name and states
*Aug 8 21:44:14.659: %HA_EM-6-LOG: tm_wanmon.tcl: Command: show interface gig | include line
protocol      <----- Here you can see the command which has been sent to IOS which indicates that
'show interface gig' instead of 'show interface gig1/2' has been sent
*Aug 8 21:44:14.889: %HA_EM-6-LOG: tm_wanmon.tcl: Output:
*Aug 8 21:44:14.889: %HA_EM-6-LOG: tm_wanmon.tcl: show interface gig | include line protocol
*Aug 8 21:44:14.889: %HA_EM-6-LOG: tm_wanmon.tcl: ^
*Aug 8 21:44:14.889: %HA_EM-6-LOG: tm_wanmon.tcl: % Invalid input detected at '^' marker.
*Aug 8 21:44:14.889: %HA_EM-6-LOG: tm_wanmon.tcl:
*Aug 8 21:44:14.889: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 8 21:44:14.895: %HA_EM-1-LOG: tm_wanmon.tcl: Configuration error: Interface gig does not

```

```

exist. Please check configuration.      ----- If there is a syntax error in the WANMON
statements, you will see "Configuration error" in the output following the raw session output
*Aug 8 21:44:14.899: %HA_EM-6-LOG: tm_wanmon.tcl: Processing all interface config
*Aug 8 21:44:14.915: %HA_EM-6-LOG: tm_wanmon.tcl: context_save succeeded

```

In overeenstemming met deze uitvoer, wordt het script niet uitgevoerd vanwege het feit dat er een ruimte is tussen de naam van de interface en de nummers. De opdracht die deze fout veroorzaakte was:

```
event manager environment wanmon_if_list1 {gig 2/1 {recovery {5 25} {90 180} {400 100}} }
```

De juiste configuratie moet zijn:

```
event manager environment wanmon_if_list1 {gig2/1 {recovery {5 25} {90 180} {400 100}} }
```

IPSLA-laag (Internet Protocol Service Level Agreement)

Als WANMON meerdere interfaces met IPSLA instelt.

IPSLA operaties, het kan lastig zijn om onmiddellijk te bepalen waar de mislukking is. Dit debug uitvoer toont wat gebeurt wanneer twee interfaces door WANMON met IP SLA op elke interface worden gecontroleerd:

```

*Aug 9 19:55:36.433: %HA_EM-6-LOG: tm_wanmon.tcl: Command: enable
*Aug 9 19:55:36.547: %HA_EM-6-LOG: tm_wanmon.tcl: Output:
*Aug 9 19:55:36.547: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 9 19:55:36.565: %HA_EM-6-LOG: tm_wanmon.tcl: context_retrieve succeeded
*Aug 9 19:55:36.565: %HA_EM-6-LOG: tm_wanmon.tcl: last_run: 1249847563
*Aug 9 19:55:36.565: %HA_EM-6-LOG: tm_wanmon.tcl: exec_count: 5
*Aug 9 19:55:36.565: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1,link_events: {0 ipsla
1249847563 {Sun Aug 09 19:52:43 UTC 2009}} {1 {} 1249847478 {Sun Aug 09 19:51:18 UTC 2009}}
*Aug 9 19:55:36.567: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/2,link_events: {0 lineproto
1249847478 {Sun Aug 09 19:51:18 UTC 2009}}
*Aug 9 19:55:36.567: %HA_EM-6-LOG: tm_wanmon.tcl: last_polled_run: 1249847136
*Aug 9 19:55:36.575: %HA_EM-6-LOG: tm_wanmon.tcl: Starting: Received event polltimer
*Aug 9 19:55:36.577: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_name Value: {}
*Aug 9 19:55:36.577: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_sec Value: 1249847735
*Aug 9 19:55:36.577: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_type Value: 21
*Aug 9 19:55:36.577: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain Value: 600.000
*Aug 9 19:55:36.579: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_severity Value: severity-normal
*Aug 9 19:55:36.579: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_id Value: 1
*Aug 9 19:55:36.579: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_type_string Value: timer watchdog
*Aug 9 19:55:36.581: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time_sec Value: 3458836535
*Aug 9 19:55:36.581: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_type Value: watchdog
*Aug 9 19:55:36.581: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain_msec Value: 0
*Aug 9 19:55:36.583: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_remain_sec Value: 600
*Aug 9 19:55:36.583: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time_msec Value: 908
*Aug 9 19:55:36.583: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub
*Aug 9 19:55:36.585: %HA_EM-6-LOG: tm_wanmon.tcl: Name: job_id Value: 6
*Aug 9 19:55:36.585: %HA_EM-6-LOG: tm_wanmon.tcl: Name: event_pub_msec Value: 907
*Aug 9 19:55:36.585: %HA_EM-6-LOG: tm_wanmon.tcl: Name: timer_time Value: 3458836535.908
*Aug 9 19:55:36.585: %HA_EM-6-LOG: tm_wanmon.tcl: Exec count: 6      ----- The new polling
interval has begun
*Aug 9 19:55:36.591: %HA_EM-6-LOG: tm_wanmon.tcl: All interface vars wanmon_if_list1
wanmon_if_list3      ----- Both lists are included in this output
*Aug 9 19:55:36.593: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_interfaces: {GigabitEthernet2/1 {ipsla
1} } {GigabitEthernet2/2 {ipsla 2} }      ----- Both bracketed configurations are included in
this output
*Aug 9 19:55:36.601: %HA_EM-6-LOG: tm_wanmon.tcl: last_polled_run: 1249847136

```

```

*Aug 9 19:55:36.603: %HA_EM-6-LOG: tm_wanmon.tcl: current_polled_run: 1249847736
*Aug 9 19:55:36.603: %HA_EM-6-LOG: tm_wanmon.tcl: drift: 0
*Aug 9 19:55:36.603: %HA_EM-6-LOG: tm_wanmon.tcl: abs_drift: 0
*Aug 9 19:55:36.603: %HA_EM-6-LOG: tm_wanmon.tcl: drift_thres: 3600
*Aug 9 19:55:36.605: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all interface name and states      <--
--- WANMON sends show commands to IOS for both enabled interfaces
*Aug 9 19:55:36.613: %HA_EM-6-LOG: tm_wanmon.tcl: Command: show interface GigabitEthernet2/1 |
include line protocol
*Aug 9 19:55:36.825: %HA_EM-6-LOG: tm_wanmon.tcl: Output: GigabitEthernet2/1 is up, line
protocol is up
*Aug 9 19:55:36.825: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 9 19:55:36.835: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1 admin_state:1,
line_state:1      <----- GigabitEthernet2/1 is up/up so it sets admin_state and line_state to 1
*Aug 9 19:55:36.835: %HA_EM-6-LOG: tm_wanmon.tcl: Command: show interface GigabitEthernet2/2 |
include line protocol
*Aug 9 19:55:37.047: %HA_EM-6-LOG: tm_wanmon.tcl: Output: GigabitEthernet2/2 is down, line
protocol is down
*Aug 9 19:55:37.047: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 9 19:55:37.055: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/2 admin_state:1,
line_state:0      <----- GigabitEthernet2/2 is down/down but admin_state is still set to 1
because it is administratively enabled. Since layer 2 is down, line_state is set to 0
*Aug 9 19:55:37.059: %HA_EM-6-LOG: tm_wanmon.tcl: Processing all interface config
*Aug 9 19:55:37.083: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all IP addresses
*Aug 9 19:55:37.095: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all IPSLA      <----- Due to the fact
that IP SLA operations are configured for both interfaces, WANMON now sends show commands to
check IP SLA status
*Aug 9 19:55:37.097: %HA_EM-6-LOG: tm_wanmon.tcl: Querying IP SLA for GigabitEthernet2/1
*Aug 9 19:55:37.099: %HA_EM-6-LOG: tm_wanmon.tcl: Command: show ip sla statistics 1 | include
Latest operation return code:      <----- IP SLA 1 is queried
*Aug 9 19:55:37.309: %HA_EM-6-LOG: tm_wanmon.tcl: Output: Latest operation return code: Timeout
      <----- The state is down because the last return code for the icmp-echo IP SLA process is
Timeout
*Aug 9 19:55:37.309: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 9 19:55:37.311: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1 ipsla: 0      <----- The
ipsla value for Gig2/1 is now set to 0 because the state is down
*Aug 9 19:55:37.313: %HA_EM-6-LOG: tm_wanmon.tcl: Querying IP SLA for GigabitEthernet2/2
*Aug 9 19:55:37.313: %HA_EM-6-LOG: tm_wanmon.tcl: Command: show ip sla statistics 2 | include
Latest operation return code:
*Aug 9 19:55:37.527: %HA_EM-6-LOG: tm_wanmon.tcl: Output: Latest operation return code: OK
      <----- IP SLA operation 2 is up, the remote address is reachable
*Aug 9 19:55:37.527: %HA_EM-6-LOG: tm_wanmon.tcl: CGR1000#
*Aug 9 19:55:37.529: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/2 ipsla: 1      <----- The
ipsla value for Gig2/2 is now set to 1 because the state is up
*Aug 9 19:55:37.535: %HA_EM-6-LOG: tm_wanmon.tcl: Querying all traffic stats
*Aug 9 19:55:37.539: %HA_EM-6-LOG: tm_wanmon.tcl: Processing all interface statistics
*Aug 9 19:55:37.543: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/1:
*Aug 9 19:55:37.543: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/2:
*Aug 9 19:55:37.551: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/1 lineproto=1 ipsla=0 => 0
      <----- WANMON now checks for 2 dependencies in order to determine state. For interface Gig2/1
the IP SLA state is down even though the interface is up/up.
*Aug 9 19:55:37.555: %HA_EM-6-LOG: tm_wanmon.tcl: GigabitEthernet2/2 lineproto=0 ipsla=1 => 0
      <----- For Gig2/2, the IP SLA state is up but the interface is down
*Aug 9 19:55:37.589: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/1, Level 0 recovery
within 10 min
*Aug 9 19:55:37.593: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/1, Level 1 recovery
within 60 min
*Aug 9 19:55:37.595: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/1, Level 2 recovery
within 480 min
*Aug 9 19:55:37.597: %HA_EM-2-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/1: Level 0 recovery
in 10 min
*Aug 9 19:55:37.603: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/2, Level 0 recovery
within 10 min
*Aug 9 19:55:37.605: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/2, Level 1 recovery
within 60 min

```

```

*Aug 9 19:55:37.609: %HA_EM-6-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/2, Level 2 recovery
within 480 min
*Aug 9 19:55:37.609: %HA_EM-2-LOG: tm_wanmon.tcl: Interface GigabitEthernet2/2: Level 0 recovery
in 10 min
*Aug 9 19:55:37.613: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,admin_state) = 1
*Aug 9 19:55:37.615: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,causes) = ipsla
*Aug 9 19:55:37.615: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,check_ipsla) = 1
*Aug 9 19:55:37.615: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,checkip) = 0
*Aug 9 19:55:37.615: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,checklist) =
lineproto ipsla
*Aug 9 19:55:37.617: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,exists) = 1
*Aug 9 19:55:37.617: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,fullname) =
GigabitEthernet2/1
*Aug 9 19:55:37.617: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,ipsla,state) = 0
*Aug 9 19:55:37.619: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,lineproto,state) =
1
*Aug 9 19:55:37.619: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,recovery,0,max) =
10
*Aug 9 19:55:37.619: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,0,thresh) = 10
*Aug 9 19:55:37.621: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,recovery,1,max) =
60
*Aug 9 19:55:37.621: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,1,thresh) = 60
*Aug 9 19:55:37.621: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,recovery,2,max) =
60
*Aug 9 19:55:37.621: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,2,thresh) = 480
*Aug 9 19:55:37.623: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,next,level) = 0
*Aug 9 19:55:37.623: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,next,repeat) = 0
*Aug 9 19:55:37.623: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/1,recovery,next,time_left) = 600
*Aug 9 19:55:37.625: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,slaid) = 1
----- This output gives you the SLA ID (1) of the process bound to the Gig2/1 interface
*Aug 9 19:55:37.625: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/1,state) = 0
----- The state has been marked 0 or down due to the fact that check_ipsla value is 0 even
though the interface is up and line_state is 1
*Aug 9 19:55:37.627: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,admin_state) = 1
*Aug 9 19:55:37.627: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,causes) =
lineproto
*Aug 9 19:55:37.627: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,check_ipsla) = 1
*Aug 9 19:55:37.629: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,checkip) = 0
*Aug 9 19:55:37.629: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,checklist) =
lineproto ipsla
*Aug 9 19:55:37.629: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,exists) = 1
*Aug 9 19:55:37.631: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,fullname) =
GigabitEthernet2/2
*Aug 9 19:55:37.631: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,ipsla,state) = 1
*Aug 9 19:55:37.631: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,lineproto,state) =
0
*Aug 9 19:55:37.631: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,recovery,0,max) =
10
*Aug 9 19:55:37.633: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/2,recovery,0,thresh) = 10
*Aug 9 19:55:37.633: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,recovery,1,max) =
60
*Aug 9 19:55:37.635: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/2,recovery,1,thresh) = 60
*Aug 9 19:55:37.635: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,recovery,2,max) =
60
*Aug 9 19:55:37.635: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/2,recovery,2,thresh) = 480

```

```

*Aug 9 19:55:37.637: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/2,recovery,next,level) = 0
*Aug 9 19:55:37.637: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/2,recovery,next,repeat) = 0
*Aug 9 19:55:37.637: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_ctx(GigabitEthernet2/2,recovery,next,time_left) = 600
*Aug 9 19:55:37.639: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,slaid) = 2
*Aug 9 19:55:37.639: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(GigabitEthernet2/2,state) = 0
<----- Gig2/2 has been marked 0 or down due to the fact that the line_state is 0, despite the
fact that the IP SLA operation is still UP and the check_ipsla value is 1
*Aug 9 19:55:37.639: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(current_polled_run) = 1249847736
*Aug 9 19:55:37.639: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_ctx(if_list) = GigabitEthernet2/1
GigabitEthernet2/2
*Aug 9 19:55:37.641: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_saved_ctx(GigabitEthernet2/1,link_events) = {0 ipsla 1249847563 {Sun Aug 09 19:52:43 UTC
2009}} {1 {} 1249847478 {Sun Aug 09 19:51:18 UTC 2009}}
*Aug 9 19:55:37.641: %HA_EM-6-LOG: tm_wanmon.tcl:
wanmon_saved_ctx(GigabitEthernet2/2,link_events) = {0 lineproto 1249847478 {Sun Aug 09 19:51:18
UTC 2009}}
*Aug 9 19:55:37.641: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_saved_ctx(exec_count) = 6
*Aug 9 19:55:37.641: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_saved_ctx(last_polled_run) = 1249847136
*Aug 9 19:55:37.643: %HA_EM-6-LOG: tm_wanmon.tcl: wanmon_saved_ctx(last_run) = 1249847563
*Aug 9 19:55:37.643: %HA_EM-6-LOG: tm_wanmon.tcl: Finished
*Aug 9 19:55:37.661: %HA_EM-6-LOG: tm_wanmon.tcl: context_save succeeded

```

Gerelateerde informatie

- http://www.cisco.com/c/en/us/td/docs/routers/connectedgrid/cgr1000/ios/software/15_4_1_cg/WANMon.html
- http://www.cisco.com/c/en/us/td/docs/routers/connectedgrid/cgr1000/1_0/software/configuration/guide/unicast/Unicast_Book/I3_backhaul_cgr1000.html#wp998807
- [Technische ondersteuning en documentatie – Cisco Systems](#)