

Backup Bridging por ISDN

Índice

[Introdução](#)

[Pré-requisitos](#)

[Requisitos](#)

[Componentes Utilizados](#)

[Produtos Relacionados](#)

[Convenções](#)

[Configurar](#)

[Diagrama de Rede](#)

[Configurações](#)

[Verificar](#)

[Comandos show no ROUTER1 quando Serial0 estiver ativo](#)

[Comandos show no ROUTER1 quando Serial0 está desativado](#)

[Troubleshooting](#)

[Troubleshooting de Recursos](#)

[Comandos para Troubleshooting](#)

[Saída debug em ROUTER1 quando Serial0 cair e ISDN retornar](#)

[Saída de debug em ROUTER1 quando Serial0 é reativada e o ISDN descarta a chamada](#)

[Informações Relacionadas](#)

[Introdução](#)

Este documento explica e fornece um exemplo de como configurar o Backup Bridging com ISDN. Essa configuração usa o método de interface de backup para identificar que o enlace principal está inoperante. Para obter mais informações sobre do backup, veja [configurando e pesquisando defeitos o backup de chamada DDR](#).

Em ambientes de WAN construídos uma ponte sobre, a única solução de backup do Dial-on-Demand Routing (DDR) disponível é o uso do ISDN, como construir uma ponte sobre sobre o async não é apoiada.

Esteja ciente que construir uma ponte sobre em uma conexão ISDN tende a manter muito a conexão ativa por períodos longos, se não permanentemente. Se a companhia telefônica (telco) carrega para o ISDN baseado no tempo de conexão e no enlace serial que está seguido está para baixo por muito um muito tempo, este pode conduzir a uma conta muito grande.

Nota: Essa configuração refere-se a um site e a um canal B. Para mais de um canal B, você deve usar Perfis de discagem. (Refira os [Perfis de discagem configurando para construir uma ponte sobre usando a configuração ISDN](#).)

Para obter informações sobre da configuração de Bridging em um ambiente do NON-backup, veja

- o [Bridging através de ISDN](#).

Pré-requisitos

Requisitos

Antes de você tentar esta configuração, verifique se estes requisitos são atendidos:

- Tenha um conhecimento básico de ISDN.

Componentes Utilizados

As informações neste documento são baseadas nestas versões de software e hardware:

- Cisco 2500 Series Router com uma interface serial MACILENTO e uma interface BRI cada um.
- Software Release 12.2(7b) de Cisco IOS®.

Nota: Esta configuração pode ser usada com qualquer roteador que tiver um enlace WAN (serial) e uma porta BRI.

As informações neste documento foram criadas a partir de dispositivos em um ambiente de laboratório específico. Todos os dispositivos utilizados neste documento foram iniciados com uma configuração (padrão) inicial. Se a sua rede estiver ativa, certifique-se de que entende o impacto potencial de qualquer comando.

Produtos Relacionados

Esta configuração pode ser usada com qualquer par de roteadores que execute o Software Cisco IOS, tendo cada um pelo menos uma interface serial WAN e uma interface BRI.

Convenções

Para obter mais informações sobre convenções de documento, consulte as [Convenções de dicas técnicas Cisco](#).

Configurar

Nesta seção, você encontrará informações para configurar os recursos descritos neste documento.

Nota: Para localizar informações adicionais sobre os comandos usados neste documento, utilize a Ferramenta Command Lookup (somente clientes [registrados](#)).

Diagrama de Rede

Este documento utiliza a seguinte configuração de rede:

Configurações

Este documento utiliza as seguintes configurações:

- [Roteador1](#)
- [Roteador2](#)

Roteador1

```
!  
hostname ROUTER1  
!  
!  
username ROUTER2 password 0 same  
!--- This is required for PPP Challenge Handshake  
Authentication Protocol !--- (CHAP) authentication  
during dial backup. !! isdn switch-type basic-5ess !---  
The ISDN switch type for this circuit. !--- Obtain this  
information from the Telco. !--- This ISDN switch type  
is specific to the United States, !--- and could change  
based on the requirements of the country and Telco. !  
interface Ethernet0 ip address 172.16.55.33  
255.255.255.240 no ip directed-broadcast no ip mroute-  
cache bridge-group 1 !--- Assign this interface to  
bridge-group 1. !--- Frames are bridged only among  
interfaces in the same group. !--- Note that the BRI  
interface and serial interface are also !--- in this  
bridge-group 1. ! interface Serial0 description Serial  
link to ROUTER2 backup interface BRI0 !--- This defines  
the backup interface. !--- Cisco IOS Software tracks the  
Serial0 interface, and !--- uses BRI0 if Serial0 fails.  
ip address 172.16.54.1 255.255.255.0 no ip directed-  
broadcast no ip mroute-cache no fair-queue bridge-group  
1 !--- Enable bridging on Serial0 for normal operation.  
! interface BRI0 description ISDN to ROUTER2 ip address  
172.16.53.19 255.255.255.240 no ip directed-broadcast  
encapsulation ppp no ip mroute-cache dialer map bridge  
name ROUTER2 broadcast 5552000 !--- The broadcast  
keyword is required to initiate the ISDN call. !---  
Dialer map bridge to the remote router. The statement  
includes !--- the name of the remote router and the  
phone number to be dialed. !--- Note that this dialer  
map statement includes the keyword bridge, !--- and does  
not include the IP address of the peer, as required for  
!--- IP routing-based dialer maps. dialer-group 1 !---  
Defines the interesting traffic as configured in the  
dialer-list. isdn switch-type basic-5ess !--- Check with  
your Telco for the correct values. ppp authentication  
chap bridge-group 1 !--- Enable bridging on BRI0. !  
dialer-list 1 protocol bridge permit !--- Defines the  
interesting traffic. In this case, all bridged traffic.  
bridge 1 protocol ieee !--- Defines the type of Spanning  
Tree Protocol (STP) used for the !--- interface in  
bridge-group 1. Here, the IEEE STP is used. !--- The  
IEEE 802.1D STP is the preferred way to run the bridge.  
!
```

Roteador2

```
hostname router2  
!  
!  
username ROUTER1 password 0 same  
!--- Required for PPP CHAP Authentication during dial  
backup. ! isdn switch-type basic-5ess !--- Check with  
your Telco at the Router2 side for the correct values. !
```

```

interface Ethernet0 ip address 172.16.55.2
255.255.255.240 bridge-group 1 !--- Enable bridging on
Ethernet0. ! interface Serial0 description Serial link
to ROUTER1 !--- The backup interface bri0 command is not
required on this side, !--- because it is sufficient if
one side tracks the serial interface. ip address
172.16.54.2 255.255.255.0 no fair-queue bridge-group 1
!--- Enable bridging on Serial0 for normal operation.
interface BRI0 description ISDN to ROUTER1 ip address
172.16.53.17 255.255.255.240 encapsulation ppp no ip
mroute-cache dialer map bridge name ROUTER1 broadcast
5551000 !--- The broadcast keyword is required to
initiate the ISDN call. dialer-group 1 !--- Defines the
interesting traffic as configured in the dialer-list.
isdn switch-type basic-5ess !--- Check with your Telco
at the Router2 side for the correct values. ppp
authentication chap bridge-group 1 !--- Enable bridging
on BRI0. ! dialer-list 1 protocol bridge permit !---
Defines the interesting traffic. In this case, all
bridged traffic. bridge 1 protocol ieee !--- Defines the
type of STP used for the interface in !--- bridge-group
1. Here the IEEE STP is used. !--- The IEEE 802.1D STP
is the preferred way to run the bridge. !

```

Verificar

Esta seção fornece informações que você pode usar para confirmar se sua configuração funciona adequadamente.

A [Output Interpreter Tool \(somente clientes registrados\)](#) oferece suporte a determinados comandos show, o que permite exibir uma análise da saída do comando show.

- **status de ISDN da mostra** — indica o Layer 1 (L1), a camada 2 (L2), e mergulham 3 o estado (L3) das interfaces.
- **discador da mostra** — indica o estado do discador e o status individual dos canais ISDN.
- **ponte da mostra** — classes dos indicadores de entradas no Bridge Forwarding Database.
- **relação da mostra** — indica o estado das várias relações, tais como a série e as interfaces BRI.
- **medir-árvore da mostra** — indica a topologia de Spanning Tree conhecida ao roteador.

Comandos show no ROUTER1 quando Serial0 estiver ativo

```

ROUTER1# show isdn status Global ISDN Switchtype = basic-5ess ISDN BRI0 interface dsl 0,
interface ISDN Switchtype = basic-5ess Layer 1 Status: DEACTIVATED Layer 2 Status: Layer 2 NOT
Activated Layer 3 Status: 0 Active Layer 3 Call(s) Activated dsl 0 CCBs = 0 The Free Channel
Mask: 0x80000003 Number of L2 Discards = 36, L2D_Task Discards = 35 Total Allocated ISDN CCBS =
0 ROUTER1# show dialer BRI0 - dialer type = ISDN Dial String Successes Failures Last DNIS Last
status 5552000 29 977 00:45:08 successful 0 incoming call(s) have been screened. 0 incoming
call(s) rejected for callback. BRI0:1 - dialer type = ISDN Idle timer (120 secs), Fast idle
timer (20 secs) Wait for carrier (30 secs), Re-enable (15 secs) Dialer state is shutdown BRI0:2
- dialer type = ISDN Idle timer (120 secs), Fast idle timer (20 secs) Wait for carrier (30
secs), Re-enable (15 secs) Dialer state is shutdown ROUTER1# show bridge Total of 300 station
blocks, 298 free Codes: P - permanent, S - self Bridge Group 1: Address Action Interface Age RX
count TX count 0000.0c76.2882 forward Serial0 0 5 4 !--- Bridging traffic goes through Serial0.
00d0.58ad.ae13 forward Ethernet0 0 42 5

```

Comandos show no ROUTER1 quando Serial0 está desativado

```
ROUTER1# show isdn status Global ISDN Switchtype = basic-5ess ISDN BRI0 interface dsl 0,
interface ISDN Switchtype = basic-5ess Layer 1 Status: ACTIVE Layer 2 Status: TEI = 114, Ces =
1, SAPI = 0, State = MULTIPLE_FRAME_ESTABLISHED !--- ISDN L1 and L2 will be up (when Serial0
fails) !--- even if interesting traffic is not present. Layer 3 Status: 1 Active Layer 3 Call(s)
Activated dsl 0 CCBs = 1 CCB:callid=8484, sapi=0, ces=1, B-chan=1, calltype=DATA The Free
Channel Mask: 0x80000002 Total Allocated ISDN CCBs = 1 ROUTER1# show dialer BRI0 - dialer type =
ISDN Dial String Successes Failures Last DNIS Last status 5552000 30 977 00:00:16 successful 0
incoming call(s) have been screened. 0 incoming call(s) rejected for callback. BRI0:1 - dialer
type = ISDN Idle timer (120 secs), Fast idle timer (20 secs) Wait for carrier (30 secs), Re-
enable (15 secs) Dialer state is data link layer up Dial reason: bridge (0xFFFF) Time until
disconnect 106 secs Connected to 5552000 (ROUTER2) BRI0:2 - dialer type = ISDN Idle timer (120
secs), Fast idle timer (20 secs) Wait for carrier (30 secs), Re-enable (15 secs) Dialer state is
idle ROUTER1# show bridge Total of 300 station blocks, 298 free Codes: P - permanent, S - self
Bridge Group 1: Address Action Interface Age RX count TX count 0000.0c76.2882 forward BRI0 0 5 4
!--- Bridging traffic now goes through BRI0. 00d0.58ad.ae13 forward Ethernet0 0 5 5
```

Troubleshooting

Esta seção fornece informações que podem ser usadas para o troubleshooting da sua configuração.

Troubleshooting de Recursos

Use estes recursos como necessário:

- [Apoio de tecnologia ISDN](#)
- [Troubleshooting de Linhas Seriais](#)
- [Conexões back-to-back HDLC](#)

Comandos para Troubleshooting

A [Output Interpreter Tool](#) ([somente clientes registrados](#)) oferece suporte a determinados comandos show, o que permite exibir uma análise da saída do comando show.

Nota: [Antes de emitir comandos de depuração, consulte Informações Importantes sobre Comandos de Depuração.](#)

- **debug dialer** — fornece a informação sobre eventos da interface do discador.
- **debug isdn event** — os indicadores debugam as mensagens relativas à atividade de ISDN que ocorre no lado do usuário da interface.
- **debugar o q931 de ISDN** — fornece a informação sobre a configuração de chamada e desconexão das conexões de rede ISDN (L3) entre o roteador local (lado do usuário) e a rede.
- **debugar isdn q921** — indicadores debugam as mensagens relativas aos procedimentos de acesso da camada de link de dados (L2) que ocorrem no roteador no canal D (LAPD) de sua interface.
- **debugar a negociação ppp** — os indicadores debugam as mensagens relativas à negociação de opções de PPP e aos parâmetros do protocolo network control (NCP).
- **debugar a autenticação de PPP** — Os indicadores debugam as mensagens relativas à troca de pacotes da RACHADURA e do protocolo password authentication (PAP).

Saída debug em ROUTER1 quando Serial0 cair e ISDN retornar

```
ROUTER1# show debug Dial on demand: Dial on demand events debugging is on PPP: PPP
authentication debugging is on PPP protocol negotiation debugging is on ISDN: ISDN events
debugging is on ISDN Q921 packets debugging is on ISDN Q931 packets debugging is on ROUTER1# !--
- Interface serial0 goes down. ROUTER1# 00:56:53: %LINK-3-UPDOWN: Interface Serial0, changed
state to down *Mar 1 00:56:53.103: ISDN BR0 EVENT: isdn_sw_cstate: State = 0, Old State = 6
00:56:53: %LINK-3-UPDOWN: Interface BRI0:1, changed state to down *Mar 1 00:56:53.107: BR0:1
LCP: State is Closed *Mar 1 00:56:53.111: BR0:1 DDR: disconnecting call 00:56:53: %LINK-3-
UPDOWN: Interface BRI0:2, changed state to down *Mar 1 00:56:53.119: BR0:2 LCP: State is Closed
*Mar 1 00:56:53.119: BR0:2 DDR: disconnecting call *Mar 1 00:56:53.127: ISDN BR0 EVENT:
isdn_sw_cstate: State = 4, Old State = 6 *Mar 1 00:56:53.135: ISDN BR0 EVENT: isdn_sw_cstate:
State = 4, Old State = 6 *Mar 1 00:56:53.567: ISDN BR0: RX <- IDCKRQ ri=0 ai=127 *Mar 1
00:56:53.567: ISDN Recvd L1 prim 3 dsl 0 state 3 ctrl_state 0 *Mar 1 00:56:53.571: ISDN BR0: L1
persistent Deactivated *Mar 1 00:56:53.571: ISDN Recvd L1 prim 7 dsl 0 state 3 ctrl_state 0 *Mar
1 00:56:53.575: ISDN BR0: Recvd MPH_IIC_IND from L1 *Mar 1 00:56:53.575: ISDN Recvd L1 prim 7
dsl 0 state 3 ctrl_state 0 *Mar 1 00:56:53.579: ISDN BR0: Recvd MPH_IIC_IND from L1 *Mar 1
00:56:53.579: ISDN Recvd L1 prim 1 dsl 0 state 3 ctrl_state 0 *Mar 1 00:56:53.583: ISDN BR0: L1
is IF_ACTIVE *Mar 1 00:56:53.583: ISDN BR0 EVENT: isdn_sw_cstate: State = 4, Old State = 6 *Mar
1 00:56:53.587: ISDN BR0: L2-TERM: ces/tei=1/0 AWAIT_ESTABLISH->TERM_DOWN *Mar 1 00:56:53.591:
ISDN BR0: Incoming call id = 0x0010, dsl 0 *Mar 1 00:56:53.595: ISDN BR0: L2-TERM: ces/tei=1/0
TERM_DOWN->AWAIT_ESTABLISH 00:56:53: %LINK-3-UPDOWN: Interface BRI0, changed state to up *Mar 1
00:56:53.631: ISDN BR0 EVENT: isdn_sw_cstate: State = 4, Old State = 6 *Mar 1 00:56:53.655: ISDN
BR0: TX -> IDREQ ri=48769 ai=127 00:56:54: %LINEPROTO-5-UPDOWN: Line protocol on Interface
Serial0, changed state to down *Mar 1 00:56:54.387: ISDN BR0: RX <- IDCKRQ ri=0 ai=127 *Mar 1
00:56:55.655: ISDN BR0: TX -> IDREQ ri=42642 ai=127 *Mar 1 00:56:55.699: ISDN BR0: RX <- IDASSN
ri=42642 ai=68 *Mar 1 00:56:55.791: ISDN BR0: TX -> SABMEp c/r=0 sapi=0 tei=68 *Mar 1
00:56:55.823: ISDN BR0: RX <- Uaf c/r=0 sapi=0 tei=68 00:56:55: %ISDN-6-LAYER2UP: Layer 2 for
Interface BR0, TEI 68 changed to up *Mar 1 00:56:55.831: ISDN BR0: L2-TERM: ces/tei=1/68
AWAIT_ESTABLISH->ESTABLISHED !--- Interesting traffic has not arrived yet from Host1, !--- but
ISDN L1 and L2 are up now. ROUTER1# show isdn stat Global ISDN Switchtype = basic-5ess ISDN BRI0
interface dsl 0, interface ISDN Switchtype = basic-5ess Layer 1 Status: ACTIVE Layer 2 Status:
TEI = 68, Ces = 1, SAPI = 0, State = MULTIPLE_FRAME_ESTABLISHED I_Queue_Len 0, UI_Queue_Len 0
Layer 3 Status: 0 Active Layer 3 Call(s) Active dsl 0 CCBs = 0 The Free Channel Mask: 0x80000003
Number of L2 Discards = 0, L2 Session ID = 34 Total Allocated ISDN CCBs = 0 ROUTER1# *Mar 1
00:57:25.839: ISDN BR0: TX -> RRP sapi=0 tei=68 nr=0 *Mar 1 00:57:25.871: ISDN BR0: RX <- RRF
sapi=0 tei=68 nr=0 ROUTER1# !--- Interesting traffic arrives now, !--- which triggers ISDN
Dialup (see below). *Mar 1 00:57:32.519: BR0 DDR: Dialing cause bridge (0xFFFF) *Mar 1
00:57:32.519: BR0 DDR: Attempting to dial 5552000 *Mar 1 00:57:32.523: ISDN BR0: Outgoing call
id = 0x800E, dsl 0 *Mar 1 00:57:32.527: ISDN BR0: Event: Call to 5552000 at 64 Kb/s *Mar 1
00:57:32.527: ISDN BR0: process_bri_call(): call id 0x800E, called_number 5552000, speed 64,
call type DATA *Mar 1 00:57:32.531: CCBRI_Go Fr Host InPkgInfo (Len=22) : *Mar 1 00:57:32.535: 1
0 1 80 E 0 4 2 88 90 18 1 83 2C 7 35 35 35 32 30 30 30 *Mar 1 00:57:32.543: *Mar 1 00:57:32.547:
CC_CHAN_GetIdleChanbri: dsl 0 *Mar 1 00:57:32.547: Found idle channel B1 *Mar 1 00:57:32.563:
ISDN BR0: TX -> INFOc sapi=0 tei=68 ns=0 nr=0 i=0x08010E05040288901801832C0735353532303030 *Mar
1 00:57:32.583: SETUP pd = 8 callref = 0x0E *Mar 1 00:57:32.591: Bearer Capability i = 0x8890
*Mar 1 00:57:32.599: Channel ID i = 0x83 *Mar 1 00:57:32.603: Keypad Facility i = '5552000' *Mar
1 00:57:32.867: ISDN BR0: RX <- INFOc sapi=0 tei=68 ns=0 nr=1 i=0x08018E02180189 *Mar 1
00:57:32.875: CALL_PROC pd = 8 callref = 0x8E *Mar 1 00:57:32.883: Channel ID i = 0x89 *Mar 1
00:57:32.899: ISDN BR0: TX -> RRR sapi=0 tei=68 nr=1 *Mar 1 00:57:32.907: CCBRI_Go Fr L3 pkt
(Len=7) : *Mar 1 00:57:32.907: 2 1 E 98 18 1 89 *Mar 1 00:57:32.911: *Mar 1 00:57:32.915: ISDN
BR0: LIF_EVENT: ces/callid 1/0x800E HOST_PROCEEDING *Mar 1 00:57:32.919: ISDN BR0:
HOST_PROCEEDING *Mar 1 00:57:32.919: ISDN BR0: HOST_MORE_INFO *Mar 1 00:57:33.159: ISDN BR0: RX
<- INFOc sapi=0 tei=68 ns=1 nr=1 i=0x08018E07 *Mar 1 00:57:33.167: CONNECT pd = 8 callref = 0x8E
*Mar 1 00:57:33.183: ISDN BR0: TX -> RRR sapi=0 tei=68 nr=2 *Mar 1 00:57:33.191: CCBRI_Go Fr L3
pkt (Len=4) : *Mar 1 00:57:33.191: 7 1 E 91 *Mar 1 00:57:33.195: *Mar 1 00:57:33.199: ISDN BR0:
LIF_EVENT: ces/callid 1/0x800E HOST_CONNECT 00:57:33: %LINK-3-UPDOWN: Interface BRI0:1, changed
state to up *Mar 1 00:57:33.215: ISDN: get_isdn_service_state(): idb 0x19F4D8 bchan 2 is_isdn 1
Not a Pri *Mar 1 00:57:33.215: BR0:1 PPP: Treating connection as a callout *Mar 1 00:57:33.219:
BR0:1 PPP: Phase is ESTABLISHING, Active Open [0 sess, 1 load] *Mar 1 00:57:33.223: BR0:1 LCP: O
CONFREQ [Closed] id 27 len 15 *Mar 1 00:57:33.227: BR0:1 LCP: AuthProto CHAP (0x0305C22305) *Mar
1 00:57:33.231: BR0:1 LCP: MagicNumber 0x6091A5F6 (0x05066091A5F6) *Mar 1 00:57:33.235: ISDN
BR0: Event: Connected to 5552000 on B1 at 64 Kb/s *Mar 1 00:57:33.247: ISDN BR0: TX -> INFOc
sapi=0 tei=68 ns=1 nr=2 i=0x08010E0F *Mar 1 00:57:33.251: CONNECT_ACK pd = 8 callref = 0x0E *Mar
1 00:57:33.267: BR0:1 LCP: I CONFREQ [REQsent] id 4 len 15 *Mar 1 00:57:33.271: BR0:1 LCP:
AuthProto CHAP (0x0305C22305) *Mar 1 00:57:33.275: BR0:1 LCP: MagicNumber 0x6062D6EA
```

```
(0x05066062D6EA) *Mar 1 00:57:33.279: BR0:1 LCP: O CONFACK [REQsent] id 4 len 15 *Mar 1
00:57:33.283: BR0:1 LCP: AuthProto CHAP (0x0305C22305) *Mar 1 00:57:33.287: BR0:1 LCP:
MagicNumber 0x6062D6EA (0x05066062D6EA) *Mar 1 00:57:33.291: BR0:1 LCP: I CONFACK [ACKsent] id
27 len 15 *Mar 1 00:57:33.291: BR0:1 LCP: AuthProto CHAP (0x0305C22305) *Mar 1 00:57:33.295:
BR0:1 LCP: MagicNumber 0x6091A5F6 (0x05066091A5F6) *Mar 1 00:57:33.299: BR0:1 LCP: State is Open
*Mar 1 00:57:33.303: BR0:1 PPP: Phase is AUTHENTICATING, by both [0 sess, 1 load] *Mar 1
00:57:33.307: BR0:1 CHAP: O CHALLENGE id 14 len 28 from "ROUTER1" *Mar 1 00:57:33.319: BR0:1
CHAP: I CHALLENGE id 4 len 28 from "ROUTER2" *Mar 1 00:57:33.327: BR0:1 CHAP: O RESPONSE id 4
len 28 from "ROUTER1" *Mar 1 00:57:33.335: ISDN BR0: RX <- RRr sapi=0 tei=68 nr=2 *Mar 1
00:57:33.351: BR0:1 CHAP: I SUCCESS id 4 len 4 *Mar 1 00:57:33.367: BR0:1 CHAP: I RESPONSE id 14
len 28 from "ROUTER2" *Mar 1 00:57:33.371: BR0:1 CHAP: O SUCCESS id 14 len 4 *Mar 1
00:57:33.375: BR0:1 PPP: Phase is UP [0 sess, 0 load] *Mar 1 00:57:33.379: BR0:1 BNCP: O CONFREQ
[Closed] id 14 len 4 *Mar 1 00:57:33.387: BR0:1 CDPCP: O CONFREQ [Closed] id 14 len 4 *Mar 1
00:57:33.395: BR0:1 BNCP: I CONFREQ [REQsent] id 4 len 4 *Mar 1 00:57:33.399: BR0:1 BNCP: O
CONFACK [REQsent] id 4 len 4 *Mar 1 00:57:33.403: BR0:1 IPCP: I CONFREQ [Not negotiated] id 4
len 10 *Mar 1 00:57:33.407: BR0:1 IPCP: Address 172.16.53.17 (0x0306AC103511) *Mar 1
00:57:33.415: BR0:1 LCP: O PROTREJ [Open] id 28 len 16 protocol IPCP
(0x80210104000A0306AC103511) *Mar 1 00:57:33.419: BR0:1 CDPCP: I CONFREQ [REQsent] id 4 len 4
*Mar 1 00:57:33.423: BR0:1 CDPCP: O CONFACK [REQsent] id 4 len 4 *Mar 1 00:57:33.427: BR0:1
BNCP: I CONFACK [ACKsent] id 14 len 4 *Mar 1 00:57:33.431: BR0:1 BNCP: State is Open *Mar 1
00:57:33.435: BR0:1 CDPCP: I CONFACK [ACKsent] id 14 len 4 *Mar 1 00:57:33.439: BR0:1 CDPCP:
State is Open *Mar 1 00:57:33.443: BR0:1 DDR: dialer protocol up 00:57:34: %LINEPROTO-5-UPDOWN:
Line protocol on Interface BRI0:1, changed state to up 00:57:39: %ISDN-6-CONNECT: Interface
BRI0:1 is now connected to 5552000 ROUTER2 ROUTER1# ROUTER1# show isdn status Global ISDN
Switchtype = basic-5ess ISDN BRI0 interface dsl 0, interface ISDN Switchtype = basic-5ess Layer
1 Status: ACTIVE Layer 2 Status: TEI = 68, Ces = 1, SAPI = 0, State = MULTIPLE_FRAME_ESTABLISHED
I_Queue_Len 0, UI_Queue_Len 0 Layer 3 Status: 1 Active Layer 3 Call(s) CCB:callid=800E, sapi=0,
ces=1, B-chan=1, calltype=DATA Active dsl 0 CCBs = 1 The Free Channel Mask: 0x80000002 Number of
L2 Discards = 0, L2 Session ID = 34 Total Allocated ISDN CCBs = 1 *Mar 1 00:58:03.343: ISDN BR0:
TX -> RRp sapi=0 tei=68 nr=2 *Mar 1 00:58:03.379: ISDN BR0: RX <- RRf sapi=0 tei=68 nr=2pann
ROUTER1# show spanning-tree Bridge group 1 is executing the ieee compatible Spanning Tree
protocol Bridge Identifier has priority 32768, address 0060.5cf4.a9a8 Configured hello time 2,
max age 20, forward delay 15 Current root has priority 32768, address 0060.5cf4.a955 Root port
is 3 (BRI0), cost of root path is 15625 Topology change flag set, detected flag not set Number
of topology changes 10 last change occurred 00:01:15 ago from Serial0 Times: hold 1, topology
change 35, notification 2 hello 2, max age 20, forward delay 15 Timers: hello 0, topology change
0, notification 0, aging 15 Port 2 (Ethernet0) of Bridge group 1 is forwarding Port path cost
100, Port priority 128, Port Identifier 128.2. Designated root has priority 32768, address
0060.5cf4.a955 Designated bridge has priority 32768, address 0060.5cf4.a9a8 Designated port id
is 128.2, designated path cost 15625 Timers: message age 0, forward delay 0, hold 0 Number of
transitions to forwarding state: 2 BPDU: sent 751, received 0 Port 3 (BRI0) of Bridge group 1 is
forwarding !--- BRI Interface forwards the bridged traffic now. Port path cost 15625, Port
priority 128, Port Identifier 128.3. Designated root has priority 32768, address 0060.5cf4.a955
Designated bridge has priority 32768, address 0060.5cf4.a955 Designated port id is 128.3,
designated path cost 0 Timers: message age 2, forward delay 0, hold 0 Number of transitions to
forwarding state: 3 BPDU: sent 1014, received 608 Port 6 (Serial0) of Bridge group 1 is down
Port path cost 647, Port priority 128, Port Identifier 128.6. Designated root has priority
32768, address 0060.5cf4.a955 Designated bridge has priority 32768, address 0060.5cf4.a9a8
Designated port id is 128.6, designated path cost 15625 Timers: message age 0, forward delay 0,
hold 0 Number of transitions to forwarding state: 1 BPDU: sent 15, received 27 ROUTER1# *Mar 1
00:58:33.387: ISDN BR0: TX -> RRp sapi=0 tei=68 nr=2 *Mar 1 00:58:33.423: ISDN BR0: RX <- RRF
sapi=0 tei=68 nr=2
```

[Saída de debug em ROUTER1 quando Serial0 é reativada e o ISDN descarta a chamada](#)

```
00:58:37: %LINK-3-UPDOWN: Interface Serial0, changed state to up *Mar 1 00:58:37.671: BR0:1 DDR:
disconnecting call *Mar 1 00:58:37.675: BR0:2 DDR: disconnecting call *Mar 1 00:58:37.675: ISDN
BR0: Event: Hangup call to call id 0x800E *Mar 1 00:58:37.679: ISDN BR0: process_disconnect():
call id 0x800E, call type is DATA, b_idb 0x19F4D8, ces 1, cause Normal call clearing(0x10)
00:58:37: %ISDN-6-DISCONNECT: Interface BRI0:1 disconnected from 5552000 ROUTER2, call lasted 64
seconds *Mar 1 00:58:37.691: ISDN: get_isdn_service_state(): idb 0x19F4D8 bchan 2 is_isdn 1 Not
a Pri *Mar 1 00:58:37.695: CCBRI_Go Fr Host InPkgInfo (Len=13) : *Mar 1 00:58:37.699: 5 0 1 80 E
```

```

3 8 1 90 8 2 80 90 *Mar 1 00:58:37.703: *Mar 1 00:58:37.719: ISDN BR0: TX -> INFOc sapi=0 tei=68
ns=2 nr=2 i=0x08010E4508028090 *Mar 1 00:58:37.727: DISCONNECT pd = 8 callref = 0x0E *Mar 1
00:58:37.735: Cause i = 0x8090 - Normal call clearing *Mar 1 00:58:37.743: ISDN BR0 EVENT:
isdn_sw_cs!!!!!!!!!!!!!!!!!!!!!!!!!!!!tate: State = 6, Old State = 4 00:58:37: %LINK-3-UPDOWN: Interface
BRI0:1, changed state to down *Mar 1 00:58:37.751: BR0:1 BNCP: State is Closed *Mar 1
00:58:37.755: BR0:1 CDPCP: State is Closed *Mar 1 00:58:37.755: BR0:1 PPP: Phase is TERMINATING
[0 sess, 1 load] *Mar 1 00:58:37.759: BR0:1 LCP: State is Closed *Mar 1 00:58:37.763: BR0:1 PPP:
Phase is DOWN [0 sess, 1 load] *Mar 1 00:58:37.763: BR0:1 DDR: disconnecting call *Mar 1
00:58:37.775: ISDN Recvd L1 prim 3 dsl 0 state 1 ctrl_state 0 *Mar 1 00:58:37.779: ISDN BR0:
Physical layer is IF_DOWN *Mar 1 00:58:37.783: ISDN BR0: Shutting down ME 00:58:37: %ISDN-6-
LAYER2DOWN: Layer 2 for Interface BRI0, TEI 68 changed to down *Mar 1 00:58:37.791: ISDN BR0:
L2-TERM: ces/tei=1/68 ESTABLISHED->TERM_DOWN *Mar 1 00:58:37.795: ISDN BR0: LIF_EVENT:
ces/callid 1/0x800E HOST_DISCONNECT_ACK *Mar 1 00:58:37.803: ISDN: get_isdn_service_state(): idb
0x19F4D8 bchan 2 is_isdn 1 Not a Pri *Mar 1 00:58:37.807: ISDN BR0: HOST_DISCONNECT_ACK: call
type is DATA 00:58:37: %LINK-3-UPDOWN: Interface BRI0:1, changed state to down *Mar 1
00:58:37.815: BR0:1 LCP: State is Closed *Mar 1 00:58:37.815: BR0:1 DDR: disconnecting call *Mar
1 00:58:37.819: ISDN BR0: Shutting down ISDN Layer 3 00:58:37: %ISDN-6-LAYER2DOWN: Layer 2 for
Interface BR0, TEI 68 changed to down 00:58:37: %LINK-5-CHANGED: Interface BRI0, changed state
to standby mode *Mar 1 00:58:37.847: ISDN BR0 EVENT: isdn_sw_cstate: State = 6, Old State = 4
00:58:37: %LINK-3-UPDOWN: Interface BRI0:2, changed state to down *Mar 1 00:58:37.855: BR0:2
LCP: State is Closed *Mar 1 00:58:37.855: BR0:2 DDR: disconnecting call *Mar 1 00:58:37.895:
ISDN BR0: Incoming call id = 0x0011, dsl 0 *Mar 1 00:58:37.895: ISDN BR0: L2-TERM: ces/tei=1/0
TERM_DOWN->AWAIT_ESTABLISH *Mar 1 00:58:37.935: ISDN BR0: Activating 00:58:38: %LINEPROTO-5-
UPDOWN: Line protocol on Interface Serial0, changed state to up 00:58:38: %LINEPROTO-5-UPDOWN:
Line protocol on Interface BRI0:1, changed state to down *Mar 1 00:58:39.939: ISDN BR0: Could
not bring up interface *Mar 1 00:58:39.943: ISDN BR0: Shutting down ISDN Layer 3 *Mar 1
00:58:39.963: ISDN BR0: Activating *Mar 1 00:58:41.943: ISDN BR0: Could not bring up interface
*Mar 1 00:58:41.947: ISDN BR0: Shutting down ISDN Layer 3 *Mar 1 00:58:41.947: ISDN BR0:
Activating ROUTER1# ROUTER1# show isdn status Global ISDN Switchtype = basic-5ess ISDN BRI0
interface dsl 0, interface ISDN Switchtype = basic-5ess Layer 1 Status: DEACTIVATED Layer 2
Status: Layer 2 NOT Activated !--- ISDN L1 and L2 are back to the deactivated state. Layer 3
Status: 0 Active Layer 3 Call(s) Active dsl 0 CCBs = 0 The Free Channel Mask: 0x80000003 Number
of L2 Discards = 0, L2 Session ID = 39 Total Allocated ISDN CCBs = 0 ROUTER1# *Mar 1
00:58:49.951: ISDN BR0: Could not bring up interface *Mar 1 00:58:49.951: ISDN BR0: Shutting
down ISDN Layer 3 ROUTER1# ROUTER1# show spanning-tree Bridge group 1 is executing the ieee
compatible Spanning Tree protocol Bridge Identifier has priority 32768, address 0060.5cf4.a9a8
Configured hello time 2, max age 20, forward delay 15 Current root has priority 32768, address
0060.5cf4.a955 Root port is 6 (Serial0), cost of root path is 647 Topology change flag not set,
detected flag not set Number of topology changes 13 last change occurred 00:28:23 ago from
Serial0 Times: hold 1, topology change 35, notification 2 hello 2, max age 20, forward delay 15
Timers: hello 0, topology change 0, notification 0, aging 300 Port 2 (Ethernet0) of Bridge group
1 is forwarding Port path cost 100, Port priority 128, Port Identifier 128.2. Designated root
has priority 32768, address 0060.5cf4.a955 Designated bridge has priority 32768, address
0060.5cf4.a9a8 Designated port id is 128.2, designated path cost 647 Timers: message age 0,
forward delay 0, hold 0 Number of transitions to forwarding state: 2 BPDU: sent 1633, received 0
Port 3 (BRI0) of Bridge group 1 is down !--- BRI0 is in the down state when Serial 0 is up. Port
path cost 15625, Port priority 128, Port Identifier 128.3. Designated root has priority 32768,
address 0060.5cf4.a955 Designated bridge has priority 32768, address 0060.5cf4.a9a8 Designated
port id is 128.3, designated path cost 647 Timers: message age 0, forward delay 0, hold 0 Number
of transitions to forwarding state: 3 BPDU: sent 1014, received 622 Port 6 (Serial0) of Bridge
group 1 is forwarding !--- Serial0 forwards the bridged traffic now. Port path cost 647, Port
priority 128, Port Identifier 128.6. Designated root has priority 32768, address 0060.5cf4.a955
Designated bridge has priority 32768, address 0060.5cf4.a955 Designated port id is 128.6,
designated path cost 0 Timers: message age 1, forward delay 0, hold 0 Number of transitions to
forwarding state: 2 BPDU: sent 18, received 896 ROUTER1#

```

[Informações Relacionadas](#)

- [Bridging através do ISDN](#)
- [Backup de BRI ISDN com interface de backup](#)
- [Configurando backup ISDN BRI de vários enlaces com relógio do discador](#)
- [Configurando backup ISDN BRI com relógio do discador](#)

- [Configurando o backup de ISDN com rotas flutuantes](#)
- [Backup de chamada DDR usando BRI e o comando backup interface](#)
- [Configurando a interface de backup BRI com perfis de discadores](#)
- [Configurando o backup de DDR com uso de BRIs e relógio de discador](#)
- [Configurando backup de ISDN para enlaces de WAN usando rotas estáticas flutuantes](#)
- [Configurando o backup do Frame Relay](#)
- [Configuração de Backup de Discagem para Linhas Seriais](#)
- [O seletor do Cisco IOS presta serviços de manutenção a comandos](#)
- [Suporte por tecnologia do Discar e acessar](#)
- [Suporte Técnico e Documentação - Cisco Systems](#)