

Controladores sem fio Catalyst 9800 Problemas comuns de conectividade de cliente sem fio

Contents

[Introduction](#)

[Prerequisites](#)

[Requirements](#)

[Componentes Utilizados](#)

[Coletar logs](#)

[Cenários](#)

[As credenciais de autenticação da Web não funcionarão](#)

[O cliente não pode se conectar porque não há VLAN válida definida no perfil de política](#)

[O cliente não pode se conectar devido à senha incorreta](#)

[O cliente não pode se conectar porque a ACL enviada pelo RADIUS não existe na WLC 9800](#)

[O cliente não pode se conectar porque a VLAN enviada por RADIUS não existe na WLC 9800](#)

[Cliente desconectado devido a alterações na WLAN ou no perfil de política](#)

[Cliente removido manualmente da rede](#)

[Cliente desconectado devido ao tempo limite de EAP](#)

[Cliente desconectado devido à reinicialização do rádio AP](#)

[Cliente desconectado devido ao tempo limite de autenticação da Web](#)

[Cliente desconectado devido ao tempo limite da sessão](#)

[Cliente desconectado devido ao tempo limite de ociosidade](#)

[Cliente movido entre SSIDs](#)

Introduction

Este documento descreve os cenários de problemas mais comuns de conectividade de clientes sem fio e como resolvê-los nos Catalyst 9800 Wireless Controllers.

Prerequisites

Requirements

A Cisco recomenda que você tenha conhecimento destes tópicos:

- Controladores sem fio Cisco Catalyst 9800 Series
- Acesso à CLI (Command Line Interface, interface de linha de comando) para os controladores sem fio.

Componentes Utilizados

- IOS-XE Gibraltar 16.10 ou superior

As informações neste documento foram criadas a partir de dispositivos em um ambiente de laboratório específico. All of the devices used in this document started with a cleared (default) configuration. If your network is live, make sure that you understand the potential impact of any command.

Coletar logs

O WLC 9800 oferece recursos de rastreamento SEMPRE ACESO. Isso garante que todos os erros relacionados à conectividade do cliente, mensagens de aviso e nível de aviso sejam constantemente registrados e você pode exibir registros de um incidente ou condição de falha depois que ele ocorreu.

Nota: Dependendo do volume de registros sendo gerado, você pode voltar algumas horas para vários dias.

Para visualizar os rastreamentos que a WLC 9800 coletou por padrão, você pode se conectar via SSH/Telnet à WLC 9800 e seguir estas etapas (certifique-se de que está fazendo o log da sessão em um arquivo de texto).

Etapa 1. Verifique a hora atual do controlador para que você possa rastrear os registros no tempo até quando o problema ocorreu.

```
# show clock
```

Etapa 2. Colete syslogs do buffer do controlador ou do syslog externo conforme indicado pela configuração do sistema. Isso fornece uma visão rápida da integridade e dos erros do sistema, se houver.

```
# show logging
```

Etapa 3. Verifique se alguma condição de depuração está ativada.

```
# show debugging
```

```
IOSXE Conditional Debug Configs:
```

```
Conditional Debug Global State: Stop
```

```
IOSXE Packet Tracing Configs:
```

```
Packet Infra debugs:
```

```
Ip Address
```

```
Port
```

```
-----|-----
```

Nota: Se você vir alguma condição listada, isso significa que os rastreamentos estão sendo registrados no nível de depuração para todos os processos que encontram as condições habilitadas (endereço mac, endereço ip etc.). Isso aumentaria o volume de registros. Portanto, é recomendável limpar todas as condições quando não a depuração ativa

Etapa 4. Supondo que o endereço mac em teste não estivesse listado como uma condição na

Etapa 3, colete os rastreamentos de nível de aviso sempre ativo para o endereço mac específico.

```
# show logging profile wireless filter { mac | ip } { <aaaa.bbbb.cccc> | <a.b.c.d> } to-file  
always-on-<FILENAME.txt>
```

Você pode exibir o conteúdo da sessão ou pode copiar o arquivo para um servidor TFTP externo.

```
# more bootflash:always-on-<FILENAME.txt>  
or  
# copy bootflash:always-on-<FILENAME.txt> tftp://a.b.c.d/path/always-on-<FILENAME.txt>
```

Depuração Condicional e Rastreamento Ativo de Rádio

Se os rastreamentos sempre ativos não fornecerem informações suficientes para determinar o disparo para o problema em investigação, você poderá ativar a depuração condicional e capturar o rastreamento de rádio ativo (RA), que fornecerá rastreamentos de nível de depuração para todos os processos que interagem com a condição especificada (endereço mac do cliente neste caso). Para habilitar a depuração condicional, siga estas etapas.

Etapa 5. Verifique se não há condições de depuração habilitadas.

```
# clear platform condition all
```

Etapa 6. Ative a condição de depuração para o endereço mac do cliente sem fio que você deseja monitorar.

Esses comandos começam a monitorar o endereço mac fornecido por 30 minutos (1800 segundos). Você também pode aumentar esse tempo para até 2085978494 segundos.

```
# debug wireless mac <aaaa.bbbb.cccc> {monitor-time <seconds>}
```

Observação: para monitorar mais de um cliente por vez, execute o comando `debug wireless mac <aaaa.bbbb.ccc>` por endereço mac.

Nota: Você não vê a saída da atividade do cliente na sessão de terminal, pois tudo é colocado em buffer internamente para ser visualizado posteriormente.

Passo 7. Reproduza o problema ou comportamento que você deseja monitorar.

Etapa 8. Interrompa as depurações se o problema for reproduzido antes que o tempo padrão ou configurado do monitor esteja esgotado.

```
# no debug wireless mac <aaaa.bbbb.cccc>
```

Depois que o `monitor-time` tiver transcorrido ou a depuração sem fio tiver sido interrompida, a WLC 9800 gera um arquivo local com o nome:

ra_trace_MAC_aaaabbbcccc_HHMMSS.XXX_timezone_DayWeek_Month_Day_year

Etapa 9. Colete o arquivo da atividade de endereço MAC. Você pode copiar o arquivo .log do rastreo para um servidor externo ou exibir a saída diretamente na tela.

Verifique o nome do arquivo de rastreamento RA

```
# dir bootflash: | inc ra_trace
```

Copie o arquivo para um servidor externo:

```
# copy bootflash:ra_trace_MAC_aaaabbbcccc_HHMMSS.XXX_timezone_DayWeek_Month_Day_year.log  
tftp://a.b.c.d/ra-FILENAME.txt
```

Exibir o conteúdo:

```
# more bootflash:ra_trace_MAC_aaaabbbcccc_HHMMSS.XXX_timezone_DayWeek_Month_Day_year.log
```

Etapa 10. Se a causa raiz ainda não for óbvia, colete os logs internos, que são uma visão mais detalhada dos logs de nível de depuração. Você não precisa depurar o cliente novamente, pois estamos apenas analisando detalhadamente os logs de depuração que já foram coletados e armazenados internamente.

```
# show logging profile wireless internal filter { mac | ip } { <aaaa.bbbb.cccc> | <a.b.c.d> }  
to-file ra-internal-<FILENAME>.txt
```

Nota: Essa saída de comando retorna rastreamentos para todos os níveis de registro para todos os processos e é bastante volumosa. Entre em contato com o Cisco TAC para ajudar a analisar esses rastreamentos.

Você pode copiar o ra-internal-FILENAME.txt para um servidor externo ou exibir a saída diretamente na tela.

Copie o arquivo para um servidor externo:

```
# copy bootflash:ra-internal-<FILENAME>.txt tftp://a.b.c.d/ra-internal-<FILENAME>.txt
```

Exibir o conteúdo:

```
# more bootflash:ra-internal-<FILENAME>.txt
```

Etapa 11. Remova as condições de depuração.

```
# clear platform condition all
```

Nota: Certifique-se de sempre remover as condições de depuração após uma sessão de solução de problemas.

Cenários

As credenciais de autenticação da Web não funcionarão

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [27915]: UUID: 100000000015b, ra: 15, (info): [e4b3.1851.90ff:capwap_90800003] Authc failure from WebAuth, Auth event fail
```

Razão

- O cliente não está usando credenciais válidas
- Não há uma rede de autorização padrão definida na WLC 9800

Soluções possíveis

- Verifique se o cliente está usando credenciais válidas
- Adicionar um método de rede de autorização padrão

GUI:

Navegue até **Configuration > Security > AAA > AAA Method List > Authorization > + Add** e crie um novo método de autorização com esses parâmetros.

Quick Setup: AAA Authorization

Method List Name*

Type*

Group Type

Available Server Groups: radius, ldap, tacacs+, ISF-KCG-grp

Assigned Server Groups: (empty)

Buttons: Cancel, Save & Apply to Device

CLI:

```
# config t
# aaa authorization network default local
```

O cliente não pode se conectar porque não há VLAN válida definida no perfil de política

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [epm] [25054]: UUID: 10000000000019, ra: 15, (ERR): EPM_PLUGIN_VLAN_ERR: [HDL = 0x0] Unable to get active_feature_ctx for vlan group name YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [sanet-shim-miscellaneous] [25054]: UUID: 10000000000019, ra: 15,
```

(ERR): MAC: 0874.0277.1345 Error in fetching vlans YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [sanet-shim-miscellaneous] [25054]: UUID: 1000000000019, ra: 15, (ERR): MAC: 0874.0277.1345 building Mobile Announce Vlanid payload failed

Razão

Não há uma VLAN válida definida no perfil de política atribuída à WLAN

Solução

1. Verifique qual perfil de política é usado pelo cliente.

GUI:

Navegue até **Monitoring > Wireless > Clients > Client row > Client Properties**. (Pesquisa opcional de um cliente específico usando seu endereço mac)

The screenshot shows the 'Clients' management interface. On the left is a navigation menu with 'Monitoring' selected. The main area displays a table of clients with columns for Client MAC Address, IPv4/IPv6 Address, and AP Name. A filter dropdown is open over the IPv4/IPv6 Address column, showing 'Is equal to' and the value 'aaaa.bbbb.cccc'. On the right, the 'Client Properties' page is open for a selected client. The 'Policy Profile' field is highlighted with a red box, showing the value 'default-policy-profile'.

CLI:

```
# show wireless client mac-address <aaaa.bbbb.cccc> detail | inc Policy Profile  
Policy Profile : default-policy-profile
```

2. Verifique qual VLAN está atribuída a esse perfil de política.

GUI:

Navegue até **Configuration > Tags & Profiles > Policy > Policy Profile row > Access Policies**

The screenshot shows the 'Policy Profile' management interface. On the left is a navigation menu with 'Configuration' selected. The main area displays a table of policy profiles with columns for Policy Profile Name and Description. The 'default-policy-profile' is selected. On the right, the 'Edit Policy Profile' page is open for the selected profile. The 'Access Policies' tab is selected, and the 'VLAN/VLAN Group' field is highlighted with a red box, showing the value 'VLAN2686'.

CLI:

```
# show wireless profile policy detailed default-policy-profile | inc VLAN  
VLAN : VLAN2686
```

3. Verifique se o parâmetro VLAN tem um nome de VLAN ou ID de VLAN válido e ativo.

GUI:

Navegue até **Configuration > Layer2 > VLAN > VLAN**

VLAN ID	Name	Status
<input type="checkbox"/> 1	default	active
<input type="checkbox"/> 210	VLAN0210	active
<input type="checkbox"/> 2600	VLAN2600	active
<input type="checkbox"/> 2601	VLAN2601	active
<input type="checkbox"/> 2602	VLAN2602	active
<input type="checkbox"/> 2686	VLAN2686	active

CLI:

```
# show vlan brief
```

```
VLAN Name                               Status    Ports  
-----  
1    default                               active    Te0/0/2, Te0/0/3  
210  VLAN0210                               active  
1002 fddi-default                           act/unsup  
1003 token-ring-default                   act/unsup  
1004 fddinet-default                       act/unsup  
1005 trnet-default                       act/unsup  
  
VLAN Name                               Status    Ports  
-----  
2600 VLAN2600                               active  
2601 VLAN2601                               active  
2602 VLAN2602                               active  
2686 VLAN2686                             active
```

Observação: se o nome da VLAN for usado, ele diferencia maiúsculas de minúsculas, portanto, certifique-se de que seja exatamente o mesmo visto no comando **show vlan brief**.

4. Corrija a VLAN conforme necessário.

GUI:

Navegue para **Configuração > Marcas e perfis > Política > Linha Perfil de política > Políticas de**

acesso e corrija a VLAN

CLI:

```
# config t
# wireless profile policy default-policy-profile
# shutdown # vlan <vlan-# or vlan-name>
# no shutdown
```

O cliente não pode se conectar devido à senha incorreta

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-keymgmt] [27782]: UUID: 1000000000088, ra: 15,
(ERR): MAC: e4b3.187c.3058 Keymgmt: Failed to validate eapol mic. MIC mismatch. YYYY/DD/MM
HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-keymgmt] [27782]: UUID: 1000000000088, ra: 15, (ERR):
MAC: e4b3.187c.3058 Keymgmt: Failed to validate eapol key m2. MIC validation failed
```

Razão

O cliente está digitando uma senha incorreta

Soluções possíveis

- Corrija a senha no dispositivo de endpoint
- Corrija a senha no SSID

GUI:

Navegue até **Configuration > Wireless > WLANs > WLAN name > Security > Layer2** e corrija a senha.

The image shows the Cisco Wireless LAN Controller (WLC) configuration interface. On the left is a navigation menu with options: Dashboard, Monitoring, Configuration (highlighted), Administration, and Troubleshooting. The main area is titled 'Edit WLAN' and has two tabs: 'General' and 'Security' (highlighted). Under the 'Security' tab, there are sub-sections for 'Layer2' (highlighted) and 'Layer3'. The 'Layer2' section includes:

- Layer 2 Security Mode: WPA + WPA2
- MAC Filtering:
- Protected Management Frame:
- PMF: Disabled
- WPA Parameters:
 - WPA Policy:
 - WPA2 Policy:
 - WPA2 Encryption:
 - AES(CCMP128):
 - CCMP256:
 - GCMP128:
 - GCMP256:
 - Auth Key Mgmt: PSK
 - PSK Format: ASCII
 - Pre-Shared Key: [masked]

CLI:

```
# config t
# wlan <wlan-name>
# shut
# security wpa psk set-key ascii 0 <clear-text-password>
# no shut
```

O cliente não pode se conectar porque a ACL enviada pelo RADIUS não existe na WLC 9800

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [epm-acl] [8104]: (ERR): ACL acl-sent-by-ise is
missing in configuration for mac e4b3.187c.3058
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [epm-acl] [8104]: (ERR): Unable to parse EPM
attributes
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8104]: (info): Sanet App Event
EV_PLUGIN_CONF
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [epm] [8104]: (ERR): Error in activating feature (EPM
ACL PLUG-IN)
```

```
.
.
EPM Data Base:
Number of Authz_info: 2
Authz info 1 details
Number of feat info: 2, State: Success, Priority: 254
EPM Vlan PLUG-IN Status: Success
VLAN Group: VLAN2602
VLAN-ID: 2602
SM Reauth PLUG-IN Status: Success
Authz info 2 details
Number of feat info: 4, State: Fail, Priority: 100
EPM MISC PLUG-IN Status: Success
Anchor Vlan: 0
EPM ACL PLUG-IN Status: Activate Failure
SM ACCOUNTING PLUG-IN Status: Success
linksec Status: Success
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-infra-evq-lib] [8104]: (note): already
started radioactive trace on key:[e4b3.187c.3058]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8104]: (info): Sanet App Event
EV_SVM_APPLY_UP_FAIL
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [auth-mgr] [8104]: (ERR):
[e4b3.187c.3058:capwap_90000003] SM unable to apply User Profile for 0x1A000004 - 'Subsystem(4)'
detected the 'fatal' condition 'Code(47)'
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [auth-mgr] [8104]: (ERR):
[e4b3.187c.3058:capwap_90000003] Unable to process authc result for 0x1A000004 - success
handling failed
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8104]: (info): Sanet eventQ: AUTH_MGR_MQ,
message:3
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-auth] [8104]: (ERR): MAC: e4b3.187c.3058
client authz result: FAILURE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-exclusion] [8104]: (info): MAC:
e4b3.187c.3058 Add client to exclusionlist, sending ipc to add client to client exclusion
table, reason: ACL failure, timeout: 60, AP: MAC: f07f.06ee.f590
```

Razão

A ACL enviada pelo servidor RADIUS não existe na WLC 9800

Soluções possíveis

- Corrija a configuração do servidor RADIUS para enviar o nome da ACL correto
- Adicione a ACL ausente à WLC 9800

O cliente não pode se conectar porque a VLAN enviada por RADIUS não existe na WLC 9800

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [epm] [8104]: (ERR): Error in activating feature (EPM
Vlan PLUG-IN)
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8104]: (info): Sanet App Event EV_START_CALL
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-infra-evq] [8104]: (ERR):
EPM Data Base:
Number of Authz_info: 2
Authz info 1 details
Number of feat info: 2, State: Success, Priority: 254
EPM Vlan PLUG-IN Status: Conflict
SM Reauth PLUG-IN Status: Success
Authz info 2 details
Number of feat info: 4, State: Activate, Priority: 100
```

```
EPM MISC PLUG-IN Status: Success
Anchor Vlan: 0
SM ACCOUNTING PLUG-IN Status: Success
EPM Vlan PLUG-IN Status: Activate Failure
VLAN Group: vlan-sent-by-ise
VLAN-ID: 0
linksec Status: Success
.
.
.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8104]: (info): Sanet App Event
EV_SVM_APPLY_UP_FAIL
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [auth-mgr] [8104]: (ERR):
[e4b3.187c.3058:capwap_90000003] SM unable to apply User Profile for 0x0E000005 - 'Subsystem(4)'
detected the 'fatal' condition 'Code(47)'
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [auth-mgr] [8104]: (ERR):
[e4b3.187c.3058:capwap_90000003] Unable to process authc result for 0x0E000005 - success
handling failed
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8104]: (info): Sanet eventQ: AUTH_MGR_MQ,
message:3
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-auth] [8104]: (ERR): MAC: e4b3.187c.3058
client authz result: FAILURE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-exclusion] [8104]: (info): MAC: e4b3.187c.3058
Add client to exclusionlist, sending ipc to add client to client exclusion table, reason: VLAN
failure, timeout: 60, AP: MAC: f07f.06ee.f590
```

Razão

A VLAN enviada pelo servidor RADIUS não existe na WLC 9800

Soluções possíveis

- Corrija a configuração do servidor RADIUS para enviar o nome/ID da VLAN correto
- Adicione a VLAN ausente à WLC 9800

Cliente desconectado devido a alterações na WLAN ou no perfil de política

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-infra-evq] [8522]: (note): Mcast: Sent L2
MGID 2602 DEL to AP vap_id 2
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [apmgr-bssid] [8522]: (ERR): 00c8.8b26.d790 Radio:0
BSSID:1 - Bssid ifid is not created so no need to push data to fman
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [8522]: (info): MAC: e4b3.187c.3058
Deleting the client, reason: 5, CO_CLIENT_DELETE_REASON_BSSID_DOWN, Client state S_CO_RUN
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [8522]: (note): MAC: e4b3.187c.3058
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_BSSID_DOWN
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [8522]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-qos-client] [8522]: (ERR): MAC:
e4b3.187c.3058 Fail to get qos lib ctxt while handle sip cac on client delete
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [multicast-main] [8522]: (info): MAC: e4b3.187c.3058
No Flex/Fabric main record exists for client
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-iplearn] [8522]: (info): MAC: e4b3.187c.3058
IP-learn state transition: S_IPLEARN_COMPLETE -> S_IPLEARN_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {mobilityd_R0-0}{1}: [mm-transition] [19496]: (info): MAC:
e4b3.187c.3058 MMFSM transition: S_MC_RUN -> S_MC_HANDOFF_END_RCVD_TR on E_MC_HANDOFF_END_RCVD
from WNCID[0]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dpath_svc] [8522]: (note): MAC: e4b3.187c.3058 Client
datapath entry deleted for ifid 0xfa0000001
```

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [mm-transition] [8522]: (info): MAC: e4b3.187c.3058
MMIF FSM transition: S_MA_LOCAL -> S_MA_DELETE_PROCESSED_TR on E_MA_CO_DELETE_RCVD
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [mm-client] [8522]: (ERR): MAC: e4b3.187c.3058 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8522]: (info): Sanet App Event
EV_SESSION_DELETE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [auth-mgr] [8522]: (info):
[e4b3.187c.3058:capwap_90000003] Disconnect request from SANET-SHIM (12) for e4b3.187c.3058 /
0xfb6000001 - term: service-unavailable, abort: Unknown, disc: session disconnect
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [aaa-attr-inf] [8522]: (info): [ Applied attribute
:bsn-vlan-interface-name 0 "VLAN2602" ]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [aaa-attr-inf] [8522]: (info): [ Applied attribute :
timeout 0 1800 (0x708) ]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-auth] [8522]: (info): MAC: e4b3.187c.3058
Client auth-interface state transition: S_AUTHIF_PSK_AUTH_DONE -> S_SANET_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dot11] [8522]: (info): MAC: e4b3.187c.3058 Sent
deauth to client, deauth reason: 252, CLIENT_DEAUTH_REASON_ADMIN_RESET delete reason: 5,
CO_CLIENT_DELETE_REASON_BSSID_DOWN.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dot11] [8522]: (info): MAC: e4b3.187c.3058 DOT11
state transition: S_DOT11_ASSOCIATED -> S_DOT11_DELETED
```

Razão

Houve alterações feitas na GUI ou o SSID ou o perfil de política foram desativados manualmente.

Solução

Esse é um comportamento normal, evite fazer alterações nos SSIDs ou nos perfis de política nas horas de produção.

Cliente removido manualmente da rede

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [8522]: (info): MAC: e4b3.187c.3058
Deleting the client, reason: 12, CO_CLIENT_DELETE_REASON_ADMIN_RESET, Client state S_CO_RUN
YYYY/DD/MM HH:MM:SS.xxx {mobilityd_R0-0}{1}: [mm-transition] [19496]: (info): MAC:
e4b3.187c.3058 MMFSM transition: S_MC_RUN -> S_MC_HANDOFF_END_RCVD_TR on E_MC_HANDOFF_END_RCVD
from WNCd[0]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [8522]: (note): MAC: e4b3.187c.3058
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_ADMIN_RESET
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [8522]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-qos-client] [8522]: (ERR): MAC:
e4b3.187c.3058 Fail to get qos lib ctxt while handle sip cac on client delete
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [multicast-main] [8522]: (info): MAC: e4b3.187c.3058
No Flex/Fabric main record exists for client
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-iplearn] [8522]: (info): MAC: e4b3.187c.3058
IP-learn state transition: S_IPLEARN_COMPLETE -> S_IPLEARN_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dpath_svc] [8522]: (note): MAC: e4b3.187c.3058 Client
datapath entry deleted for ifid 0xfa0000001
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [mm-transition] [8522]: (info): MAC: e4b3.187c.3058
MMIF FSM transition: S_MA_LOCAL -> S_MA_DELETE_PROCESSED_TR on E_MA_CO_DELETE_RCVD
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [mm-client] [8522]: (ERR): MAC: e4b3.187c.3058 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [wncd_0] [8522]: (info): Sanet App Event
EV_SESSION_DELETE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [auth-mgr] [8522]: (info):
[e4b3.187c.3058:capwap_90000003] Disconnect request from SANET-SHIM (12) for e4b3.187c.3058 /
0x30000003 - term: admin-reset, abort: Unknown, disc: session disconnect
```

```

YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [aaa-attr-inf] [8522]: (info): [ Applied attribute
:bsn-vlan-interface-name 0 "VLAN2602" ]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [aaa-attr-inf] [8522]: (info): [ Applied attribute :
timeout 0 1800 (0x708) ]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-auth] [8522]: (info): MAC: e4b3.187c.3058
Client auth-interface state transition: S_AUTHIF_PSK_AUTH_DONE -> S_SANET_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dot11] [8522]: (info): MAC: e4b3.187c.3058 Sent
death to client, death reason: 252, CLIENT_DEAUTH_REASON_ADMIN_RESET delete reason: 12,
CO_CLIENT_DELETE_REASON_ADMIN_RESET.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dot11] [8522]: (info): MAC: e4b3.187c.3058 DOT11
state transition: S_DOT11_ASSOCIATED -> S_DOT11_DELETED

```

Razão

O cliente foi removido manualmente da rede por uma CLI

wireless client mac-address aaaa.bbbb.cccc deauthenticate
ou por GUI

The screenshot shows a network management interface. On the left is a dark sidebar with menu items: Dashboard, Monitoring (highlighted with a red box), Configuration, Administration, and Troubleshooting. The main area is titled 'Clients' and has three tabs: 'Clients' (highlighted with a red box), 'Sleeping Clients', and 'Excluded Clients'. Below the tabs is a blue 'Delete' button with a red box around it. The text 'Total Client(s) in the Network: 1' is displayed above a table. The table has columns for Client MAC Address, IPv4/IPv6 Address, and AP Name. One row is shown with MAC address e4:b3:18:7c:30:58, IP address 172.16.1.253, and AP Name 3702-02. A green checkmark in a box is visible in the first column of this row. At the bottom of the table, there is a pagination control showing '1' items per page.

Solução

Nenhum, comportamento normal iniciado pelo usuário.

Cliente desconectado devido ao tempo limite de EAP

Exemplo de log

```

YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [errmsg] [8681]: (note): %DOT1X-5-FAIL: Authentication
failed for client (0874.0277.1345) with reason (Timeout) on Interface capwap_90800003
AuditSessionID 34AD580A0000000D7F735399
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Authc failure from Dot1X, Auth event timeout
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] (Re)try failed method Dot1X - 0874.0277.1345
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Retrying (count 3) method dot1x
.
.
.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-sm] [8681]: (info): MAC: 0874.0277.1345
Deleting the client, reason: 7, CO_CLIENT_DELETE_REASON_CONNECT_TIMEOUT, Client state
S_CO_L2_AUTH_IN_PROGRESS

```

```

YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-sm] [8681]: (note): MAC: 0874.0277.1345
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_CONNECT_TIMEOUT
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-state] [8681]: (note): MAC:
0874.0277.1345 Client state transition: S_CO_L2_AUTH_IN_PROGRESS -> S_CO_DELETE_IN_PROGRESS
.
.
.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [mm-transition] [8681]: (info): MAC: 0874.0277.1345
MMIF FSM transition: S_MA_INIT -> S_MA_LOCAL_DELETE_PROCESSED_TR on E_MA_CO_DELETE_RCVD
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [mm-client] [8681]: (ERR): MAC: 0874.0277.1345 Client
not present in DB. Responding to CO with Delete Ack
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [wncd_2] [8681]: (info): Sanet App Event
EV_SESSION_DELETE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Disconnect request from SANET-SHIM (12) for 0874.0277.1345 /
0x30000003 - term: supplicant-restart, abort: Unknown, disc: authorization failure
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-auth] [8681]: (info): MAC: 0874.0277.1345
Client auth-interface state transition: S_AUTHIF_DOT1XAUTH_PENDING -> S_SANET_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [dot11] [8681]: (info): MAC: 0874.0277.1345 Sent
deauth to client, deauth reason: 252, CLIENT_DEAUTH_REASON_ADMIN_RESET delete reason: 7,
CO_CLIENT_DELETE_REASON_CONNECT_TIMEOUT.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [dot11] [8681]: (info): MAC: 0874.0277.1345 DOT11
state transition: S_DOT11_ASSOCIATED -> S_DOT11_DELETED
.
.
.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-auth] [8681]: (info): MAC: 0874.0277.1345
Client auth-interface state transition: S_SANET_DELETE_IN_PROGRESS -> S_AUTHIF_DELETED
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [wncd_2] [8681]: (info): Sanet eventQ: EAP_CORE_MQ,
message:2
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-state] [8681]: (note): MAC:
0874.0277.1345 Client state transition: S_CO_DELETE_IN_PROGRESS -> S_CO_DELETED

```

Razão

O cliente não está respondendo ao pacote EAP enviado pela WLC 9800 dentro do intervalo de tempo limite de solicitação EAP nem os tempos de Tentativas máximas de solicitação EAP.

Soluções possíveis

- Atualize os drivers do cliente sem fio para o mais recente
- Garantir que o cliente sem fio confie no certificado RADIUS
- Aumente o tempo limite de solicitação EAP e/ou as tentativas máximas de solicitação EAP

CLI:

```

# config t
# wireless security dot1x request retries <0-20>
# wireless security dot1x timeout <1-120 seconds>

```

GUI:

Navegue até **Configuration > Security > Advanced EAP** e personalize as configurações necessárias.

Cliente desconectado devido à reinicialização do rádio AP

Exemplo de log

```

YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [apmgr-capwap-config] [8621]: (info): f07f.06ee.f590
Radio: 1 is Operationally DOWN.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [apmgr-db] [8621]: (note): MAC: f07f.06ee.f590 Radio 1
is disabled, on receiving change state event message from AP
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [radio-history-reset] [8621]: (info): Radio reset of
the AP f07f.06ee.f590 Slot:1 Band:802.11a due to Cause:0, Detailed Cause : 56 - Interface UP for
Channel Change
YYYY/DD/MM HH:MM:SS.xxx {mobilityd_R0-0}{1}: [mm-transition] [19496]: (info): MAC:
e4b3.187c.3058 MMFSM transition: S_MC_RUN -> S_MC_HANDOFF_END_RCVD_TR on E_MC_HANDOFF_END_RCVD
from WNCID[1]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-sm] [8621]: (info): MAC: e4b3.187c.3058
Deleting the client, reason: 5, CO_CLIENT_DELETE_REASON_BSSID_DOWN, Client state S_CO_RUN
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-sm] [8621]: (note): MAC: e4b3.187c.3058
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_BSSID_DOWN
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-state] [8621]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_DELETE_IN_PROGRESS
.
.
.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [dpath_svc] [8621]: (note): MAC: e4b3.187c.3058 Client
datapath entry deleted for ifid 0xfa000001
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [mm-transition] [8621]: (info): MAC: e4b3.187c.3058
MMIF FSM transition: S_MA_LOCAL -> S_MA_DELETE_PROCESSED_TR on E_MA_CO_DELETE_RCVD
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [mm-client] [8621]: (ERR): MAC: e4b3.187c.3058 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [wncd_1] [8621]: (info): Sanet App Event
EV_SESSION_DELETE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [auth-mgr] [8621]: (info):
[e4b3.187c.3058:capwap_90400003] Disconnect request from SANET-SHIM (12) for e4b3.187c.3058 /
0xf89000008 - term: service-unavailable, abort: Unknown, disc: session disconnect
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-auth] [8621]: (info): MAC: e4b3.187c.3058
Client auth-interface state transition: S_AUTHIF_PSK_AUTH_DONE -> S_SANET_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [dot11] [8621]: (info): MAC: e4b3.187c.3058 Sent
deauth to client, deauth reason: 252, CLIENT_DEAUTH_REASON_ADMIN_RESET delete reason: 5,
CO_CLIENT_DELETE_REASON_BSSID_DOWN.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [dot11] [8621]: (info): MAC: e4b3.187c.3058 DOT11
state transition: S_DOT11_ASSOCIATED -> S_DOT11_DELETED

```

Razão

O AP ao qual o cliente foi associado para alterar o canal ou a alimentação, causando uma reinicialização do rádio.

Soluções possíveis

- Este é um comportamento normal
- Você pode configurar com que frequência a WLC 9800 pode fazer alterações de canal

CLI:

```

# config t
# ap dot11 { 5ghz | 24ghz } rrm channel dca interval <0-24>

Valid values 1,2,3,4,6,8,12 and 24 hours, 0 = 10 minutes (default)

```

GUI:

Navegue até **Configuração > Configurações de rádio > RRM > Banda de 5 GHz / Banda de 2,4 GHz > DCA > Aumentar configuração de intervalo**

Cliente desconectado devido ao tempo limite de autenticação da Web

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Authc failure from WebAuth, Auth event no-response
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [wncd_2] [8681]: (info): Sanet eventQ: AUTH_MGR_MQ,
message:6
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [wncd_2] [8681]: (info): Sanet App Event
EV_SESSION_AUTHC_FAILED
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] AUTHC_FAIL - unauthorize by default
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [9800 WLC-infra-evq] [8681]: (ERR): Authc failure for
mac 0874.0277.1345, username , audit session id 34AD580A0000000E7FFA4ED8, Failure reason: No
Response from Client
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Signalling Authc fail for client 0874.0277.1345
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [errmsg] [8681]: (note): %SESSION_MGR-5-FAIL:
Authorization failed or unapplied for client (0874.0277.1345) on Interface capwap_90800003
AuditSessionID 34AD580A0000000E7FFA4ED8. Failure reason: Authc fail. Authc failure reason: No
Response from Client.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Authz failed/unapplied for 0x08000004 (0874.0277.1345), method:
webauth. Signal switch PI.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [wncd_2] [8681]: (info): Sanet App Event
EV_SESSION_AUTHZ_FAILED
.
.
.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-auth] [8681]: (info): MAC: 0874.0277.1345
Client auth-interface state transition: S_AUTHIF_WEBAUTH_PENDING -> S_AUTHIF_WEBAUTH_PENDING
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-auth] [8681]: (ERR): MAC: 0874.0277.1345 L3
Authentication FAIL.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-auth] [8681]: (info): MAC: 0874.0277.1345
Client auth-interface state transition: S_AUTHIF_WEBAUTH_PENDING -> S_WAIT_FOR_CO_DELETE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [9800 WLC-infra-evq] [8681]: (ERR): WLAN profile =
prof-name, Policy profile = default-policy-profile, AP name = AP1702-05
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-sm] [8681]: (info): MAC: 0874.0277.1345
Deleting the client, reason: 0, CO_CLIENT_DELETE_REASON_NONE, Client state
S_CO_L3_AUTH_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-sm] [8681]: (note): MAC: 0874.0277.1345
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_NONE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-orch-state] [8681]: (note): MAC:
0874.0277.1345 Client state transition: S_CO_L3_AUTH_IN_PROGRESS -> S_CO_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [9800 WLC-qos-client] [8681]: (ERR): MAC:
0874.0277.1345 Fail to get qos lib ctxt while handle sip cac on client delete
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [multicast-main] [8681]: (info): MAC: 0874.0277.1345
No Flex/Fabric main record exists for client
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-iplearn] [8681]: (info): MAC: 0874.0277.1345
IP-learn state transition: S_IPLEARN_COMPLETE -> S_IPLEARN_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [dpath_svc] [8681]: (note): MAC: 0874.0277.1345 Client
datapath entry deleted for ifid 0xfa000002
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [mm-transition] [8681]: (info): MAC: 0874.0277.1345
MMIF FSM transition: S_MA_LOCAL -> S_MA_DELETE_PROCESSED_TR on E_MA_CO_DELETE_RCVD
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [mm-client] [8681]: (ERR): MAC: 0874.0277.1345 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [wncd_2] [8681]: (info): Sanet App Event
EV_SESSION_DELETE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [auth-mgr] [8681]: (info):
[0874.0277.1345:capwap_90800003] Disconnect request from SANET-SHIM (12) for 0874.0277.1345 /
0x08000004 - term: none, abort: Unknown, disc: (default)
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [aaa-attr-inf] [8681]: (info): [ Applied attribute
:bsn-vlan-interface-name 0 "VLAN2602" ]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [aaa-attr-inf] [8681]: (info): [ Applied attribute :
```



```
timeout 0 1800 (0x708) ]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [client-auth] [8681]: (info): MAC: 0874.0277.1345
Client auth-interface state transition: S_WAIT_FOR_CO_DELETE -> S_SANET_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {mobilityd_R0-0}{1}: [mm-transition] [19496]: (info): MAC:
0874.0277.1345 MMFSM transition: S_MC_RUN -> S_MC_HANDOFF_END_RCVD_TR on E_MC_HANDOFF_END_RCVD
from WNCd[2]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-2}{1}: [dot11] [8681]: (info): MAC: 0874.0277.1345 DOT11
state transition: S_DOT11_ASSOCIATED -> S_DOT11_DELETED
```

Razão

O cliente não concluiu a autenticação da Web dentro do tempo permitido (cerca de 120 segundos)

Solução

- Verifique se os clientes concluem a autenticação da Web em 120 segundos

Cliente desconectado devido ao tempo limite da sessão

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-auth] [8621]: (info): MAC: e4b3.187c.3058
Client auth-interface state transition: S_AUTHIF_PSK_AUTH_DONE -> S_SANET_DELETED
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-sm] [8621]: (info): MAC: e4b3.187c.3058
Deleting the client, reason: 23, CO_CLIENT_DELETE_REASON_SESSION_TIMEOUT, Client state S_CO_RUN
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-sm] [8621]: (note): MAC: e4b3.187c.3058
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_SESSION_TIMEOUT
YYYY/DD/MM HH:MM:SS.xxx {mobilityd_R0-0}{1}: [mm-transition] [19496]: (info): MAC:
e4b3.187c.3058 MMFSM transition: S_MC_RUN -> S_MC_HANDOFF_END_RCVD_TR on E_MC_HANDOFF_END_RCVD
from WNCd[1]
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-state] [8621]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [9800 WLC-qos-client] [8621]: (ERR): MAC:
e4b3.187c.3058 Fail to get qos lib ctxt while handle sip cac on client delete
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [multicast-main] [8621]: (info): MAC: e4b3.187c.3058
No Flex/Fabric main record exists for client
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-iplearn] [8621]: (info): MAC: e4b3.187c.3058
IP-learn state transition: S_IPLEARN_COMPLETE -> S_IPLEARN_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [dpath_svc] [8621]: (note): MAC: e4b3.187c.3058 Client
datapath entry deleted for ifid 0xfa0000001
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [mm-transition] [8621]: (info): MAC: e4b3.187c.3058
MMIF FSM transition: S_MA_LOCAL -> S_MA_DELETE_PROCESSED_TR on E_MA_CO_DELETE_RCVD
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [mm-client] [8621]: (ERR): MAC: e4b3.187c.3058 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-auth] [8621]: (info): MAC: e4b3.187c.3058
Client auth-interface state transition: S_SANET_DELETED -> S_AUTHIF_DELETED
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [dot11] [8621]: (info): MAC: e4b3.187c.3058 Sent
deauth to client, deauth reason: 252, CLIENT_DEAUTH_REASON_ADMIN_RESET delete reason: 23,
CO_CLIENT_DELETE_REASON_SESSION_TIMEOUT.
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [dot11] [8621]: (info): MAC: e4b3.187c.3058 DOT11
state transition: S_DOT11_ASSOCIATED -> S_DOT11_DELETED
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-state] [8621]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_DELETE_IN_PROGRESS -> S_CO_DELETED
```

Razão

O cliente atingiu seu tempo limite de sessão

Soluções possíveis

- Este é um comportamento normal
- Aumentar o tempo limite da sessão do perfil de política associada ao SSID

CLI:

```
# config t
# wireless profile policy <policy-profile-name>
# shutdown
# session-timeout <20-86400 seconds>
# no shutdown
```

GUI:

Navegue até **Configuration > Tags & Profiles > Policy > Policy Profile Name > Advanced > WLAN Timeout** e personalize os temporizadores conforme necessário.

Cliente desconectado devido ao tempo limite de ociosidade

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [7807]: (note): MAC: e4b3.187c.3058
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_MN_IDLE_TIMEOUT
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [7807]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-qos-client] [7807]: (ERR): MAC:
e4b3.187c.3058 Fail to get qos lib ctxt while handle sip cac on client delete
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dpath_svc] [7807]: (note): MAC: e4b3.187c.3058 Client
datapath entry deleted for ifid 0xfa000002
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [mm-client] [7807]: (ERR): MAC: e4b3.187c.3058 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [7807]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_DELETE_IN_PROGRESS -> S_CO_DELETED
```

Razão

O cliente não enviou tráfego (ou tráfego suficiente) dentro do intervalo configurado de tempo limite de ociosidade.

Soluções possíveis

- Este é um comportamento normal
- Personalizar as configurações de ociosidade do perfil de política associadas ao SSID

CLI:

```
# config t
# wireless profile policy <policy-profile-name>
# shutdown
# idle-timeout <15-100000 seconds>
# idle-threshold <0-4294967295 bytes>
# no shutdown
```

GUI:

Navegue até **Configuration > Tags & Profiles > Policy > Policy Profile Name > Advanced > WLAN Timeout** e personalize a configuração de ociosidade conforme necessário.

Observação: se você não configurar um limite de ociosidade, o cliente precisará enviar qualquer quantidade de tráfego dentro do período de tempo limite de ociosidade para não ser desconectado. Se você configurar um limite de ociosidade, o cliente deverá enviar essa quantidade de bytes dentro do intervalo de ociosidade para não ser desconectado (isto é, você configura um limite de ociosidade de 10 bytes e um limite de ociosidade de 30 segundos, os clientes sem fio precisam enviar pelo menos 10 bytes de tráfego a cada 30 segundos para não serem desconectados da rede).

Cliente movido entre SSIDs

Exemplo de log

```
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [7807]: (note): MAC: e4b3.187c.3058
Association received. BSSID f07f.06ee.f59d, old BSSID f07f.06ee.f59e, WLAN 1, Slot 1 AP
f07f.06ee.f590, 3702-02
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [7807]: (ERR): MAC: e4b3.187c.3058
Failed to start dot11 processing. Failed to populate client record in DB
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [7807]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_RUN
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-sm] [7807]: (note): MAC: e4b3.187c.3058
Client delete initiated. Reason: CO_CLIENT_DELETE_REASON_WLAN_CHANGE
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [7807]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_RUN -> S_CO_DELETE_IN_PROGRESS
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [9800 WLC-qos-client] [7807]: (ERR): MAC:
e4b3.187c.3058 Fail to get qos lib ctxt while handle sip cac on client delete
YYYY/DD/MM HH:MM:SS.xxx {fman_fp_F0-0}{1}: [wireless-client] [10254]: UUID: 1000000006930, ra: 5
(note): WLCLIENT 0xa0000002 pd_hdl 0x33 AOM delete succeeded
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [dpath_svc] [7807]: (note): MAC: e4b3.187c.3058 Client
datapath entry deleted for ifid 0xfa0000002
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [mm-client] [7807]: (ERR): MAC: e4b3.187c.3058 Invalid
transmitter ip in build client context
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-0}{1}: [client-orch-state] [7807]: (note): MAC:
e4b3.187c.3058 Client state transition: S_CO_DELETE_IN_PROGRESS -> S_CO_DELETED
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-sm] [8009]: (note): MAC: e4b3.187c.3058
Association received. BSSID 00c8.8b26.d79d, old BSSID 0000.0000.0000, WLAN 1, Slot 1 AP
00c8.8b26.d790, AP-1700-x
YYYY/DD/MM HH:MM:SS.xxx {wncd_x_R0-1}{1}: [client-orch-state] [8009]: (note): MAC:
e4b3.187c.3058 Client state transition: client_orch_sm_state__none -> S_CO_ASSOCIATING
```

Razão

O cliente foi conectado a um SSID e movido para outro.

Soluções possíveis

- Comportamento normal
- Remova o 2º SSID do cliente