

访问SPA500系列IP电话上的基于Web的设置页

目标

所有设备都具有内置的设置页面，允许用户自定义设置并设置设备中的高级属性。设置页面可轻松配置设备的功能。本文档显示如何访问SPA500系列IP电话的设置页。

适用设备

·SPA 500系列IP电话

访问SPA设备设置页面的步骤。

注意：尽管本文也适用于所有SPA 500系列IP电话，但使用的设备是SPA509G。

注意：在访问SPA509G的设置页之前，请确保设备通过其SW端口连接到启用PoE（以太网供电）的路由器或交换机。

访问SPA509G的设置页

步骤1. IP电话打开后，会执行网络配置和设置配置。完成网络配置后，按“Setup（设置）”按钮（上面是纸质符号），如图所示。



步骤2.这将在IP电话的LCD上显示“设置”菜单，其中包含不同的选项。



步骤3.按3。这将在液晶屏上显示“设置”菜单。



步骤4.按5。这将打开液晶屏上的“网络配置”菜单。

步骤5.向下导航至选项3或按3。请注意，IP地址显示在“IP地址”下方。

步骤6.转到Web浏览器并输入IP地址。

注意：计算机和IP电话应位于同一网络上才能访问基于Web的实用程序。

The screenshot shows the Cisco SPA509G Configuration Utility interface. At the top, there are tabs for 'Voice' (highlighted in green), 'Call History', 'Personal Directory', and 'Attendant Console Status'. Below these are sub-tabs: 'Info' (highlighted in blue), 'System', 'Phone', and 'User'. The main content area is divided into sections: 'System Information', 'Product Information', and 'Phone Status'. In 'System Information', details include Connection Type: DHCP, Host Name: SEPC89C1D6E6F6F, Current Netmask: 255.255.255.0, Primary DNS: 192.168.137.1, Secondary DNS: (empty). On the right, Current IP: 192.168.137.162, Domain: mshome.net, and Current Gateway: 192.168.137.1 are listed. In 'Product Information', Product Name: SPA509G, Software Version: 7.4.8a, MAC Address: C89C1D6E6F6F, Customization: Open, Serial Number: CBT151508BR, Hardware Version: 1.0.2(0001), Client Certificate: Installed, and Licenses: None. In 'Phone Status', Current Time: 1/1/2003 14:27:55, Elapsed Time: 02:13:56, Broadcast Pkts Sent: 21, Broadcast Bytes Sent: 2138, Broadcast Pkts Recv: 353, and Broadcast Bytes Recv: 36800 are shown. At the bottom, there are 'Undo All Changes' and 'Submit All Changes' buttons.

步骤7.将显示基于Web的设置实用程序。如果没有显示，则计算机和IP电话可能未连接到同一网络。从计算机ping IP电话的IP地址以检查连接。