

MRA与未提供的服务的呼叫失效

Contents

[Introduction](#)

[Prerequisites](#)

[Requirements](#)

[Components Used](#)

[问题](#)

[解决方案](#)

Introduction

本文描述如何排除移动和远程访问(MRA)故障，当呼叫发生故障由于“503项服务未提供的”错误时。

贡献用Ishan Sambhi，Cisco TAC工程师。

Prerequisites

Requirements

Cisco建议您有下个题目知识：

- Cisco视频通信服务器(VCS)或ExpresswayC和ExpresswayE platform
- Cisco Unified Communications管理器(CUCM)

The information in this document was created from the devices in a specific lab environment.All of the devices used in this document started with a cleared (default) configuration.如果您的网络实际，请保证您了解所有命令的潜在影响。

Components Used

This document is not restricted to specific software and hardware versions.

The information in this document was created from the devices in a specific lab environment.All of the devices used in this document started with a cleared (default) configuration.如果您的网络实际，请保证您了解所有命令的潜在影响。

问题

在两个Jabber客户端之间的呼叫注册对CUCM通过MRA失效与未提供错误信息“503的服务”

呼叫流：

Jabber client1 > ExpresswayE > ExpresswayC > CUCM > ExpresswayC > ExpresswayE > Jabber client2

Note:在呼叫流， Jabber client1和Jabber client2，注册对同样MRA配置，在CUCM前后，意味着Expressway对是相同的。

解决方案

会话初始化协议(SIP)邀请从CUCM去ExpresswayC

```
2014-06-06T10:27:20+10:00 kcec tvcs: UTCTime="2014-06-06 00:27:20,782" Module="network.sip"
Level="DEBUG": Action="Received" Local-ip="10.200.1.220" Local-port="5060" Src-
ip="10.200.1.210" Src-port="49071" Msg-Hash="12136618272786736242"
SIPMSG:
|INVITE sip:80d713ba-514d-fc2a-6b7e-af527f9eb37f@10.200.1.220:5060;transport=tcp;orig-
hostport=10.100.94.116:58991 SIP/2.0
Via: SIP/2.0/TCP 10.200.1.210:5060;branch=z9hG4bK4ca27d4986
Call-ID: 50f2a980-39110ae8-1fb3-d201c80a@10.200.1.210
CSeq: 101 INVITE
Remote-Party-ID: "Jabber client 1" <sip:sip%3Ajabber.client1@domain.com;x-cisco-number=168;x-
cisco-callback-number=168>;party=calling;screen=yes;privacy=off
Contact: <sip:sip%3Ajabber.client1i@10.200.1.210:5060;transport=tcp>
From: "Jabber Client 1" <sip:sip%3Ajabber.client1@domain.com>;tag=132472~2b8aa2ec-85b4-4b2c-
b662-3d078784a480-27388704
To: <sip:jabber.client2@10.200.1.210>
Max-Forwards: 70
Allow: INVITE,OPTIONS,INFO,BYE,CANCEL,ACK,PRACK,UPDATE,REFER,SUBSCRIBE,NOTIFY
User-Agent: Cisco-CUCM9.1
Expires: 180
Date: Fri, 06 Jun 2014 00:27:20 GMT
Supported: timer,resource-priority,replaces
Min-SE: 1800
Allow-Events: presence
Send-Info: conference,x-cisco-conference
Call-Info: <urn:x-cisco-remotecallinfo>; security= NotAuthenticated; orientation= from; gci=
1-7197; call-instance= 2
Alert-Info: <file://Bellcore-dr1/>
Content-Length: 0
```

ExpresswayC设法调用呼叫许可证。

```
Module="network.http" Level="DEBUG": Message="Request" Method="POST"
URL="http://127.0.0.1:4370/status/call/call/uid/86cc754d-ee2-4202-aa07-ea89c8afc47d";
Ref="0x7fd3780034e0"
Module="network.http" Level="DEBUG": Message="Response" Src-ip="127.0.0.1" Src-port="4370" Dst-
ip="127.0.0.1" Dst-port="32769" Response="200 OK" ResponseTime="0.002091" Ref="0x7fd3780034e0"
Module="developer.licensemanager.service.licensepool" Level="INFO"
CodeLocation="licensepool(818)" Detail="Call license limit reached"license_type="nontraversal"
tokens="2" cluster_token_inuse="0" cluster_token_limit="0"
Module="developer.licensemanager.service.licensepool" Level="INFO"
CodeLocation="licensepool(818)" Detail="Call license limit reached"license_type="traversal"
tokens="2" cluster_token_inuse="0" cluster_token_limit="0"
Module="developer.licensemanager.service.manager" Level="INFO"
CodeLocation="licensemanager(155)" Detail="License not granted" call_id="6355985b-0d26-4a48-
8b24-balac5de38c6" lic_type="nontraversal" tokens=2 licensemanager: Level="INFO" Detail="License
not granted" call_id="6355985b-0d26-4a48-8b24-balac5de38c6" lic_type="nontraversal" tokens=2
UTCTime="2014-06-06 00:27:20,799"
Module="network.http" Level="DEBUG": Message="Response" Src-ip="127.0.0.1" Src-port="9999" Dst-
ip="127.0.0.1" Dst-port="32516" Response="200 OK" ResponseTime="0.012601" Ref="0x7fd366097b00"
Event="Search Completed" Reason="Service Unavailable" Service="SIP" Src-alias-type="SIP" Src-
alias="sip%3Ajabber.client1@domain.com" Dst-alias-type="SIP" Dst-alias="sip:80d713ba-514d-fc2a-
```

```
6b7e-af527f9eb37f@10.100.94.116:58991;transport\=tls" Call-serial-number="86cc754d-eec2-4202-aa07-ea89c8afc47d" Tag="92f548cb-a8a6-4339-8b3b-814cb85ae25a" Detail="found:false, searchtype:INVITE, Info:No License Available" Level="1" UTCTime="2014-06-06 00:27:20,800" Event="Call Rejected" Service="SIP" Src-ip="10.200.1.210" Src-port="5060" Src-alias-type="SIP" Src-alias="sip:sip%3Ajabber.client1@domain.com" Dst-alias-type="SIP" Dst-alias="sip:80d713ba-514d-fc2a-6b7e-af527f9eb37f@10.100.94.116:58991;transport\=tls" Call-serial-number="86cc754d-eec2-4202-aa07-ea89c8afc47d" Tag="92f548cb-a8a6-4339-8b3b-814cb85ae25a" Detail="Service Unavailable" Protocol="TCP" Response-code="503" Level="1" UTCTime="2014-06-06 00:27:20,801" Module="network.sip" Level="INFO": Action="Sent" Local-ip="10.200.1.220" Local-port="5060" Dst-ip="10.200.1.210" Dst-port="49071" Detail="Sending Response Code=503, Method=INVITE, CSeq=101, To=sip:168@10.200.1.210, Call-ID=50f2a980-39110ae8-1fb3-d201c80a@10.200.1.210, From-Tag=132472~2b8aa2ec-85b4-4b2c-b662-3d078784a480-27388704, To-Tag=111a6c358c828b39, Msg-Hash=17852441825048296421"
```

尽管没有可用的许可证，ExpresswayC回复以错误“未提供的服务”

```
2014-06-06T10:27:20+10:00 kcec tvcs: UTCTime="2014-06-06 00:27:20,801" Module="network.sip" Level="DEBUG": Action="Sent" Local-ip="10.200.1.220" Local-port="5060" Dst-ip="10.200.1.210" Dst-port="49071" Msg-Hash="17852441825048296421" SIPMSG: |SIP/2.0 503 Service Unavailable Via: SIP/2.0/TCP 10.200.1.210:5060;branch=z9hG4bK4ca27d4986;received=10.200.1.210;ingress-zone=CEtcp102001210 Call-ID: 50f2a980-39110ae8-1fb3-d201c80a@10.200.1.210 CSeq: 101 INVITE From: "Jabber Client 1" <sip:sip%3Ajabber.client1@domain.com>;tag=132472~2b8aa2ec-85b4-4b2c-b662-3d078784a480-27388704 To: <sip:jabber.client2@10.200.1.210>;tag=111a6c358c828b39 Server: TANDBERG/4129 (X8.1.1) Warning: 399 10.200.1.220:5061 "No License Available" Content-Length: 0
```

呼叫发生故障，因为没找到一个可用的许可证，但是在同样CUCM注册的两个Jabber客户端之间的一次呼叫通过MRA不要求在ExpresswayC的任何许可证。当ExpresswayC统一的通信穿越区域指向ExpresswayE内部IP地址对ExpresswayE公共IP地址时，此问题发生。

在单个NIC ExpresswayE配置，必须指向统一的通信穿越区域ExpresswayE的公共IP地址，并且必须配置有在ExpresswayE和互联网之间的防火墙网络地址转换(NAT)反映允许ExpresswayC和ExpresswayE之间的通信。