

语音电话服务提供商调试

目录

[简介](#)

[开始使用前](#)

[规则](#)

[先决条件](#)

[使用的组件](#)

[T.38 debug vtsp all 命令显示传真编码下载](#)

[VoFR debug vtsp all 命令的运作示例](#)

[始发路由器](#)

[终结路由器](#)

[相关信息](#)

简介

本文档提供了成功传递了传真的一个呼叫的 debug vtsp all 命令的两个输出。第一个输出针对 T.38 传真，但也与 IP 语音 (VoIP) 上的传真中继有关。此输出包含的注释用于说明确定已下载并使用传真编解码器的过程。第二段解码针对 Voice over Frame Relay (VoFR)，并且未加注释。debug vtsp all 输出不包含太多 T.30 协议方面的信息，但确实提供了有用的路由器状态信息，例如：

- 路由器已进入传真模式的确认
- 传真速率、编解码器以及是否使用了纠错模式 (ECM)
- 终端网关从终端传真机接收到传真音的确认

开始使用前

规则

有关文档规则的详细信息，请参阅 [Cisco 技术提示规则](#)。

先决条件

本文档没有任何特定的前提条件。

使用的组件

本文档中的信息主要基于 Cisco IOS 软件版本 12.2(5)，但其中的大部分信息对于其他 Cisco IOS 软件版本应该同样有用。

本文档中的信息都是基于特定实验室环境中的设备创建的。本文档中使用的所有设备最初均采用原始（默认）配置。如果您是在真实网络上操作，请确保您在使用任何命令前已经了解其潜在影响。

T.38 debug vtsp all 命令显示传真编码下载

对于 T.38 传真中继，在呼叫已连接并且路由器检测到传真音调试后，将显示类似下面的消息。

debug vtsp all 命令

```
!--- Prior to the ccCallConnect message and during the
capabilities !--- exchange phase, the fax_rate message
may be displayed as follows: .Jun 4 21:06:43.677:
cc_api_caps_ack (dstVdbPtr=0x62F07650, dstCallId=0x18,
srcCallId=0x19, caps={codec=0x4, fax_rate=0x2, vad=0x2,
modem=0x0 codec_bytes=20, signal_type=2}) !--- In this
case the fax rate 0x02 refers to the voice rate, which
!--- with this codec (g.729), is less than or equal to 8
kbps. !--- Listed below are the other possible fax rate
values. !--- Below is a listing of fax rate values for
Cisco IOS Software Release 12.2.x or earlier: !--- hex
value fax rate value !--- 0x2 Voice !--- 0x4 14400 !---
0x8 9600 !--- 0x10 7200 !--- 0x20 4800 !--- 0x40 2400 !-
-- 0x80 1200 !--- Below is a listing of new fax rate
values for Cisco IOS Software Release 12.3.x or later:
!--- Note the hex values now map to slightly different
speeds than the list above. !--- !--- #define
CC_CAP_FAX_NONE 0x01 !--- #define CC_CAP_FAX_VOICE 0x02
!--- #define CC_CAP_FAX_24 0x04 !--- #define
CC_CAP_FAX_48 0x08 !--- #define CC_CAP_FAX_72 0x10 !---
#define CC_CAP_FAX_96 0x20 !--- #define CC_CAP_FAX_120
0x40 !--- #define CC_CAP_FAX_144 0x80 !--- Usually,
after the call is connected, the ccCallConnect debug !-
- message is seen as follows: .Jun 4 21:06:44.841:
ccCallConnect (callID=0x18), prog_ind = 0 .Jun 4
21:06:44.841: ssaFlushPeerTagQueue cid(24) peer list:
(empty) .Jun 4 21:06:47.437: vtsp_process_dsp_message:
MSG_TX_GET_TX_STAT: rtp_timestamp=0xD4D85071 .Jun 4
21:06:47.437: vtsp:[4/0:15 (25), S_CONNECT,
E_DSP_GET_TX] .Jun 4 21:06:49.049:
vtsp_process_dsp_message: MSG_TX_GET_TX_STAT:
rtp_timestamp=0xD4D882D1 .Jun 4 21:06:49.049:
vtsp:[4/0:15 (25), S_CONNECT, E_DSP_GET_TX] .Jun 4
21:06:50.129: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=1 tone_id=0 .Jun 4
21:06:50.129: vtsp:[4/0:15 (25), S_CONNECT,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.129:
vtsp_modem_proto_from_cdb: cap_modem_proto 0 .Jun 4
21:06:50.129: cc_api_call_feature: (vdbPtr=0x63387EDC,
callID=0x19,feature_ind.type=1 .Jun 4 21:06:50.129:
act_lfax_switch: cap_modem_proto=16, fax_relay_on=1,
state=19 .Jun 4 21:06:50.129: vtsp_t38_switchover:2 -
data_mode:1 !--- Note that 2 means T.38; 1 means Cisco
proprietary. .Jun 4 21:06:50.129: cc_api_t38_fax_start
(dstVdbPtr=0x62F07650, dstCallId=0x18, srcCallId=0x19,
caps={codec=0x10000, fax_rate=0x2, vad=0x2, modem=0x0
codec_bytes=20, signal_type=2}) .Jun 4 21:06:50.129:
vtsp_timer: 20362254 .Jun 4 21:06:50.129: sess_appl:
ev(28=CC_EV_CALL_FEATURE), cid(25), disp(0) .Jun 4
21:06:50.129:
cid(25)st(SSA_CS_ACTIVE)ev(SSA_EV_CALL_FEATURE)
oldst(SSA_CS_CONFERENCED_ALERT)cfid(8)csize(0)in(0)fDest
(0) .Jun 4 21:06:50.129: -
cid2(24)st2(SSA_CS_ACTIVE)oldst2
(SSA_CS_CONFERENCING_ALERT) .Jun 4 21:06:50.129:
```

```
ccCallFeature (callID=0x18, feature.type=1) .Jun 4
21:06:50.249: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=0 tone_id=0 .Jun 4
21:06:50.249: vtsp:[4/0:15 (25), S_LFAX_WAIT_CAPS_ACK,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.249:
vtsp_process_event(): prev_state = 0.11 , state =
S_LFAX_WAIT_CAPS_ACK, event = E_DSP_TONE_DETECT .Jun 4
21:06:50.389: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=1 tone_id=0 .Jun 4
21:06:50.389: vtsp:[4/0:15 (25), S_LFAX_WAIT_CAPS_ACK,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.389:
vtsp_process_event(): prev_state = 0.11 , state =
S_LFAX_WAIT_CAPS_ACK, event = E_DSP_TONE_DETECT .Jun 4
21:06:50.489: vtsp_process_dsp_message:
MSG_TX_TONE_DETECT: type=0 trigger=0 tone_id=0 .Jun 4
21:06:50.489: vtsp:[4/0:15 (25), S_LFAX_WAIT_CAPS_ACK,
E_DSP_TONE_DETECT] .Jun 4 21:06:50.489:
vtsp_process_event(): prev_state = 0.11 , state =
S_LFAX_WAIT_CAPS_ACK, event = E_DSP_TONE_DETECT Invalid
FSM Input on channel 4/0:15 (25) .Jun 4 21:06:50.529:
cc_api_t38_fax_start (dstVdbPtr=0x63387EDC,
dstCallId=0x19, srcCallId=0x18, caps={codec=0x10000,
fax_rate=0x2, vad=0x2, modem=0x0 codec_bytes=160,
signal_type=2}) .Jun 4 21:06:50.529: vtsp:[4/0:15 (25),
S_LFAX_WAIT_CAPS_ACK, E_CC_T38_START] .Jun 4
21:06:50.529: act_caps_ack_lfax_dnld .Jun 4
21:06:50.529: vtsp_timer_stop: 20362294 .Jun 4
21:06:50.529: dsp_idle_mode: [4/0:15 (25)] packet_len=8
channel_id=1 packet_id=68 .Jun 4 21:06:50.529:
vtsp:[4/0:15 (25), S_LFAX_DOWNLOAD,
E_DSPRM_PEND_SUCCESS] .Jun 4 21:06:50.529: act_lfax_mode
.Jun 4 21:06:50.529: cc_api_local_codec_dnld_done
(dstVdbPtr=0x62F07650, dstCallId=0x18, srcCallId=0x19)
!--- The previous three messages confirm that the fax
codec was successfully !--- downloaded into the DSP. You
may not see all the messages above !--- and below. The
important point is that you do not see error !---
messages saying that the fax codec was not downloaded
correctly. .Jun 4 21:06:50.529: vtsp_timer: 20362294
.Jun 4 21:06:50.929: cc_api_t38_fax_start
(dstVdbPtr=0x63387EDC, dstCallId=0x19, srcCallId=0x18,
caps={codec=0x10000, fax_rate=0x2, vad=0x2, modem=0x0
codec_bytes=160, signal_type=2}) .Jun 4 21:06:50.929:
cc_api_remote_codec_dnld_done (dstVdbPtr=0x63387EDC,
dstCallId=0x19, srcCallId=0x18) .Jun 4 21:06:50.929:
vtsp:[4/0:15 (25), S_LFAX_WAIT_FAX, E_CC_T38_START] .Jun
4 21:06:50.929: vtsp:[4/0:15 (25), S_LFAX_WAIT_FAX,
E_CC_T30_CAP_ACK] .Jun 4 21:06:50.929: act_t38_lfax_mode
.Jun 4 21:06:50.929: vtsp_timer_stop: 20362334 .Jun 4
21:06:50.929: dsp_idle_mode: [4/0:15 (25)] packet_len=8
channel_id=1 packet_id=68 .Jun 4 21:06:50.929:
dsp_encap_config: T38 .Jun 4 21:06:50.929: dsp_fax_mode:
[4/0:15 (25)] FaxRate 0x2, Codec 0x10000 dsp_fax_mode()
ECM_DISABLE not set, debug_info requested .Jun 4
21:06:50.929: dsp_fax_mode: [] packet_len=28
channel_id=1 packet_id=69 max_trans=3 info_size=20,
fax_protocol_type=3, ls_data_red=0, hs_data_red=0,
tcf_handling=2, fax_relay_cntl=0x2 nsf_country = 0xAD,
nsf_mfg = 0x0051 !--- During the fax transmission the
Cisco IOS Software polls the DSP !--- statistics
periodically, and the following message appears: .Jun 4
21:06:50.929: vtsp:[4/0:15 (25), S_FAX, E_DSP_GET_TX
```

不同版本的 Cisco IOS 软件中的跟踪消息可能看起来不同，但您应该始终能够根据“FAX”关键字后面的输出来了解是否已正确加载传真编解码器以及使用的传真协议。

如果传真编解码器未正确加载，则可能存在软件问题。确保使用最新的维护版本，如果仍有问题，请通过技术支持中心 (TAC) 建立一个案例。

[VoFR debug vtsp all 命令的运作示例](#)

始发路由器

debug vtsp all - 始发路由器

```
vdtl-2600-2d#
Jun  5 10:10:34.053: vtsp_tsp_call_setup_ind
(sdb=0x81FD48DC, tdm_info=0x0,
 tsp_info=0x81FF74DC, calling_number= calling_oct3 =
0x0,
 called_number= called_oct3 = 0x81, oct3a=0x0):
peer_tag=0
Jun  5 10:10:34.053: : ev.clg.clir is 0
ev.clg.clid_transparent
 is 0 ev.clg.null_orig_clg is 1
ev.clg.calling_translated is false

Jun  5 10:10:34.057: vtsp_do_call_setup_ind
Jun  5 10:10:34.057: vtsp_allocate_cdb,cdb 0x821D9344
Jun  5 10:10:34.057: vtsp_do_call_setup_ind: Call
ID=65589, guid=821D9874
Jun  5 10:10:34.057: vtsp_do_call_setup_ind: type=0,
under_spec=-2119571356,
 name=f<0HNhf< 1=@, id0=1, id1=1, id2=-32567, calling=,
 called= subscriber=RegularLine
Jun  5 10:10:34.057: vtsp_do_normal_call_setup_ind
Jun  5 10:10:34.057: vtsp_insert_cdb,cdb 0x821D9344
Jun  5 10:10:34.057: vtsp_open_voice_and_set_params
Jun  5 10:10:34.057: dsp_close_voice_channel: [1/1:0:27]
packet_len=8
 channel_id=2 packet_id=75
Jun  5 10:10:34.057: dsp_open_voice_channel_20:
[1/1:0:27] packet_len=16
 channel_id=2 packet_id=74 alaw_ulaw_select=0
 associated_signaling_channel=129 time_slot=1
serial_port=0
Jun  5 10:10:34.057: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun  5 10:10:34.057: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun  5 10:10:34.057: dsp_encap_config: [1/1:0:27]
packet_len=30
 channel_id=2 packet_id=92 TransportProtocol 2
t_ssrc=0x0 r_ssrc=0x0
 t_vpxcc=0x0 r_vpxcc=0x0 sid_support=1,
tse_payload=65535, seq_num=0x0,
 redundancy=0
Jun  5 10:10:34.061: dsp_set_playout_delay
Jun  5 10:10:34.061: dsp_set_playout: [1/1:0:27]
packet_len=18
 channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
```

```
dsp_set_playout_delay_config
Jun  5 10:10:34.061: dsp_set_playout_config
Jun  5 10:10:34.061: mode 0, init 60, min 40, max 200
playout default

Jun  5 10:10:34.061: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:34.061: dsp_set_playout_config: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:34.061: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:34.061: dsp_echo_canceler_control:
[1/1:0:27] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:34.061: dsp_echo_canceler_control:
[1/1:0:27] packet_len=10
  channel_id=2 packet_id=66 flags=0x0
Jun  5 10:10:34.061: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:34.061: dsp_set_gains: [1/1:0:27]
packet_len=12
  channel_id=2 packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:34.061: dsp_vad_enable: [1/1:0:27] enable:
packet_len=12
  channel_id=2 packet_id=78 thresh=-38
Jun  5 10:10:34.061: vtsp_report_digit_control:
  enable=1: digit reporting enabled
Jun  5 10:10:34.061: : vtsp_get_digit_timeouts
Jun  5 10:10:34.065: vtsp:[1/1:0:27, S_SETUP_INDICATED,
E_CC_SETUP_ACK]
Jun  5 10:10:34.065: act_setup_ind_ack
Jun  5 10:10:34.065: vtsp_modem_proto_from_cdb:
cap_modem_proto 0
Jun  5 10:10:34.065: vtsp_modem_proto_from_cdb:
cap_modem_proto 0
Jun  5 10:10:34.065: dsp_encap_config: [1/1:0:27]
packet_len=30
  channel_id=2 packet_id=92 TransportProtocol 2
t_ssrc=0x0 r_ssrc=0x0
  t_vpxcc=0x0 r_vpxcc=0x0 sid_support=1,
tse_payload=65535, seq_num=0x0,
  redundancy=0
Jun  5 10:10:34.065: dsp_voice_mode: [1/1:0:27] cdb
821D9344,
  cdb->codec_params.modem 2, inband_detect flags 0x21
Jun  5 10:10:34.065: map_dtmf_relay_type--digit relay
mode: 2
Jun  5 10:10:34.065: dsp_voice_mode: [1/1:0:27]
packet_len=24
  channel_id=2 packet_id=73 coding_type=1
voice_field_size=80 VAD_flag=0
  echo_length=64 comfort_noise=1 inband_detect=33
digit_relay_mode=2
  AGC_flag=0act_setup_ind_ack: modem_mode = 0,
fax_relay_on = 1
Jun  5 10:10:34.065: act_setup_ind_ack():
  dsp_dtmf_mode()dsp_dtmf_mode(VTSP_TONE_DTMF_MODE)

Jun  5 10:10:34.065: dsp_dtmf_mode: [1/1:0:27]
packet_len=10
  channel_id=2 packet_id=65 dtmf_or_mf=0
Jun  5 10:10:34.065: vtsp_timer: 43525550
```

```
Jun  5 10:10:34.065: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_CC_GEN_TONE]
Jun  5 10:10:34.065: act_gen_tone
Jun  5 10:10:34.065: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:34.065: dsp_cp_tone_on: [1/1:0:27]
packet_len=38
  channel_id=2 packet_id=72 tone_id=4 n_freq=2
freq_of_first=350
  freq_of_second=440 amp_of_first=5514 amp_of_second=5514
direction=1
  on_time_first=65535 off_time_first=0 on_time_second=0
off_time_second=0
Jun  5 10:10:34.065: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_CC_GEN_TONE]
Jun  5 10:10:34.069: act_gen_tone
Jun  5 10:10:34.069: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:34.069: dsp_cp_tone_on: [1/1:0:27]
packet_len=38
  channel_id=2 packet_id=72 tone_id=4 n_freq=2
freq_of_first=350
  freq_of_second=440 amp_of_first=5514 amp_of_second=5514
direction=1
  on_time_first=65535 off_time_first=0 on_time_second=0
off_time_second=0
Jun  5 10:10:35.544: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=4,
rtp_timestamp=0xD455BA67

Jun  5 10:10:35.544: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:35.544: act_report_digit_begin
Jun  5 10:10:35.612: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=4, duration=120
Jun  5 10:10:35.616: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_DSP_DTMF_DIGIT]
Jun  5 10:10:35.616: act_report_digit_end
Jun  5 10:10:35.616: vtsp_timer_stop: 43525705
Jun  5 10:10:35.616: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:35.616: vtsp_timer: 43525705
Jun  5 10:10:35.732: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=0,
rtp_timestamp=0xD455BA67
Jun  5 10:10:35.732: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:35.732: act_report_digit_begin
Jun  5 10:10:35.792: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=0, duration=110
Jun  5 10:10:35.792: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
E_DSP_DTMF_DIGIT]
Jun  5 10:10:35.792: act_report_digit_end
Jun  5 10:10:35.792: vtsp_timer_stop: 43525722
Jun  5 10:10:35.796: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:35.796: vtsp_timer: 43525723
Jun  5 10:10:35.933: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=0,
rtp_timestamp=0xD455BA67
```

```
Jun  5 10:10:35.933: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:35.933: act_report_digit_begin
Jun  5 10:10:36.005: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=0, duration=120
Jun  5 10:10:36.005: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT]
Jun  5 10:10:36.005: act_report_digit_end
Jun  5 10:10:36.005: vtsp_timer_stop: 43525744
Jun  5 10:10:36.005: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:36.005: vtsp_timer: 43525744
Jun  5 10:10:36.133: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_BEGIN: digit=1,
  rtp_timestamp=0xD455BA67
Jun  5 10:10:36.133: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT_BEGIN]
Jun  5 10:10:36.133: act_report_digit_begin
Jun  5 10:10:36.193: vtsp_process_dsp_message:
  MSG_TX_DTMF_DIGIT_OFF: digit=1, duration=110
Jun  5 10:10:36.193: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_DSP_DTMF_DIGIT]
Jun  5 10:10:36.193: act_report_digit_end
Jun  5 10:10:36.193: vtsp_timer_stop: 43525762
Jun  5 10:10:36.193: dsp_cp_tone_off: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=71
Jun  5 10:10:36.193: vtsp_timer: 43525762
Jun  5 10:10:36.197: vtsp_report_digit_control:
  enable=0: digit reporting disabled
Jun  5 10:10:36.197: : vtsp_get_digit_timeouts
Jun  5 10:10:36.197: vtsp_save_dialpeer_tag: tag = 4001
Jun  5 10:10:36.197: vtsp:[1/1:0:27, S_DIGIT_COLLECT,
  E_CC_PROCEEDING]
Jun  5 10:10:36.197: act_dcollect_proc
Jun  5 10:10:36.205: vtsp_get_dialpeer_tag: tag = 4001
Jun  5 10:10:36.890: vtsp_get_dialpeer_tag: tag = 4001
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
  E_CC_PROGRESS]
Jun  5 10:10:36.890: act_progress
Jun  5 10:10:36.890: vtsp_timer_stop: 43525832
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
  E_CC_BRIDGE]
Jun  5 10:10:36.890: act_bridge
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
  E_CC_CAPS_IND]
Jun  5 10:10:36.890: act_caps_ind
Jun  5 10:10:36.890: act_caps_ind: passthrough:
  cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.890: act_caps_ind:CC_CAP_ENCAP_FRF11
  Encap 2, Vad 2,
  Codec 0x4, CodecBytes 30, FaxRate 2, FaxBytes 30,
  FaxNsf 0xAD0051
  Sub-channel 8, Bitmask 0x0 SignalType 2, SeqNumStart
  0x0
Jun  5 10:10:36.890: act_caps_ind: [ mode:0,init:60,
  min:40, max:200]
Jun  5 10:10:36.890: vtsp:[1/1:0:27, S_PROCEEDING,
  E_CC_CAPS_ACK]
Jun  5 10:10:36.890: act_caps_ack
Jun  5 10:10:36.894: act_caps_ack: passthrough:
  cap_modem_proto 0,
```

```
cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.894: dsp_idle_mode: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=68
Jun  5 10:10:36.894: act_caps_ack: codec = 16, ret = 2
Jun  5 10:10:36.894: vtsp_timer: 43525833
Jun  5 10:10:36.894: vtsp:[1/1:0:27, S_NULL,
E_DSPRM_PEND_SUCCESS]
Jun  5 10:10:36.894: act_pend_codec_success
Jun  5 10:10:36.894: vtsp_timer_stop: 43525833
Jun  5 10:10:36.894: vtsp_open_voice_and_set_params
Jun  5 10:10:36.894: dsp_close_voice_channel: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=75
Jun  5 10:10:36.894: dsp_open_voice_channel_20:
[1/1:0:27] packet_len=16
  channel_id=2 packet_id=74 alaw_ulaw_select=0
  associated_signaling_channel=129 time_slot=1
  serial_port=0
Jun  5 10:10:36.894: dsp_encap_config: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=92 TransportProtocol 3
  SID_support=0
  sequence_number=0 rotate_flag=0 header_bytes 0x80
Jun  5 10:10:36.894: dsp_set_playout_delay
Jun  5 10:10:36.894: dsp_set_playout: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
  dsp_set_playout_delay_config
Jun  5 10:10:36.894: dsp_set_playout_config
Jun  5 10:10:36.894: mode 0, init 60, min 40, max 200
playout default
Jun  5 10:10:36.894: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:36.894: dsp_set_playout_config: [1/1:0:27]
packet_len=18
  channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:36.894: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:36.894: dsp_echo_canceler_control:
[1/1:0:27] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:36.898: dsp_echo_canceler_control:
[1/1:0:27] packet_len=10
  channel_id=2 packet_id=66 flags=0x0
Jun  5 10:10:36.898: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:36.898: dsp_set_gains: [1/1:0:27]
packet_len=12
  channel_id=2 packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:36.898: dsp_vad_enable: [1/1:0:27] enable:
packet_len=12
  channel_id=2 packet_id=78 thresh=-38
Jun  5 10:10:36.898: dsp_voice_mode: [1/1:0:27] cdb
821D9344,
  cdb->codec_params.modem 0, inband_detect flags 0x1
Jun  5 10:10:36.898: map_dtmf_relay_type--digit relay
mode: 2
Jun  5 10:10:36.898: dsp_voice_mode: [1/1:0:27]
packet_len=24
  channel_id=2 packet_id=73 coding_type=19
voice_field_size=30
```



```
VAD_flag=250 echo_length=64 comfort_noise=1
inband_detect=1
  digit_relay_mode=2 AGC_flag=0
Jun  5 10:10:43.024: vtsp_get_dialpeer_tag: tag = 4001
Jun  5 10:10:43.024: vtsp:[1/1:0:27, S_PROCEEDING,
E_CC_CONNECT]
Jun  5 10:10:43.024: act_connect
Jun  5 10:10:43.024: vtsp_ring_noan_timer_stop: 43526446

Jun  5 10:10:48.710: vtsp:[1/1:0:27, S_CONNECT,
E_PH_CODEC_FAX]
Jun  5 10:10:48.710: act_rfax_switch
Jun  5 10:10:48.710: dsp_idle_mode: [1/1:0:27]
packet_len=8
  channel_id=2 packet_id=68
Jun  5 10:10:48.710: vtsp_timer_stop: 43527014
Jun  5 10:10:48.910: vtsp:[1/1:0:27, S_RFAX_DOWNLOAD,
E_DSPRM_PEND_SUCCESS]
Jun  5 10:10:48.910: act_rfax_mode
Jun  5 10:10:48.910: vtsp:[1/1:0:27, S_RFAX_WAIT_ACK,
E_PH_CODEC_ACK]
Jun  5 10:10:48.910: act_wait_ack_ack
Jun  5 10:10:48.910: vtsp_timer_stop: 43527034
Jun  5 10:10:48.914: dsp_fax_mode: [1/1:0:27] FaxRate
0x2, Codec 0x4
  dsp_fax_mode() ECM_DISABLE not set, debug_info not
requested
Jun  5 10:10:48.914: dsp_fax_mode: [1/1:0:27]
packet_len=28
  channel_id=2 packet_id=69 max_trans=3 info_size=30,
fax_protocol_type=2,
  hs_data_len=0, ls_data_red=0, hs_data_red=0,
tcf_handling=0,
fax_relay_cntl=0x0 nsf_country = 0xAD, nsf_mfg = 0x0051
  !--- fax codecs: enum { !--- DSP_TELELOGY_FAX = 1, !---
DSP_FRF11_FAX, !--- DSP_T38_FAX vdt1-2600-2d# vdt1-2600-
2d# vdt1-2600-2d# Jun  5 10:11:21.516:
vtsp_process_dsp_message: MSG_TX_FAX_CLEARDOWN: Jun  5
10:11:21.516: vtsp:[1/1:0:27, S_FAX,
E_DSP_FAX_CLEARDOWN] Jun  5 10:11:21.516:
act_fax_to_voice Jun  5 10:11:21.516: vtsp_timer_stop:
43530295 Jun  5 10:11:21.520: dsp_idle_mode: [1/1:0:27]
packet_len=8 channel_id=2 packet_id=68 Jun  5
10:11:21.520: dsp_close_voice_channel: [1/1:0:27]
packet_len=8 channel_id=2 packet_id=75act_fax_to_voice
codec= 16 Jun  5 10:11:21.520: vtsp_timer: 43530295 Jun  5
10:11:21.520: vtsp:[1/1:0:27, S_FAX_TERM,
E_DSPRM_PEND_SUCCESS] Jun  5 10:11:21.520:
vtsp_timer_stop: 43530295 Jun  5 10:11:21.520:
act_fax_complete Jun  5 10:11:21.520:
vtsp_open_voice_and_set_params Jun  5 10:11:21.520:
dsp_close_voice_channel: [1/1:0:27] packet_len=8
channel_id=2 packet_id=75 Jun  5 10:11:21.520:
dsp_open_voice_channel_20: [1/1:0:27] packet_len=16
channel_id=2 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=129 time_slot=1
serial_port=0 Jun  5 10:11:21.520: dsp_encap_config:
[1/1:0:27] packet_len=18 channel_id=2 packet_id=92
TransportProtocol 3 SID_support=0 sequence_number=0
rotate_flag=0 header_bytes 0x80 Jun  5 10:11:21.520:
dsp_set_playout_delay Jun  5 10:11:21.520:
dsp_set_playout: [1/1:0:27] packet_len=18 channel_id=2
packet_id=76 mode=1 initial=60 min=40 max=200
fax_nom=300 dsp_set_playout_delay_config Jun  5
```

```
10:11:21.520: dsp_set_playout_config Jun 5 10:11:21.520:
mode 0, init 60, min 40, max 200 playout default Jun 5
10:11:21.520: dsp_set_playout_config:mode 0, init 60,
min 40, max 200 Jun 5 10:11:21.520:
dsp_set_playout_config: [1/1:0:27] packet_len=18
channel_id=2 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300 Jun 5 10:11:21.520:
dsp_echo_canceler_control: echo_cancel: 1 Jun 5
10:11:21.520: dsp_echo_canceler_control: [1/1:0:27]
echo_cancel 1, disable_hpf 0, flags=0x0 Jun 5
10:11:21.525: dsp_echo_canceler_control: [1/1:0:27]
packet_len=10 channel_id=2 packet_id=66 flags=0x0 Jun 5
10:11:21.525: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0 Jun 5 10:11:21.525:
dsp_set_gains: [1/1:0:27] packet_len=12 channel_id=2
packet_id=91 in_gain=0 out_gain=0 Jun 5 10:11:21.525:
dsp_vad_enable: [1/1:0:27] enable: packet_len=12
channel_id=2 packet_id=78 thresh=-38 Jun 5 10:11:21.525:
dsp_voice_mode: [1/1:0:27] cdb 821D9344, cdb-
>codec_params.modem 0, inband_detect flags 0x1 Jun 5
10:11:21.525: map_dtmf_relay_type--digit relay mode: 2
Jun 5 10:11:21.525: dsp_voice_mode: [1/1:0:27]
packet_len=24 channel_id=2 packet_id=73 coding_type=19
voice_field_size=30 VAD_flag=250 echo_length=64
comfort_noise=1 inband_detect=1 digit_relay_mode=2
AGC_flag=0 Jun 5 10:11:24.033: vtsp:[1/1:0:27,
S_CONNECT, E_TSP_DISCONNECT_IND] Jun 5 10:11:24.033:
act_generate_disc Jun 5 10:11:24.033:
vtsp_ring_noan_timer_stop: 43530546 Jun 5 10:11:24.033:
vtsp_timer_stop: 43530546 Jun 5 10:11:24.033:
vtsp_pcm_tone_detect_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_pcm_switchover_timer_stop: 43530546
Jun 5 10:11:24.033: vtsp:[1/1:0:27, S_CONNECT,
E_CC_BRIDGE_DROP] Jun 5 10:11:24.033: act_bdrop Jun 5
10:11:24.033: vtsp:[1/1:0:27, S_CONNECT,
E_CC_DISCONNECT] Jun 5 10:11:24.033: act_disconnect Jun
5 10:11:24.033: vtsp_ring_noan_timer_stop: 43530546 Jun
5 10:11:24.033: vtsp_pcm_tone_detect_timer_stop:
43530546 Jun 5 10:11:24.033:
vtsp_pcm_switchover_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_cot_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_timer_stop: 43530546 Jun 5
10:11:24.033: vtsp_timer: 43530546 Jun 5 10:11:24.037:
vtsp:[1/1:0:27, S_WAIT_STATS, E_DSP_GET_ERROR] Jun 5
10:11:24.037: act_get_error Jun 5 10:11:24.037:
1/1:0:27: rx_dropped=0 tx_dropped=0 rx_control=51
tx_control=14 tx_control_dropped=0 dsp_mode_channel_1=0
dsp_mode_channel_2=2 c[0]=68 c[1]=3 c[2]=10 c[3]=69
c[4]=68 c[5]=75 c[6]=75 c[7]=74 c[8]=92 c[9]=76 c[10]=76
c[11]=66 c[12]=91 c[13]=78 c[14]=73 c[15]=6 Jun 5
10:11:24.037: dsp_get_levels: [1/1:0:27] packet_len=8
channel_id=2 packet_id=89 Jun 5 10:11:24.041:
vtsp:[1/1:0:27, S_WAIT_STATS, E_DSP_GET_LEVELS] Jun 5
10:11:24.041: act_get_levels Jun 5 10:11:24.045:
vtsp_process_dsp_message: MSG_TX_GET_TX_STAT:
rtp_timestamp=0xFD908919 Jun 5 10:11:24.045:
vtsp:[1/1:0:27, S_WAIT_STATS, E_DSP_GET_TX] Jun 5
10:11:24.049: act_stats_complete Jun 5 10:11:24.049:
vtsp_timer_stop: 43530548 Jun 5 10:11:24.049:
vtsp_ring_noan_timer_stop: 43530548 Jun 5 10:11:24.049:
dsp_idle_mode: [1/1:0:27] packet_len=8 channel_id=2
packet_id=68 Jun 5 10:11:24.049: vtsp_timer: 43530548
Jun 5 10:11:24.850: vtsp:[1/1:0:27, S_WAIT_RELEASE,
E_TSP_CALL_FEATURE_IND] Jun 5 10:11:24.850:
```

```
act_call_feature_ind Jun 5 10:11:24.850: vtsp:[1/1:0:27,
S_WAIT_RELEASE, E_TSP_DISCONNECT_CONF] Jun 5
10:11:24.850: act_wrelease_release Jun 5 10:11:24.850:
vtsp_timer_stop: 43530628 Jun 5 10:11:24.854:
dsp_cp_tone_off: [1/1:0:27] packet_len=8 channel_id=2
packet_id=71 Jun 5 10:11:24.854: dsp_idle_mode:
[1/1:0:27] packet_len=8 channel_id=2 packet_id=68 Jun 5
10:11:24.854: dsp_close_voice_channel: [1/1:0:27]
packet_len=8 channel_id=2
packet_id=75vtsp_do_call_historyvtsp_do_call_history
CoderRate 20 Jun 5 10:11:24.854: vtsp:[1/1:0:27,
S_CLOSE_DSPRM, E_DSPRM_CLOSE_COMPLETE] Jun 5
10:11:24.854: act_terminate Jun 5 10:11:24.854:
vtsp_free_cdb,cdb 0x821D9344 vdtl-2600-2d#
```

终结路由器

debug vtsp all - 终端路由器

```
vdtl-7200-2c#
Jun 5 10:10:36.200: vtsp_do_call_setup_req
Jun 5 10:10:36.200: vtsp_allocate_cdb,cdb 0x620F01FC
Jun 5 10:10:36.200: vtsp_insert_cdb,cdb 0x620F01FC
Jun 5 10:10:36.200: vtsp_do_call_setup_req calling oct3
0x0, called oct3 0x0
Jun 5 10:10:36.200: vtsp_do_call_setup_req: Call ID=55,
guid=62F8AC6C
Jun 5 10:10:36.200: digit_strip:1, pcn:4001, poa:4001
Jun 5 10:10:36.200: pcn:, poa:
Jun 5 10:10:36.200: Final pcn:, poa:, dial_string:
Jun 5 10:10:36.200: calling oct3 0x0, called oct3 0x0
Jun 5 10:10:36.200: vtsp:[2/1:0 (39), S_SETUP_REQUEST,
E_TSP_PROCEEDING]
Jun 5 10:10:36.200: act_setup_pend_proceeding
Jun 5 10:10:36.200: vtsp_open_voice_and_set_params
Jun 5 10:10:36.200: dsp_close_voice_channel: [2/1:0
(39)] packet_len=8
channel_id=1 packet_id=75
Jun 5 10:10:36.200: dsp_open_voice_channel_20: [2/1:0
(39)] packet_len=16
channel_id=1 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=128 time_slot=0
serial_port=0
Jun 5 10:10:36.200: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun 5 10:10:36.204: vtsp_modem_proto_from_cdb:
cap_modem_proto 1073741824
Jun 5 10:10:36.204: dsp_encap_config: [2/1:0 (39)]
packet_len=30
channel_id=1 packet_id=92 TransportProtocol 2
t_ssrc=0x0 r_ssrc=0x0
t_vpxcc=0x0 r_vpxcc=0x0 sid_support=1,
tse_payload=65535, seq_num=0x0,
redundancy=0
Jun 5 10:10:36.204: dsp_set_playout_delay
Jun 5 10:10:36.204: dsp_set_playout: [2/1:0 (39)]
packet_len=18
channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
dsp_set_playout_delay_config
Jun 5 10:10:36.204: dsp_set_playout_config
Jun 5 10:10:36.204: mode 0, init 60, min 40, max 200
playout default
```

```
Jun  5 10:10:36.204: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:36.204: dsp_set_playout_config: [2/1:0
(39)] packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:36.204: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:36.204: dsp_echo_canceler_control: [2/1:0
(39)] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:36.204: dsp_echo_canceler_control: [2/1:0
(39)] packet_len=10
  channel_id=1 packet_id=66 flags=0x0
Jun  5 10:10:36.204: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:36.204: dsp_set_gains: [2/1:0 (39)]
packet_len=12
  channel_id=1 packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:36.204: dsp_vad_enable: [2/1:0 (39)]
enable: packet_len=12
  channel_id=1 packet_id=78 thresh=-38
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_TSP_PROGRESS]
Jun  5 10:10:36.888: act_setup_pend_progress
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_CC_BRIDGE]
Jun  5 10:10:36.888: act_bridge
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_CC_CAPS_IND]
Jun  5 10:10:36.888: act_caps_ind
Jun  5 10:10:36.888: act_caps_ind: passthrough:
cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.888: act_caps_ind:CC_CAP_ENCAP_FRF11
Encap 2, Vad 2,
  Codec 0x4, CodecBytes 30,
    FaxRate 2, FaxBytes 30, FaxNsf 0xAD0051
    Sub-channel 8, Bitmask 0x0
    SignalType 2, SeqNumStart 0x0
Jun  5 10:10:36.888: act_caps_ind: [ mode:0,init:60,
min:40, max:200]
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_CC_CAPS_ACK]
Jun  5 10:10:36.888: act_caps_ack
Jun  5 10:10:36.888: act_caps_ack: passthrough:
cap_modem_proto 0,
  cap_modem_codec 0, cap_modem_redundancy 0, payload 0
Jun  5 10:10:36.888: dsp_idle_mode: [2/1:0 (39)]
packet_len=8
  channel_id=1 packet_id=68
Jun  5 10:10:36.888: act_caps_ack: codec = 16, ret = 2

Jun  5 10:10:36.888: vtsp_timer: 94714681
Jun  5 10:10:36.888: vtsp:[2/1:0 (39), S_NULL,
E_DSPRM_PEND_SUCCESS]
Jun  5 10:10:36.888: act_pend_codec_success
Jun  5 10:10:36.888: vtsp_timer_stop: 94714681
Jun  5 10:10:36.888: vtsp_open_voice_and_set_params
Jun  5 10:10:36.888: dsp_close_voice_channel: [2/1:0
(39)] packet_len=8
  channel_id=1 packet_id=75
```

```
Jun  5 10:10:36.888: dsp_open_voice_channel_20: [2/1:0
(39)] packet_len=16
  channel_id=1 packet_id=74 alaw_ulaw_select=0
  associated_signaling_channel=128 time_slot=0
serial_port=0
Jun  5 10:10:36.888: dsp_encap_config: [2/1:0 (39)]
packet_len=18
  channel_id=1 packet_id=92 TransportProtocol 3
SID_support=0
  sequence_number=0 rotate_flag=0 header_bytes 0x80
Jun  5 10:10:36.888: dsp_set_playout_delay
Jun  5 10:10:36.888: dsp_set_playout: [2/1:0 (39)]
packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
  dsp_set_playout_delay_config
Jun  5 10:10:36.888: dsp_set_playout_config
Jun  5 10:10:36.888: mode 0, init 60, min 40, max 200
playout default

Jun  5 10:10:36.888: dsp_set_playout_config:mode 0, init
60, min 40, max 200
Jun  5 10:10:36.888: dsp_set_playout_config: [2/1:0
(39)] packet_len=18
  channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300
Jun  5 10:10:36.888: dsp_echo_canceler_control:
echo_cancel: 1
Jun  5 10:10:36.888: dsp_echo_canceler_control: [2/1:0
(39)] echo_cancel 1,
  disable_hpf 0, flags=0x0
Jun  5 10:10:36.888: dsp_echo_canceler_control: [2/1:0
(39)] packet_len=10
  channel_id=1 packet_id=66 flags=0x0
Jun  5 10:10:36.888: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0
Jun  5 10:10:36.888: dsp_set_gains: [2/1:0 (39)]
packet_len=12 channel_id=1
  packet_id=91 in_gain=0 out_gain=0
Jun  5 10:10:36.888: dsp_vad_enable: [2/1:0 (39)]
enable: packet_len=12
  channel_id=1 packet_id=78 thresh=-38
Jun  5 10:10:36.888: dsp_voice_mode: [2/1:0 (39)] cdb
620F01FC,
  cdb->codec_params.modem 0, inband_detect flags 0x1
Jun  5 10:10:36.888: map_dtmf_relay_type--digit relay
mode: 2
Jun  5 10:10:36.888: dsp_voice_mode: [2/1:0 (39)]
packet_len=24
  channel_id=1 packet_id=73 coding_type=19
voice_field_size=30 VAD_flag=250
  echo_length=64 comfort_noise=1
  inband_detect=1 digit_relay_mode=2 AGC_flag=0
Jun  5 10:10:43.024: vtsp:[2/1:0 (39), S_SETUP_REQ_PROC,
E_TSP_CONNECT]
Jun  5 10:10:43.024: act_setup_pend_connect
Jun  5 10:10:43.024: vtsp_ring_noan_timer_stop: 94715294
Jun  5 10:10:43.024: dsp_cp_tone_off: [2/1:0 (39)]
packet_len=8
  channel_id=1 packet_id=71

Jun  5 10:10:48.492: vtsp_process_dsp_message:
  MSG_TX_TONE_DETECT: type=0 trigger=1 tone_id=0
Jun  5 10:10:48.492: vtsp:[2/1:0 (39), S_CONNECT,
```

```
E_DSP_TONE_DETECT]
Jun  5 10:10:48.492: vtsp_modem_proto_from_cdb:
cap_modem_proto 0
Jun  5 10:10:48.492: act_lfax_switch:
cap_modem_proto=16,
fax_relay_on=1, state=19
!--- sys/if/dsp_cntl_msgs.h * Definitions for the tone
detect !--- */ !--- #define TONE_TYPE_V_21 0x0000 !---
#define TONE_TYPE_CED 0x0001 !--- #define TONE_TYPE_CNG
0x0002 !--- #define TONE_SDT_DISC 0x0003 !--- #define
TONE_TYPE_COT 0x0004 !--- #define TONE_TYPE_MODEM 0x0005
!--- #define SILENCE_DETECTED 0x0006 !--- #define
VOICE_DETECTED 0x0007 !--- #define DUAL_TONE_DETECTED
0x0008 !--- #define SEQ_TONE_DETECTED 0x0009 !---
#define TONE_DETECT_ON 0x0001 !--- #define
TONE_DETECT_OFF ~TONE_DETECT_ Jun 5 10:10:48.492:
vtsp_timer: 94715841 Jun 5 10:10:48.492: vtsp:[2/1:0
(39), S_LFAX_WAIT_ACK, E_PH_CODEEC_ACK] Jun 5
10:10:48.492: act_lfax_download Jun 5 10:10:48.492:
vtsp_timer_stop: 94715841 Jun 5 10:10:48.492:
dsp_idle_mode: [2/1:0 (39)] packet_len=8 channel_id=1
packet_id=68 Jun 5 10:10:48.492: vtsp:[2/1:0 (39),
S_LFAX_DOWNLOAD, E_DSPRM_PEND_SUCCESS] Jun 5
10:10:48.492: act_lfax_mode Jun 5 10:10:48.492:
vtsp:[2/1:0 (39), S_LFAX_WAIT_FAX, E_PH_CODEEC_FAX] Jun 5
10:10:48.492: act_wait_fax_fax ph_set_codec_ack Jun 5
10:10:48.492: dsp_fax_mode: [2/1:0 (39)] FaxRate 0x2,
Codec 0x4 dsp_fax_mode() ECM_DISABLE not set, debug_info
not requested Jun 5 10:10:48.492: dsp_fax_mode: [2/1:0
(39)] packet_len=28 channel_id=1 packet_id=69
max_trans=3 info_size=30, fax_protocol_type=2,
hs_data_len=0, ls_data_red=0, hs_data_red=0,
tcf_handling=0, fax_relay_cntl=0x0 nsf_country = 0xAD,
nsf_mfg = 0x0051 vdt1-7200-2c# vdt1-7200-2c# vdt1-7200-
2c# Jun 5 10:11:21.736: vtsp_process_dsp_message:
MSG_TX_FAX_CLEARDOWN: Jun 5 10:11:21.740: vtsp:[2/1:0
(39), S_FAX, E_DSP_FAX_CLEARDOWN] Jun 5 10:11:21.740:
act_fax_to_voice Jun 5 10:11:21.740: vtsp_timer_stop:
94719166 Jun 5 10:11:21.740: dsp_idle_mode: [2/1:0 (39)]
packet_len=8 channel_id=1 packet_id=68 Jun 5
10:11:21.740: dsp_close_voice_channel: [2/1:0 (39)]
packet_len=8 channel_id=1 packet_id=75 act_fax_to_voice
codec= 16 Jun 5 10:11:21.740: vtsp_timer: 94719166 Jun 5
10:11:21.740: vtsp:[2/1:0 (39), S_FAX_TERM,
E_DSPRM_PEND_SUCCESS] Jun 5 10:11:21.740:
vtsp_timer_stop: 94719166 Jun 5 10:11:21.740:
act_fax_complete Jun 5 10:11:21.740:
vtsp_open_voice_and_set_params Jun 5 10:11:21.740:
dsp_close_voice_channel: [2/1:0 (39)] packet_len=8
channel_id=1 packet_id=75 Jun 5 10:11:21.740:
dsp_open_voice_channel_20: [2/1:0 (39)] packet_len=16
channel_id=1 packet_id=74 alaw_ulaw_select=0
associated_signaling_channel=128 time_slot=0
serial_port=0 Jun 5 10:11:21.740: dsp_encap_config:
[2/1:0 (39)] packet_len=18 channel_id=1 packet_id=92
TransportProtocol 3 SID_support=0 sequence_number=0
rotate_flag=0 header_bytes 0x80 Jun 5 10:11:21.740:
dsp_set_playout_delay Jun 5 10:11:21.740:
dsp_set_playout: [2/1:0 (39)] packet_len=18 channel_id=1
packet_id=76 mode=1 initial=60 min=40 max=200
fax_nom=300 dsp_set_playout_delay_config Jun 5
10:11:21.740: dsp_set_playout_config Jun 5 10:11:21.740:
mode 0, init 60, min 40, max 200 playout default Jun 5
10:11:21.740: dsp_set_playout_config: mode 0, init 60,
```

```
min 40, max 200 Jun 5 10:11:21.740:
dsp_set_playout_config: [2/1:0 (39)] packet_len=18
channel_id=1 packet_id=76 mode=1 initial=60 min=40
max=200 fax_nom=300 Jun 5 10:11:21.740:
dsp_echo_canceler_control: echo_cancel: 1 Jun 5
10:11:21.740: dsp_echo_canceler_control: [2/1:0 (39)]
echo_cancel 1, disable_hpf 0, flags=0x0 Jun 5
10:11:21.740: dsp_echo_canceler_control: [2/1:0 (39)]
packet_len=10 channel_id=1 packet_id=66 flags=0x0 Jun 5
10:11:21.740: sgf: FXx/E&M: msg-
>message.set_codec_gains.out_gain=0 Jun 5 10:11:21.740:
dsp_set_gains: [2/1:0 (39)] packet_len=12 channel_id=1
packet_id=91 in_gain=0 out_gain=0 Jun 5 10:11:21.740:
dsp_vad_enable: [2/1:0 (39)] enable: packet_len=12
channel_id=1 packet_id=78 thresh=-38 Jun 5 10:11:21.740:
dsp_voice_mode: [2/1:0 (39)] cdb 620F01FC, cdb-
>codec_params.modem 0, inband_detect flags 0x1 Jun 5
10:11:21.740: map_dtmf_relay_type--digit relay mode: 2
Jun 5 10:11:21.740: dsp_voice_mode: [2/1:0 (39)]
packet_len=24 channel_id=1 packet_id=73 coding_type=19
voice_field_size=30 VAD_flag=250 echo_length=64
comfort_noise=1 inband_detect=1 digit_relay_mode=2
AGC_flag=0 Jun 5 10:11:24.036: vtsp:[2/1:0 (39),
S_CONNECT, E_CC_BRIDGE_DROP] Jun 5 10:11:24.036:
act_bdrop Jun 5 10:11:24.036: vtsp:[2/1:0 (39),
S_CONNECT, E_CC_DISCONNECT] Jun 5 10:11:24.036:
act_disconnect Jun 5 10:11:24.036:
vtsp_ring_noan_timer_stop: 94719396 Jun 5 10:11:24.036:
vtsp_pcm_tone_detect_timer_stop: 94719396 Jun 5
10:11:24.036: vtsp_pcm_switchover_timer_stop: 94719396
Jun 5 10:11:24.036: vtsp_cot_timer_stop: 94719396 Jun 5
10:11:24.036: vtsp_timer_stop: 94719396 Jun 5
10:11:24.036: vtsp_timer: 94719396 Jun 5 10:11:24.036:
vtsp:[2/1:0 (39), S_WAIT_STATS, E_DSP_GET_ERROR] Jun 5
10:11:24.036: act_get_error Jun 5 10:11:24.036: 2/1:0
(39): rx_dropped=1 tx_dropped=0 rx_control=39
tx_control=5 tx_control_dropped=0 dsp_mode_channel_1=2
dsp_mode_channel_2=0 c[0]=0 c[1]=0 c[2]=73 c[3]=71
c[4]=68 c[5]=69 c[6]=68 c[7]=75 c[8]=75 c[9]=74 c[10]=92
c[11]=76 c[12]=76 c[13]=66 c[14]=91 c[15]=78 Jun 5
10:11:24.036: dsp_get_levels: [2/1:0 (39)] packet_len=8
channel_id=1 packet_id=89 Jun 5 10:11:24.036:
vtsp:[2/1:0 (39), S_WAIT_STATS, E_DSP_GET_LEVELS] Jun 5
10:11:24.036: act_get_levels Jun 5 10:11:24.040:
vtsp_process_dsp_message: MSG_TX_GET_TX_STAT:
rtp_timestamp=0x94D00079 Jun 5 10:11:24.040: vtsp:[2/1:0
(39), S_WAIT_STATS, E_DSP_GET_TX] Jun 5 10:11:24.040:
act_stats_complete Jun 5 10:11:24.040: vtsp_timer_stop:
94719396 Jun 5 10:11:24.040: vtsp_ring_noan_timer_stop:
94719396 Jun 5 10:11:24.040: dsp_idle_mode: [2/1:0 (39)]
packet_len=8 channel_id=1 packet_id=68 Jun 5
10:11:24.040: vtsp_timer: 94719396 Jun 5 10:11:24.840:
vtsp:[2/1:0 (39), S_WAIT_RELEASE,
E_TSP_CALL_FEATURE_IND] Jun 5 10:11:24.840:
act_call_feature_ind Jun 5 10:11:24.840: vtsp:[2/1:0
(39), S_WAIT_RELEASE, E_TSP_DISCONNECT_CONF] Jun 5
10:11:24.840: act_wrelease_release Jun 5 10:11:24.840:
vtsp_timer_stop: 94719476 Jun 5 10:11:24.840:
dsp_cp_tone_off: [2/1:0 (39)] packet_len=8 channel_id=1
packet_id=71 Jun 5 10:11:24.840: dsp_idle_mode: [2/1:0
(39)] packet_len=8 channel_id=1 packet_id=68 Jun 5
10:11:24.840: dsp_close_voice_channel: [2/1:0 (39)]
packet_len=8 channel_id=1
packet_id=75vtsp_do_call_historyvtsp_do_call_history
```

```
CoderRate 20 Jun 5 10:11:24.840: vtsp:[2/1:0 (39),  
S_CLOSE_DSPRM, E_DSPRM_CLOSE_COMPLETE] Jun 5  
10:11:24.840: act_terminate Jun 5 10:11:24.840:  
vtsp_free_cdb,cdb 0x620F01FC
```

[相关信息](#)

- [语音 - 对 VoIP 配置传真中继 \(T.38\)](#)
- [语音技术支持](#)
- [语音和统一通信产品支持](#)
- [Cisco IP 电话故障排除](#)
- [技术支持 - Cisco Systems](#)