

訪問SPA500系列IP電話上的基於Web的設定頁

目標

所有裝置都有內建的設定頁面，允許使用者自定義設定和設定裝置中的高級屬性。設定頁面允許輕鬆配置裝置的功能。本文檔介紹如何訪問SPA500系列IP電話的設定頁。

適用裝置

·SPA 500系列IP電話

訪問SPA裝置的設定頁面的步驟。

附註：雖然本文也適用於所有SPA 500系列IP電話，但使用的裝置是SPA509G。

附註：在訪問SPA509G的設定頁面之前，請確保裝置通過其SW埠連線到啟用了PoE（乙太網供電）的路由器或交換機。

訪問SPA509G的設定頁面

步驟1.當IP電話開啟時，它會執行網路配置和設定配置。完成「Network Configuration（網路配置）」後，按「Setup（設定）」按鈕（上面有紙張符號），如圖所示。



步驟2.這將在IP電話的LCD上顯示具有不同選項的「設定」選單。



步驟3.按3。這將在LCD上顯示「設定」選單。



步驟4.按5。這將在液晶屏上開啟「Network Configuration (網路配置)」選單。

步驟5.向下導航到選項3，或只按3。請注意，IP地址顯示在IP地址下。

步驟6.轉到Web瀏覽器並輸入IP地址。

附註：電腦和IP電話應該位於同一網路上，才能訪問基於Web的實用程式。

Small Business
cisco SPA509G Configuration Utility

Admin Login basic | advanced

Voice Call History Personal Directory Attendant Console Status

Info System Phone User

System Information

Connection Type:	DHCP	Current IP:	192.168.137.162
Host Name:	SEPC89C1D6E6F8F	Domain:	mshome.net
Current Netmask:	255.255.255.0	Current Gateway:	192.168.137.1
Primary DNS:	192.168.137.1		
Secondary DNS:			

Product Information

Product Name:	SPA509G	Serial Number:	CBT151508BR
Software Version:	7.4.8a	Hardware Version:	1.0.2(0001)
MAC Address:	C89C1D6E6F8F	Client Certificate:	Installed
Customization:	Open	Licenses:	None

Phone Status

Current Time:	1/1/2003 14:27:55	Elapsed Time:	02:13:56
Broadcast Pkts Sent:	21	Broadcast Bytes Sent:	2138
Broadcast Pkts Recv:	353	Broadcast Bytes Recv:	36800

Undo All Changes Submit All Changes

© 2009 Cisco Systems, Inc. All Rights Reserved. SPA509G IP Phone

步驟7.將顯示基於Web的設定實用程式。如果未顯示，則電腦和IP電話可能未連線到同一網路。從電腦ping IP電話的IP地址以檢查連線。