

# 確定Catalyst交換機元件的序列號

## 目錄

---

[簡介](#)

[必要條件](#)

[需求](#)

[採用元件](#)

[慣例](#)

[背景資訊](#)

[Catalyst 6500](#)

[Catalyst 4500](#)

[含監督器引擎2的Catalyst 4500](#)

[Catalyst 4500監督器引擎II+/III/IV](#)

[Catalyst 3750](#)

[Catalyst 3560](#)

[Catalyst 3550](#)

[Catalyst 2950/2970/2940](#)

[Catalyst 2900XL/3500XL](#)

[Catalyst 2948GL3/4908G-L3/4980G-L3](#)

[Catalyst 9000](#)

[相關資訊](#)

---

## 簡介

本文說明如何確定Cisco Catalyst交換機上各種可更換元件的序列號。

## 必要條件

### 需求

本文件沒有特定需求。

### 採用元件

本文中的資訊係根據以下軟體和硬體版本：

- 各種Catalyst交換器
- 各種軟體版本

本文中的資訊是根據特定實驗室環境內的裝置所建立。文中使用到的所有裝置皆從已清除（預設）的組態來啟動。如果您的網路運作中，請確保您瞭解任何指令可能造成的影響。

## 慣例


如需文件慣例的詳細資訊，請參閱[思科技術提示慣例](#)。

## 背景資訊

序列號是建立網路中部件資料庫所必需的。當您使用[思科技術支援](#)建立服務請求時，必須手頭有受影響裝置的序列號。在需要更換部件或退貨授權(RMA)時，尤其如此。

無法修改Cisco Catalyst交換機的序列號。出於管理目的，您可以將執行Cisco IOS®軟體的Cisco Catalyst交換器設定為傳回自訂字串。要建立自定義字串，請在全域性配置模式下發出snmp-server chassis-id 命令。

---

 注意：有關show命令的特定資訊，請參閱[Show命令](#)。

---

## Catalyst 6500

要確定機箱和其他元件的序列號，請發出 `show idprom` 指令：

```
<#root>
6506#
show idprom ?

  all           selects all FRU-types
  backplane     specify backplane
  clock         specify clock <number>
  earl          specify earl <slot>
  fan-tray      specify fan-tray <number>
  interface     interface name
  module        specify module <slot>
  power-supply specify power-supply <number>
  rp            specify RP (MSFC) <slot>
  supervisor    specify supervisor <slot>
  vtt           specify VTT <number>
```

要獲取機箱序列號，請發出show idprom backplane 命令：

```
<#root>
6506#
show idprom backplane

IDPROM for backplane #0
(FRU is 'Catalyst 6500 6-slot backplane')
OEM String = 'Cisco Systems'
```

Product Number = 'WS-C6506'

Serial Number = 'TBA03270652'

Manufacturing Assembly Number = '73-3436-01'

Manufacturing Assembly Revision = 'A0'

Hardware Revision = 1.0

Current supplied (+) or consumed (-) = -A

要獲取模組序列號，請發出show idprom module slot <slot number>命令。或者，您可以發出show module命令：

<#root>

6506#

show module

Mod Ports Card Type Model

Serial No.

-----  
1 2 Catalyst 6000 supervisor 2 (Active) WS-X6K-S2U-MSFC2

SAD055006NE

3 0 2 port adapter FlexWAN WS-X6182-2PA

SAD04350EEU

4 48 SFM-capable 48-port 10/100 Mbps RJ45 WS-X6548-RJ-45

SAD055108C2

Mod MAC addresses Hw Fw Sw Status

-----  
1 0001.6415.a602 to 0001.6415.a603 3.2 6.1(3) 7.5(0.6)HUB6 Ok

3 0001.6413.c86b to 0001.6413.c8aa 1.5 12.1(13)E1 12.1(13)E1 Ok

4 0001.63d3.e77a to 0001.63d3.e7a9 4.0 6.3(1) 7.5(0.6)HUB6 Ok

Mod Sub-Module Model Serial Hw Status

-----  
1 Policy Feature Card 2 WS-F6K-PFC2 SAD055004VA 3.0 Ok

1 Cat6k MSFC 2 daughterboard WS-F6K-MSFC2 SAD055006VF 2.0 Ok

Mod Online Diag Status

-----  
1 Pass

3 Not Supported

4 Pass



註：使用 show diagbus 命令確定Flex WAN模組上埠介面卡的序列號。

# Catalyst 4500

## 含監督器引擎2的Catalyst 4500

在Catalyst 4500/4000 Supervisor 2上，機箱序列號在5.5(10)、6.3(2)及更新版本中可通過CLI獲得。在早期版本中，show version命令會在機箱序列號的位置顯示Supervisor Engine序列號。要獲取這些早期版本中的機箱序列號，請檢查機箱上的外部標籤。

## Catalyst 4500監督器引擎II+/III/IV

要確定機箱和其他元件的序列號，請使用show idprom命令：

```
<#root>
```

```
Switch#
```

```
show idprom ?
```

```
all          show all non-interface IDPROMs
chassis      show IDPROM for chassis
fan-tray     show IDPROM for system fan tray
interface    show contents of gbic connected to this interface
module       show IDPROM for module
power-supply show IDPROM for power supply
supervisor   show IDPROM for supervisor
```

要獲取機箱序列號，請使用 show idprom chassis 指令：

```
<#root>
```

```
Switch#
```

```
show idprom chassis
```

```
Chassis Idprom :
```

```
Common Block Signature = 0xABAB
Common Block Version = 1
Common Block Length = 144
Common Block Checksum = 4081
Idprom Size = 256
Block Count = 2
FRU Major Type = 0x4001
FRU Minor Type = 37
OEM String = Cisco Systems, Inc.
Product Number = WS-C4506
Serial Number = FOX0627A001
Part Number = 73-8107-04
Part Revision = 01
Manufacturing Deviation String = 0
Hardware Revision = 0.4
Manufacturing Bits = 0x0000
Engineering Bits = 0x0000
```

```
Snmp OID = 0.0.0.0.0.0.0
Power Consumption = 0
RMA Failure Code = 0 0 0 0
Chassis Block Signature = 0x4001
Chassis Block Version = 1
Chassis Block Length = 22
Chassis Block Checksum = 628
Feature Bits = 0x0000000000000000
MAC Base = 000a.4172.df40
MAC Count = 64
```

要獲取電源序列號，請使用show idprom power-supply {1 | 2}命令：

```
<#root>
```

```
Switch#
```

```
show idprom power-supply 1
```

```
Power Supply 1 Idprom :
Common Block Signature = 0xABAB
Common Block Version = 1
Common Block Length = 144
Common Block Checksum = 5857
Idprom Size = 256
Block Count = 2
FRU Major Type = 0x4501
FRU Minor Type = 1
OEM String = Cisco Systems, Inc.
```

```
Product Number = PWR-C4K-1400AC
```

```
Serial Number = ABC06260005
```

```
Part Number = 34-1846-01
Part Revision = 45
Manufacturing Deviation String =
Hardware Revision = 1.0
Manufacturing Bits = 0x0000
Engineering Bits = 0x0000
Snmp OID = 22616.22616.22616.22616.22616.22616.22616.22616
Power Consumption = 1400
RMA Failure Code = 0 0 0 0
Power Supply Block Signature = 0x4501
PowerSupply Block Version = 1
PowerSupply Block Length = 20
PowerSupply Block Checksum = 293
Feature Bits = 0x0000000000000000
Current @ 110V = 17
Current @ 220V = 9
StackMIB OID = 22616
```

要獲取模組序列號，請使用show idprom module slot <slot number>命令。或者，可以使用show module命令：

```
<#root>
```

```
Switch#
```

```
show module
```

```
Mod  Ports Card Type                               Model          Serial No.
-----+-----+-----+-----+-----+-----+-----
 1      2 1000BaseX (GBIC) Supervisor(active) WS-X4014
JAB054109H1

 3     48 10/100BaseTX (RJ45)                               WS-X4148
JAB025202M6

 4      6 1000BaseX (GBIC)                               WS-X4306
JAB023403BG
```

```
M MAC addresses                               Hw Fw          Sw          Status
-----+-----+-----+-----+-----+-----
 1 000a.4172.df40 to 000a.4172.df41 0.5 12.1(12r)EW 12.1(13)EW(0.34) Ok
 3 0050.730b.2340 to 0050.730b.236f 1.0                               Ok
 4 0010.7bfa.7ca4 to 0010.7bfa.7ca9 2.0                               Ok
```

## Catalyst 3750

使用show version命令確定機箱序列號和交換機型號型別，如以下示例所示。您可以在輸出中找到所有交換器堆疊成員、機箱和序列編號資訊：

```
<#root>
```

```
3750#
```

```
show version
```

```
Cisco Internetwork Operating System Software
Cisco IOS (tm) C3750 Software (C3750-I5-M), Version 12.1(14)EA1, RELEASE SOFTWARE (fc1
)
Copyright (c) 1986-2003 by cisco Systems, Inc.
Compiled Tue 22-Jul-03 13:17 by antonino
Image text-base: 0x00003000, data-base: 0x008F0CF8
```

```
ROM: Bootstrap program is C3750 boot loader
BOOTLDR: C3750 Boot Loader (C3750-HBOOT-M) Version 12.1(11r)AX, RELEASE SOFTWARE
(fc1)
```

```
3750RJ uptime is 1 hour, 29 minutes
System returned to ROM by power-on
System image file is "flash:c3750-i5-mz.121.14-EA1/c3750-i5-mz.121.14-EA1.bin"
```

cisco WS-C3750-24TS (PowerPC405) processor (revision A0) with 120822K/10240K bytes of memory.  
Processor board ID CAT0726R0ZU  
Last reset from power-on  
Bridging software.  
2 Virtual Ethernet/IEEE 802.3 interface(s)  
48 FastEthernet/IEEE 802.3 interface(s)  
16 Gigabit Ethernet/IEEE 802.3 interface(s)  
The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address : 00:0D:29:B4:18:00  
Motherboard assembly number : 73-7055-06  
Power supply part number : 341-0034-01  
Motherboard serial number : CAT0726043V  
Power supply serial number : PHI0708009K  
Model revision number : A0  
Motherboard revision number : A0

Model number : WS-C3750-24TS-E

System serial number : CAT0726R0ZU

Switch Ports Model SW Version SW Image

```
-----  
* 1 26 WS-C3750-24TS 12.1(14)EA1 C3750-I5-M  
2 26 WS-C3750-24TS 12.1(14)EA1 C3750-I5-M  
3 12 WS-C3750G-12S 12.1(14)EA1 C3750-I5-M
```

Switch 02

```
-----  
Switch Uptime : 1 hour, 29 minutes  
Base ethernet MAC Address : 00:0D:29:B4:3F:00  
Motherboard assembly number : 73-7055-06  
Power supply part number : 341-0034-01  
Motherboard serial number : CAT07260438  
Power supply serial number : PHI0708008X  
Model revision number : A0  
Motherboard revision number : A0
```

Model number : WS-C3750-24TS-E

System serial number : CAT0726R10A

Switch 03

```
-----  
Switch Uptime : 1 hour, 29 minutes  
Base ethernet MAC Address : 00:0D:BD:6A:3E:00  
Motherboard assembly number : 73-8307-06  
Power supply part number : 341-0048-01  
Motherboard serial number : CAT073205S2  
Power supply serial number : DTH0731055Z  
Model revision number : A0  
Motherboard revision number : A0
```

Model number : WS-C3750G-12S-E

System serial number : CAT0732R0M4

Top assembly part number : 800-23419-01  
Top assembly revision number : A0

Configuration register is 0xF

3750#

## Catalyst 3560

要確定機箱序列號和交換機型號型別，請使用show version命令：

<#root>

3560#

show version

Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3560 Software (C3560-I5-M), Version 12.1(19)EA1c, RELEASE SOFTWARE (fc2)  
Copyright (c) 1986-2004 by cisco Systems, Inc.  
Compiled Tue 03-Feb-04 05:56 by yenh  
Image text-base: 0x00003000, data-base: 0x0091D404

ROM: Bootstrap program is C3560 boot loader  
BOOTLDR: C3560 Boot Loader (C3560-HBOOT-M) Version 12.1(19r)EA1b, RELEASE SOFTWARE (fc2)

3-8-03-CATS3560 uptime is 8 weeks, 4 days, 18 hours, 16 minutes  
System returned to ROM by power-on  
System image file is "flash:c3560-i5-mz.121-19.EA1c.bin"

cisco WS-C3560-24PS (PowerPC405) processor (revision D0) with 118776K/12288K bytes of memory.

Processor board ID CSG0802P0G4

Last reset from power-on

Bridging software.

1 Virtual Ethernet/IEEE 802.3 interface(s)

24 FastEthernet/IEEE 802.3 interface(s)

2 Gigabit Ethernet/IEEE 802.3 interface(s)

The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.

Base ethernet MAC Address : 00:0E:39:E9:32:80

Motherboard assembly number : 73-9299-01

Power supply part number : 341-0029-03

Motherboard serial number : CAT075108EK

Power supply serial number : LIT074900K3

Model revision number : D0

Motherboard revision number : C0

Model number : WS-C3560-24PS-E

System serial number : CSG0802P0G4

Top Assembly Part Number : 800-24814-01

Top Assembly Revision Number : D0

Version ID : N/A

Hardware Board Revision Number : 0x08



# Catalyst 3550

要確定機箱序列號和交換機型號型別，請使用show version命令：

```
<#root>
```

```
Cat3550#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3550 Software (C3550-I5Q3L2-M), Version 12.1(12c)EA1, RELEASE SOFTWARE (fc1)  
Copyright (c) 1986-2002 by cisco Systems, Inc.  
Compiled Mon 25-Nov-02 00:07 by antonino  
Image text-base: 0x00003000, data-base: 0x0075FE48
```

```
ROM: Bootstrap program is C3550 boot loader
```

```
Cat3550 uptime is 4 days, 2 hours, 57 minutes  
System returned to ROM by power-on  
System image file is "flash:c3550-i5q3l2-mz.121-12c.EA1.bin"
```

```
cisco WS-C3550-48 (PowerPC) processor (revision G0) with 65526K/8192K bytes of memory.  
Processor board ID CHK0642W02B  
Last reset from warm-reset  
Bridging software.  
Running Layer2/3 Switching Image
```

```
Ethernet-controller 1 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 2 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 3 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 4 has 12 Fast Ethernet/IEEE 802.3 interfaces
```

```
Ethernet-controller 5 has 1 Gigabit Ethernet/IEEE 802.3 interface
```

```
Ethernet-controller 6 has 1 Gigabit Ethernet/IEEE 802.3 interface
```

```
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
The password-recovery mechanism is enabled.  
384K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:0B:46:8A:2F:80  
Motherboard assembly number: 73-5701-07  
Power supply part number: 34-0967-01  
Motherboard serial number: CAT0641027L  
Power supply serial number: DCA06392BU2  
Model revision number: G0  
Motherboard revision number: A0
```

```
Model number: WS-C3550-48-SMI
```

```
System serial number: CHK0642W02B
```

```
Configuration register is 0x10F
```

# Catalyst 2950/2970/2940

要確定機箱序列號和交換機型號型別，請使用 `show version` 指令：

```
<#root>
```

```
Cat2950#
```

```
show version
```

```
Cisco Internetwork Operating System Software  
Cisco IOS (tm) C2950 Software (C2950-I6Q4L2-M), Version 12.1(12c)EA1, RELEASE SOFTWARE (fc1)  
Copyright (c) 1986-2002 by cisco Systems, Inc.  
Compiled Sun 24-Nov-02 23:31 by antonino  
Image text-base: 0x80010000, data-base: 0x80562000
```

```
ROM: Bootstrap program is CALHOUN boot loader
```

```
Cat2950 uptime is 4 days, 2 hours, 52 minutes  
System returned to ROM by power-on  
System image file is "flash:c2950-i6q4l2-mz.121-12c.EA1.bin"
```

```
cisco WS-C2950G-48-EI (RC32300) processor (revision C0) with 21002K bytes of memory.  
Processor board ID FHK0624W0HS  
Last reset from system-reset  
Running Enhanced Image  
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)
```

```
32K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:09:E8:89:4A:40  
Motherboard assembly number: 73-7409-08  
Power supply part number: 34-0965-01  
Motherboard serial number: FOC06230ERQ  
Power supply serial number: DAB062143BP  
Model revision number: C0  
Motherboard revision number: B0
```

```
Model number: WS-C2950G-48-EI
```

```
System serial number: FHK0624W0HS
```

```
Configuration register is 0xF
```

# Catalyst 2900XL/3500XL

要確定機箱序列號和交換機型號型別，請使用 `show version` 指令：

```
<#root>
```

```
Switch#
```

```
show version
```

Cisco Internetwork Operating System Software  
Cisco IOS (tm) C3500XL Software (C3500XL-C3H2S-M), Version 12.0(5.2)XU, MAINTENANCE  
INTERIM SOFTWARE  
Copyright (c) 1986-2000 by cisco Systems, Inc.  
Compiled Mon 17-Jul-00 18:29 by ayounes  
Image text-base: 0x00003000, data-base: 0x00301F3C

ROM: Bootstrap program is C3500XL boot loader

Switch uptime is 4 days, 3 hours, 4 minutes  
System returned to ROM by power-on  
System image file is "flash:c3500XL-c3h2s-mz-120.5.2-XU.bin"

Cisco WS-C3548-XL (PowerPC403) processor (revision 0x01) with 16384K/1024K bytes  
of memory. Processor board ID FOC0616X0RG, with hardware revision 0x00  
Last reset from power-on

Processor is running Enterprise Edition Software  
Cluster command switch capable  
Cluster member switch capable  
48 FastEthernet/IEEE 802.3 interface(s)  
2 Gigabit Ethernet/IEEE 802.3 interface(s)

32K bytes of flash-simulated non-volatile configuration memory.  
Base ethernet MAC Address: 00:09:7C:8E:78:80  
Motherboard assembly number: 73-3903-09  
Power supply part number: 34-0971-02  
Motherboard serial number: FOC06160L07  
Power supply serial number: APQ061200VZ  
Model revision number: M0  
Motherboard revision number: A0

Model number: WS-C3548-XL-EN

System serial number: FOC0616X0RG

Configuration register is 0xF

## Catalyst 2948GL3/4908G-L3/4980G-L3

要確定機箱序列號，請使用 `show hardware` 指令：

```
<#root>
```

```
2948g-13#
```

```
show hardware
```

```
Model: Cat-2948G-L3 Date: 17:49:42 UTC Tue Mar 18 2003
```

```
XPIF FPGA File:      xpif_fpga_0_72b_CC1k.rbt  
XPIF FPGA Date:     Wed Dec  8 17:05:42 1999
```

```
Slot 0/0:
```

```
  Chip 0  Reset Count: 0          Chip 1  Reset Count: 0  
  Chip 2  Reset Count: 0          Chip 3  Reset Count: 0
```

```
Chip 4 Reset Count: 0      Chip 5 Reset Count: 0
Chip 6 Reset Count: 0      Chip 7 Reset Count: 0
Chip 8 Reset Count: 0      Chip 9 Reset Count: 0
Chip 10 Reset Count: 0     Chip 11 Reset Count: 0
EPIF Version      : 0      CAM size: 32 KB
Ucode Version     : 1.0
Ucode Image       : EPIF_UCODE_RUNTIME
Port Phy Setup
Port1 :DONE      Port2 :DONE      Port3 :DONE      Port4 :DONE
Port5 :DONE      Port6 :DONE      Port7 :DONE      Port8 :DONE
Port9 :DONE      Port10:DONE     Port11:DONE     Port12:DONE
Port13:DONE     Port14:DONE     Port15:DONE     Port16:DONE
Port17:DONE     Port18:DONE     Port19:DONE     Port20:DONE
Port21:DONE     Port22:DONE     Port23:DONE     Port24:DONE
Port25:DONE     Port26:DONE     Port27:DONE     Port28:DONE
Port29:DONE     Port30:DONE     Port31:DONE     Port32:DONE
Port33:DONE     Port34:DONE     Port35:DONE     Port36:DONE
Port37:DONE     Port38:DONE     Port39:DONE     Port40:DONE
Port41:DONE     Port42:DONE     Port43:DONE     Port44:DONE
Port45:DONE     Port46:DONE     Port47:DONE     Port48:DONE
```

```
Slot 0/1:
XPIF Version      : 0      CAM size: 128 KB
Ucode Version     : 1.0
Ucode Image       : XPIF_UCODE_RUNTIME
Port Phy Setup
Port49:DONE      Port50:DONE
```

```
IDPROM Contents      :
FRU Type             : 0x0.0x0
OEM String           : Cisco_Systems
```

```
Product Number      : WS-C2948G-L3
```

```
Serial Number       : FOX05330ADH
Mfg. Assembly No.   : 73-4083-07
Mfg. Assembly Ver.  : A0
Hardware Version     : 1.7
FPGA Version         : 0
SNMP IOD             : 9.5.1.3.1.1.2.275
RMA Code             : 0
Feature Bits         : 0x00000000
MAC Address Base     : 00:07:85:07:DC:00
Total MAC Adrs.     : 1024
```

## Catalyst 9000

要確定機箱序列號，請使用show version命令。或者，可以使用show module命令顯示較小的輸出：

```
<#root>
```

```
C9300#
```

show version

Cisco IOS XE Software, Version 17.06.04  
Cisco IOS Software [Bengaluru], Catalyst L3 Switch Software (CAT9K\_IOSXE), Version 17.6.4, RELEASE SOFTWARE (FC2)  
Technical Support: <http://www.cisco.com/techsupport>  
Copyright (c) 1986-2022 by Cisco Systems, Inc.  
Compiled Sun 14-Aug-22 08:58 by mcpre

Cisco IOS-XE software, Copyright (c) 2005-2022 by Cisco Systems, Inc.  
All rights reserved. Certain components of Cisco IOS-XE software are licensed under the GNU General Public License ("GPL") Version 2.0. The software code licensed under GPL Version 2.0 is free software that comes with ABSOLUTELY NO WARRANTY. You can redistribute and/or modify such GPL code under the terms of GPL Version 2.0. For more details, see the documentation or "License Notice" file accompanying the IOS-XE software, or the applicable URL provided on the flyer accompanying the IOS-XE software.

ROM: IOS-XE ROMMON  
BOOTLDR: System Bootstrap, Version 17.8.1r[FC2], RELEASE SOFTWARE (P)

C9300 uptime is 1 week, 2 days, 17 hours, 51 minutes  
Uptime for this control processor is 1 week, 2 days, 17 hours, 54 minutes  
System returned to ROM by Reload Command at 07:14:20 jst Wed Aug 2 2023  
System restarted at 07:29:56 jst Wed Aug 2 2023  
System image file is "flash:packages.conf"  
Last reload reason: Reload Command

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at:  
<http://www.cisco.com/wwl/export/crypto/tool/stqrg.html>

If you require further assistance please contact us by sending email to [export@cisco.com](mailto:export@cisco.com).

Technology Package License Information:

Technology-package Current	Type	Technology-package Next reboot
network-advantage	Smart License	network-advantage
dna-advantage	Subscription Smart License	dna-advantage

AIR License Level: AIR DNA Advantage  
Next reload AIR license Level: AIR DNA Advantage

Smart Licensing Status: Registration Not Applicable/Not Applicable

cisco C9300-24UX (X86) processor with 1317097K/6147K bytes of memory.  
Processor board ID FJC2325E0HB  
5 Virtual Ethernet interfaces  
8 Gigabit Ethernet interfaces  
64 Ten Gigabit Ethernet interfaces  
4 TwentyFive Gigabit Ethernet interfaces  
4 Forty Gigabit Ethernet interfaces  
2048K bytes of non-volatile configuration memory.  
8388608K bytes of physical memory.  
1638400K bytes of Crash Files at crashinfo:.  
11264000K bytes of Flash at flash:.

Base Ethernet MAC Address : c4:c6:03:9a:bd:80  
Motherboard Assembly Number : 73-18276-03  
Motherboard Serial Number : FJZ23210BTF  
Model Revision Number : D0  
Motherboard Revision Number : B0

Model Number : C9300-24UX

System Serial Number : FJC2325E0HB

CLEI Code Number :

Switch	Ports	Model	SW Version	SW Image	Mode
*	1 41	C9300-24UX	17.06.04	CAT9K_IOSXE	INSTALL

C9300#

show module

Switch	Ports	Model	Serial No.	MAC address	Hw Ver.	Sw Ver.
1	41					

C9300-24UX

FJC2325E0HB

c4c6.039a.bd80 V02 17.06.04  
C9300#

## 相關資訊

- [顯示命令](#)
- [思科技術支援與下載](#)

## 關於此翻譯

思科已使用電腦和人工技術翻譯本文件，讓全世界的使用者能夠以自己的語言理解支援內容。請注意，即使是最佳機器翻譯，也不如專業譯者翻譯的內容準確。Cisco Systems, Inc. 對這些翻譯的準確度概不負責，並建議一律查看原始英文文件（提供連結）。