

對小型企業VOIP路由器後面的電腦實施訪問限制

目錄

[簡介](#)

[如何對路由器後面的電腦實施訪問限制？](#)

[相關資訊](#)

簡介

本文是系列文章中的一篇，旨在幫助安裝、故障排除和維護Cisco Small Business產品（前身為Linksys Business系列）。

如需文件慣例的詳細資訊，請參閱[思科技術提示慣例](#)。

問：如何對路由器後面的電腦實施訪問限制？

A. 訪問限制允許您限制網路上的Internet訪問。您可以拒絕某些電腦訪問Internet，阻止某些應用程式，例如DNS、Ping、HTTP、HTTPS、FTP、POP3、IMAO、SMTP、NNTP、Telnet、SNMP、TFTP和IKE以及服務，並在給定時間使用關鍵字或URL阻止某些網站。此功能允許您為特定PC自定義最多十個不同的Internet訪問策略，這些PC由其IP或MAC地址標識。

在Linksys路由器上啟用訪問限制

請完成以下步驟：

1. 訪問路由器的基於Web的設定頁。有關詳細資訊，請參閱[訪問VOIP路由器的基於Web的設定頁](#)。
2. 當路由器的基於Web的設定頁面出現時，選擇Access Restrictions > Internet Access。



3. 在Internet Access Policy下拉選單中選擇從1到10的策略編號。
4. 在Enter Policy Name欄位中輸入策略名稱（例如MyPolicy），然後按一下Edit List of PC以將PC新增到策略中。出現一個類似於步驟7的視窗。

Internet Access

Internet Access Policy:

Status: Enable Disable

Enter Policy Name: **Enter your Policy Name here.**

PCs: **Click Edit List of PCs to include computers to the policy.**

Deny
 Allow

Days

Everyday Wed Thu Fri Sat

Times

24 Hours From: : To: :

5. 出現「PC清單」螢幕時，按IP地址或MAC地址指定PC。在IP欄位中輸入適當的IP地址。如果要過濾的IP地址範圍，請填寫相應的IP範圍欄位。在MAC欄位中輸入適當的MAC地址。

List of PCs

Enter MAC Address of the PCs in this format : xxxxxxxxxx

MAC 01 : MAC 05 :

MAC 02 : MAC 06 : **Either enter the computer's MAC Address here.**

MAC 03 : MAC 07 :

MAC 04 : MAC 08 :

Enter the IP Address of the PCs

IP 01 : 192.168.1. IP 04 : 192.168.1.

IP 02 : 192.168.1. IP 05 : 192.168.1. **And/or enter the computer's IP Address here.**

IP 03 : 192.168.1. IP 06 : 192.168.1.

Enter the IP Range of the PCs

IP Range 01 : 192.168.1. ~

IP Range 02 : 192.168.1. ~ **And/or enter the computer's IP Range here.**

注意：Linksys提供三列（MAC地址、IP地址和IP範圍）的原因是允許您根據地址進行輸入。例如，如果客戶的MAC地址需要限制，則需要在MAC地址列中鍵入特定MAC地址；對於IP地址也是相同的。對於IP範圍，如果要限制一組IP地址，例如192.168.1.20到192.168.1.40，則需要在IP範圍列中鍵入IP地址範圍。

- 按一下**Save Settings**，然後關閉視窗以返回到Internet Access螢幕。
- 如果要在指定的日期和時間阻止列出的PC訪問Internet，請選擇**Deny**。
- 設定過濾訪問的時間。選擇**Everyday**或一週中的適當日期。
- 設定過濾訪問的時間。選擇**24 Hours**或選擇**From**旁邊的框，然後從下拉框中選擇特定時間段。

The screenshot shows the 'Internet Access' configuration window. At the top, the 'Internet Access Policy' is set to '10', with 'Delete' and 'Summary' buttons. The 'Status' is set to 'Enable'. The 'Enter Policy Name' field contains 'MyPolicy', and there is an 'Edit List of PCs' button. Under 'PCs', the 'Deny' radio button is selected. The 'Days' section has 'Everyday' checked, with checkboxes for Sun, Mon, Tue, Wed, Thu, Fri, and Sat. The 'Times' section has 'From' selected, with 'From' set to 12:00 AM and 'To' set to 1:00 AM. Three yellow callout boxes provide instructions: 'Select Deny.' points to the Deny radio button; 'Select Everyday or the appropriate days of the week.' points to the Everyday checkbox; 'Select 24 Hours or check the box next to From and select a specific time period from the drop-down boxes.' points to the From radio button and the time selection dropdowns.

- 按一下「**Save Settings**」。
- 重複步驟3-10以建立或編輯其他策略。

相關資訊

- [技術支援與文件 - Cisco Systems](#)