

如何在CUCM 11.X中配置立即會議功能

目錄

[簡介](#)

[必要條件](#)

[需求](#)

[採用元件](#)

[背景資訊](#)

[設定](#)

[組態](#)

[驗證](#)

[疑難排解](#)

簡介

本檔案介紹思科整合通訊管理員(CUCM)中的Conference Now新功能。

必要條件

需求

思科建議您瞭解Call Manager上的媒體資源。

採用元件

本文檔中的資訊基於CUCM版本11.5.0.99838-4。

本文中的資訊是根據特定實驗室環境內的裝置所建立。文中使用到的所有裝置皆從已清除 (預設) 的組態來啟動。如果您的網路正在作用，請確保您已瞭解任何指令可能造成的影響。

背景資訊

Conference Now功能允許外部和內部呼叫者通過撥打Conference Now IVR目錄號碼加入會議，該號碼是一個集中式會議助理號碼。IVR應用通過播放通知引導呼叫者加入會議。在主機正確輸入會議號碼和PIN後，會根據主機的媒體資源組清單(MRGL)分配會議網橋。在會議開始前加入的參與者將被重定向到同一會議橋。主持人可以為安全電話會議設定與會者訪問代碼。


設定

以下是設定「立即召開會議」功能的程式。


組態

步驟1.立即配置會議。

導覽至Call Routing > Conference Now，如下圖所示：




此處將Conference Now DN保留在Partition中，可使用相應的呼叫搜尋空間(CSS)訪問。





步驟2.現在在Device下並分配Owner User。


導覽至Device > Phone，然後搜尋裝置。



選擇正確的裝置。



在此處選擇Owner作為User並分配Owner User ID。此處cisco用作Owner User ID。



步驟3.如圖所示，導覽至User Management > End User。

Cisco Unified CM Administration
For Cisco Unified Communications Solutions

System version: 11.5.0.99838-4
VMware Installation: 4 vCPU Intel(R) Xeon(R) CPU E5-4669 v3 @ 2.10GHz, disk 1: 120Gbytes, 5120Mbytes RAM, Partitions aligned

WARNING: No backup device is configured. This is required in case of failure.

User Management menu items:
 Application User
 End User
 User/Phone Add
 SIP Realm
 User Settings
 Self-Provisioning
 Assign Presence Users

搜尋使用者，並選擇步驟2中電話上分配的使用者。

Find and List Users

4 records found

User ID	Meeting Number	First Name	Last Name	Department	Directory URI	User Status
cisco	3006		cisco2		cisco1@cisco.com	Enabled Local User
cisco3	3001	A	Phone		cisco3@cisco.com	Enabled Local User
cisco4	3002	B	Phone		cisco4@cisco.com	Enabled Local User

保留使用者PIN。如果你是會議的主持人，則使用此pin。

End User Configuration

Update successful

User Information

User Status: Enabled Local User
 User ID*: cisco
 Password: [Redacted] **Edit Credential**
 Confirm Password: [Redacted]
 Self-Service User ID: 3002
 PIN: [Redacted] **Edit Credential**
 Confirm PIN: [Redacted] **Edit Credential**
 Last name*: cisco2
 Middle name: [Redacted]
 First name: [Redacted]
 Display name: [Redacted]
 Title: [Redacted]
 Directory URI: cisco1@cisco.com

This is mandatory to set the pin.

步驟4.選中Enable End User to Host Conference Now覈取方塊，如下圖所示：

Conference Now Information

Enable End User to Host Conference Now

Meeting Number 3002

Attendees Access Code 1234



This pin is used to join the participant in the conference.

驗證

要驗證您的配置，請致電Conference Now Directory Number(DN)，即3030。輸入會議號碼3002，然後按#鍵。

作為主持人，請保持步驟3中配置的pin碼。現在，其他參與者請共用會議號碼3002和參與者代碼1234。

疑難排解

此配置的故障排除步驟在單獨的文檔中介紹。