



Route Processor Redundancy Plus (RPR+)

Route Processor Redundancy (RPR) provides an alternative to the High System Availability (HSA) feature. HSA enables a system to reset and use a standby Route Switch Processor (RSP) if the active RSP fails. Using RPR, you can reduce unplanned downtime because RPR enables a quicker switchover between an active and standby RSP if the active RSP experiences a fatal error.

RPR Plus (RPR+) is an enhancement of the RPR feature. RPR+ keeps the Versatile Interface Processors (VIPs) from being reset and reloaded when a switchover occurs between the active and standby RSPs.

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the “[Feature Information for Route Processor Redundancy Plus \(RPR+\)](#)” section on page 12.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.

Contents

- [Prerequisites for Route Processor Redundancy Plus \(RPR+\), page 2](#)
- [Restrictions for Route Processor Redundancy Plus \(RPR+\), page 2](#)
- [Information About Route Processor Redundancy Plus \(RPR+\), page 2](#)
- [How to Configure Route Processor Redundancy Plus \(RPR+\), page 3](#)
- [Configuration Examples for Route Processor Redundancy Plus \(RPR+\), page 10](#)
- [Additional References, page 11](#)
- [Feature Information for Route Processor Redundancy Plus \(RPR+\), page 12](#)
- [Glossary, page 14](#)



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

© 2007 Cisco Systems, Inc. All rights reserved.

Prerequisites for Route Processor Redundancy Plus (RPR+)

RPR and RPR+ require a Cisco 7500 series router loaded with two RSP16s, one RSP16 and one RSP8, two RSP8s, or a combination of RSP2s and RSP4s. If you are using the one RSP16 and one RSP8 combination, you must use the same memory—256 MB—in both RSPs because the secondary RSP must be able to support the primary RSP during a failover.

Restrictions for Route Processor Redundancy Plus (RPR+)

- RSP1s do not support RPR or HSA.
- RPR is supported only on routers that support dual RSPs. Only the Cisco 7507 and Cisco 7513 support dual RSPs.
- RPR+ operates only in a system with VIPs as the line cards. Systems with legacy interface processors default to RPR.
- In RPR+ mode, configuration changes done through Simple Network Management Protocol (SNMP) may not be automatically configured on the standby RSP after a switchover occurs.
- RPR+ does not work on routers configured with MPLS.

Information About Route Processor Redundancy Plus (RPR+)

- [RPR, page 2](#)
- [RPR+, page 2](#)

RPR

Route Processor Redundancy (RPR) provides an alternative to the High System Availability (HSA) feature currently available on Cisco 7500 series routers. HSA enables a system to reset and use a standby Route Switch Processor (RSP) if the active RSP fails.

Using RPR, you can reduce unplanned downtime. RPR enables a quicker switchover between an active and standby RSP if the active RSP experiences a fatal error. When you configure RPR, the standby RSP loads a Cisco IOS image on bootup and initializes itself in standby mode. In the event of a fatal error on the active RSP, the system switches to the standby RSP, which reinitializes itself as the active RSP, reloads all of the line cards, and restarts the system.

RPR+

The RPR+ feature is an enhancement of the RPR feature on Cisco 7500 series routers. RPR+ keeps the VIPs from being reset and reloaded when a switchover occurs between the active and standby RSPs. Because VIPs are not reset and microcode is not reloaded on the VIPs, and the time needed to parse the configuration is eliminated, switchover time is reduced to 30 seconds.

[Table 1](#) describes the average time for a router to switchover to a standby RSP if the active RSP fails.

Table 1 Average Switchover Time Comparison Table

Feature	Time to Immediately Switch a Packet on New RSP After Failover	Expected Overall Time to Have New RSP in New High Availability State After Failover	Notes
HSA	10 minutes	20 minutes	System default.
RPR	5 minutes	15 minutes	VIPs and legacy interface processors (IPs) supported.
RPR+	30 seconds	11 minutes	VIPs supported. ¹

1. Legacy IPs default to RPR. To allow RPR+ for VIPs when up to two legacy IPs exist in the router, you must configure the **service single-slot-reload-enable** command. If you do not enable the **service single-slot-reload-enable** command or if you have more than two legacy IPs, all the line cards are reloaded.



Note Table 1 shows average switchover times. Recovery time will vary depending on the configuration of the router.

In Table 1 we have noted that RPR+ supports up to two legacy IPs in the router if the **service single-slot-reload-enable** command is configured. By default, the existence of any legacy IPs in the router causes all the line cards to be reloaded during an RPR+ switchover and a message similar to the following to be displayed:

```
%HA-2-MAX_NO_Quiesce: 1 linecard(s) not quiesced exceeds limit of 0, all slots will be reloaded.
```

If the **service single-slot-reload-enable** command is configured, then the NO_Quiесce limit is set to two, allowing two quiesce failures during an RPR+ switchover. When more than two legacy IPs exist in the router, all the line cards are reloaded during an RPR+ switchover, and a message similar to the following is displayed:

```
%HA-2-MAX_NO_Quiesce: 3 linecard(s) not quiesced exceeds limit of 2, all slots will be reloaded.
```

How to Configure Route Processor Redundancy Plus (RPR+)

- [Copying an Image onto Active and Standby RSPs, page 3](#) (required)
- [Setting the Configuration Register Boot Variable, page 5](#) (optional)
- [Configuring RPR+, page 7](#) (required)
- [Verifying RPR+, page 9](#) (optional)

Copying an Image onto Active and Standby RSPs

Perform this task to use TFTP to copy a high availability Cisco IOS image onto the active and standby RSPs.

Prerequisites

Before copying a file to flash memory, you must ensure that there is enough space available in flash memory. Compare the size of the file that you are copying to the amount of available flash memory shown. If the space available is less than the space required by the file that you will copy, the copy process will not continue and an error message similar to the following will be displayed:

```
%Error copying tftp://image@server/tftpboot/file-location/image-name (Not
enough space on
device).
```

SUMMARY STEPS

1. **enable**
2. **copy tftp slot*slot-number*:**
3. **copy tftp slaveslot*slot-number*:**

DETAILED STEPS

Step 1 **enable**

Enables privileged EXEC mode. Enter your password if prompted.

```
Router> enable
```

Step 2 **copy tftp slot*slot-number*:**

Use this command to copy a high availability Cisco IOS image onto the flash memory card of the active RSP. The *slot* keyword and argument specify the flash memory card of the active RSP.

```
Router# copy tftp slot0:
```

```
Address or name of remote host []? ip-address
```

Enter the IP address of the TFTP server that contains the new image.

```
Router# 172.18.2.3
```

```
Source filename []? image-name
```

Enter the name of the image file that you are copying to the flash memory card.

```
Router# rsp-pv-mz
```

```
Destination file name? [image-name1] <Return>
```

Enter the name under which you want the image file to appear at the destination. The destination name is optional. To use the same image name as the source file, press the Enter key.

```
Accessing tftp://ip-address/...
```

Step 3 **copy tftp slaveslot*slot-number*:**

Use this command to copy a high availability Cisco IOS image onto the flash memory card of the standby RSP. The *slaveslot* keyword and argument specify the flash memory card of the standby RSP.

```
Router# copy tftp slaveslot0:
```

```
Address or name of remote host []? ip-address
```

Enter the IP address of the TFTP server that contains the new image.

```
Router# 172.18.2.3
```

```
Source filename []? image-name
```

Enter the name of the image file that you are copying to the flash memory card.

```
Router# rsp-pv-mz
```

```
Destination file name? [image-name1] <Return>
```

Enter the name under which you want the image file to appear at the destination. The destination name is optional. To use the same image name as the source file, press the Enter key.

```
Accessing tftp://ip-address/...
```

What to Do Next

If you do not want to modify the software configuration register boot field, proceed to the “[Configuring RPR+](#)” section on page 7.

Setting the Configuration Register Boot Variable

Perform this optional task to modify the software configuration register boot field to ensure that the system boots the same image as that specified by the **hw-module slot image** command in the “[Configuring RPR+](#)” section on page 7.

SUMMARY STEPS

1. **enable**
2. **show version**
3. **configure terminal**
4. **boot system flash slot_{slot-number}:*[image-name]***
5. **config-register *value***
6. **exit**
7. **reload**

■ How to Configure Route Processor Redundancy Plus (RPR+)

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
	Example: Router> enable	
Step 2	show version	Displays the current configuration register setting at the end of the display.
	Example: Router# show version	
Step 3	configure terminal	Enters global configuration mode.
	Example: Router# configure terminal	
Step 4	boot system flash slot <i>slot-number</i> : [<i>image-name</i>]	Specifies the filename of an image stored in flash memory. <ul style="list-style-type: none"> • <i>slot-number</i>—Specifies the active RSP slot where the flash memory card is located. Valid slot numbers are 0 and 1 for the Cisco 7500 series RSP. • <i>image-name</i>—Specifies the name of the image. It is recommended that you set the boot variable so that the system boots the same image as that specified by the hw-module slot <i>slot-number</i> image <i>file-spec</i> command. See Step 3 of the “Configuring RPR+” section on 7.
	Example: Router(config)# boot system flash slot0:rsp-pv-mz	
Step 5	config-register <i>value</i>	Modifies the existing configuration register setting to reflect the way in which you want to load a system image. <ul style="list-style-type: none"> • Use the <i>value</i> argument to specify the configuration register setting. Valid values are in the range from 0x0 to 0xFFFF. • In this example, when a reload command is issued, the router automatically boots the image specified in the boot system flash <i>image-name</i> configuration.
	Example: Router(config)# config-register 0x2102	
Step 6	exit	Exits global configuration mode and returns to privileged EXEC mode.
	Example: Router(config)# exit	
Step 7	reload	Reboots the router to make your configuration changes take effect.
	Example: Router# reload	

Examples

The following is sample partial output from the **show version** command; the output displays the current configuration register setting.

```
Router# show version

Cisco IOS Software, C7500 Software (C7500-IPBASE-MZ), Version 12.3(7)T, RELEASE)
TAC Support: http://www.cisco.com/tac
Copyright (c) 1986-2004 by Cisco Systems, Inc.
Compiled Fri 16-Jan-04 18:03 by engineer

ROM: System Bootstrap, Version 12.1(3r)T2, RELEASE SOFTWARE (fc1)
.
.
.

Configuration register is 0x2102
```

Configuring RPR+

Perform this task to configure RPR+.

Restrictions

RPR+ operates only in a system with VIPs as the line cards. Systems with legacy IPs default to RPR mode. Up to two legacy IPs can be supported by RPR+ if the **service single-slot-reload-enable** command is configured. For more details, see the “[RPR+](#)” section on page 2.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **hw-module slot slot-number image file-spec**
4. Repeat Step 3 for the standby RSP.
5. **redundancy**
6. **mode {hsa | rpr | rpr-plus}**
7. **exit**
8. **copy system:running-config nvram:startup-config**
9. **hw-module sec-cpu reset**

■ How to Configure Route Processor Redundancy Plus (RPR+)

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
	Example: Router> enable	
Step 2	configure terminal	Enters global configuration mode.
	Example: Router# configure terminal	
Step 3	hw-module slot slot-number image file-spec	Specifies a high availability Cisco IOS image to run on an active RSP. <ul style="list-style-type: none"> • Use the <i>slot-number</i> argument to specify the RSP slot. • Use the <i>file-spec</i> argument to specify the flash memory card to load the image into and the name of the image. • In this example, the active RSP is loaded in slot 6.
Step 4	Repeat Step 3 for the standby RSP.	Repeat Step 3 to specify a high availability Cisco IOS image to run on the standby RSP. <ul style="list-style-type: none"> • In this example, the standby RSP is loaded in slot 7.
	Example: Router(config)# hw-module slot 7 image slot0:rsp-pv-mz	
Step 5	redundancy	Enters redundancy configuration mode.
	Example: Router(config)# redundancy	
Step 6	mode {hsa rpr rpr-plus}	Configures the redundancy mode. <ul style="list-style-type: none"> • Use the rpr-plus keyword to configure the mode as RPR+ on both the active and standby RSPs. • If no mode is specified, the default mode is HSA.
Step 7	exit	Exits redundancy configuration mode and returns to global configuration mode. <ul style="list-style-type: none"> • Repeat this step one more time to exit global configuration mode. • Exiting global configuration mode after the redundancy mode has been set to RPR+ will trigger a timer to run for a few seconds, after which the standby RSP resets and reloads.

Command or Action	Purpose
Step 8 <code>copy system:running-config nvram:startup-config</code> Example: Router# copy system:running-config nvram:startup-config	(Optional) Copies the running configuration to the startup configuration to save the RPR+ configuration. <ul style="list-style-type: none"> This command can be run manually immediately after exiting global configuration mode when the redundancy mode is set to RPR+, or it can be run after the standby RSP is reloaded and initialized.
Step 9 <code>hw-module sec-cpu reset</code> Example: Router# hw-module sec-cpu reset	(Optional) Resets and reloads the standby RSP with the specified Cisco IOS image and executes the image. <ul style="list-style-type: none"> Although changing the redundancy mode to RPR+ will trigger a reload, using this command may initiate the standby RSP reset a few seconds faster than the automatic reload. <p>Note If you do not specify a Cisco IOS image in Step 3, this command loads and executes the bundled default Cisco IOS standby image. The system then operates in HSA mode.</p>

Verifying RPR+

Perform this task to verify whether RPR+ is configured on the router and to display other redundancy statistics.

SUMMARY STEPS

- enable
- show redundancy

DETAILED STEPS

Step 1 enable

Enables privileged EXEC mode. Enter your password if prompted.

Router> **enable**

Step 2 show redundancy

Use this command to verify what type of redundancy is configured on the router and to display other redundancy information.

Router# **show redundancy**

```
Operating mode is rpr-plus
redundancy mode rpr-plus
hw-module slot 2 image disk0:rsp-pv-mz
hw-module slot 3 image disk0:rsp-pv-mz
```

The system total uptime since last reboot is 5 days, 19 hours 36 minutes.

The system has experienced 27 switchovers.

The system has been active (become master) for 5 days, 15 hours 14 minutes.

Reason for last switchover:User forced.

Configuration Examples for Route Processor Redundancy Plus (RPR+)

- [Configuring RPR+: Example, page 10](#)

Configuring RPR+: Example

In the following example, the active RSP is installed in slot 2 and the standby RSP is installed in slot 3 of a Cisco 7507 router.

```

Router# copy tftp slot0:rsp-pv-mz
Router# copy tftp slaveslot0:rsp-pv-mz
Router# configure terminal
Router(config)# hw-module slot 2 image slot0:rsp-pv-mz
Router(config)# hw-module slot 3 image slot0:rsp-pv-mz
Router(config)# redundancy
Router(config-r)# mode rpr-plus
Router(config-r)# end
Router# hw-module sec-cpu reset
Router# show running-config
version 12.3(7)T
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
service single-slot-reload-enable
!
hostname Router
!
boot system rcp://path/to/image/rsp-boot-mz
boot system tftp://path/to/image/rsp-boot-mz
boot bootldr bootflash:rsp-boot-mz
enable password password
!
redundancy
mode rpr-plus ! Indicates that redundancy mode has been configured for RPR+.
!
hw-module slot 2 image slot0:rsp-pv-mz
hw-module slot 3 image slot0:rsp-pv-mz
ip subnet-zero
ip rcmd remote-username Router
ip cef distributed
ip host iphost 192.168.0.1
mpls traffic-eng auto-bw timers
!
!
controller T3 6/0/0
clock source line
!
!
interface Ethernet0/0/0
ip address 10.0.0.1 255.255.0.0
no ip directed-broadcast
ip route-cache distributed
no keepalive

```

```

.
.
exec-timeout 0 0
history size 40
transport preferred none
transport input none
line aux 0
line vty 0 4
login
!
end

```

Additional References

Related Documents

Related Topic	Document Title
File management and other configuration commands: complete command syntax, command mode, defaults, usage guidelines, and examples	<i>Cisco IOS Configuration Fundamentals and Network Management Command Reference</i>
File management and other configuration examples	<i>Cisco IOS Configuration Fundamentals and Network Management Configuration Guide</i>
Fast Software Upgrade	<i>Route Processor Redundancy and Fast Software Upgrade on Cisco 7500 Series Routers</i>
Single Line Card Reload (SLCR)	<i>Cisco 7500 Single Line Card Reload</i> feature document

Standards

Standards	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	—

MIBs

MIBs	MIBs Link
No new or modified MIBs are supported by this feature, and support for existing MIBs has not been modified by this feature.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

RFCs

RFCs	Title
No new or modified RFCs are supported by this feature, and support for existing RFCs has not been modified by this feature.	—

Technical Assistance

Description	Link
Technical Assistance Center (TAC) home page, containing 30,000 pages of searchable technical content, including links to products, technologies, solutions, technical tips, and tools. Registered Cisco.com users can log in from this page to access even more content.	http://www.cisco.com/public/support/tac/home.shtml

Feature Information for Route Processor Redundancy Plus (RPR+)

Table 2 lists the release history for this feature.

Use Cisco Feature Navigator to find information about platform support and software image support. Cisco Feature Navigator enables you to determine which software images support a specific software release, feature set, or platform. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.



Note Table 2 lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Table 2 Feature Information for <Phrase Based on Module Title>

Feature Name	Releases	Feature Information
Route Processor Redundancy Plus (RPR+)	12.0(19)ST1	This feature was introduced.
Route Processor Redundancy Plus (RPR+)	12.0(22)S	This feature was integrated into Cisco IOS Release 12.0(22)S.

Table 2 Feature Information for <Phrase Based on Module Title> (continued)

Feature Name	Releases	Feature Information
Route Processor Redundancy Plus (RPR+)	12.2(14)S	This feature was integrated into Cisco IOS Release 12.2(14)S.
Route Processor Redundancy Plus (RPR+)	12.3(7)T	This feature was integrated into Cisco IOS Release 12.3(7)T. The following commands are introduced or modified in the feature: hw-module sec-cpu reset, hw-module slot image, redundancy, redundancy force-switchover, show redundancy (HSA redundancy).

Glossary

Active RSP—The RSP that controls and runs the routing protocols and that presents the system management interface.

HSA—High System Availability. HSA enables a system to reset and use a standby RSP if the active RSP fails.

RPR—Route Processor Redundancy. An alternative to HSA that reduces unplanned downtime.

RPR+—Route Processor Redundancy Plus. An enhancement to RPR in which the standby RSP is fully initialized. An RPR+ switchover does not involve resetting line cards or reloading line card software for VIPs. Legacy interface processors are reset and reloaded during switchover.

RSP—Route Switch Processor. The Route Processor on the Cisco 7500 series router.

Standby RSP—The RSP that waits ready to take over the functions of the active RSP in the event of unplanned or planned downtime.



Note

Refer to [Internetworking Terms and Acronyms](#) for terms not included in this glossary.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.

© 2007-2009 Cisco Systems, Inc. All rights reserved.