



# File System Commands on Cisco IOS XR Software

---

This chapter describes the Cisco IOS XR software commands used to manage file systems.



## Caution

The commands in this chapter should not be used to access or modify any Cisco IOS XR software or configuration files. Use only the documented commands for installing and configuring the router. Modifying, deleting, or moving configuration or software package files using the manual commands described in this chapter is not required and can result in router downtime, loss of service, and a corrupted database.

---

# cd

To change the present working directory, use the **cd** command in EXEC mode.

**cd** [*filesystem:*]

## Syntax Description

|                    |  |
|--------------------|--|
| <i>filesystem:</i> | (Optional) Location of the new present working directory. Include the file system alias for the <i>filesystem</i> argument, followed by a colon, and, optionally, the name of a directory. |
|--------------------|--|

## Defaults

The default file directory is disk0:/usr.

## Command Modes

EXEC

## Command History

| Releases      | Modifications   |
|---------------|---|
| Release 2.0   | This command was introduced on the Cisco CRS-1.                       |
| Release 3.0   | No modification.  |
| Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. |
| Release 3.3.0 | No modification.  |
| Release 3.4.0 | No modification.  |
| Release 3.5.0 | No modification.  |
| Release 3.6.0 | No modification.  |
| Release 3.7.0 | No modification.  |

## Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

The present working directory is the directory used when EXEC commands that have an optional *filesystem* argument are entered without that argument. Use the **cd** command to define the present working directory. For example, when the **dir** command is entered without specifying the *filesystem* argument, the files in the present working directory are displayed.

Use the **pwd** command to display the present working directory.

Use the **show filesystem** command to display the available storage devices.

Enter the **cd** command without an argument to return the present working directory to disk0:/usr.

## Task ID

| Task ID    | Operations |
|------------|------------|
| filesystem | read       |

## Examples

The following example shows how to change the present working directory to the root directory on the hard disk. In this example, the **pwd** command confirms that the present working directory has changed to the root directory on the hard disk.

```
RP/0/RP0/CPU0:router# cd harddisk:  
RP/0/RP0/CPU0:router# pwd
```

```
harddisk:
```

The following example shows how to change the present working directory to the default file directory by specifying the **cd** command without a location. In this example, the **pwd** command confirms that the present working directory has changed to the default file directory.

```
RP/0/RP0/CPU0:router# cd  
RP/0/RP0/CPU0:router# pwd
```

```
disk0:/usr
```

## Related Commands

| Command                         | Description  |
|---------------------------------|--|
| <a href="#">dir</a>             | Displays the contents of a file system.                          |
| <a href="#">pwd</a>             | Displays the current working directory of the <b>cd</b> command. |
| <a href="#">show filesystem</a> | Displays the layout and contents of a file system.               |

# cfs check

To perform a check of the Configuration File System (CFS), use the **cfs check** command in EXEC or administration EXEC mode.

## cfs check

**Syntax Description** This command has no arguments or keywords.

**Defaults** No default behavior or values

**Command Modes** EXEC  
Administration EXEC

| Command History | Release       | Modification  |
|-----------------|---------------|---|
|                 | Release 2.0   | This command was introduced on the Cisco CRS-1.                       |
|                 | Release 3.0   | No modification.  |
|                 | Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. |
|                 | Release 3.3.0 | No modification.  |
|                 | Release 3.4.0 | No modification.  |
|                 | Release 3.5.0 | No modification.  |
|                 | Release 3.6.0 | No modification.  |
|                 | Release 3.7.0 | No modification.  |

**Usage Guidelines** To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Use the **cfs check** command to check the sanity of the configuration file system and attempt to recover from internal inconsistencies; one or more rollback points may be lost depending on the severity of the state of the file system.



### Note

While this command runs, redundancy of the designated secure domain router system controller (DSDRSC) is disabled.

| Task ID | Task ID | Operations  |
|---------|---------|-------------|
|         | root-lr | read, write |

---

**Examples**

The following example shows how to perform a CFS check:

```
RP/0/RP0/CPU0:router# cfs check
```

```
Creating any missing directories in Configuration File system...OK  
Initializing Configuration Version Manager...OK  
Syncing commit database with running configuration...OK  
Re-initializing cache files...OK  
Updating Commit Database. Please wait...[OK]
```

# clear-classic-config

To clear or truncate the Cisco IOS software running configuration stored in NVRAM, use the **clear-classic-config** command in EXEC mode.

## clear-classic-config

**Syntax Description** This command has no arguments or keywords.

**Defaults** No default behavior or values

**Command Modes** EXEC

| Command History | Release       | Modification   |
|-----------------|---------------|--|
|                 | Release 3.2   | This command was introduced on the Cisco XR 12000 Series Router. |
|                 | Release 3.3.0 | No modification.   |
|                 | Release 3.4.0 | No modification.   |
|                 | Release 3.5.0 | No modification.   |
|                 | Release 3.6.0 | No modification.   |
|                 | Release 3.7.0 | No modification.   |

**Usage Guidelines** To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Use the **clear-classic-config** command to clear space on the NVRAM, if the Cisco IOS software configuration is no longer needed or to boot the Cisco IOS software with no configuration.

| Task ID | Task ID         | Operations |
|---------|-----------------|------------|
|         | config-services | execute    |

**Examples** The following example shows how to clear the Cisco IOS software running configuration stored in NVRAM:

```
RP/0/0/CPU0:router# clear-classic-config
```

# copy

To copy a file from a source (such as a network server) to a destination (such as a flash disk), use the **copy** command in EXEC or administration EXEC mode.

```
copy source {location node-id destination {location node-id | location all} | running-config
[atomic]}
```

| Syntax Description |                                |  |
|--------------------|--------------------------------|--|
|                    | <i>source</i>                  | <p>Filename including the directory path or network location of the file. The possible sources are:</p> <ul style="list-style-type: none"> <li>• <i>directory-path</i>—Directory path of the file from which the file is copied.</li> <li>• <b>access-list</b> {<b>ipv4</b>   <b>ipv6</b>}—Copies an access list (EXEC mode only).</li> <li>• <b>bootflash:</b>—Copies from the bootflash: file system.</li> <li>• <b>compactflash:</b>—Copies from the compactflash: file system (Cisco XR 12000 Series Router only).</li> <li>• <b>compactflasha:</b>—Copies from the compactflasha: file system partition (Cisco XR 12000 Series Router only).</li> <li>• <b>disk0:</b>—Copies from disk0: file system.</li> <li>• <b>disk0a:</b>—Copies from disk0a: file system partition.</li> <li>• <b>disk1:</b>—Copies from disk1: file system.</li> <li>• <b>disk1a:</b>—Copies from disk1a: file system partition.</li> <li>• <b>flash:</b>—Copies from the flash: file system. The <b>flash:</b> keyword is an alias for bootflash:.</li> <li>• <b>ftp:</b>—Copies from an FTP network server. The syntax is <b>ftp</b>:<i>[[//username[:password]@] location]/directory]/filename</i>.</li> <li>• <b>harddisk:</b>—Copies from the hard disk drive file system (if present).</li> <li>• <b>harddiska:</b>—Copies from the hard disk partition a.</li> <li>• <b>harddiskb:</b>—Copies from the hard disk partition b.</li> <li>• <b>nvr:</b>—Copies from the NVRAM file system.</li> <li>• <b>prefix-list</b> {<b>ipv4</b>   <b>ipv6</b>}—Copies from a prefix list (EXEC mode only).</li> <li>• <b>rcp:</b>—Copies from a remote copy protocol (rcp) network server. The syntax is <b>rcp</b>:<i>[[//username@] location]/directory]/filename</i>.</li> <li>• <b>running-config</b>—Copies from the current system configuration.</li> <li>• <b>tftp:</b>—Copies from a TFTP network server. The syntax is <b>tftp</b>:<i>[[//location]/directory]/filename</i>.</li> <li>• <b>xml-schema</b>—Copies the XML schema files as a tar ball file (.tar.gz) [EXEC mode only].</li> </ul> |
|                    | <i>destination</i>             | Filename including the directory path or network location of the file.   |
|                    | <b>location</b> <i>node-id</i> | Specifies a node. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.  |
|                    | <b>location</b> <b>all</b>     | Copies to all nodes.   |

|                       |   |
|-----------------------|---|
| <b>running-config</b> | Applies the source configuration file to the running configuration of the system.       |
| <b>atomic</b>         | (Optional) Applies the changes to the running configuration only if there are no errors |

**Defaults**

No default behavior or values

**Command Modes**

EXEC  
Administration EXEC

**Command History**

| Releases      | Modifications  |
|---------------|--|
| Release 2.0   | This command was introduced on the Cisco CRS-1.  |
| Release 3.0   | No modification.   |
| Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. The command was made available in administration EXEC mode.<br><br>Support was added to copy to a designated node or to all nodes. Hardware partition support was added. |
| Release 3.3.0 | No modification.   |
| Release 3.4.0 | No modification.   |
| Release 3.5.0 | Support was added to copy XML schema files.  |
| Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .   |
| Release 3.7.0 | No modification.   |

**Usage Guidelines**

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Source and destination can each be a configuration file, a text file, or a file system. Enter source and destination URL information, usernames, and passwords and issue the **copy** command. The networking device prompts for any missing information.

The exact format of the *source* and *destination* arguments vary according to the file or directory location. Enter the device or network location for the file system type.

Filenames can include the following characters:

! # \$ % & ' + 0 1 2 3 4 5 6 7 8 9 ; @ A B C D E F G H I J K L M N O P Q R S T U V W X Y Z [ ] ^ \_ a b c d e f g h i j k l m n o p q r s t u v w x y z { } ~

The following characters can be used with the stated limitations:

- ` needs backslash before this character
- - cannot be the first character
- . cannot be the last character
- = cannot be the filename without other characters



The following characters cannot be used in filenames:

" ( ) \* , / : < > ? \ |

The maximum length allowed by the Cisco CRS-1 router for a filename is 254 characters including the path. If a filename longer than 254 characters is specified, the filename is truncated to 254 characters.

To copy a file from a source on the router to a destination on the router, specify a source **location node-id** and a destination **location node-id**. To copy the file to all nodes, use the keywords **location all**.

In the alias syntax for the **ftp:**, **rcp:**, and **tftp:** keywords, the location is either an IP address or a hostname. The filename is specified relative to the directory used for file transfers.

When no alias is specified, the networking device looks for a file in the current directory. To view the current directory, enter the **pwd** command.



#### Note

During processing of the **copy** command, you might see the “C” character. For all files being copied, “C” indicates that the copy process is taking place. The entire copying process might take several minutes and differs from protocol to protocol and from network to network.

[Table 28](#) describes the network protocols supported by Cisco IOS XR software.

**Table 28** *Network Protocols Supported by Cisco IOS XR Software*

| Prefix       | Name                           | Description   |
|--------------|--------------------------------|---|
| <b>tftp:</b> | Trivial File Transfer Protocol | TFTP is a simplified version of FTP that allows files to be transferred from one computer to another over a network, usually without the use of client authentication (for example, username and password).                                 |
| <b>ftp:</b>  | File Transfer Protocol         | FTP is an application protocol, part of the TCP/IP protocol stack, and is used for transferring files between network nodes. FTP requires a username and password.  |
| <b>rcp:</b>  | Remote Copy Protocol           | The rcp protocol allows users to copy files to and from a file system residing on a remote host or server on the network. The rcp protocol uses TCP to ensure the reliable delivery of data. The rcp protocol downloads require a username. |

Additional usage guidelines are in the following sections:

- [Invalid Combinations of Source and Destination, page 305](#)
- [Using TFTP, page 306](#)
- [Using FTP, page 306](#)
- [Using rcp, page 306](#)

#### Invalid Combinations of Source and Destination

Some combinations of source and destination are invalid. Specifically, you cannot copy the following:

- From a running configuration to a running configuration
- From a network device to a network device (for example, **copy ftp: rcp:**)

### Using TFTP

TFTP is a simplified version of FTP that allows files to be transferred from one computer to another over a network, usually without the use of client authentication (for example, username and password).

The syntax is as follows:

**copy tftp://hostname | ipaddress/directory-path/pie-name target-device** [**location node-id** | **location all**]

Example:

```
RP/0/RP0/CPU0:router# copy tftp://1.1.1.1/images/crs_software.pie disk1:
```



#### Note

Some Cisco IOS XR software images may be larger than 32 MB, and the TFTP services provided by some vendors may not support a file this large. If you do not have access to a TFTP server that supports files larger than 32 MB, download the software image using FTP or rcp as described in the following sections.

### Using FTP

FTP servers require a username and password for each client request. Cisco IOS XR software sends the first valid username in the following list:

1. The username and password specified in the **copy** command, if a username is specified.

The syntax is as follows:

**copy ftp://username:password@hostname or ipaddress/directory-path/pie-name target-device**  
[**location node-id** | **location all**]

Example:

```
RP/0/RP0/CPU0:router# copy ftp://john:secret@10.1.1.1/images/crs_software.pie disk1:
```

2. An “anonymous” username and password. The anonymous password is “root@ip address,” where “ip address” is the IP address of the local networking device.
3. A password “username@iosname.domain” formed by the networking device. The variable “username” is the username associated with the current session, “iosname” is the configured hostname, and “domain” is the domain of the networking device.

The username and password must be associated with an account on the FTP server. If you are writing to the network server, the FTP server must be properly configured to accept the FTP write request from the user on the networking device.

If the network server has a directory structure, the configuration file or image is written to or copied from the directory associated with the username on the network server. For example, if the system image resides in the home directory of a user on the network server, specify the name of that user as the remote username.

Refer to the documentation for your FTP server for more details.

### Using rcp

The rcp protocol requires a username upon each request. When you copy a configuration file or image between the networking device and an rcp server, the Cisco IOS XR software sends the first valid username in the following list:

1. The remote username specified in the **copy** command, if one is specified.
2. The username set by the **rcp client username** command, if the command is configured.

### 3. The networking device hostname.

For the rcp copy request to process successfully, an account must be defined on the network server for the remote username. If the network administrator of the destination server did not establish an account for the remote username, this command does not run successfully. If the network server has a directory structure, the configuration file or image is written to or copied from the directory associated with the remote username on the network server. For example, if the system image resides in the home directory of a user on the network server, specify the name of that user as the remote username.

If you are writing to the network server, the rcp server must be properly configured to accept the rcp write request from the user on the networking device. For UNIX systems, add an entry to the .rhosts file for the remote user on the rcp server. Suppose the networking device contains the following configuration lines:

```
hostname Rtrl
ip rcp remote-username User0
```

If the IP address of the networking device translates to company.com, then the .rhosts file for User0 on the rcp server should contain the following line:

```
company.com Rtrl
```

See the documentation for your rcp server for more details.

If you are using a personal computer as a file server, the computer must support remote shell (rsh) protocol.

Table 29 shows the syntax and example for the **copy** command when used with FTP, rcp, and TFTP network servers.

**Table 29 Syntax and Examples of the copy Command**

| Type | Syntax and Example   |
|------|--|
| FTP  | <b>copy ftp://username:password@{hostname   ipaddress}/directory-path/pie-name target-device [location node-id   location all]</b><br>Example:<br>RP/0/RP0/CPU0:router# <b>copy ftp://john:secret@10.1.1.1/images/comp-crs-full.pie disk1:</b> |
| rcp  | <b>copy rcp://username@{hostname   ipaddress}/directory-path/pie-name target-device [location node-id   location all]</b><br>Example:<br>RP/0/RP0/CPU0:router# <b>copy rcp://john@10.1.1.1/images/comp-crs-full.pie disk1:</b>                 |
| TFTP | <b>copy tftp://{hostname   ipaddress}/directory-path/pie-name target-device [location node-id   location all]</b><br>Example:<br>RP/0/RP0/CPU0:router# <b>copy tftp://10.1.1.1/images/comp-crs-full.pie disk1:</b>                             |

### Using xml-schema

Use the **xml-schema** keyword to obtain the most up-to-date XML schemas (.xsd files) from the router. This is useful to prevent the use of outdated schemas in the event that router software updates include schema updates. The tar ball file includes all active schema files. It does not include schemas that are activated by specific Package Installation Envelopes (PIEs), if those PIEs are not installed and activated on the router.

### Copying to the Running Configuration

When you use the **copy** command to copy a configuration file to the **running-config** destination, the configuration in the file is applied to the running configuration of the system. This is a configuration operation. By default, the copy is carried out in a best-effort manner. This means that if some configuration lines from the file cannot be applied, the remaining configuration is still integrated into the system. In this case, a partial configuration is committed. When the **atomic** option is used, partial configurations are not committed. This means that even if one error occurs in the parsing or committing phase, no changes are made to the system. To view any errors when applying the configuration, use the **show configuration failed** command.

#### Task ID

| Task ID    | Operations |
|------------|------------|
| filesystem | execute    |

#### Examples

The following example shows how to copy a file from a FTP server to disk1:

```
RP/0/RP0/CPU0:router# copy ftp://john:secret@10.1.1.1/images/comp-crs-full.pie disk1:
```

#### Related Commands

| Command  | Description  |
|--|--|
| <a href="#">cd</a>                                 | Changes the default directory or file system.                                  |
| <a href="#">dir</a>                                | Displays the contents of a file system.  |
| <a href="#">show configuration failed (config)</a> | Displays information about a configuration that failed during the last commit. |

# delete

To delete files, use the **delete** command in EXEC or administration EXEC mode.

**delete** [/noprompt] [/ena] [filesystem:] filename {location node-id | location all}

|                           |                         |   |
|---------------------------|-------------------------|---|
| <b>Syntax Description</b> | <b>/noprompt</b>        | (Optional) Causes no prompt for confirmation before deleting the specified files.   |
|                           | <b>/ena</b>             | (Optional) Deletes all files from and below the current working directory.  |
|                           | <b>filesystem:</b>      | (Optional) Location of the file to be deleted. Include the file system alias for the <i>filesystem</i> argument, followed by a colon, and, optionally, the name of a directory. |
|                           | <b>filename</b>         | Filename of the file to be deleted.   |
|                           | <b>location node-id</b> | Deletes a file from a designated node. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.  |
|                           | <b>location all</b>     | Deletes a file from all nodes.  |
|                           |                         |   |

|                 |  |
|-----------------|--|
| <b>Defaults</b> | A filename must be specified. If a filename is entered without a file system or directory path, the present working directory is used. |
|-----------------|--|

|                      |                             |
|----------------------|-----------------------------|
| <b>Command Modes</b> | EXEC<br>Administration EXEC |
|----------------------|-----------------------------|

|                        |                |   |
|------------------------|----------------|---|
| <b>Command History</b> | <b>Release</b> | <b>Modification</b>   |
|                        | Release 2.0    | This command was introduced on the Cisco CRS-1.   |
|                        | Release 3.0    | No modification.  |
|                        | Release 3.2    | This command was first supported on the Cisco XR 12000 Series Router. The command was made available in administration EXEC mode. |
|                        |                | Support was added to delete files from a node or from all nodes.  |
|                        | Release 3.3.0  | No modification.  |
|                        | Release 3.4.0  | No modification.  |
|                        | Release 3.5.0  | No modification.  |
|                        | Release 3.6.0  | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .                              |
|                        | Release 3.7.0  | No modification.  |

|                         |  |
|-------------------------|--|
| <b>Usage Guidelines</b> | To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the <i>Configuring AAA Services on Cisco IOS XR Software</i> module of the <i>Cisco IOS XR System Security Configuration Guide</i> . |
|-------------------------|--|

## ■ delete

When a file is deleted, it is removed from the system and cannot be restored (undeleted).

Use the **dir** command to display the list of files on a storage device.

**Task ID**

| Task ID    | Operations |
|------------|------------|
| filesystem | execute    |

**Examples**

The following example shows how to delete a file:

```
RP/0/RP0/CPU0:router# delete rbtest
```

```
Delete disk1:/rbtest[confirm]y
```

**Related Commands**

| Command         | Description   |
|-----------------|---|
| <b>cd</b>       | Changes the default directory or file system.                     |
| <b>dir</b>      | Displays the contents of a file system.                           |
| <b>squeeze</b>  | Permanently deletes flash files by squeezing a flash file system. |
| <b>undelete</b> | Recovers a file marked “deleted” on a flash file system.          |

# dir

To display a list of files on a file system or in a specific directory, use the **dir** command in EXEC or administration EXEC mode.

**dir** [/all | /ena | /recurse] [*filesystem:*] [*filename*] {**location** *node-id* | **location** **all**}

| Syntax Description             |   |
|--------------------------------|---|
| <b>/all</b>                    | (Optional) Lists deleted files, undeleted files, and files with errors.   |
| <b>/ena</b>                    | (Optional) Recognizes subdirectories.   |
| <b>/recurse</b>                | (Optional) Recursively lists subdirectories.  |
| <i>filesystem:</i>             | (Optional) Name of the directory containing the files to be displayed. Include the file system alias for the <i>filesystem</i> argument, followed by a colon, and, optionally, the name of a directory. |
| <i>filename</i>                | (Optional) Name of the files to display. The files can be of any type. You can use wildcards in the filename. A wildcard character (*) matches all patterns. Strings following a wildcard are ignored.  |
| <b>location</b> <i>node-id</i> | Displays a lists of files from a directory on the designated node. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.  |
| <b>location</b> <b>all</b>     | Displays a lists of files from a directory on all nodes.  |

**Defaults** When the **dir** command is entered without keywords or arguments, the contents of the present working directory are displayed.

**Command Modes** EXEC  
Administration EXEC

| Command History | Releases      | Modifications   |
|-----------------|---------------|---|
|                 | Release 2.0   | This command was introduced on the Cisco CRS-1.   |
|                 | Release 3.0   | No modification.  |
|                 | Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. The command was made available in administration EXEC mode.<br><br>Support was added to display a list of files from a directory on a node or from all nodes. |
|                 | Release 3.3.0 | No modification.  |
|                 | Release 3.4.0 | No modification.  |
|                 | Release 3.5.0 | No modification.  |
|                 | Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .  |
|                 | Release 3.7.0 | No modification.  |

**Usage Guidelines**

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

If you enter the **dir** command without specifying a directory, the contents of the present working directory are displayed. The **all** keyword displays all files, including deleted files. The size associated with the directory name is the total size for all files in that directory.

**Task ID**

| Task ID    | Operations |
|------------|------------|
| filesystem | execute    |

**Examples**

The following example shows how to display the contents of a directory:

```
RP/0/RP0/CPU0:router# dir harddisk:/log
```

```
Directory of harddisk:/log
```

```
5527      drwx  4096      Thu Aug 28 11:21:48 2003  boot_28_Aug_2003_11_21_49
5533      drwx  4096      Thu Aug 28 11:38:54 2003  boot_28_Aug_2003_11_38_54
5538      drwx  4096      Fri Sep  5 13:28:54 2003  boot_05_Sep_2003_13_28_54
5543      drwx  4096      Mon Sep  8 08:55:52 2003  boot_08_Sep_2003_06_59_08
--More--
```

**Related Commands**

| Command                | Description  |
|------------------------|--|
| <b>cd</b>              | Changes the default directory or file system.                    |
| <b>pwd</b>             | Displays the current working directory of the <b>cd</b> command. |
| <b>show filesystem</b> | Displays the layout and contents of a file system.               |



## erase nvram:

To erase the NVRAM file system, use the **erase nvram:** command in EXEC mode.

**erase nvram:** [format]

|                           |  |
|---------------------------|--|
| <b>Syntax Description</b> | <b>format</b> (Optional) Formats the entire NVRAM. |
|---------------------------|--|

|                 |                               |
|-----------------|-------------------------------|
| <b>Defaults</b> | No default behavior or values |
|-----------------|-------------------------------|

|                      |      |
|----------------------|------|
| <b>Command Modes</b> | EXEC |
|----------------------|------|

| <b>Command History</b> | <b>Release</b> | <b>Modification</b>   |
|------------------------|----------------|---|
|                        | Release 2.0    | This command was introduced on the Cisco CRS-1.                       |
|                        | Release 3.0    | No modification.  |
|                        | Release 3.2    | This command was first supported on the Cisco XR 12000 Series Router. |
|                        | Release 3.3.0  | No modification.  |
|                        | Release 3.4.0  | No modification.  |
|                        | Release 3.5.0  | No modification.  |
|                        | Release 3.6.0  | No modification.  |
|                        | Release 3.7.0  | No modification.  |

|                         |  |
|-------------------------|--|
| <b>Usage Guidelines</b> | To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the <i>Configuring AAA Services on Cisco IOS XR Software</i> module of the <i>Cisco IOS XR System Security Configuration Guide</i> . |
|-------------------------|--|




### Caution

Using the **erase nvram:** command permanently removes the files.

| <b>Task ID</b> | <b>Task ID</b> | <b>Operations</b> |
|----------------|----------------|-------------------|
|                | filesystem     | execute           |

|                 |  |
|-----------------|--|
| <b>Examples</b> | <p>The following example shows how to erase the NVRAM file system:</p> <pre>RP/0/RP0/CPU0:router# <b>erase nvram:</b></pre> <p>Erase operation will destroy IOS/ENA files in "nvram:". Continue? [confirm]<b>y</b></p> |
|-----------------|--|

**Related Commands**

| Command                | Description                                |
|------------------------|--|
| <a href="#">delete</a> | Deletes a file from a flash memory device. |

## erase nvram-raw:

To format the NVRAM raw data partition with a '0' value, use the **erase nvram-raw:** command in EXEC or administration EXEC mode.

**erase nvram-raw:** [**location** {*node-id* | **all**}]

### Syntax Description

|   |   |
|---|---|
| <b>location</b> { <i>node-id</i>   <b>all</b> } | (Optional) Specifies the node where the file system is located. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation. Use the <b>all</b> keyword to indicate all nodes. |
|---|---|

### Defaults

No default behavior or values

### Command Modes

EXEC  
Administration EXEC

### Command History

| Release       | Modification   |
|---------------|--|
| Release 3.6.0 | This command was introduced on the Cisco CRS-1 and Cisco XR 12000 Series Router. |
| Release 3.7.0 | No modification.   |

### Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

The NVRAM is divided into two partitions. The first partition, consisting of 1 megabyte (MB), is used by the existing NVRAM file-system partition. The second partition, consisting of 1 MB, is a raw data partition and is used by the Kernel Dumper to store reboot historical logs, critical crash information, syslog, and Kernel Dumper traces. The **erase nvram-raw:** command formats the raw data partition of the NVRAM.


### Task ID

| Task ID    | Operations |
|------------|------------|
| filesystem | execute    |

### Examples

The following example shows how to erase the raw data partition of the NVRAM file system:

```
RP/0/RP0/CPU0:router# erase nvram-raw:
```

**Related Commands**

| Command                | Description                                |
|------------------------|--|
| <a href="#">delete</a> | Deletes a file from a flash memory device. |

# format

To format a file system, use the **format** command in EXEC or administration EXEC mode.

**format** *filesystem:* [**partition**] [*monlib-filename*] [**location** *node-id* | **all**] [**spare** *spare-number*] [**force**] [**recover**]

| Syntax Description               |  |   |
|----------------------------------|--|---|
| <i>filesystem:</i>               |  | Name of the file system to format, followed by a colon. Possible values are <b>bootflash:</b> , <b>disk0:</b> , <b>disk0a:</b> , <b>disk1:</b> , <b>disk1a:</b> , <b>harddisk:</b> , <b>harddiska:</b> , <b>harddiskb:</b> , <b>compactflash:</b> , and <b>compactflasha:</b> . |
| <b>partition</b>                 |  | (Optional) Creates a partition on a hard disk. This option is not available when the <b>bootflash:</b> keyword is entered for the <i>filesystem:</i> argument.  |
| <i>monlib-filename</i>           |  | (Optional) Name of the ROM monitor library (monlib) file to use for formatting the file system. The default monlib file is the one bundled with the system software.<br><br><b>Note</b> The monlib is used by ROMMON for accessing the file system on the media.                |
| <b>location</b> <i>node-id</i>   |  | (Optional) Specifies the node where the file system is located. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.   |
| <b>all</b>                       |  | (Optional) Specifies all nodes where the file system is located.  |
| <b>spare</b> <i>spare-number</i> |  | (Optional) Reserves spare sectors as specified by the <i>spare-number</i> argument when formatting flash memory. Valid values are from 0 to 16.   |
| <b>force</b>                     |  | (Optional) Forces a monlib update, without verifying the monlib version on the device.  |
| <b>recover</b>                   |  | (Optional) Recovers any sector read errors on a flash disk.   |

| Defaults | The default monlib file is the one included with the Cisco IOS XR software.<br><i>spare-number:</i> 0 |
|----------|---|
|----------|---|

| Command Modes | EXEC<br>Administration EXEC |
|---------------|-----------------------------|
|---------------|-----------------------------|

| Command History | Release       | Modification  |
|-----------------|---------------|---|
|                 | Release 2.0   | This command was introduced on the Cisco CRS-1.   |
|                 | Release 3.0   | No modification.  |
|                 | Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. The command was made available in administration EXEC mode.<br>Support was added to create a hard disk partition. |
|                 | Release 3.3.0 | No modification.  |
|                 | Release 3.4.0 | No modification.  |

| Release       | Modification   |
|---------------|--|
| Release 3.5.0 | No modification.   |
| Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> . |
| Release 3.7.0 | No modification.   |

### Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Before you can use a new flash memory card, you must format it.



#### Caution

Formatting a storage device deletes all data on that device.



#### Note

The file systems that are available on the router and the formatting options available for file systems differ according to platform.

Use the online help (?) function to display the file systems available to be formatted on the router and the formatting options available for a file system.

As of Cisco IOS XR Release 3.6.0, disk0: and disk1: can be partitioned into two partitions each: disk0: and disk0a:, disk1: and disk1a:. The harddisk: can be partitioned into three partitions: harddisk:, harddiska:, and harddiskb:. The primary partitions are used to store critical data. The secondary partitions are used to store noncritical data.

If you partition disk0:, disk1: or the compactflash:, the size of the partitions are as indicated in [Table 30](#):

**Table 30**      **Size of Disk Partitions in Relation to Size of Disk**

| Size of Disk     | Primary Partition Percentage | Secondary Partition Percentage |
|------------------|------------------------------|--------------------------------|
| less than 900 MB | Partitioning not supported   | Partitioning not supported     |
| 900 MB to 1.5 GB | 80%                          | 20%                            |
| 1.5 GB to 3 GB   | 60%                          | 40%                            |
| more than 3 GB   | 50%                          | 50%                            |

The size of the three hard disk partitions are as follows:

- Primary partition (harddisk:)—30%
- Secondary partition (harddiska:)—60%
- Third partition (harddiskb:)—10%

### Task ID

| Task ID                           | Operations |
|-----------------------------------|------------|
| root-lr (EXEC)                    | execute    |
| root-system (administration EXEC) | execute    |

## Examples

The following example shows how to format disk1:

```
RP/0/RP0/CPU0:router# format disk1:
```

The following example shows how to format disk1 with instructions to recover any sectors on the device that have read errors:

```
RP/0/RP0/CPU0:router# format disk1: recover
```

This format operation will try to recover sectors with read error

This operation may take a while. Continue? [confirm]

Format will destroy all data on "disk1:". Continue? [confirm]



### Note

When the console returns to the EXEC prompt, the new flash disk has been formatted and is ready for use.

## Related Commands

| Command              | Description   |
|----------------------|---|
| <a href="#">fsck</a> | Checks a file system for a damage and repairs any problems. |

# fsck

To check a file system for damage, use the **fsck** command in EXEC or administration EXEC mode.

**fsck** *filesystem*: [**location** *node-id*]

## Syntax Description

|                                   |   |
|-----------------------------------|---|
| <i>filesystem</i> :               | Name of the file system to check, followed by a colon. Possible values are <b>disk0:</b> , <b>disk0a:</b> , <b>disk1:</b> , <b>disk1a:</b> , <b>harddisk:</b> , <b>harddiska:</b> , <b>harddiskb:</b> , and <b>compactflasha:</b> . |
| <b>location</b><br><i>node-id</i> | (Optional) Specifies the node where the file system is located. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.   |

## Defaults

No default behavior or values

## Command Modes

EXEC  
Administration EXEC

## Command History

| Release       | Modification   |
|---------------|--|
| Release 2.0   | This command was introduced on the Cisco CRS-1.  |
| Release 3.0   | No modification.   |
| Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. Support was added to check the hard-disk A file system for damage and repair any problems.                     |
| Release 3.3.0 | No modification.   |
| Release 3.4.0 | No modification.   |
| Release 3.5.0 | No modification.   |
| Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .<br><br>The command checks the file system, but does not repair the file system. |
| Release 3.7.0 | No modification.   |

## Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

## Task ID

| Task ID    | Operations |
|------------|------------|
| filesystem | execute    |



## Examples

The following example shows how to check the file system on flash disk0: for damage:

```
RP/0/RP0/CPU0:router# fsck disk0:
```

```
Phase 1 - Read and compare FATs
```

```
Phase 2 - Check cluster chains
```

```
Phase 3 - Check directories
```

```
Phase 4 - Check for lost files
```

```
157280 kb used, 843344 kb free, 2541 files, 190 directories
```

```
Filesystem is clean.
```

## Related Commands

| Command                         | Description  |
|---------------------------------|--|
| <a href="#">show filesystem</a> | Displays the layout and contents of a file system. |

# mkdir

To create a new directory on a file system, use the **mkdir** command in EXEC or administration EXEC mode.

**mkdir** *filesystem:* [**location** *node-id* | **location** **all**]

## Syntax Description

|                                |   |
|--------------------------------|---|
| <i>filesystem:</i>             | File system on which to create a new directory.   |
| <b>location</b> <i>node-id</i> | (Optional) Creates a new directory on a file system on the designated node. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation. |
| <b>location</b> <b>all</b>     | (Optional) Creates a new directory on a file system on all RP and DRP nodes.  |

## Defaults

No default behavior or values

## Command Modes

EXEC  
Administration EXEC

## Command History

| Releases      | Modifications   |
|---------------|---|
| Release 2.0   | This command was introduced on the Cisco CRS-1.   |
| Release 3.0   | No modification.  |
| Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. The command was made available in administration EXEC mode.<br><br>Support was added to create a new directory on a file system on a designated node or on all nodes. |
| Release 3.3.0 | No modification.  |
| Release 3.4.0 | No modification.  |
| Release 3.5.0 | No modification.  |
| Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .  |
| Release 3.7.0 | No modification.  |

## Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

After you issue the **mkdir** command, Cisco IOS XR software prompts you to specify the name of the directory to be created. When specifying the name of the new directory, include the directory path where you want the new directory to reside. If you do not specify a directory path, the new directory is created in the /usr directory of the file system specified for the *filesystem:* argument.

| Task ID | Task ID    | Operations |
|---------|------------|------------|
|         | filesystem | execute    |

### Examples

The following example shows how to create a directory named newdir. The **dir** command is used to verify that the directory has been added.

```
RP/0/RP0/CPU0:router# mkdir harddisk:
```

```
Create directory filename []?newdir
```

```
Created dir harddisk:/newdir
```

```
RP/0/RP0/CPU0:router# dir harddisk:
```

```
Directory of harddisk:
```

```

11193      drwx  4096      Fri Feb 13 06:45:05 2004  newdir
37146      drwx  4096      Sun Dec 14 15:30:48 2003  malloc_dump
43030      drwx  4096      Wed Dec 24 11:20:52 2003  tracebacks
43035      drwx  4096      Thu Jan  8 18:59:18 2004  sau
51026      drwx  4096      Sat Dec 27 02:52:46 2003  tempA
51027      drwx  4096      Sat Dec 27 02:04:10 2003  dir.not.del
-430307552 -rwx   342      Fri Jan 16 10:47:38 2004  running-config
-430305504 -rwx  39790      Mon Jan 26 23:45:56 2004  cf.dat
```

```
39929724928 bytes total (39883231232 bytes free)
```

| Related Commands | Command               | Description   |
|------------------|-----------------------|---|
|                  | <a href="#">dir</a>   | Displays the contents of a file system.               |
|                  | <a href="#">rmdir</a> | Removes an existing directory in a flash file system. |

# pwd

To display the present working directory, use the **pwd** command in EXEC mode.

**pwd**

|                           |  |
|---------------------------|--|
| <b>Syntax Description</b> | This command has no arguments or keywords. |
|---------------------------|--|

|                 |                               |
|-----------------|-------------------------------|
| <b>Defaults</b> | No default behavior or values |
|-----------------|-------------------------------|

|                      |      |
|----------------------|------|
| <b>Command Modes</b> | EXEC |
|----------------------|------|

| Command History | Releases      | Modifications   |
|-----------------|---------------|---|
|                 | Release 2.0   | This command was introduced on the Cisco CRS-1.                       |
|                 | Release 3.0   | No modification.  |
|                 | Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. |
|                 | Release 3.3.0 | No modification.  |
|                 | Release 3.4.0 | No modification.  |
|                 | Release 3.5.0 | No modification.  |
|                 | Release 3.6.0 | No modification.  |
|                 | Release 3.7.0 | No modification.  |

|                         |  |
|-------------------------|--|
| <b>Usage Guidelines</b> | To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the <i>Configuring AAA Services on Cisco IOS XR Software</i> module of the <i>Cisco IOS XR System Security Configuration Guide</i> . |
|-------------------------|--|

Use the **pwd** command to show what directory or file system is specified as the default by the **cd** command.

| Task ID | Task ID    | Operations |
|---------|------------|------------|
|         | filesystem | read       |

|                 |   |
|-----------------|---|
| <b>Examples</b> | The following example shows how to display the present working directory: |
|-----------------|---|

```
RP/0/RP0/CPU0:router# pwd
```

```
disk0:/usr
```

| Related Commands | Command             | Description                                   |
|------------------|---------------------|---|
|                  | <a href="#">cd</a>  | Changes the default directory or file system. |
|                  | <a href="#">dir</a> | Displays the contents of a file system.       |

# rmdir

To remove an existing directory, use the **rmdir** command in EXEC or administration EXEC mode.

**rmdir** *filesystem*: {**location** *node-id* | **location** **all**}

## Syntax Description

|                                |  |
|--------------------------------|--|
| <i>filesystem</i>              | Name of the file system from which to delete a directory, followed by a colon. |
| <b>location</b> <i>node-id</i> | Removes a directory from the designated node.                                  |
| <b>location</b> <b>all</b>     | Removes a directory from all nodes.  |

## Defaults

No default behavior or values

## Command Modes

EXEC  
Administration EXEC

## Command History

| Releases      | Modifications   |
|---------------|---|
| Release 2.0   | This command was introduced on the Cisco CRS-1.   |
| Release 3.0   | No modification.  |
| Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. The command was made available in administration EXEC mode.<br>Support was added to remove a directory from a node or from all nodes. |
| Release 3.3.0 | No modification.  |
| Release 3.4.0 | No modification.  |
| Release 3.5.0 | No modification.  |
| Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .  |
| Release 3.7.0 | No modification.  |

## Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Use the **rmdir** command to remove directories (for example, to free up disk space) from a file system. After you issue the **rmdir** command, the Cisco IOS XR software prompts you to specify the name of the directory to be deleted.

When a directory contains files, you must remove the files before deleting the directory. Use the **delete** command to remove files.

| Task ID | Task ID    | Operations |
|---------|------------|------------|
|         | filesystem | execute    |

## Examples

The following example shows how to delete a subdirectory from the hard disk. The **dir** command is used to verify that the directory has been deleted.

```
RP/0/RP0/CPU0:router# rmdir harddisk:
```

```
Remove directory filename []?newdir
```

```
Delete harddisk:/newdir[confirm]y
```

```
RP/0/RP0/CPU0:router# dir harddisk:
```

```
Directory of harddisk:
```

```

37146      drwx  4096      Sun Dec 14 15:30:48 2003  malloc_dump
43030      drwx  4096      Wed Dec 24 11:20:52 2003  tracebacks
43035      drwx  4096      Thu Jan  8 18:59:18 2004  sau
51026      drwx  4096      Sat Dec 27 02:52:46 2003  tempA
51027      drwx  4096      Sat Dec 27 02:04:10 2003  dir.not.del
-430307552 -rwx   342      Fri Jan 16 10:47:38 2004  running-config
-430305504 -rwx  39790      Mon Jan 26 23:45:56 2004  cf.dat
```

```
39929724928 bytes total (39883235328 bytes free)
```

| Related Commands | Command                | Description                                     |
|------------------|------------------------|---|
|                  | <a href="#">delete</a> | Deletes a file from a flash memory device.      |
|                  | <a href="#">dir</a>    | Displays the contents of a file system.         |
|                  | <a href="#">mkdir</a>  | Creates a new directory on a flash file system. |

# show filesystem

To display the layout and contents of file systems, use the **show filesystem** command in EXEC or administration EXEC mode.

**show filesystem** *filesystem*: [**firmware** | **stats** | **verbose level**] [**location** *node-id* | **location all**]

## Syntax Description

|                                |   |
|--------------------------------|---|
| <b>filesystem:</b>             | Name of the file system for which to display information, followed by a colon. Possible values are: <b>disk0:</b> , <b>disk1:</b> , <b>harddisk:</b> , <b>compactflash:</b> . |
| <b>firmware</b>                | (Optional) Displays the firmware level.   |
| <b>stats</b>                   | (Optional) Displays device statistics.  |
| <b>verbose level</b>           | (Optional) Changes the device driver verbose level.   |
| <b>location</b> <i>node-id</i> | (Optional) Displays the layout and contents of file systems on the designated node. The <i>node-id</i> argument is entered in the <i>rack/slot/module</i> notation.           |
| <b>location all</b>            | (Optional) Displays the layout and contents of file systems on all nodes.   |

## Defaults

The file system for the active RP is displayed.

## Command Modes

EXEC  
Administration EXEC

## Command History

| Release       | Modification   |
|---------------|--|
| Release 2.0   | This command was introduced on the Cisco CRS-1.  |
| Release 3.0   | No modification.   |
| Release 3.2   | This command was first supported on the Cisco XR 12000 Series Router. Support was added to display the layout and contents of file systems on all nodes. |
| Release 3.3.0 | No modification.   |
| Release 3.4.0 | No modification.   |
| Release 3.5.0 | No modification.   |
| Release 3.6.0 | The following file systems were added: <b>disk0a:</b> , <b>disk1a:</b> , and <b>compactflasha:</b> .   |
| Release 3.7.0 | No modification.   |

## Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.



Use the **show filesystem** command to learn the alias names (prefixes) of the file systems supported by your networking device.

| Task ID | Task ID        | Operations |
|---------|----------------|------------|
|         | basic-services | read       |

## Examples

The following is sample output from the **show filesystem** command:

```
RP/0/RP0/CPU0:router# show filesystem
```

File Systems:

| Size(b)     | Free(b)     | Type       | Flags | Prefixes               |
|-------------|-------------|------------|-------|------------------------|
| -           | -           | network    | rw    | qsm/dev/fs/tftp: tftp: |
| -           | -           | network    | rw    | qsm/dev/fs/rcp: rcp:   |
| -           | -           | network    | rw    | qsm/dev/fs/ftp: ftp:   |
| 39929724928 | 39852978176 | harddisk   | rw    | harddisk:              |
| 1024606208  | 863584256   | flash-disk | rw    | disk0:                 |
| 2092032     | 2059264     | nvr        | rw    | nvr:                   |
| 62390272    | 62381260    | flash      | rw    | bootflash:             |

The following is sample output from the **show filesystem** command using the optional **location** keyword and **node-id** argument:

```
RP/0/RP0/CPU0:router# show filesystem location 0/rp0/cpu0
```

File Systems:

| Size(b)     | Free(b)     | Type       | Flags | Prefixes               |
|-------------|-------------|------------|-------|------------------------|
| -           | -           | network    | rw    | qsm/dev/fs/tftp: tftp: |
| -           | -           | network    | rw    | qsm/dev/fs/rcp: rcp:   |
| -           | -           | network    | rw    | qsm/dev/fs/ftp: ftp:   |
| 39929724928 | 39883235328 | harddisk   | rw    | harddisk:              |
| 2092032     | 2019328     | nvr        | rw    | nvr:                   |
| 1024606208  | 847888384   | flash-disk | rw    | disk0:                 |
| 62390272    | 62153616    | flash      | rw    | bootflash:             |

Table 31 describes the significant fields shown in the display.

**Table 31** *show filesystem Field Descriptions*

| Field    | Description  |
|----------|--|
| Size(b)  | Amount of memory in the file system (in bytes).      |
| Free(b)  | Amount of free memory in the file system (in bytes). |
| Type     | Type of file system.                                 |
| Flags    | Permissions for file system.                         |
| Prefixes | Alias for the file system.                           |

# show media

To display the current state of the disk storage media, use the **show media** command in EXEC or administration EXEC mode.

**show media** [*location node-id* | *location all*]

|                           |                         |  |
|---------------------------|-------------------------|--|
| <b>Syntax Description</b> | <b>location node-id</b> | (Optional) Displays the disk storage media on the designated node. The <i>node-id</i> argument is entered in the <i>rack/slot/module</i> notation. |
|                           | <b>location all</b>     | (Optional) Displays the disk storage media on all nodes.   |

**Defaults** The disk storage media for the active RP is displayed.

**Command Modes** EXEC  
Administration EXEC

|                        |                |  |
|------------------------|----------------|--|
| <b>Command History</b> | <b>Release</b> | <b>Modification</b>  |
|                        | Release 3.6.0  | This command was introduced on the Cisco CRS-1 and Cisco XR 12000 Series Router. |
|                        | Release 3.7.0  | No modification.   |

**Usage Guidelines** To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Use the **show media** command to view the status of the storage media on your system.

|                |                |                   |
|----------------|----------------|-------------------|
| <b>Task ID</b> | <b>Task ID</b> | <b>Operations</b> |
|                | filesystem     | read              |

**Examples** The following sample output disk displays the disk storage media for the active RP:

RP/0/RP0/CPU0:router# **show media**

Media Information for 0/RP0/CPU0.

| Mountpoint  | FsType | State       | DrvrPid | Mirror  | Flags |
|-------------|--------|-------------|---------|---------|-------|
| /disk0:     | FAT16  | Mounted     | 0024598 | Enabled |       |
| /disk0a:    | FAT16  | Not Present |         |         |       |
| /disk1:     | FAT16  | Mounted     | 0024599 |         |       |
| /disk1a:    | FAT16  | Not Present |         |         |       |
| /harddisk:  | FAT32  | Mounted     | 0143421 |         |       |
| /harddiska: | FAT32  | Not Present |         |         |       |

```
/harddiskb:      FAT32  Not Present
```

The following sample output displays the disk storage media on all nodes:

```
RP/0/RP0/CPU0:router# show media location all
```

Media Information for 0/4/CPU0.

| Mountpoint  | FsType | State       | DrvrPid | Mirror  | Flags |
|-------------|--------|-------------|---------|---------|-------|
| /disk0:     | FAT16  | Mounted     | 0024598 | Enabled |       |
| /disk0a:    | FAT16  | Not Present |         |         |       |
| /disk1:     | FAT16  | Not Present |         |         |       |
| /disk1a:    | FAT16  | Not Present |         |         |       |
| /harddisk:  | FAT32  | Mounted     | 0061493 |         |       |
| /harddiska: | FAT32  | Not Present |         |         |       |
| /harddiskb: | FAT32  | Not Present |         |         |       |

Media Information for 0/4/CPU1.

| Mountpoint  | FsType | State       | DrvrPid | Mirror  | Flags |
|-------------|--------|-------------|---------|---------|-------|
| /disk0:     | FAT16  | Mounted     | 0024598 | Enabled |       |
| /disk0a:    | FAT16  | Not Present |         |         |       |
| /disk1:     | FAT16  | Not Present |         |         |       |
| /disk1a:    | FAT16  | Not Present |         |         |       |
| /harddisk:  | FAT32  | Mounted     | 0036919 |         |       |
| /harddiska: | FAT32  | Not Present |         |         |       |
| /harddiskb: | FAT32  | Not Present |         |         |       |

Media Information for 0/RP0/CPU0.

| Mountpoint  | FsType | State       | DrvrPid | Mirror  | Flags |
|-------------|--------|-------------|---------|---------|-------|
| /disk0:     | FAT16  | Mounted     | 0024598 | Enabled |       |
| /disk0a:    | FAT16  | Not Present |         |         |       |
| /disk1:     | FAT16  | Mounted     | 0024599 |         |       |
| /disk1a:    | FAT16  | Not Present |         |         |       |
| /harddisk:  | FAT32  | Mounted     | 0143421 |         |       |
| /harddiska: | FAT32  | Not Present |         |         |       |
| /harddiskb: | FAT32  | Not Present |         |         |       |

Media Information for 0/RP1/CPU0.

| Mountpoint  | FsType | State       | DrvrPid | Mirror  | Flags |
|-------------|--------|-------------|---------|---------|-------|
| /disk0:     | FAT16  | Mounted     | 0024598 | Enabled |       |
| /disk0a:    | FAT16  | Not Present |         |         |       |
| /disk1:     | FAT16  | Mounted     | 0024599 |         |       |
| /disk1a:    | FAT16  | Not Present |         |         |       |
| /harddisk:  | FAT32  | Mounted     | 0131133 |         |       |
| /harddiska: | FAT32  | Not Present |         |         |       |
| /harddiskb: | FAT32  | Not Present |         |         |       |

Table 32 describes the significant fields shown in the display.

**Table 32** *show media Field Descriptions*

| Field      | Description                     |
|------------|---------------------------------|
| Mountpoint | File system name.               |
| FsType     | File system type.               |
| State      | State of the storage media.     |
| DrvrPid    | Process ID of the media driver. |

**Table 32**      *show media Field Descriptions (continued)*

| Field  | Description  |
|--------|--|
| Mirror | Indicates if disk mirroring is enabled or not.   |
| Flags  | Where disk mirroring is enabled, indicates whether the partition has been repaired, formatted, or the driver has been restarted. |

**Related Commands**

| Command                      | Description                                  |
|------------------------------|--|
| <a href="#">mirror</a>       | Configures disk mirroring on a node.         |
| <a href="#">mirror pause</a> | Temporarily pauses disk mirroring on a node. |

# squeeze

To permanently erase files tagged as “deleted” or “error” on a flash file system, use the **squeeze** command in EXEC mode.

**squeeze** *filesystem:*

| Syntax Description | <i>filesystem:</i> | Name of the file system, followed by a colon. |
|--------------------|--------------------|---|
|--------------------|--------------------|---|

| Defaults | No default behavior or values |
|----------|-------------------------------|
|----------|-------------------------------|

| Command Modes | EXEC |
|---------------|------|
|---------------|------|

| Command History | Release       | Modification   |
|-----------------|---------------|--|
|                 | Release 3.2   | This command was introduced on the Cisco XR 12000 Series Router. |
|                 | Release 3.3.0 | No modification.   |
|                 | Release 3.4.0 | No modification.   |
|                 | Release 3.5.0 | No modification.   |
|                 | Release 3.6.0 | No modification.   |
|                 | Release 3.7.0 | No modification.   |

| Usage Guidelines | <p>To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the <i>Configuring AAA Services on Cisco IOS XR Software</i> module of the <i>Cisco IOS XR System Security Configuration Guide</i>.</p> |
|------------------|--|
|------------------|--|

When flash memory is full, you might need to rearrange the files so that the space used by the files marked “deleted” can be reclaimed. (This “squeeze” process is required for linear flash memory cards to make sectors contiguous; the free memory must be in a “block” to be usable.)

When you enter the **squeeze** command, the router copies all valid files to the beginning of flash memory and erases all files marked “deleted.” After the squeeze process is completed, you can write to the reclaimed flash memory space.

**Caution**

After performing the squeeze process you cannot recover deleted files using the **undelete** command.

In addition to removing deleted files, the **squeeze** command removes any files that the system has marked as “error.” An error file is created when a file write fails (for example, the device is full). To remove error files, you must use the **squeeze** command.

Rewriting flash memory space during the squeeze operation may take several minutes.

## ■ squeeze

| Task ID | Task ID        | Operations |
|---------|----------------|------------|
|         | basic-services | execute    |

**Examples**

The following example shows how to permanently erase files tagged as “deleted” or “error” on the bootflash file system:

```
RP/0/0/CPU0:router# squeeze bootflash:
```

```
All deleted files will be removed. Continue? [confirm] y
Squeeze operation may take a while. Continue? [confirm] y
```

```
Squeeze under progress 30
Squeeze of bootflash: complete
```

| Related Commands | Command         | Description  |
|------------------|-----------------|--|
|                  | <b>delete</b>   | Deletes a file from a flash memory device.               |
|                  | <b>dir</b>      | Displays the contents of a file system.                  |
|                  | <b>undelete</b> | Recovers a file marked “deleted” on a flash file system. |

# undelete

To recover a file marked “deleted” on a flash file system, use the **undelete** command in EXEC mode.

**undelete** *index filesystem:*

|                           |                    |   |
|---------------------------|--------------------|---|
| <b>Syntax Description</b> | <i>index</i>       | Number that indexes the file in the <b>dir</b> command output.    |
|                           | <i>filesystem:</i> | File system containing the file to undelete, followed by a colon. |

|                 |  |
|-----------------|--|
| <b>Defaults</b> | The default file system is the one specified by the <b>cd</b> command. |
|-----------------|--|

|                      |      |
|----------------------|------|
| <b>Command Modes</b> | EXEC |
|----------------------|------|

|                        |                |  |
|------------------------|----------------|--|
| <b>Command History</b> | <b>Release</b> | <b>Modification</b>  |
|                        | Release 3.2    | This command was introduced on the Cisco XR 12000 Series Router. |
|                        | Release 3.3.0  | No modification.   |
|                        | Release 3.4.0  | No modification.   |
|                        | Release 3.5.0  | No modification.   |
|                        | Release 3.6.0  | No modification.   |
|                        | Release 3.7.0  | No modification.   |

|                         |  |
|-------------------------|--|
| <b>Usage Guidelines</b> | <p>To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the <i>Configuring AAA Services on Cisco IOS XR Software</i> module of the <i>Cisco IOS XR System Security Configuration Guide</i>.</p> |
|-------------------------|--|

For flash file systems, when you delete a file, Cisco IOS XR software simply marks the file as deleted, but it does not erase the file. The **undelete** command allows you to recover a deleted file on a specified flash memory device. You must undelete a file by its index, because you could have multiple deleted files with the same name. For example, the “deleted” list could contain multiple configuration files with the name router-config. You undelete by index to indicate which of the many router-config files from the list to undelete. Use the **dir** command to learn the index number of the file you want to undelete.

You cannot undelete a file if a valid (undeleted) file with the same name exists. Instead, you first delete the existing file and then undelete the file you want. For example, if you had an undeleted version of the router-config file and you wanted to use a previous, deleted version instead, you could not simply undelete the previous version by index. You would first delete the existing router-config file and then undelete the previous router-config file by index. You can delete and undelete a file up to 15 times.

On flash file systems, if you try to recover the configuration file pointed to by the CONFIG\_FILE environment variable, the system prompts you to confirm recovery of the file. This prompt reminds you that the CONFIG\_FILE environment variable points to an undeleted file. To permanently delete all files marked “deleted” on a flash memory device, use the **squeeze** command.

**■ undelete**

| Task ID | Task ID    | Operations |
|---------|------------|------------|
|         | filesystem | execute    |

**Examples**

The following example recovers the deleted file whose index number is 1 on the bootflash file system:

```
RP/0/0/CPU0:router# undelete 1 bootflash:
```

**Related Commands**

| Command                 | Description   |
|-------------------------|---|
| <a href="#">cd</a>      | Changes the default directory or file system.                     |
| <a href="#">delete</a>  | Deletes a file from a flash memory device.                        |
| <a href="#">dir</a>     | Displays the contents of a file system.                           |
| <a href="#">pwd</a>     | Displays the current working directory of the <b>cd</b> command.  |
| <a href="#">squeeze</a> | Permanently deletes flash files by squeezing a flash file system. |



# unmount

To render a media device safe to be removed, use the **unmount** command in EXEC or administration EXEC mode.

**unmount** *filesystem:* [**location** *node-id*] [**undo**]

## Syntax Description

|                                |  |
|--------------------------------|--|
| <i>filesystem:</i>             | File system to unmount, followed by a colon. Possible values are <b>disk0:</b> , <b>disk1:</b> , <b>harddisk:</b> , and <b>compactflash:</b> . |
| <b>location</b> <i>node-id</i> | (Optional) Specifies a node. The <i>node-id</i> argument is expressed in the <i>rack/slot/module</i> notation.                                 |
| <b>undo</b>                    | Remounts the device if it is not removed and reinserted.   |

## Defaults

No default behavior or values

## Command Modes

EXEC  
Administration EXEC

## Command History

| Release       | Modification   |
|---------------|--|
| Release 3.6.0 | This command was introduced on the Cisco CRS-1 and Cisco XR 12000 Series Router. |
| Release 3.7.0 | No modification.   |

## Usage Guidelines

To use this command, you must be in a user group associated with a task group that includes the proper task IDs. For detailed information about user groups and task IDs, see the *Configuring AAA Services on Cisco IOS XR Software* module of the *Cisco IOS XR System Security Configuration Guide*.

Use the **unmount** command before removing the media device. The command unmounts all partitions and ensures that no further access is made to the device. Use the **undo** option to remount the device if it is not removed and reinserted.

## Task ID

| Task ID                           | Operations |
|-----------------------------------|------------|
| root-lr (EXEC)                    | execute    |
| root-system (administration EXEC) | execute    |

## Examples

The following example unmounts the disk0: file system so that it can be safely removed:

```
RP/0/0/CPU0:router# unmount disk0:
```

| Related Commands | Command                 | Description   |
|------------------|-------------------------|---|
|                  | <a href="#">cd</a>      | Changes the default directory or file system.                     |
|                  | <a href="#">delete</a>  | Deletes a file from a flash memory device.                        |
|                  | <a href="#">dir</a>     | Displays the contents of a file system.                           |
|                  | <a href="#">pwd</a>     | Displays the current setting of the <b>cd</b> command.            |
|                  | <a href="#">squeeze</a> | Permanently deletes flash files by squeezing a flash file system. |