



Send document comments to nexus7k-docfeedback@cisco.com



Cisco Nexus 7000 Series NX-OS Quality of Service Command Reference

August 2011

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.

Cisco Nexus 7000 Series NX-OS Quality of Service Command Reference
© 2008–2010 Cisco Systems, Inc. All rights reserved.

Send document comments to nexus7k-docfeedback@cisco.com



CONTENTS

New and Changed Information v

Preface vii

Audience vii

Organization vii

Document Conventions vii

Related Documentation viii

Obtaining Documentation and Submitting a Service Request ix

Cisco Nexus 7000 Series NX-OS Quality of Service Commands QoS-1

bandwidth (QoS) QoS-2

bandwidth remaining QoS-5

class (policy map type qos) QoS-7

class type queuing (policy map type queuing) QoS-9

class-map type qos QoS-11

class-map type queuing match-any QoS-13

clear qos statistics QoS-14

default (table map) QoS-16

description QoS-17

from (table map) QoS-18

match access-group QoS-19

match class-map QoS-20

match cos (class map type qos) QoS-21

match cos (class map type queuing) QoS-23

match discard-class QoS-25

match dscp QoS-26

match ip rtp QoS-28

match packet length QoS-29

match precedence QoS-30

match protocol QoS-32

match qos-group QoS-34

police (QoS) QoS-36

Send document comments to nexus7k-docfeedback@cisco.com

| | |
|---|---------------|
| police aggregate | QoS-39 |
| policy-map type qos | QoS-41 |
| policy-map type queuing | QoS-43 |
| priority (queuing) | QoS-45 |
| qos shared-policer | QoS-47 |
| qos statistics | QoS-50 |
| queue-limit | QoS-51 |
| random-detect | QoS-53 |
| random-detect cos-based | QoS-56 |
| service-policy | QoS-58 |
| set cos (policy map type qos) | QoS-60 |
| set cos (policy map type queuing) | QoS-61 |
| set discard-class | QoS-63 |
| set dscp (QoS) | QoS-64 |
| set precedence (QoS) | QoS-66 |
| set qos-group | QoS-68 |
| set table | QoS-69 |
| shape | QoS-71 |
| show class-map type qos | QoS-73 |
| show class-map type queuing | QoS-75 |
| show policy-map | QoS-77 |
| show policy-map interface | QoS-79 |
| show policy-map interface brief | QoS-82 |
| show policy-map vlan | QoS-84 |
| show qos shared-policer | QoS-86 |
| show queuing interface | QoS-87 |
| show running-config ipqos | QoS-89 |
| show table-map | QoS-94 |
| table-map | QoS-96 |



New and Changed Information

This chapter provides release-specific information for each new and changed feature in the *Cisco Nexus 7000 Series NX-OS Quality of Service Command Reference, Release 5.1(1)*.

To check for additional information about Cisco NX-OS Release 5.1(1), see the *Cisco Nexus 7000 Series NX-OS Release Notes, Release 5.1* available at the following Cisco website:

http://www.cisco.com/en/US/docs/switches/datacenter/sw/5_x/nx-os/release/notes/51_nx-os_release_note.html

Table 1 summarizes the new and changed features for the *Cisco Nexus 7000 Series NX-OS Quality of Service Command Reference, Release 5.1(1)*.

Table 1 *New and Changed Features for Release 5.1(1)*

| Feature | Description | Changed in Release | Where Documented |
|---------------------------------------|--|--------------------|---|
| Network QoS Policy | Added the ability to define the characteristics of each CoS value by configuring a network qos policy. | 5.1(1) | <code>class-map type network-qos match-any</code> , <code>congestion-control</code> , <code>match cos (class map type network-qos)</code> , <code>mtu</code> , <code>pause</code> , <code>policy-map type network-qos</code> , <code>qos copy policy-map</code> , <code>show class-map type network-qos</code> , <code>show policy-map system type network-qos</code> , <code>show policy-map type network-qos</code> , <code>show qos dcbxp</code> |
| Priority Flow Control | Added the ability to configure priority flow control to avoid frame loss due to congestion. | 5.1(1) | <code>priority-flow-control mode</code> , <code>show interface priority-flow-control</code> |
| The <code>qos-dynamic</code> variable | Added the ability for the <code>qos-dynamic</code> variable to list the class-map and policy-map names that are already configured in a class. | 4.2(1) | <code>class (policy map type qos)</code> |

Send document comments to nexus7k-docfeedback@cisco.com

Table 1 ***New and Changed Features for Release 5.1(1) (continued)***

| Feature | Description | Changed in Release | Where Documented |
|---|--|---------------------------|-------------------------------------|
| Match IPv6 | Added the ability to match match IPv6 as well as IPv4 ACLs. | 4.1(2) | match access-group |
| Only similar values in mutation mapping | Added the limitation to set only similar values when a mutation map is created. For example, you can set cos-cos or dscp-dscp; you cannot set cos-dscp or dscp-precedence. | 4.1(2) | set table |
| Ignore variable for default command. | The ignore variable is no longer supported for the default command. | 4.0(2) | default (table map) |

Send document comments to nexus7k-docfeedback@cisco.com



Preface

This preface describes the audience, organization, and conventions of the *Cisco Nexus 7000 Series NX-OS Quality of Service Command Reference*. It also provides information on how to obtain related documentation.

This chapter includes the following sections:

- [Audience, page vii](#)
- [Organization, page vii](#)
- [Document Conventions, page vii](#)
- [Related Documentation, page viii](#)
- [Obtaining Documentation and Submitting a Service Request, page ix](#)

Audience

This publication is for experienced users who configure and maintain NX-OS devices.

Organization

This reference is organized as follows:

| Chapter and Title | Description |
|---|--|
| New and Changed Information | Describes the new and changed information for each Cisco NX-OS software release. |
| Cisco Nexus 7000 Series NX-OS Quality of Service Commands | Describes the Cisco NX-OS quality of service commands. |

Document Conventions

Command descriptions use these conventions:

| Convention | Description |
|----------------------|--|
| boldface font | Commands and keywords are in boldface. |

Send document comments to nexus7k-docfeedback@cisco.com

| | |
|--------------------|---|
| <i>italic font</i> | Arguments for which you supply values are in italics. |
| [] | Elements in square brackets are optional. |
| [x y z] | Optional alternative keywords are grouped in brackets and separated by vertical bars. |
| string | A nonquoted set of characters. Do not use quotation marks around the string or the string will include the quotation marks. |

Screen examples use these conventions:

| | |
|-----------------------------|---|
| screen font | Terminal sessions and information that the switch displays are in screen font. |
| boldface screen font | Information you must enter is in boldface screen font. |
| <i>italic screen font</i> | Arguments for which you supply values are in italic screen font. |
| < > | Nonprinting characters, such as passwords, are in angle brackets. |
| [] | Default responses to system prompts are in square brackets. |
| !, # | An exclamation point (!) or a pound sign (#) at the beginning of a line of code indicates a comment line. |

This document uses the following conventions:



Note

Means reader *take note*. Notes contain helpful suggestions or references to material not covered in the manual.



Caution

Means *reader be careful*. In this situation, you might do something that could result in equipment damage or loss of data.



Tip

Means *the following information will help you solve a problem*.

Related Documentation

[Cisco NX-OS](#) includes the following documents:

Release Notes

Cisco Nexus 7000 Series NX-OS Release Notes, Release 5.0

NX-OS Configuration Guides

Cisco Nexus 7000 Series NX-OS Getting Started with Virtual Device Contexts, Release 5.0

Cisco Nexus 7000 Series OTV Quick Start Guide

Cisco Nexus 7000 Series NX-OS Fundamentals Configuration Guide, Release 5.0

Cisco Nexus 7000 Series NX-OS Interfaces Configuration Guide, Release 5.0

Send document comments to nexus7k-docfeedback@cisco.com

Cisco Nexus 7000 Series NX-OS Layer 2 Switching Configuration Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS Quality of Service Configuration Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS Unicast Routing Configuration Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS Multicast Routing Configuration Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS Security Configuration Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS OTV Configuration Guide, Release 5.x
Cisco Nexus 7000 Series NX-OS Virtual Device Context Configuration Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS FabricPath Configuration Guide, Release 5.x
Cisco Nexus 7000 Series NX-OS Software Upgrade and Downgrade Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS Licensing Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS High Availability and Redundancy Guide, Release 5.0
Cisco Nexus 7000 Series NX-OS System Management Configuration Guide, Release 5.0
Cisco NX-OS XML Management Interface User Guide, Release 5.0
Cisco NX-OS System Messages Reference
Cisco Nexus 7000 Series NX-OS MIB Quick Reference

NX-OS Command References

Cisco Nexus 7000 Series NX-OS Command Reference Master Index, Release 5.0
Cisco Nexus 7000 Series NX-OS Fundamentals Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS Interfaces Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS Layer 2 Switching Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS Quality of Service Command Reference
Cisco Nexus 7000 Series NX-OS Unicast Routing Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS Multicast Routing Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS Security Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS OTV Command Reference, Release 5.x
Cisco Nexus 7000 Series NX-OS Virtual Device Context Command Reference, Release 5.0
Cisco Nexus 7000 Series NX-OS FabricPath Command Reference, Release 5.x
Cisco Nexus 7000 Series NX-OS System Management Command Reference, Release 5.0

Other Software Document

Cisco Nexus 7000 Series NX-OS Troubleshooting Guide, Release 5.0

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Send document comments to nexus7k-docfeedback@cisco.com

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

Send document comments to nexus7k-docfeedback@cisco.com



Cisco Nexus 7000 Series NX-OS Quality of Service Commands

This chapter describes the Cisco NX-OS quality of service (QoS) commands.

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

bandwidth (QoS)

To allocate a minimum percentage of the interface bandwidth to a queue and configure the bandwidth on both ingress and egress queues, use the **bandwidth** command. To remove a bandwidth configuration, use the **no** form of this command.

bandwidth {*rate* [**bps** | **kbps** | **mbps** | **gbps**] | **percent** *percent*}

no bandwidth {*rate* [**bps** | **kbps** | **mbps** | **gbps**] | **percent** *percent*}

Syntax Description

| | |
|----------------|--|
| <i>rate</i> | Bandwidth rate. The range is from 1 to 10000000000. |
| bps | (Optional) Specifies the units of bits per second. |
| kbps | (Optional) Specifies the units of 1000 bits per second. |
| mbps | (Optional) Specifies the units of megabits per second. |
| gbps | (Optional) Specifies the units of gigabits per second. |
| percent | Specifies the percentage of bandwidth of the underlying link rate. |
| <i>percent</i> | Percent value in the range from 1 to 100. |

Defaults

None

Command Modes

Policy map type queuing class configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

You can use the system-defined ingress or egress queue class for the type of module to which you want to apply the policy map. For more information about system-defined type queuing class maps, see [Table 1](#).

Table 1 System-Defined Type queuing Class Maps

| Class Map Queue Name | Description | Default CoS Values |
|---|------------------------------------|--------------------|
| 1 Gigabit Module Ingress: 2 queues with 4 thresholds per queue | | |
| 2q4t-in-q1 | Ingress queue 1 of 2q4t type | 5-7 |
| 2q4t-in-q-default | Ingress default queue of 2q4t type | 0-4 |
| 1 Gigabit Module Egress: 1 strict priority queue and 3 normal queues with 4 thresholds per queue | | |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

Table 1 System-Defined Type queuing Class Maps (continued)

| Class Map Queue Name | Description | Default CoS Values |
|--|--------------------------------------|--------------------|
| 1p3q4t-out-pq1 ¹ | Egress priority queue of 1p3q4t type | 5-7 |
| 1p3q4t-out-q2 | Egress queue 2 of 1p3q4t type | — |
| 1p3q4t-out-q3 | Egress queue 3 of 1p3q4t type | — |
| 1p3q4t-out-q-default | Egress default queue of 1p3q4t type | 0-4 |
| 10 Gigabit Module Ingress: 8 queues with 2 thresholds per queue | | |
| 8q2t-in-q1 | Ingress queue 1 of 8q2t type | 5-7 |
| 8q2t-in-q2 | Ingress queue 2 of 8q2t type | — |
| 8q2t-in-q3 | Ingress queue 3 of 8q2t type | — |
| 8q2t-in-q4 | Ingress queue 4 of 8q2t type | — |
| 8q2t-in-q5 | Ingress queue 5 of 8q2t type | — |
| 8q2t-in-q6 | Ingress queue 6 of 8q2t type | — |
| 8q2t-in-q7 | Ingress queue 7 of 8q2t type | — |
| 8q2t-in-q-default | Ingress default queue of 8q2t type | 0-4 |
| 10 Gigabit Module Egress: 1 strict priority queue and 7 normal queues with 4 thresholds per queue | | |
| 1p7q4t-out-pq1 ¹ | Egress priority queue of 1p7q4t type | 5-7 |
| 1p7q4t-out-q2 | Egress queue 2 of 1p7q4t type | — |
| 1p7q4t-out-q3 | Egress queue 3 of 1p7q4t type | — |
| 1p7q4t-out-q4 | Egress queue 4 of 1p7q4t type | — |
| 1p7q4t-out-q5 | Egress queue 5 of 1p7q4t type | — |
| 1p7q4t-out-q6 | Egress queue 6 of 1p7q4t type | — |
| 1p7q4t-out-q7 | Egress queue 7 of 1p7q4t type | — |
| 1p7q4t-out-q-default | Egress default queue of 1p7q4t type | 0-4 |

1. These are either priority or normal queues. If you use the priority keyword in your configuration, these are used as priority queues. Otherwise, they are used as normal queues.



Note

After you use this command in a specified policy map, you cannot use the **priority** or **shape** command in the same policy map.

This command does not require a license.

Examples

This example shows how to specify a bandwidth rate for a queue:

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)# class type queuing 1p7q4t-out-pq1
switch(config-pmap-c-que)# bandwidth 10 mbps
```

This example shows how to remove a bandwidth rate for a queue:

```
switch(config)# policy-map type queuing my_policy1
```

Send document comments to nexus7k-docfeedback@cisco.com

```
switch(config-pmap-que)# class type queuing lp7q4t-out-pq1
switch(config-pmap-c-que)# no bandwidth 10 mbps
```

Related Commands

| Command | Description |
|----------------------------|---|
| bandwidth remaining | Configures the bandwidth remaining on the interface in a queue. |
| show class-map | Displays class maps. |
| show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

bandwidth remaining

To configure the percentage of the bandwidth remaining on the interface after other allocations are configured on both ingress and egress queues, use the **bandwidth remaining** command. To remove the remaining bandwidth allocation, use the **no** form of this command.

bandwidth remaining percent *{percent}*

no bandwidth remaining percent *{percent}*

| | | |
|---------------------------|----------------|---|
| Syntax Description | <i>percent</i> | Percentage of remaining bandwidth on the underlying link. Valid values are from 0 to 100. |
|---------------------------|----------------|---|

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|---|
| Command Modes | Policy map type queuing class configuration |
|----------------------|---|

| | |
|---------------------------|----------------------------|
| SupportedUserRoles | network-admin vdc-admin |
|---------------------------|----------------------------|

| Command History | Release | Modification |
|------------------------|----------------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines You can use the system-defined ingress or egress queue class for the type of module to which you want to apply the policy map. For more information about system-defined type queuing class maps, see [Table 1](#). You can use this command with the **priority** command.

For more information on using this command, see the *Cisco Nexus 7000 Series NX-OS Quality of Service Configuration Guide, Release 5.0*.

This command does not require a license.

Examples This example shows how to set the bandwidth remaining for the specified queue:

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)# class type queuing lp7q4t-out-pq1
switch(config-pmap-c-que)# bandwidth remaining percent 25
```

This example shows how to remove the bandwidth remaining for the specified queue:

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)# class type queuing lp7q4t-out-pq1
switch(config-pmap-c-que)# no bandwidth remaining percent 25
```

■ bandwidth remaining

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|------------------------|---|
| bandwidth | Allocates a minimum percentage of the interface bandwidth to a queue. |
| show class-map | Displays class maps. |
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

class (policy map type qos)

To add a reference to an existing qos class map in a policy map and enter the class mode, use the **class** command. To remove a class from the policy map, use the **no** form of this command.

```
class [type qos] {class-map-name | qos-dynamic | class-default} [insert-before [type qos]
before-class-map-name]
```

```
no class {class-map-name | class-default}
```

| Syntax Description | type qos | (Optional) Specifies the component type, which is qos for this class. By default, the type is qos. |
|--------------------|--|--|
| | <i>class-map-name</i> | Reference to a class map. |
| | qos-dynamic | Specifies already configured class maps. |
| | class-default | Specifies the reserved class name that matches all traffic not classified in other classes in a policy map. |
| | insert-before <i>before-class-map-name</i> | (Optional) Specifies the position of this class in the policy. If not specified, the class is placed at the end of the classes in the policy. Policy actions in the first class that matches the traffic type are performed. |

Defaults None

Command Modes Policy map type qos configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|--|
| | 4.0 | This command was introduced. |
| | 4.2(1) | The qos-dynamic variable was added. |

Usage Guidelines Policy actions in the first class that matches the traffic type are performed.
This command does not require a license.

Examples This example shows how to add a reference to a class map at the end of a policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap)# class traffic_class2
switch(config-pmap-c-qos)#
```

Send document comments to nexus7k-docfeedback@cisco.com

This example shows how to add a reference to a class map before an existing class map reference in a policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class insert-before traffic_class2 traffic_class1
switch(config-pmap-c-qos)#
```

This example shows how to add a reference to the class-default class map in a policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class class-default
switch(config-pmap-c-qos)#
```

This example shows how to remove a class map reference in a policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap)# no class traffic_class1
switch(config-pmap)#
```

Related Commands

| Command | Description |
|---------------------------|--------------------------------------|
| show class-map qos | Displays class maps. |
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

class type queuing (policy map type queuing)

To add a reference to an existing queuing class map in a policy map and enter the class mode, use the **class type queuing** command. To remove a class from the policy map, use the **no** form of this command.

class type queuing *class-map-name*

no class type queuing *class-map-name*

| | | |
|---------------------------|-----------------------|--|
| Syntax Description | <i>class-map-name</i> | Reference to a system-defined class map. For a list of the system-defined type queuing class maps, see Table 1 . |
|---------------------------|-----------------------|--|

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|---------------------------------------|
| Command Modes | policy map type queuing configuration |
|----------------------|---------------------------------------|

| | |
|-----------------------------|----------------------------|
| Supported User Roles | network-admin vdc-admin |
|-----------------------------|----------------------------|

| Command History | Release | Modification |
|------------------------|----------------|------------------------------|
| | 4.0 | This command was introduced. |

| | |
|-------------------------|--|
| Usage Guidelines | Policy actions in the first class that matches the traffic type are performed. This command does not require a license. |
|-------------------------|--|

| | |
|-----------------|---|
| Examples | This example shows how to add a reference to a class map at the end of a type queuing policy map: |
|-----------------|---|

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)# class type queuing 8q2t-in-q4
switch(config-pmap-c-que)#
```

This example shows how to add a reference to a class map before an existing class map reference in a type queuing policy map:

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)# class type queuing 8q2t-in-q4 insert-before type queuing
8q2t-in-q2
switch(config-pmap-c-que)#
```

This example shows how to remove a class map reference in a type queuing policy map:

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)# no class type queuing 8q2t-in-q4
switch(config-pmap-que)#
```

■ class type queuing (policy map type queuing)

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|-------------------------------|--------------------------------------|
| | show class-map queuing | Displays class maps. |
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

class-map type network-qos match-any

To configure a class map and enter the type network qos configuration mode, use the **class-map type network-qos** command. To remove the class map of the type network qos, use the **no** form of this command.

```
class-map type network-qos match-any {class-map-name} {c-nq-4e-drop | c-nq-4e-ndrop |
c-nq-4e-ndrop-fcoe | c-nq-6e-drop | c-nq-6e-ndrop | c-nq-6e-ndrop-fcoe | c-nq-7e-drop |
c-nq-7e-ndrop-fcoe | c-nq-8e | eth}
```

```
no class-map type network-qos match-any {class-map-name} {c-nq-4e-drop | c-nq-4e-ndrop |
c-nq-4e-ndrop-fcoe | c-nq-6e-drop | c-nq-6e-ndrop | c-nq-6e-ndrop-fcoe | c-nq-7e-drop |
c-nq-7e-ndrop-fcoe | c-nq-8e | eth}
```

Syntax Description

| | |
|---------------------------|--|
| <i>class-map-name</i> | Class-map name. The policy map names can contain alphabetic, hyphen, or underscore characters, are case sensitive, and can be up to 40 characters. |
| c-nq-4e-drop | Specifies the default 4e drop class. |
| c-nq-4e-ndrop | Specifies the default 4e no-drop class. |
| c-nq-4e-ndrop-fcoe | Specifies the default 4e no-drop Fibre Channel over Ethernet (FCoE) class. |
| c-nq-6e-drop | Specifies the default 6e drop class. |
| c-nq-6e-ndrop | Specifies the default 6e no-drop class. |
| c-nq-6e-ndrop-fcoe | Specifies the default 6e no-drop FCoE class. |
| c-nq-7e-drop | Specifies the default 7e drop class. |
| c-nq-7e-ndrop-fcoe | Specifies the default 7e no-drop FCoE class. |
| c-nq-8e | Specifies the default 8e drop class. |
| eth | Specifies the class map name of the type network qos. |

Defaults

type—qos

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 5.1(1) | This command was introduced. |

Usage Guidelines

This command does not require a license.

Send document comments to nexus7k-docfeedback@cisco.com

Examples

This example shows how to configure the class map of the type network qos:

```
switch# configure terminal
switch(config)# class-map type network-qos match-any eth
switch(config)#
```

This example shows how to remove the class map of the type network qos:

```
switch# configure terminal
switch(config)# no class-map type network-qos match-any eth
switch(config)#
```

Related Commands

| Command | Description |
|---|--|
| show class-map network-qos | Display type network-qos class maps. |
| match cos (class map type network-qos) | Defines the class of traffic in type network-qos class maps. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

class-map

To create or modify a class map that defines a class of traffic and enter the class-map configuration mode, use the **class-map** command. To remove a class map, use the **no** form of this command.

```
class-map [type qos] {[match-any | match-all] class-map-name | conform-color-in |
conform-color-out | exceed-color-in | exceed-color-out}
```

```
no class-map [type qos] {class-map-name | [match-any | match-all]}
```

Syntax Description

| | |
|--------------------------|--|
| type qos | (Optional) Specifies the component type qos for the class map. By default, the class map type is qos. |
| match-any | Specifies that if the packet matches any of the criteria configured for this class map with the match command, then this class map is applied to the packet. |
| match-all | Specifies that if the packet matches all the criteria configured for this class map with the match command, then this class map is applied to the packet. This is the default action if match-any is not specified. Note This option does not work. The match criteria is always treated as <i>match-any</i> . |
| <i>class-map-name</i> | Name assigned to the class map. The name class-default is reserved. |
| conform-color-in | Specifies the type qos conform color class map in the input direction. This color-aware class map makes a policer color-aware for conform action. |
| conform-color-out | Specifies the type qos conform color class map in the output direction. This color-aware class map makes a policer color-aware for conform action. |
| exceed-color-in | Specifies the type qos exceed color class map in the input direction. This color-aware class map makes a policer color-aware for exceed action. |
| exceed-color-out | Specifies the type qos exceed color class map in the output direction. This color-aware class map makes a policer color-aware for exceed action. |

Defaults

type—qos

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

Usage Guidelines

You cannot delete the system-defined queuing class map names. For more information about the **class-map** command, see the *Cisco Nexus 7000 Series NX-OS Quality of Service Configuration Guide, Release 5.0*.



Note

When you configure match all for a qos class map by entering the **class-map type qos match-all** command, the match-all option does not work. Instead, the match criteria is always treated as match any.

This command does not require a license.

Examples

This example shows how to create or modify a qos class map:

```
switch(config)# class-map my_class1
switch(config-cmap-qos)#
```

This example shows how to remove a qos class map:

```
switch(config)# no class-map my_class1
switch(config)#
```

This example shows how to modify a qos color class map:

```
switch(config)# class-map conform-color-in
switch(config-color-map)#
```

Related Commands

| Command | Description |
|---------------------------|----------------------|
| show class-map qos | Displays class maps. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

class-map type queuing match-any

To modify a type queuing class map and enter the class-map configuration mode, use the **class-map type queuing match-any** command.

```
class-map type queuing match-any {queuing-class-map-name | WORD}
```

Syntax Description

| | |
|-------------------------------|---|
| <i>queuing-class-map-name</i> | System-defined queuing class map name. For the list of system-defined queuing class maps, see Table 1 . |
| <i>WORD</i> | Hierarchical class-map name. It can be a string of 40 alphanumeric characters. |

Defaults

None

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|---------------------------------|
| 5.1(1) | Added the <i>WORD</i> argument. |
| 4.0 | This command was introduced. |

Usage Guidelines

The argument *WORD* is supported only on the F-Series Modules.

When a non-8e template is active, it allows you to specify a hierarchical queuing (both ingress and egress) policy.

If the packet matches any of the criteria configured for this class map with the **match** command, this class map is applied to the packet. Class maps of type queuing support only this option.

Any modification made to the class maps type queuing changes the configuration for all ports of the specified port type on all VDCs.

You cannot delete system-defined queuing class map names. For more information on using the **class-map type queuing match-any** command, see the *Cisco Nexus 7000 Series NX-OS Quality of Service Configuration Guide, Release 5.0*.

This command does not require a license.

Examples

This example shows how to modify a queuing class map:

```
switch(config)# class-map type queuing match-any 2q4t-in-q1
switch(config-cmap-que)#
```

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|-------------------------------|--|
| | show class-map queuing | Displays class maps. |
| | match cos | Defines the class of traffic in type queuing class maps. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

clear qos statistics

To clear the quality of service (QoS) statistics, use the **clear qos statistics** command.

```
clear qos statistics [{interface [ethernet type/slot | port-channel number] | [vlan [vlan-id]}] [input
| output] [type {qos | queuing}]
```

| Syntax Description | |
|----------------------------|--|
| interface | (Optional) Specifies which interface to clear. |
| ethernet | (Optional) Specifies the statistics that are assigned to the Ethernet interface. |
| port-channel | (Optional) Specifies the statistics that are assigned to the port channel. |
| vlan <i>vlan-id</i> | (Optional) Specifies a VLAN to clear. Valid values are from 1 to 4094. |
| input | (Optional) Clears only input statistics. |
| output | (Optional) Clears only output statistics. |
| type | (Optional) Specifies the type of statistics to clear. |
| qos | Specifies to clear QoS statistics. |
| queuing | Specifies to clear queuing statistics. |

Defaults None

Command Modes Any command mode

SupportedUserRoles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines If you do not specify the interface or VLAN, the device clears the counters for all VLANs and interfaces. This command does not require a license.

Examples This example shows how to clear all the QoS statistics:

```
switch# clear qos statistics
switch#
```

This example shows how to clear all input QoS statistics for VLAN 1:

```
switch# clear qos statistics vlan 1 input
switch#
```

■ clear qos statistics

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|---------------------|-------------------------------------|
| | qos statistics | Enables or disables QoS statistics. |
| | show qos statistics | Displays QoS statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

congestion-control

To configure congestion control, use the **congestion-control** command. To remove the congestion control configuration, use the **no** form of this command.

```
congestion-control [random-detect {threshold [burst-optimized | mesh-optimized]} | tail-drop
{threshold [burst-optimized | mesh-optimized]}]
```

```
no congestion-control [random-detect {threshold [burst-optimized | mesh-optimized]} |
tail-drop {threshold [burst-optimized | mesh-optimized]}]
```

| Syntax Description | |
|------------------------|--|
| random-detect | (Optional) Specifies the weighted random early detection (WRED). |
| threshold | Specifies the threshold for the optimized traffic. |
| burst-optimized | (Optional) Specifies the burst-optimized traffic. |
| mesh-optimized | (Optional) Specifies the mesh-optimized traffic. |
| tail-drop | (Optional) Specifies the tail-drop algorithm for queue management. |

Defaults None

Command Modes Policy-map type network qos configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to configure congestion control:

```
switch# config t
switch(config)# policy-map type network-qos my_template
switch(config-pmap-nqos)# class type network-qos eth
switch(config-pmap-nqos-c)# congestion-control tail-drop threshold mesh-optimized
switch(config-pmap-nqos-c)#
```

This example shows how to configure congestion control:

```
switch# config t
switch(config)# policy-map type network-qos my_template
switch(config-pmap-nqos)# class type network-qos eth
switch(config-pmap-nqos-c)# no congestion-control tail-drop threshold mesh-optimized
```

Send document comments to nexus7k-docfeedback@cisco.com

```
switch(config-pmap-nqos-c)#
```

| Related Commands | Command | Description |
|------------------|-----------------|--|
| | mtu | Configures the maximum transmission unit (MTU) size in a network qos policy. |
| | pause | Configure no-drop per CoS. |
| | priority | Marks the priority level in a traffic queue. |
| | shape | Configures the traffic rate for a given traffic profile. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

default (table map)

To specify the default action for mapping input field values to output field values in a table map, use the **default** command.

```
default {value | copy}
```

```
no default {value | copy}
```

Syntax Description

| | |
|--------------|---|
| <i>value</i> | Default value to use for the output value in the range from 0 to 63. |
| copy | Specifies that the default action is to copy all equal values to an equal output value. |

Defaults

Copies the input value to the output value.

Command Modes

Table map configuration
Default table map configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|---|
| 4.0 | This command was introduced. |
| 4.0(2) | The <i>ignore</i> variable for this command is no longer supported. |

Usage Guidelines

The **copy** keyword is available only in the table map configuration mode. In the default table map configuration mode, the **copy** keyword is not available because all values must be assigned a mapping. This command does not require a license.

Examples

This example shows how to remove the default mapping action copy. The resulting default action is ignore:

```
switch(config)# table-map my_table1
switch(config-tmap)# no default copy
switch(config-tmap)#
```

Related Commands

| Command | Description |
|-----------------------|---|
| from | Specifies the input field to output field mappings in table maps. |
| show table-map | Displays table maps. |

Send document comments to nexus7k-docfeedback@cisco.com

description

To add a description to a class map, policy map, or table map, use the **description** command. To remove the description, use the **no** form of this command.

description *text*

no description *text*

Syntax Description

| | |
|-------------|---|
| <i>text</i> | Description for the class map, policy map, or table map. The description has a maximum of 200 characters. |
|-------------|---|

Defaults

None

Command Modes

Class map type qos configuration
 Policy map type qos configuration
 Policy map type queuing configuration
 Table map configuration

Supported User Roles

network-admin
 vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

This command does not require a license.

Examples

This example shows how to add a description to a policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap)# description this policy applies to input packets
switch(config-pmap)#
```

Related Commands

| Command | Description |
|-------------------|-----------------------------------|
| class-map | Creates or modifies a class map. |
| policy-map | Creates or modifies a policy map. |
| table-map | Creates or modifies a table map. |

Send document comments to nexus7k-docfeedback@cisco.com

from (table map)

To specify a set of mappings of input field values to output field values in a table map, use the **from** command.

from *source-value* **to** *dest-value*

Syntax Description

| | |
|---------------------|--|
| <i>source-value</i> | Source value in the range from 0 to 63. |
| <i>dest-value</i> | Destination value in the range from 0 to 63. |

Defaults

To configure the default mapping action for table maps, see the **default (table map)** command.

Command Modes

Table map configuration
Default table map configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

This command does not require a license.

Examples

This example shows how to create a mapping from three source values to the corresponding destination values:

```
switch(config)# table-map my_table1
switch(config-tmap)# from 0 to 7
switch(config-tmap)# from 1 to 6
switch(config-tmap)# from 2 to 5
```

Related Commands

| Command | Description |
|----------------------------|---|
| default (table map) | Specifies the default action for mapping of the input field value to the output field value in a table map. |
| show table-map | Displays table maps. |


[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

match access-group

To identify a specified access control list (ACL) group as a match criteria for a class map, use the **match access-group** command in the class map configuration mode. To remove ACL match criteria from a class map, use the **no** form of this command.

match access-group name *acl-name*

no match access-group name *acl-name*

| | | |
|---|--|--|
| Syntax Description | <i>acl-name</i> | Name of the ACL. |
| Defaults | None | |
| Command Modes | Class-map type qos configuration | |
| Supported User Roles | network-admin vdc-admin | |
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |
| | 4.1(2) | This command was updated to allow matching on IPv6 ACLs and IPv4 ACLs. |
| Usage Guidelines | | |
|  Note | The permit and deny ACL keywords do not affect the matching of packets. | |
| | This command does not require a license. | |
| Examples | This example shows how to create a qos class map that matches characteristics of the ACL my_acl: | |
| | <pre>switch(config)# class-map class_acl switch(config-cmap-qos)# match access-group name my_acl</pre> | |
| Related Commands | Command | Description |
| | show class-map | Displays class maps. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

match class-map

To match on the **match** commands in a specified class map, use the **match class-map** command in the class map configuration mode. To remove the match on the specified class map, use the **no** form of this command.

match [**not**] **class-map** *class-map-name*

no match [**not**] **class-map** *class-map-name*

Syntax Description

| | |
|-----------------------|--|
| not | (Optional) Negates the specified match result. |
| <i>class-map-name</i> | Specified class-map name where the match commands need to be matched. |

Defaults

None

Command Modes

Class-map type qos configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

This command does not require a license.

Examples

This example shows how to match on the matches specified in class map named my_test:

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match class-name my_test
```

Related Commands

| Command | Description |
|-----------------------|----------------------|
| show class-map | Displays class maps. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

match cos (class map type network-qos)

To define the class of traffic in a type network qos class map, use the **match cos** command. To remove the match configuration, use the **no** form of this command.

match cos *cos-list*

no match cos *cos-list*

| Syntax Description | <i>cos-list</i> | CoS value or list of specified CoS values. Valid values are from 0 to 7. |
|--------------------|-----------------|--|
|--------------------|-----------------|--|

| Defaults | None |
|----------|------|
|----------|------|

| Command Modes | Class-map type qos configuration |
|---------------|----------------------------------|
|---------------|----------------------------------|

| SupportedUserRoles | network-admin vdc-admin |
|--------------------|----------------------------|
|--------------------|----------------------------|

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

| Usage Guidelines | <p>To specify a list of values, use one of the following options:</p> <ul style="list-style-type: none"> Specify a range of values by separating each value with a dash. Specify a noncontiguous list of values by separating each value by a comma. <p>This command does not require a license.</p> |
|------------------|--|
|------------------|--|

| Examples | <p>This example shows how to match on the CoS value for a type network qos class map:</p> <pre>switch(config)# class-map type network-qos match-any eth switch(config-cmap-nqos)# match cos 3-5 switch(config-cmap-nqos)#</pre> |
|----------|---|
|----------|---|

| Related Commands | Command | Description |
|------------------|-----------------------|----------------------|
| | show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match cos (class map type qos)

To define the class of traffic using the class of service (CoS) value in a type qos class map, use the **match cos** command. To remove the match on the CoS value, use the **no** form of this command.

match [not] cos *cos-list*

no match [not] cos *cos-list*

| Syntax Description | not | (Optional) Negates the specified match result. |
|--------------------|-----------------|--|
| | <i>cos-list</i> | Specified CoS value or list of specified CoS values. Valid values are from 0 to 7. |

Defaults None

Command Modes Class-map type qos configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines To specify a list of values, use one of the following options:

- Specify a range of values by separating each value with a dash.
- Specify a noncontiguous list of values by separating each value by a comma.



Note Only class maps of type qos support the optional **not** keyword form of this command. Class maps of type queuing do not support the **not** keyword.

This command does not require a license.

Examples This example shows how to match on the CoS value for a type qos class map:

```
switch(config)# class-map class_acl
switch(config-cmap-qos)# match cos 5-7
```

■ match cos (class map type qos)

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|-----------------------|----------------------|
| show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match cos (class map type queuing)

To define the class of traffic in a type queuing class map, use the **match cos** command. To remove the **match** configuration, use the **no** form of these commands.

match cos *cos-list*

no match cos *cos-list*

| | | |
|---------------------------|-----------------|---|
| Syntax Description | <i>cos-list</i> | Specified class of service (CoS) value or list of specified CoS values. Valid values are from 0 to 7. |
|---------------------------|-----------------|---|

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|--------------------------------------|
| Command Modes | Class-map type queuing configuration |
|----------------------|--------------------------------------|

| | |
|---------------------------|----------------------------|
| SupportedUserRoles | network-admin vdc-admin |
|---------------------------|----------------------------|

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

| | |
|-------------------------|---|
| Usage Guidelines | <p>To specify a list of values, use one of the following options:</p> <ul style="list-style-type: none"> Specify a range of values by separating each value with a dash. Specify a noncontiguous list of values by separating each value by a comma. <p>Any modifications that you make to the class map type queuing changes the configuration for all ports of the specified port type on all VDCs.</p> |
|-------------------------|---|



Note

Only class maps of type qos support the optional **not** keyword form of this command.

This command does not require a license.

| | |
|-----------------|--|
| Examples | This example shows how to modify a type queuing class map to match on CoS: |
|-----------------|--|

```
switch(config)# class-map type queuing match-any 8q2t-in-q4
switch(config-cmap-que)# match cos 3
switch(config-cmap-que)#
```

■ match cos (class map type queuing)

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|----------------|----------------------|
| | show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match discard-class

To identify specific discard class values as a match criteria, use the **match discard-class** command. To remove specified discard class values as a match criteria, use the **no** form of this command.

match [**not**] **discard-class** *discard-class-list*

no match [**not**] **discard-class** *discard-class-list*

| | | |
|-----------------------------|--|---|
| Syntax Description | not | (Optional) Negates the specified match result. |
| | <i>discard-class-list</i> | Specified discard class value or list of discard class values. Valid values are from 0 to 63. |
| Defaults | None | |
| Command Modes | Class-map type qos configuration | |
| Supported User Roles | network-admin vdc-admin | |
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |
| Usage Guidelines | <p>The discard-class value is an internal label and is not part of the packet payload or any packet header. The discard-class values have no mathematical significance.</p> <p>To specify a list of values, use one of the following options:</p> <ul style="list-style-type: none"> Specify a range of values by separating each value with a dash. Specify a noncontiguous list of values by separating each value by a comma. <p>This command does not require a license.</p> | |
| Examples | <p>This example shows how to match on the discard class value 5:</p> <pre>switch(config)# class-map my_test switch(config-cmap-qos)# match discard-class 5</pre> | |
| Related Commands | Command | Description |
| | show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match dscp

To identify specific Differentiated Services Code Point (DSCP) values as a match criteria, use the **match dscp** command. To remove specified DSCP values as a match criteria, use the **no** form of this command.

match [**not**] **dscp** *dscp-list*

no match [**not**] **dscp** *dscp-list*

| | | |
|---------------------------|------------------|---|
| Syntax Description | not | (Optional) Negates the specified match result. |
| | <i>dscp-list</i> | Specified DSCP value or list of DSCP values. For the list of valid DSCP values, see Table 2 . |

Defaults None

Command Modes Class-map type qos configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|------------------------|----------------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines The standard DSCP values are shown in [Table 2](#).

Table 2 Standard DSCP Values

| | List of DSCP Values |
|------|-------------------------------------|
| af11 | AF11 dscp (001010)—decimal value 10 |
| af12 | AF12 dscp (001100)—decimal value 12 |
| af13 | AF13 dscp (001110)—decimal value 14 |
| af21 | AF21 dscp (010010)—decimal value 18 |
| af22 | AF22 dscp (010100)—decimal value 20 |
| af23 | AF23 dscp (010110)—decimal value 22 |
| af31 | AF31 dscp (011010)—decimal value 26 |
| af32 | AF40 dscp (011100)—decimal value 28 |
| af33 | AF33 dscp (011110)—decimal value 30 |
| af41 | AF41 dscp (100010)—decimal value 34 |

Send document comments to nexus7k-docfeedback@cisco.com

Table 2 Standard DSCP Values (continued)

| | List of DSCP Values |
|---------|---|
| af42 | AF42 dscp (100100)—decimal value 36 |
| af43 | AF43 dscp (100110)—decimal value 38 |
| cs1 | CS1 (precedence 1) dscp (001000)—decimal value 8 |
| cs2 | CS2 (precedence 2) dscp (010000)—decimal value 16 |
| cs3 | CS3 (precedence 3) dscp (011000)—decimal value 24 |
| cs4 | CS4 (precedence 4) dscp (100000)—decimal value 32 |
| cs5 | CS5 (precedence 5) dscp (101000)—decimal value 40 |
| cs6 | CS6 (precedence 6) dscp (110000)—decimal value 48 |
| cs7 | CS7 (precedence 7) dscp (111000)—decimal value 56 |
| default | Default dscp (000000)—decimal value 0 |
| ef | EF dscp (101110)—decimal value 46 |

To specify a list of values, use one of the following options:

- Specify a range of values by separating each value with a dash.
- Specify a noncontiguous list of values by separating each value by a comma.

This command does not require a license.

Examples

This example shows how to match on DSCP value af21:

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match dscp af21
```

Related Commands

| Command | Description |
|-----------------------------|----------------------|
| <code>show class-map</code> | Displays class maps. |

■ match ip rtp

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

match ip rtp

To configure a class map to use the Real-Time Protocol (RTP) port as a match criteria, use the **match ip rtp** command. To remove the RTP port as a match criteria, use the **no** form of this command.

match [not] ip rtp *port-list*

no match [not] ip rtp *port-list*

| | | |
|---------------------------|------------------|--|
| Syntax Description | not | (Optional) Negates the specified match result. |
| | <i>port-list</i> | Specified User Datagram Protocol (UDP) or list of UDP ports that are using RTP. Valid values are from 2000 to 65535. |

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|----------------------------------|
| Command Modes | Class-map type qos configuration |
|----------------------|----------------------------------|

| | |
|-----------------------------|----------------------------|
| Supported User Roles | network-admin vdc-admin |
|-----------------------------|----------------------------|

| | | |
|------------------------|----------------|------------------------------|
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |

| | |
|-------------------------|--|
| Usage Guidelines | <p>To specify a list of values, use one of the following options:</p> <ul style="list-style-type: none"> Specify a range of values by separating each value with a dash. Specify a noncontiguous list of values by separating each value by a comma. <p>This command does not require a license.</p> |
|-------------------------|--|

| | |
|-----------------|--|
| Examples | This example shows how to match on a port using RTP: |
|-----------------|--|

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match ip rtp 2300
```

| | | |
|-------------------------|----------------|----------------------|
| Related Commands | Command | Description |
| | show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match packet length

To configure a class map to use Layer 3 packet length in the IP header as a match criteria, use the **match packet length** command. To remove a previously specified Layer 3 packet length as a match criteria, use the **no** form of this command.

match [**not**] **packet length** *packet-length-list*

no match [**not**] **packet length** *packet-length-list*

| Syntax Description | not | (Optional) Negates the specified match result. |
|--------------------|---------------------------|---|
| | <i>packet-length-list</i> | Specified Layer 3 packet length or list of packets lengths specified in bytes. Valid values are from 1 to 9198. |

Defaults None

Command Modes Class-map type qos configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines To specify a list of values, use one of the following options:

- Specify a range of values by separating each value with a dash.
- Specify a noncontiguous list of values by separating each value by a comma.

This command does not require a license.

Examples This example shows how to match on a Layer 3 packet length of 600 to 660:

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match packet length 600-660
```

| Related Commands | Command | Description |
|------------------|-----------------------|----------------------|
| | show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match precedence

To configure a class map to use the precedence value in the Type of Service (ToS) byte field of the IP header as a match criteria, use the **match precedence** command. To remove the precedence values as a match criteria, use the **no** form of this command.

match [**not**] **precedence** *precedence-list*

no match [**not**] **precedence** *precedence-list*

Syntax Description

| | |
|------------------------|---|
| not | (Optional) Negates the specified match result. |
| <i>precedence-list</i> | Specified IP precedence value or list of IP precedence values specified in bytes. Valid values are shown in Table 3 . |

Defaults

None

Command Modes

Class-map type qos configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

For a list of precedence values, see [Table 3](#).

Table 3 **Precedence Values**

| Precedence Value | List of Precedence Values |
|------------------|---|
| <0-7> | IP precedence value |
| critical | Critical precedence (5) |
| flash | Flash precedence (3) |
| flash-override | Flash override precedence (4) |
| immediate | Immediate precedence (2) |
| internet | Internet network control precedence (6) |
| network | Network control precedence (7) |
| priority | Priority precedence (1) |
| routine | Routine precedence (0) |

Send document comments to nexus7k-docfeedback@cisco.com

To specify a list of values, use one of the following options:

- Specify a range of values by separating each value with a dash.
- Specify a noncontiguous list of values by separating each value by a comma.

This command does not require a license.

Examples

This example shows how to match on an IP precedence value:

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match precedence 7
```

Related Commands

| Command | Description |
|-----------------------|----------------------|
| show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match protocol

To configure a class map to use a specific protocol as a match criterion, use the **match protocol** command. To remove the specified protocol as a match criteria, use the **no** form of this command.

match [**not**] **protocol** *protocol-name*

no match [**not**] **protocol** *protocol-name*

| | | |
|---------------------------|----------------------|--|
| Syntax Description | not | (Optional) Negates the specified match result. |
| | <i>protocol-name</i> | Specified protocol name. Valid values are shown in Table 4 . |

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|----------------------------------|
| Command Modes | Class-map type qos configuration |
|----------------------|----------------------------------|

| | |
|-----------------------------|----------------------------|
| Supported User Roles | network-admin vdc-admin |
|-----------------------------|----------------------------|

| | | |
|------------------------|----------------|------------------------------|
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |

| | |
|-------------------------|--|
| Usage Guidelines | The list of valid protocol names is shown in Table 4 . |
|-------------------------|--|

Table 4 Protocol Names

| Argument | Description |
|----------|--|
| arp | Address Resolution Protocol (ARP) |
| bridging | Bridging |
| cdp | Cisco Discovery Protocol (CDP) |
| clns | Connectionless Network Service (CLNS) |
| clns_es | CLNS End Systems |
| clns_is | CLNS Intermediate System |
| dhcp | Dynamic Host Configuration (DHCP) |
| isis | Intermediate system to intermediate system (IS-IS) |
| ldp | Label Distribution Protocol (LDP) |
| netbios | NetBIOS Extended User Interface (NetBEUI) |

Send document comments to nexus7k-docfeedback@cisco.com**Note**

A maximum of eight different protocols can be matched at a time.

To specify more than one protocol, enter the **match protocol** command with the desired protocol value each time.

This command does not require a license.

Examples

This example shows how to match on a specified protocol:

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match protocol ldp
```

Related Commands

| Command | Description |
|-----------------------|----------------------|
| show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

match qos-group

To configure a class map to use a specific qos group value as a match criterion, use the **match qos-group** command. To remove the specified protocol as a match criteria, use the **no** form of this command.

match [**not**] **qos-group** *qos-group-list*

no match [**not**] **qos-group** *qos-group-list*

Syntax Description

| | |
|-----------------------|---|
| not | (Optional) Negates the specified match result. |
| <i>qos-group-list</i> | Specified qos group value or list of qos group values specified in bytes. Valid values are from 0 to 126. |

Defaults

None

Command Modes

Class-map type qos configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

The qos group is an internal label and is not part of the packet payload or any packet header. The qos group values have no mathematical significance. For example, a qos group value of 2 is not greater than 1; the values are used only to internally differentiate qos groups. As such, this value has local significance only.

You can match on the qos group only in egress policies because its value is undefined until you set it in an ingress policy.

To specify a list of values, use one of the following options:

- Specify a range of values by separating each value with a dash.
- Specify a noncontiguous list of values by separating each value by a comma.

This command does not require a license.

Examples

This example shows how to match on a specified qos group value:

```
switch(config)# class-map my_test
switch(config-cmap-qos)# match qos-group 6
```

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|-----------------------|----------------------|
| show class-map | Displays class maps. |

Send document comments to nexus7k-docfeedback@cisco.com

mtu

To configure the maximum transmission unit (MTU) size in a network qos policy, use the **mtu** command.

```
mtu [mtu_size]
```

| Syntax Description | <i>mtu_size</i> | (Optional) MTU size. The range is from 1500 to 9216. |
|--------------------|-----------------|--|
|--------------------|-----------------|--|

| Defaults | None |
|----------|------|
|----------|------|

| Command Modes | Policy-map type network qos configuration |
|---------------|---|
|---------------|---|

| Supported User Roles | network-admin vdc-admin |
|----------------------|----------------------------|
|----------------------|----------------------------|

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

| Usage Guidelines | This command does not require a license. |
|------------------|--|
|------------------|--|

| Examples | This example shows how to configure the MTU size in a network policy: |
|----------|---|
|----------|---|

```
switch# config t
switch(config)# policy-map type queuing my-4q-4e-drop-out
switch(config-pmap-que)# class type queuing lp3qlt-8e-out-pq1
switch(config-pmap-que)# priority level 2
switch(config-pmap-que)# mtu 1500
switch(config-pmap-que)#
```

| Related Commands | Command | Description |
|------------------|---------------------------|--|
| | congestion-control | Configures congestion control in a network qos policy. |
| | pause | Configure no-drop per CoS. |
| | priority | Marks the priority level in a traffic queue. |
| | shape | Configures the traffic rate for a given traffic profile. |

Send document comments to nexus7k-docfeedback@cisco.com

pause

To configure no-drop per class of service (CoS), use the **pause** command. To remove the no-drop configuration, use the **no** form of this command.

pause

no pause

Syntax Description This command has no arguments or keywords.

Defaults no pause

Command Modes Class-map type qos configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to configure no-drop CoS:

```
switch# config t
switch(config)# class-map type network-qos match-any eth
switch(config-cmap-nqos)# match cos 0,5-7
switch(config)# class-map type network-qos match-any fc1
switch(config-cmap-nqos)# match protocol fcoe
switch(config-cmap-nqos)# match cos 3
Switch(config)# class-map type network-qos match-any fc2
Switch(config-cmap-nqos)# match cos 1,2,4
switch(config)# policy-map type network-qos my_template
switch(config-pmap-nqos)# class type network-qos eth
switch(config-pmap-nqos-c)# pause
switch(config-pmap-nqos-c)#
```

| Related Commands | Command | Description |
|------------------|---------------------------|--|
| | congestion-control | Configures congestion control in a network qos policy. |

Send document comments to nexus7k-docfeedback@cisco.com

| Command | Description |
|-----------------|--|
| mtu | Configures the maximum transmission unit (MTU) size in a network qos policy. |
| priority | Marks the priority level in a traffic queue. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

police (QoS)

To configure policing of the data rates for a particular class of traffic, use the **police** command. To remove a policing configuration, use the **no** form of this command.

```
police [cir] {cir-value [bps | kbps | mbps | gbps] | percent percent} [[bc] bc-value [bytes | kbytes
| mbytes | ms | us]] | [pir {pir-value [bps | kbps | mbps | gbps] | percent percent} [[be]
be-value [bytes | kbytes | mbytes | ms | us]] | [conform {transmit | set-prec-transmit
precedence-value | set-dscp-transmit dscp-value | set-cos-transmit cos-val |
set-discard-class-transmit discard-class-value | set-qos-transmit qos-group-value} [exceed
{drop | set dscp dscp table cir-markdown-map}] [violate {drop | set dscp dscp table
pir-markdown-map}]]}]
```

```
no police [cir] {cir-value [bps | kbps | mbps | gbps] | percent percent} [[bc] bc-value [bytes |
kbytes | mbytes | ms | us]] | [pir {pir-value [bps | kbps | mbps | gbps] | percent percent} [[be]
be-value [bytes | kbytes | mbytes | ms | us]] | [conform {transmit | set-prec-transmit
precedence-value | set-dscp-transmit dscp-value | set-cos-transmit cos-val |
set-discard-class-transmit discard-class-value | set-qos-transmit qos-group-value} [exceed
{drop | set dscp dscp table cir-markdown-map}] [violate {drop | set dscp dscp table
pir-markdown-map}]]}]
```

Syntax Description

| | |
|------------------|--|
| cir | (Optional) Sets the committed information rate as a bit rate or a percentage of the link rate. |
| <i>cir-value</i> | Committed information rate. The range of values is from 1 to 80000000000; the range of policing values that are mathematically significant is 8000 to 80 Gbps. |
| bps | (Optional) Specifies the units of bits per second. |
| kbps | (Optional) Specifies the units of kilobits per second. |
| mbps | (Optional) Specifies the units of megabits per second. |
| gbps | (Optional) Specifies the units of gigabits per second. |
| percent | Specifies the percentage of the related parameter. |
| <i>percent</i> | Specifies percent. Valid values are from 1 to 100. |
| bc | Sets the committed burst rate, which is how much the cir can be exceeded, either as a bit rate or an amount of time at cir. |
| <i>bc-value</i> | Committed burst rate. Valid values are from 1 to 536870912. The default value is 200. |
| bytes | (Optional) Specifies the units of bytes per second. |
| kbytes | (Optional) Specifies the units of kilobytes per second. |
| mbytes | (Optional) Specifies the units of megabytes per second. |
| ms | (Optional) Specifies the units of milliseconds. |
| us | (Optional) Specifies the units of microseconds. |
| pir | Sets the peak information rate. |
| <i>pir-value</i> | Peak information rate. Valid values are from 1 to 80000000000; the range of policing values that are mathematically significant is 8000 to 80 Gbps. |
| be | Specifies the extended burst rate. Valid values are from 1 to 536870912. |

Send document comments to nexus7k-docfeedback@cisco.com

| | |
|--|---|
| <i>be-value</i> | Extended burst rate. If the bc value is not specified, the default is 200 milliseconds of traffic at the configured rate. The default data rate units are bytes. |
| conform | Sets the action to take when the data rate is within bounds. |
| transmit | Specifies the action of transmitting packets. |
| set-prec-transmit <i>precedence-value</i> | Sets the IP precedence field to the specified value and transmits the packet. Valid values are from 0 to 7. |
| set-dscp-transmit <i>dscp-value</i> | Sets the Differentiated Service Code Point (DSCP) field to the specified value and transmits the packet. For a list of valid values for this field, see Table 2 . |
| set-cos-transmit <i>cos-val</i> | Sets the class of service (CoS) field to the specified value and transmits the packet. Valid values are from 0 to 7. |
| set-discard-class-transmit <i>discard-class-value</i> | Sets the discard class field to the specified value and transmits the packet. Valid values are from 0 to 63. |
| set-qos-transmit <i>qos-group-value</i> | Sets the qos group field to the specified value and transmits the packet. Valid values are from 0 to 126. |
| exceed | Sets the action to take when the data rate is exceeded. The default is drop. |
| drop | Specifies the action of dropping packets. |
| set dscp dscp table cir-markdown-map | Sets the DSCP field to the corresponding value in the system-defined table map and transmits the packet. |
| violate | Sets the action to take when the data rate violates the configured rate values. The default is drop. |
| set dscp dscp table pir-markdown-map | Sets the DSCP field to the corresponding value in the system-defined table map and transmits the packet. |

Defaults

bc default value is 200 milliseconds of traffic at the configured rate. The default data rate units are bytes.
 be default value is 200 milliseconds of traffic at the configured rate. The default data rate units are bytes.
 exceed default action is drop.
 violate default action is drop.

Command Modes

Policy map type qos class configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

This command does not require a license.

Send document comments to nexus7k-docfeedback@cisco.com

Examples

This example shows a 1-rate, 2-color policer that transmits if the data rate is within 200 milliseconds of traffic at 256000 bps and marks the DSCP value based on the system-defined table map pir-markdown-map if the data rate is violated:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class default-class
switch(config-pmap-c-qos)# police cir 256000 conform transmit violate drop
switch(config-pmap-c-qos)#
```

This example shows a 1-rate, 3-color policer that transmits if the data rate is within 200 milliseconds of traffic at 256000 bps, marks DSCP based on the system-defined table map cir-markdown-map if the data rate is within 300 milliseconds of traffic at 256000 bps, and drops packets otherwise (pir must equal cir):

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class default-class
switch(config-pmap-c-qos)# police cir 256000 pir 256000 conform transmit exceed set dscp
dscp table cir-markdown-map violate drop
switch(config-pmap-c-qos)#
```

This example shows a 2-rate, 3-color policer that transmits and sets CoS to 5 if the data rate is within 200 milliseconds of traffic at 256000 bps, marks DSCP based on the system-defined table map cir-markdown-map if the data rate exceeds 200 milliseconds of traffic at 512 bps, and drops packets otherwise:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class default-class
switch(config-pmap-c-qos)# police cir 256000 pir 512000 conform set-cos-transmit 5 exceed
set dscp dscp table cir-markdown-map violate drop
switch(config-pmap-c-qos)#
```

Related Commands

| Command | Description |
|------------------------------|--------------------------------------|
| <code>show policy-map</code> | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

police aggregate

To apply an aggregate policer to a particular class of traffic across multiple interfaces, use the **police aggregate** command. To remove an aggregate policer configuration, use the **no** form of this command.

police aggregate *policer-name*

no police aggregate *policer-name*

Syntax Description

| | |
|---------------------|--|
| <i>policer-name</i> | Name of a shared aggregate policer to use. |
|---------------------|--|

Defaults

None

Command Modes

Policy map type qos class configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

Shared policers can only be applied to interfaces on the same module.



Note

For information about configuring a shared policer, see the [qos shared-policer](#) command.

This command does not require a license.

Examples

This example shows how to configure a shared policer for the class-default class of traffic:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class default-class
switch(config-pmap-c-qos)# police aggregate my_aggregate_policer
switch(config-pmap-c-qos)#
```

This example shows how to remove the configuration of a shared policer from the class-default class of traffic:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class default-class
switch(config-pmap-c-qos)# no police aggregate my_aggregate_policer
switch(config-pmap-c-qos)#
```

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|---------------------------|---|
| | qos shared-policer | Configures simultaneous policing across multiple interfaces for a specified class of traffic. |
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

policy-map type network-qos

To configure a policy map and enter the policy map type network qos configuration mode, use the **policy-map type network-qos** command. To remove a class map, use the **no** form of this command.

```
policy-map type network-qos {policy-map-name} {default-nq-4e-policy | default-nq-6e-policy | default-nq-7e-policy | default-nq-8e-policy | my_template}
```

```
no policy-map type network-qos {policy-map-name} {default-nq-4e-policy | default-nq-6e-policy | default-nq-7e-policy | default-nq-8e-policy | my_template}
```

Syntax Description

| | |
|-----------------------------|---|
| <i>policy-class-name</i> | Policy-map name. The policy map names can contain alphabetic, hyphen, or underscore characters, are case sensitive, and can be up to 40 characters. |
| default-nq-4e-policy | Specifies the default 4-ethernet policy (4-drop, 4-nodrop CoS). |
| default-nq-6e-policy | Specifies the default 6-ethernet policy (6-drop, 2-nodrop CoS). |
| default-nq-7e-policy | Specifies the default 7-ethernet policy (7-drop, 1-nodrop CoS). |
| default-nq-8e-policy | Specifies the default 8-ethernet policy (8-drop CoS). |
| my_template | Specifies the policy map name of the type network qos. |

Defaults

qos

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 5.1(1) | This command was introduced. |

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure a policy map of the type network qos:

```
switch# configure terminal
switch(config)# policy-map type network-qos my_template
switch(config-pmap-nqos)#
```

This example shows how to remove a policy map of the type network qos:

```
switch# configure terminal
switch(config)# no policy-map type network-qos my_template
switch(config)#
```

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|-----------------|--|
| | service-policy | Attaches a policy map to an interface. |
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

policy-map type qos

To create or modify a policy map and enter the policy map type qos configuration mode, use the **policy-map type qos** command. To remove a policy map, use the **no** form of this command.

policy-map [**type qos**] [**match-first**] {*qos-policy-map-name* | **qos-dynamic**}

no policy-map [**type qos**] [**match-first**] {*qos-policy-map-name* | **qos-dynamic**}

Syntax Description

| | |
|----------------------------|---|
| match-first | (Optional) Specifies the policies associated with the first class that matches the packet characteristics are executed. This is the default action if this option is not specified. |
| | Note Because this is the default action, you do not need to enter this variable; it is there to ensure compatibility with other systems. |
| <i>qos-policy-map-name</i> | Name assigned to a type qos policy map. |
| qos-dynamic | Specifies already configured policy maps. |

Defaults

The software enters the policy map type qos configuration mode if you enter the **policy-map** command without specifying a type.

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|--|
| 4.0 | This command was introduced. |
| 4.2(1) | The qos-dynamic variable was added. |

Usage Guidelines

Use the **service-policy** command to assign policy maps to interfaces.
This command does not require a license.

Examples

This example shows how to create or modify a type qos policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)#
```

This example shows how to remove a type qos policy map:

```
switch(config)# no policy-map my_policy1
```

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|------------------------|--|
| | service-policy | Attaches a policy map to an interface. |
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

policy-map type queuing

To create or modify a policy map and enter the policy map type queuing configuration mode, use the **policy-map type queuing** command. To remove a policy map, use the **no** form of this command.

policy-map type queuing [**match-first**] {*queuing-policy-map-name* | **que-dynamic**}

no policy-map type queuing [**match-first**] {*queuing-policy-map-name* | **que-dynamic**}

Syntax Description

match-first (Optional) Specifies the policies associated with the first class that matches the packet characteristics are executed. This is the default action if this option is not specified.

Note Because this is the default action, you do not need to enter this variable; it is there to ensure compatibility with other systems.

queuing-policy-map-name Name assigned to a type queuing policy map.

que-dynamic Specifies already configured policy maps.

Defaults

None

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|--|
| 4.0 | This command was introduced. |
| 4.2(1) | The que-dynamic variable was added. |

Usage Guidelines

Use the **service-policy** command to assign policy maps to interfaces.
This command does not require a license.

Examples

This example shows how to create or modify a queuing policy map:

```
switch(config)# policy-map type queuing my_policy1
switch(config-pmap-que)#
```

This example shows how to remove a type queuing policy map:

```
switch(config)# no policy-map type queuing my_policy1
switch(config)#
```


Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|------------------------|--|
| | service-policy | Attaches a policy map to an interface. |
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

priority (queuing)

To configure a single output queuing class as the priority queue, use the **priority** command. To remove the priority queue selection, use the **no** form of this command.

priority [*level priority-value*]

no priority [*level priority-value*]

Syntax Description

level (Optional) Specifies the priority level for an output queuing class. Only one priority *priority-value* level is supported. The priority value can only be 1.

Defaults

The software distributes the bandwidth among the output queues, when you do not specify the priority.

Command Modes

Policy map type queuing configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

The priority level can only be 1.

Use the **bandwidth remaining** command to allocate the remaining bandwidth among the nonpriority output queues. By default, the software evenly distributes the remaining bandwidth among the nonpriority output queues.

You can also use the **police** command to explicitly configure the priority for specified classes of traffic.



Note

After you use this command in a specified policy map, you cannot use the **bandwidth** or **shape** command in the same policy map.

This command does not require a license.

Examples

This example shows how to assign a priority queue:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# priority level 1
switch(config-pmap-c-que)#
```

This example shows how to remove a priority queue:

Send document comments to nexus7k-docfeedback@cisco.com

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# no priority level 1
switch(config-pmap-c-que)#
```

Related Commands

| Command | Description |
|----------------------------|---|
| bandwidth remaining | Configures the bandwidth remaining on the interface in a queue. |
| police | Configures policing for specified classes of traffic. |
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

priority-flow-control mode

To configure priority flow control (PFC) on an interface, use the **priority-flow-control mode** command.

priority-flow-control mode {**auto** | **off** | **on**}

| Syntax Description | auto | Sets the PFC mode to automatic. |
|--------------------|------------|---------------------------------|
| | off | Sets the PFC mode to off. |
| | on | Sets the PFC mode to on. |

Defaults auto

Command Modes Global configuration

Supported User Roles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to set the PFC mode to on:

```
switch# configure terminal
switch(config)# interface ethernet 2/5
switch(config-if)# priority-flow-control mode on
switch(config-if)#
```

This example shows how to set the PFC mode to off:

```
switch# configure terminal
switch(config)# interface ethernet 2/5
switch(config-if)# priority-flow-control mode off
switch(config-if)#
```

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|---|---|
| show interface priority-flow-control | Displays the status of priority flow control (PFC) on all interfaces. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

qos copy policy-map

To copy a system-defined network-qos policy and modify it for use, use the **qos copy policy-map** command.

```
qos copy policy-map type {network-qos [default-nq-4e-policy {prefix prefix | suffix suffix} |
default-nq-6e-policy {prefix prefix | suffix suffix} | default-nq-7e-policy {prefix prefix |
suffix suffix} | default-nq-8e-policy {prefix prefix | suffix suffix}] | queuing
[default-4q-4e-in-policy {prefix prefix | suffix suffix} | default-4q-4e-out-policy {prefix
prefix | suffix suffix}]}
```

Syntax Description

| | |
|---------------------------------|--|
| type | Specifies the component type. |
| network-qos | Specifies a network qos policy. |
| default-nq-4e-policy | (Optional) Specifies the 4-Ethernet template. |
| prefix prefix | Specifies a prefix for the policy name. A prefix can be any alphanumeric character string. |
| suffix suffix | Specifies a suffix for the policy name. A prefix can be any alphanumeric character string. |
| default-nq-6e-policy | (Optional) Specifies the 6-Ethernet template. |
| default-nq-7e-policy | (Optional) Specifies the 7-Ethernet template. |
| default-nq-8e-policy | (Optional) Specifies the 8-Ethernet template. |
| queuing | (Optional) Specifies a queuing policy. |
| default-4q-4e-in-policy | (Optional) Specifies the default 4-Ethernet input queuing policy. |
| default-4q-4e-out-policy | (Optional) Specifies the default 4-Ethernet output queuing policy. |

Defaults

None

Command Modes

Global configuration

Supported User Roles

network-admin
network-operator
vdc-admin
vdc-operator

Command History

| Release | Modification |
|---------|------------------------------|
| 5.1(1) | This command was introduced. |

Usage Guidelines

This command does not require a license.

Send document comments to nexus7k-docfeedback@cisco.com

Examples

This example shows how to copy a system-defined network qos policy and modify it for use:

```
switch# configure terminal
switch(config)# qos copy policy-map type network-qos default-nq-4e-policy prefix my_
switch(config)#
```

Related Commands

| Command | Description |
|------------------------------------|--|
| policy-map type network-qos | Configure a policy map and enter the policy map type network qos configuration mode. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

qos shared-policer

To configure simultaneous policing of the data rates for a particular class of traffic across multiple interfaces, use the **qos shared-policer** command. To remove a shared policer configuration, use the **no** form of this command.

```
qos shared-policer [type qos] policer-name [cir] {cir-value [bps | kbps | mbps | gbps] | percent percent} | [[bc] bc-value [bytes | kbytes | mbytes | ms | us]] | [pir {pir-value [bps | kbps | mbps | gbps] | percent -percent} [[be] be-value [bytes | kbytes | mbytes | ms | us]]] | [conform {transmit | set-prec-transmit precedence-value | set-dscp-transmit dscp-value | set-cos-transmit cos-val | set-discard-class-transmit discard-class-value | set-qos-transmit qos-group-value} [exceed {drop | set dscp dscp table cir-markdown-map}] [violate {drop | set dscp dscp table pir-markdown-map}]
```

```
no qos shared-policer [type qos] policer-name
```

Syntax Description

| | |
|---------------------|--|
| type qos | (Optional) Specifies the component type, which is quality of service (QoS) for this class. |
| <i>policer-name</i> | Name of a shared policer. |
| cir | (Optional) Sets the committed information rate as a bit rate or a percentage of the link rate. |
| <i>cir-value</i> | Committed information rate. Valid values are from 1 to 80000000000; the range of policing values that are mathematically significant is 8000 to 80 Gbps. |
| bps | (Optional) Specifies the units of bits per second. |
| kbps | (Optional) Specifies the units of kilobits per second. |
| mbps | (Optional) Specifies the units of megabits per second. |
| gbps | (Optional) Specifies the units of gigabits per second. |
| percent | Specifies the percentage of the related parameter. |
| <i>percent</i> | Specifies percent. Valid values are from 1 to 100. |
| bc | Sets the committed burst rate, which is how much the cir can be exceeded, either as a bit rate or an amount of time at cir. |
| <i>bc-value</i> | Committed burst rate. Valid values are from 1 to 536870912. The default value is 200. |
| bytes | (Optional) Specifies the units of bytes per second. |
| kbytes | (Optional) Specifies the units of kilobytes per second. |
| mbytes | (Optional) Specifies the units of megabytes per second. |
| ms | (Optional) Specifies the units of milliseconds. |
| us | (Optional) Specifies the units of microseconds. |
| pir | Sets the peak information rate. |
| <i>pir-value</i> | Peak information rate. Valid values are from 1 to 80000000000; the range of policing values that are mathematically significant is from 8000 to 80 Gbps. |
| be | Specifies the extended burst rate. Valid values are from 1 to 536870912. |

Send document comments to nexus7k-docfeedback@cisco.com

| | |
|--|--|
| <i>be-value</i> | Extended burst rate. If the bc value is not specified, the default is 200 milliseconds of traffic at the configured rate. The default data rate units are bytes. |
| conform | Sets the action to take when the data rate is within bounds. |
| transmit | Specifies the action of transmitting packets. |
| set-prec-transmit <i>precedence-value</i> | Sets the IP precedence field to the specified value and transmits the packet. Valid values are from 0 to 7. |
| set-dscp-transmit <i>dscp-value</i> | Sets the Differentiated Services Code Point (DSCP) field to the specified value and transmits the packet. For a list of valid values for this field, see Table 2 . |
| set-cos-transmit <i>cos-val</i> | Sets the class of service (CoS) field to the specified value and transmits the packet. Valid values are from 0 to 7. |
| set-discard-class-transmit <i>discard-class-value</i> | Sets the discard class field to the specified value and transmits the packet. Valid values are from 0 to 63. |
| set-qos-transmit <i>qos-group-value</i> | Sets the qos group field to the specified value and transmits the packet. Valid values are from 0 to 126. |
| exceed | Sets the action to take when the data rate is exceeded. The default is drop. |
| drop | Specifies the action of dropping packets. |
| set dscp dscp table cir-markdown-map | Sets the DSCP field to the corresponding value in the system-defined table map and transmits the packet. |
| violate | Sets the action to take when the data rate violates the configured rate values. The default is drop. |
| set dscp dscp table pir-markdown-map | Sets the DSCP field to the corresponding value in the system-defined table map and transmits the packet. |

Defaults

type default value is qos.

bc default value is 200 milliseconds of traffic at the configured rate. The default data rate units are bytes.

be default value is 200 milliseconds of traffic at the configured rate. The default data rate units are bytes.

exceed default action is drop.

violate default action is drop.

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Send document comments to nexus7k-docfeedback@cisco.com**Usage Guidelines**

The interfaces that are attached to the shared policer must be on the same module. For an example of using a shared policer, see the [police aggregate](#) command.

This command does not require a license.

Examples

This example shows configuration of a 2-rate, 3-color shared policer that transmits and sets CoS to 5 if the data rate is within 200 milliseconds of traffic at 256000 bps, marks DSCP based on the system-defined table map cir-markdown-map if the data rate exceeds 200 milliseconds of traffic at 512 bps, and drops packets otherwise:

```
switch(config)# qos shared-policer my_shared_policer cir 256000 pir 512000 conform
set-cos-transmit 5 exceed set dscp dscp table cir-markdown-map violate drop
switch(config)#
```

Related Commands

| Command | Description |
|-------------------------|--|
| police aggregate | Configures simultaneous policing of the data rates for a particular class of traffic across multiple interfaces. |
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

qos statistics

To enable Quality of Service (QoS) statistics, use the **qos statistics** command. To disable QoS statistics, use the **no** form of this command.

qos statistics

no qos statistics

Syntax Description This command has no arguments or keywords.

Defaults Enabled

Command Modes Global configuration

SupportedUserRoles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to enable QoS statistics:

```
switch(config)# qos statistics
switch(config)#
```

This example shows how to disable QoS statistics:

```
switch(config)# no qos statistics
switch(config)#
```

| Related Commands | Command | Description |
|------------------|------------------------|--------------------------------------|
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

queue-limit

To configure tail drop by setting queue limits on both ingress and egress queues, use the **queue-limit** command. To remove a queue limit, use the **no** form of this command.

```
queue-limit [cos cos-value] {queue-size [packets | bytes | kbytes | mbytes | ms | us] | percent
percent-queue-size}
```

```
no queue-limit [cos cos-value] {queue-size [packets | bytes | kbytes | mbytes | ms | us] | percent
percent-queue-size}
```

Syntax Description

| | |
|-----------------------------|---|
| cos <i>cos-value</i> | (Optional) Applies the queue limit to packets with the specified CoS value. Valid values are from 0 to 7. |
| <i>queue-size</i> | Queue size threshold. Valid values are from 1 to 83886080. |
| packets | (Optional) Specifies that queue size is in packets. If not specified, packets is the default units. |
| bytes | (Optional) Specifies that the queue size is in bytes. |
| kbytes | (Optional) Specifies that the queue size is in kilobytes. |
| mbytes | (Optional) Specifies that the queue size is in megabytes. |
| ms | (Optional) Specifies that the queue size is in milliseconds at the underlying interface minimum guaranteed link rate. |
| us | (Optional) Specifies that queue size is in microseconds at the underlying interface minimum guaranteed link rate. |
| percent | (Optional) Specifies the percentage of queue limit. |
| <i>percent-queue-size</i> | (Optional) Specifies the percentage of the buffer memory used by the queue. Valid values are from 1 to 100. |

Defaults

queue-size is in packets by default.

Command Modes

Policy map type queuing class configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

The system drops packets that exceed the configured queue-size threshold.

By default, the queue limit is applied to all packets with a class of service (CoS) value that is not assigned a queue limit.

Send document comments to nexus7k-docfeedback@cisco.com

The queue limit is not supported on ingress policies on the 10-Gbps interfaces.

Tail drop and weighted random early detection (WRED) cannot be configured in the same class. For information about configuring WRED, see the [random-detect](#) command.

This command does not require a license.

Examples

This example shows how to assign a queue limit to a policy map queuing class that applies only to the specified CoS value:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# queue-limit cos 3 10 mbytes
switch(config-pmap-c-que)#
```

This example shows how to remove a queue limit from a policy map queuing class:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# no queue-limit cos 3 10 mbytes
switch(config-pmap-c-que)#
```

Related Commands

| Command | Description |
|------------------------|--|
| random-detect | Configures weighted random early detection (WRED). |
| show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

random-detect

To configure weighted random early detection (WRED) on both ingress and egress queues by setting aggregate minimum and maximum packet drop threshold default values for specific class of service (CoS) values, use the **random-detect** command. To remove a WRED configuration, use the **no** form of this command.

```
random-detect {cos cos-list [minimum-threshold] {min-threshold [packets | bytes | kbytes | mbytes | ms | us] | percent min-percent-of-qsize} [maximum-threshold] {max-threshold [packets | bytes | kbytes | mbytes | ms | us] | percent max-percent-of-qsize}
```

```
no random-detect {cos cos-list [minimum-threshold] {min-threshold [packets | bytes | kbytes | mbytes | ms | us] | percent min-percent-of-qsize} [maximum-threshold] {max-threshold [packets | bytes | kbytes | mbytes | ms | us] | percent max-percent-of-qsize}
```

Syntax Description

| | |
|-----------------------------|--|
| cos <i>cos-list</i> | Specifies the CoS values where the software applies thresholds. Valid values are from 0 to 7. |
| minimum-threshold | (Optional) Specifies the minimum threshold. |
| <i>min-threshold</i> | Minimum threshold. Valid values are from 1 to 52428800. |
| packets | (Optional) Specifies that thresholds are in packets. |
| bytes | (Optional) Specifies that thresholds are in bytes. |
| kbytes | (Optional) Specifies that thresholds are in kilobytes. |
| mbytes | (Optional) Specifies that thresholds are in megabytes. |
| ms | (Optional) Specifies that thresholds are in milliseconds at the underlying interface minimum guaranteed link rate |
| us | (Optional) Specifies that thresholds are in microseconds at the underlying interface minimum guaranteed link rate. |
| percent | Specifies the percentage of the threshold. |
| <i>min-percent-of-qsize</i> | Minimum percentage of the buffer memory used by the queue. Valid values are from 1 to 100. |
| maximum-threshold | (Optional) Specifies the maximum threshold. |
| <i>max-threshold</i> | Maximum threshold. Valid values are from 1 to 52428800. |
| <i>max-percent-of-qsize</i> | (Optional) Maximum percentage of the buffer memory used by the queue. Valid values are from 1 to 100. |

Defaults

Thresholds are in packets by default.

The **random-detect cos-based** command must be specified for a queue to establish default thresholds for any CoS values that are not specified in **random-detect** commands for the same queue.

Command Modes

Policy map type queuing class configuration

Send document comments to nexus7k-docfeedback@cisco.com

SupportedUserRoles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines



Note

You must enter the **random-detect cos-based** command before you enter the **random-detect** command.

The minimum and maximum threshold units must match.

The system drops packets that exceed the minimum threshold at an increasing rate as the maximum threshold is reached. By default, the units are in packets,

WRED and tail drop cannot be configured in the same class. For information about configuring tail drop, see the **queue-limit** command.

You cannot configure WRED on ingress on the 10-Gigabit Ethernet ports.

For CoS lists, you can use the following:

- Specify only one value—**cos 1**
- Specify a range of values—**cos 1-3**
- Specify a comma-separated list of values—**cos 1, 4-6**

This command does not require a license.

Examples

This example shows how to configure WRED for a queue by setting the default WRED thresholds followed by thresholds that apply to CoS values 5 and 7:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pql
switch(config-pmap-c-que)# random-detect cos-based aggregate 10 mbytes 20 mbytes
switch(config-pmap-c-que)# random-detect cos 5,7 15 mbytes 20 mbytes
switch(config-pmap-c-que)#
```

This example shows how to configure WRED for a queue by setting the default WRED thresholds followed by queue buffer size thresholds that apply to CoS value 5:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pql
switch(config-pmap-c-que)# random-detect cos-based aggregate 10 mbytes 20 mbytes
switch(config-pmap-c-que)# random-detect cos 5 percent 5 percent 15
switch(config-pmap-c-que)#
```

This example shows how to remove a WRED configuration from a policy map queuing class:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pql
switch(config-pmap-c-que)# no random-detect cos-based aggregate 10 mbytes 20 mbytes
switch(config-pmap-c-que)# no random-detect cos 5 percent 5 percent 15
switch(config-pmap-c-que)#
```

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|-------------------------|------------------------------------|--------------------------------------|
| | random-detect cos-based | Configures WRED. |
| | queue limit | Configures tail drop. |
| | show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

random-detect cos-based

To configure weighted random early detection (WRED) on both ingress and egress queues by setting minimum and maximum packet drop thresholds, use the **random-detect cos-based** command. To remove a WRED configuration, use the **no** form of this command.

```
random-detect cos-based [aggregate [minimum-threshold] {min-threshold [packets | bytes |
kbytes | mbytes | ms | us] | percent min-percent-of-queue} [maximum-threshold]
{max-threshold [packets | bytes | kbytes | mbytes | ms | us] | percent max-percent-of-queue}]
```

```
no random-detect cos-based [aggregate [minimum-threshold] {min-threshold [packets | bytes |
kbytes | mbytes | ms | us] | percent min-percent-of-queue} [maximum-threshold]
{max-threshold [packets | bytes | kbytes | mbytes | ms | us] | percent max-percent-of-queue}]
```

Syntax Description

| | |
|-----------------------------|---|
| aggregate | (Optional) Specifies where the software applies aggregate thresholds for CoS values that are not specified in the random-detect command. |
| minimum-threshold | (Optional) Specifies the minimum threshold. |
| <i>min-threshold</i> | Minimum threshold. Valid values are from 1 to 52428800. |
| packets | (Optional) Specifies that thresholds are in packets. |
| bytes | (Optional) Specifies that thresholds are in bytes. |
| kbytes | (Optional) Specifies that thresholds are in kilobytes. |
| mbytes | (Optional) Specifies that thresholds are in megabytes. |
| ms | (Optional) Specifies that thresholds are in milliseconds at the underlying interface minimum guaranteed link rate |
| us | (Optional) Specifies that thresholds are in microseconds at the underlying interface minimum guaranteed link rate. |
| percent | Specifies the percentage of the threshold. |
| <i>min-percent-of-queue</i> | (Optional) Minimum percentage of the buffer memory used by the queue. Valid values are from 1 to 100. |
| maximum-threshold | Specifies the maximum threshold. |
| <i>max-threshold</i> | Maximum threshold. Valid values are from 1 to 52428800. |
| <i>max-percent-of-queue</i> | (Optional) Maximum percentage of the buffer memory used by the queue. Valid values are from 1 to 100. |

Defaults

Thresholds are in packets by default.

Command Modes

Policy map type queuing class configuration

Supported User Roles

network-admin
vdc-admin

Send document comments to nexus7k-docfeedback@cisco.com

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

The **random-detect cos-based** command is required when you configure WRED to establish default thresholds for class of service (CoS) values for which you do not define specific thresholds.

The minimum and maximum threshold units must match.

The system drops packets that exceed the minimum threshold at an increasing rate as the maximum threshold is reached. By default, the units are in packets,

WRED and tail drop cannot be configured in the same class. For information about configuring tail drop, see the **queue-limit** command.



Note

You cannot configure WRED on ingress 10-Gigabit Ethernet ports.

This command does not require a license.

Examples

This example shows how to configure WRED for a queue by setting the default WRED thresholds followed by thresholds that apply to CoS values 5 and 7:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# random-detect cos-based aggregate 10 mbytes 20 mbytes
switch(config-pmap-c-que)# random-detect cos 5,7 15 mbytes 20 mbytes
switch(config-pmap-c-que)#
```

This example shows how to configure WRED for a queue by setting the default WRED thresholds followed by queue buffer size thresholds that apply to CoS value 5:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# random-detect cos-based aggregate 10 mbytes 20 mbytes
switch(config-pmap-c-que)# random-detect cos 5 percent 5 percent 15
switch(config-pmap-c-que)#
```

This example shows how to remove a WRED configuration from a policy map queuing class:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# no random-detect cos-based aggregate 10 mbytes 20 mbytes
switch(config-pmap-c-que)# no random-detect cos 5 percent 5 percent 15
switch(config-pmap-c-que)#
```

Related Commands

| Command | Description |
|------------------------|--------------------------------------|
| random-detect | Configures WRED. |
| queue limit | Configures tail drop. |
| show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

service-policy

To attach a policy map to an interface, VLAN, or tunnel, use the **service-policy** command. To remove a service-policy from an interface, VLAN or tunnel, use the **no** form of this command.

```
service-policy [type {qos | queuing}] {input | output} {policy-map-name | qos-dynamic}
[no-stats]
```

```
no service-policy [type {qos | queuing}] {input | output} {policy-map-name | qos-dynamic}
[no-stats]
```

| Syntax Description | type | (Optional) Specifies whether the policy map is of type qos or queuing. |
|--------------------|------------------------|--|
| | qos | Specifies a policy map of type qos. |
| | queuing | Specifies a policy map of type queuing. |
| | input | Applies this policy map to packets coming into this interface. |
| | output | Applies this policy map to packets going out of this interface. |
| | <i>policy-map-name</i> | Name of the policy map to attach to this interface. Only one policy map can be attached to the input and one to the output of a given interface for each of the policy type qos and queuing. |
| | qos-dynamic | Specifies already configured policy maps. |
| | no-stats | (Optional) Disables generation of statistics for this policy map. |

Defaults

type default is qos.

No policies of type qos are active on an interface until the **service-policy** command is entered. The system-defined type queuing class maps are attached to each interface unless you specifically attach a different class map. For a list of the system-defined type queuing class maps, see [Table 1](#).

Command Modes

Interface configuration
VLAN configuration

SupportedUserRoles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|--|
| 4.0 | This command was introduced. |
| 4.0(3) | Support for tunnel interfaces is added. |
| 4.2(1) | The qos-dynamic variable was added. |

Send document comments to nexus7k-docfeedback@cisco.com**Usage Guidelines**

No policies of type qos are active on an interface until you enter the **service-policy** command. The system-defined type queuing class maps are attached to each interface unless you specifically attach a different class map.

You can attach one ingress and one egress type qos policy map to a port, port channel, tunnel, or VLAN. You can attach one ingress and one egress type queuing policy map to an interface of type port, port channel, tunnel, or VLAN.

Only one policy map can be attached to the input and one to the output of a given interface for each of the policy type qos and queuing.

**Note**

For more information on using service policies, see the *Cisco Nexus 7000 Series NX-OS Quality of Service Configuration Guide, Release 5.0*.

This command does not require a license.

Examples

This example shows how to attach qos type policy maps to the ingress and egress packets of a VLAN:

```
switch(config)# vlan 1
switch(config-vlan)# service-policy input my_input_policy
switch(config-vlan)# service-policy output my_output_policy
switch(config-vlan)#
```

This example shows how to attach a queuing policy map to the ingress packets of a port interface:

```
switch(config)# interface ethernet 2/1
switch(config-if)# service-policy type queuing input my_input_q_policy
switch(config-if)#
```

This example shows how to remove a policy map from a VLAN:

```
switch(config)# vlan 1
switch(config-vlan)# no service-policy input my_input_policy
switch(config-vlan)#
```

Related Commands

| Command | Description |
|--|---|
| show policy-map interface brief | Displays all interfaces and VLANs with attached service policies in a brief format. |

Send document comments to nexus7k-docfeedback@cisco.com

set cos (policy map type qos)

To assign a class of service (CoS) value for a class of traffic in a type qos policy map, use the **set** command. To remove the assigned value from the class, use the **no** form of this command.

set cos *cos-value*

no set cos *cos-value*

| | | |
|-----------------------------|---|--|
| Syntax Description | <i>cos-value</i> | CoS value to assign for this class of traffic. Valid values are from 0 to 7. |
| Defaults | None | |
| Command Modes | Policy map type qos class configuration | |
| Supported User Roles | network-admin vdc-admin | |
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |
| Usage Guidelines | <p>You can use the set cos (policy map type qos) command only on type qos policies that are attached to egress ports.</p> <p>This command does not require a license.</p> | |
| Examples | <p>This example shows how to remove an assignment of CoS for a class of traffic in a type qos policy map:</p> <pre>switch(config)# policy-map my_policy1 switch(config-pmap-qos)# class traffic_class2 switch(config-pmap-c-qos)# no set cos 3 switch(config-pmap-c-qos)#</pre> | |
| Related Commands | Command | Description |
| | show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

set cos (policy map type queuing)

To assign a class of service (CoS) value for untrusted ports in a type queuing policy map, use the **set cos** command. To remove the assigned value from the class, use the **no** form of this command.

set cos *cos-value-queuing*

no set cos *cos-value-queuing*

| | |
|---------------------------|--|
| Syntax Description | cos <i>cos-value-queuing</i> Specifies the CoS value to assign for this class of traffic. Valid values are from 0 to 7. |
|---------------------------|--|

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|---|
| Command Modes | Policy map type queuing class configuration |
|----------------------|---|

| | |
|-----------------------------|----------------------------|
| Supported User Roles | network-admin vdc-admin |
|-----------------------------|----------------------------|

| | | |
|------------------------|----------------|------------------------------|
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |

Usage Guidelines You can only use this form of the **set cos (policy map type queuing)** command for ingress default type queuing classes. For a table of system-defined queuing class maps, see [Table 1](#).



Note

The CoS values that you set by using the **set cos** command apply to all packets that ingress the specified interfaces (not just to the class-default packets that ingress the interfaces).

If you set the CoS value, the device modifies the value before ingress queuing and scheduling so that the CoS-modified packets are classified differently.

This command does not require a license.

Examples This example shows how to assign a CoS value for a class of traffic in a queuing policy map:

```
switch(config)# policy-map type queuing match-first my_queuing_policy1
switch(config-pmap-que)# class type queuing 2q4t-in-q-default
switch(config-pmap-c-que)# set cos 3
switch(config-pmap-c-que)#
```

This example shows how to remove a CoS assignment for a class of traffic in a queuing policy map:

```
switch(config)# policy-map type queuing match-first my_queuing_policy1
```

Send document comments to nexus7k-docfeedback@cisco.com

```
switch(config-pmap-que)# class type queuing 2q4t-in-q-default
switch(config-pmap-c-que)# no set cos 3
switch(config-pmap-c-que)#
```

Related Commands

| Command | Description |
|------------------------|--------------------------------------|
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

set discard-class

To assign a discard-class value for a class of traffic in a type qos policy map, use the **set discard-class** command. To leave the discard-class values unchanged, use the **no** form of this command.

set discard-class *discard-value*

no set discard-class *discard-value*

| | | |
|---------------------------|----------------------|---|
| Syntax Description | <i>discard-value</i> | Discard-class value to assign for this class of traffic. Valid values are from 0 to 63. |
|---------------------------|----------------------|---|

| | |
|-----------------|------|
| Defaults | None |
|-----------------|------|

| | |
|----------------------|---|
| Command Modes | Policy map type qos class configuration |
|----------------------|---|

| | |
|---------------------------|----------------------------|
| SupportedUserRoles | network-admin vdc-admin |
|---------------------------|----------------------------|

| | | |
|------------------------|----------------|------------------------------|
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |

| | |
|-------------------------|---|
| Usage Guidelines | You can set the discard-class value only in ingress policies. |
|-------------------------|---|



Note

If you configure this value, you cannot configure a value by using the **set dscp** or the **set precedence** command.

This command does not require a license.

| | |
|-----------------|---|
| Examples | This example shows how to assign the discard-class value for a class of traffic in a type qos policy map: |
|-----------------|---|

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class traffic_class2
switch(config-pmap-c-qos)# set discard-class 40
switch(config-pmap-c-qos)#
```

| | | |
|-------------------------|------------------------|--------------------------------------|
| Related Commands | Command | Description |
| | show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

set dscp (QoS)

To assign a Differentiated Services Code Point (DSCP) value for a class of traffic in a type qos policy map, use the **set dscp** command. To remove a previously set DSCP value, use the **no** form of this command.

```
set dscp [tunnel] dscp-value
```

```
no set dscp [tunnel] dscp-value
```

| Syntax Description | Parameter | Description |
|--------------------|-------------------|--|
| | tunnel | Sets the DSCP value in the tunnel encapsulation. This keyword is not supported in Release 4.0.1. |
| | <i>dscp-value</i> | DSCP value or parameter to assign for this class of traffic. Valid values are from 0 to 63. |

Defaults None

Command Modes Policy map type qos class configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|---|
| | 4.0 | This command was introduced. |
| | 4.0.3 | The tunnel keyword is supported. |

Usage Guidelines For a list of standard DSCP values, see [Table 2](#).



Note

If you configure this value, you cannot configure a value by the **set discard-class** or **set precedence** command.

This command does not require a license.

Examples This example shows how to assign DSCP for a class of traffic in a type qos policy map:

```
switch(config)# policy-map my_policy1
switch(config-pmap-qos)# class traffic_class2
switch(config-pmap-c-qos)# set cos 3
switch(config-pmap-c-qos)#
```

■ set dscp (QoS)

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|------------------------|--------------------------------------|
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

set precedence (QoS)

To set precedence value in an IP header for a class of traffic in a type qos policy map, use the **set precedence** command. To leave the precedence value unchanged for the class, use the **no** form of this command.

set precedence [**tunnel**] *precedence-value*

no set precedence [**tunnel**] *precedence-value*

| Syntax Description | | |
|-------------------------|--|--|
| tunnel | (Optional) Sets the IP precedence value in the tunnel encapsulation. This keyword is not supported in Release 4.0.1. | |
| <i>precedence-value</i> | IP precedence value to assign for this class of traffic. Valid values are from 0 to 7. | |

Defaults None

Command Modes Policy map type qos class configuration

Supported User Roles network-admin
vdc-admin

| Command History | Release | Modification |
|-----------------|---------|---|
| | 4.0 | This command was introduced. |
| | 4.0.3 | The tunnel keyword is supported. |

Usage Guidelines For a list of the IP precedence values, see [Table 3](#).
The device rewrites the last 3 bits of the Type of Service (ToS) field in the IP header to 0 for packets that match this class.



Note If you configure this value, you cannot configure a value by using the **set discard-class** or **set dscp** command.

This command does not require a license.

Examples This example shows how to set the IP precedence value for a class of traffic in a type qos policy map:

```
switch(config)# policy-map policy1
switch(config-pmap-qos)# class class2
switch(config-pmap-c-qos)# set precedence 3
switch(config-pmap-c-qos)#
```

■ set precedence (QoS)

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|------------------------|--------------------------------------|
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

set qos-group

To assign the QoS group identifier for a class of traffic in a type qos policy map, use the **set qos-group** command. To remove the assigned value from the class, use the **no** form of this command.

set qos-group *qos-group-value*

no set qos-group *qos-group-value*

| | | |
|-----------------------------|--|--|
| Syntax Description | <i>qos-group-value</i> | QoS group value to assign for this class of traffic. Valid values are from 0 to 126. |
| Defaults | None | |
| Command Modes | Policy map type qos class configuration | |
| Supported User Roles | network-admin vdc-admin | |
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |
| Usage Guidelines | You can set the QoS group identifier value only in ingress policies. This command does not require a license. | |
| Examples | This example shows how to assign a QoS group identifier for a class of traffic in a type qos policy map: <pre>switch(config)# policy-map my_policy1 switch(config-pmap-qos)# class traffic_class2 switch(config-pmap-c-qos)# set qos-group 100 switch(config-pmap-c-qos)#</pre> | |
| Related Commands | Command | Description |
| | show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

set table

To define a mapping between two fields for a class of traffic in a type qos policy map, use the **set table** command. To remove the assigned mapping from the class, use the **no** form of this command.

```
set header-parameter {same-header-parameter | output-header-parameter} table
    {table-map-name | mutation-map}
```

```
no set header-parameter {same-header-parameter | output-header-parameter} table
    {table-map-name | mutation-map}
```

Syntax Description

| | |
|--------------------------------|--|
| <i>header-parameter</i> | Header parameters. For example, cos , dscp , precedence , or discard-class . |
| <i>same-header-parameter</i> | Header parameter that is the same as the first header parameter in the command line. |
| <i>output-header-parameter</i> | Output header parameter that is different from the first header parameter in the command line. This parameter is used in mutation mapping. |
| <i>table-map-name</i> | User-defined table map name to use for mapping the specified header parameter. |
| <i>mutation-map</i> | System-defined table map name to use for mutation mapping of the input parameter to the output parameter. |

Defaults

None

Command Modes

Policy map type qos class configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|--|
| 4.0 | This command was introduced. |
| 4.1(2) | You can set only similar values when you create a mutation map. For example, you can set cos-cos or dscp-dscp; you cannot set cos-dscp or dscp-precedence. |

Usage Guidelines

The system-defined table maps used in the **set table** command are shown in [Table 5](#).

Send document comments to nexus7k-docfeedback@cisco.com

shape

To configure shaping on an egress queue to impose a maximum rate on it, use the **shape** command. To remove a shaping configuration, use the **no** form of this command.

```
shape [average] {average-rate [bps | kbps | mbps | gbps] | percent percent-rate}
```

```
no shape [average] {average-rate [bps | kbps | mbps | gbps] | percent percent-rate}
```

Syntax Description

| | |
|---------------------|---|
| average | (Optional) Specifies an optional keyword. Shaping is based on an average rate. |
| <i>average-rate</i> | Average rate for shaping. The range of values is from 1 to 80000000000; the range of policing values that are mathematically significant is from 8000 to 80 Gbps. |
| bps | (Optional) Specifies the units of bits per second. |
| kbps | (Optional) Specifies the units of 1000 bits per second. |
| mbps | (Optional) Specifies the units of megabits per second. |
| gbps | (Optional) Specifies the units of gigabits per second. |
| percent | Specifies the percentage of the underlying interface link rate. |
| | Note You can use the percent keyword only for interfaces that are set to autonegotiate. |
| <i>percent-rate</i> | Percentage from 1 to 100. |

Defaults

bps is default data rate.

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines

You can use the system-defined egress queue class for the type of module to which you want to apply the policy map. For a list of the system-defined type queuing class maps, see [Table 1](#).

The device forces the shape rate to the closest value in the following percentage intervals: 100, 50, 33, 25, 12.5, 6.25, 3.13, or 1.07.



Note

If you configure shaping, you cannot configure **bandwidth** or **priority** in the same policy map.

This command does not require a license.

Send document comments to nexus7k-docfeedback@cisco.com**Examples**

This example shows how to apply shaping based on a percentage rate to a policy map type queuing class:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# shape percent 25
switch(config-pmap-c-que)#
```

This example shows how to apply shaping based on an average rate to a policy map type queuing class:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# shape 500 mbps
switch(config-pmap-c-que)#
```

This example shows how to remove a shaping configuration from a policy map type queuing class:

```
switch(config)# policy-map type queuing match-first my_queue
switch(config-pmap-que)# class type queuing lp3q4t-out-pq1
switch(config-pmap-c-que)# no shape percent 25
switch(config-pmap-c-que)#
```

Related Commands

| Command | Description |
|------------------------|--------------------------------------|
| show policy-map | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show class-map type network-qos

To display type network-qos class maps, use the **show class-map type network-qos** command.

show class-map type network-qos

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Any

SupportedUserRoles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display the type network-qos class maps:

```
switch# show class-map type network-qos
Type network-qos class-maps
=====
class-map type network-qos match-any c-nq-8e
  Description: 8E Drop CoS map
  match cos 0-7
class-map type network-qos match-any c-nq-4e-drop
  Description: 4E Drop CoS map
  match cos 0,5-7
class-map type network-qos match-any c-nq-6e-drop
  Description: 6E Drop CoS map
  match cos 0-2,5-7
class-map type network-qos match-any c-nq-7e-drop
  Description: 7E Drop CoS map
  match cos 0-2,4-7
class-map type network-qos match-any c-nq-4e-ndrop
  Description: 4E No-Drop CoS map
  match cos 1-2,4
class-map type network-qos match-any c-nq-6e-ndrop
  Description: 6E No-Drop CoS map
  match cos 4
class-map type network-qos match-any c-nq-4e-ndrop-fcoe
```

Send document comments to nexus7k-docfeedback@cisco.com

```
    Description: 4E No-Drop FCoE CoS map
    match cos 3
    match protocol fcoe
class-map type network-qos match-any c-nq-6e-ndrop-fcoe
    Description: 6E No-Drop FCoE CoS map
    match cos 3
    match protocol fcoe
class-map type network-qos match-any c-nq-7e-ndrop-fcoe
    Description: 7E No-Drop FCoE CoS map
    match cos 3
    match protocol fcoe
```

Related Commands

| Command | Description |
|------------------|----------------------------------|
| class-map | Creates or modifies a class map. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show class-map type qos

To display type qos class maps, use the **show class-map type qos** command.

```
show class-map type qos [class-map-name | color-class-map-name]
```

| | | |
|---------------------------|-----------------------------|--|
| Syntax Description | <i>class-map-name</i> | (Optional) Named class map. The name <i>class-default</i> is reserved. |
| | <i>color-class-map-name</i> | (Optional) System-defined color class map. |

Defaults Displays all type qos class maps if no class map name is specified.

Command Modes Any command mode

Supported User Roles

- network-admin
- network-operator
- vdc-admin
- vdc-operator

| Command History | Release | Modification |
|------------------------|----------------|---------------------|
| | | 4.0 |

Usage Guidelines [Table 6](#) displays the list of system-defined class maps that display with this command.

Table 6 System-Defined Type QoS Class Maps That Display with This Command

| Class Map Name | Description |
|-----------------------|--|
| conform-color-in | Type qos conform color class map in the input direction. This color-aware class map makes a policer color-aware for conform action. |
| conform-color-out | Type qos conform color class map in the output direction. This color-aware class map makes a policer color-aware for conform action. |
| exceed-color-in | Type qos exceed color class map in the input direction. This color-aware class map makes a policer color-aware for exceed action. |
| exceed-color-out | Type qos exceed color class map in the output direction. This color-aware class map makes a policer color-aware for exceed action. |

When you enter the command **show class-map** with no arguments or keywords, the system also displays the Control Plane Policing (CoPP) configuration.

Send document comments to nexus7k-docfeedback@cisco.com

This command does not require a license.

Examples

This example shows how to display all type qos class maps:

```
switch(config)# show class-map type qos
```

```
Type qos class-maps
=====

class-map type qos match-all abc
  match dscp 0-3

class-map type qos conform-color-in
  Description: Conform color map in input direction

class-map type qos conform-color-out
  Description: Conform color map in output direction

class-map type qos exceed-color-in
  Description: Exceed color map in input direction

class-map type qos exceed-color-out
  Description: exceed color map in output direction
```

Related Commands

| Command | Description |
|------------------|----------------------------------|
| class-map | Creates or modifies a class map. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show class-map type queuing

To display type queuing class maps, use the **show class-map type queuing** command.

```
show class-map type queuing [class-map-name]
```

| Syntax Description | <i>class-map-name</i> | (Optional) Named class map. |
|--------------------|-----------------------|-----------------------------|
|--------------------|-----------------------|-----------------------------|

| Defaults | Displays all type queuing class maps if no class map name is specified. |
|----------|---|
|----------|---|

| Command Modes | Any command mode |
|---------------|------------------|
|---------------|------------------|

| SupportedUserRoles | network-admin network-operator vdc-admin vdc-operator |
|--------------------|--|
|--------------------|--|

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

| Usage Guidelines | For a list of the system-defined type queuing class maps, see Table 1 . This command does not require a license. |
|------------------|---|
|------------------|---|

| Examples | This example shows how to display all type queuing class maps: |
|----------|--|
|----------|--|

```
switch(config)# show class-map type queuing

Type queuing class-maps
=====

class-map type queuing match-any 2q4t-in-q1
  Description: Classifier for ingress queue 1 of type 2q4t
  match cos 5-7

class-map type queuing match-any 2q4t-in-q-default
  Description: Classifier for ingress default queue of type 2q4t
  match cos 0-4

class-map type queuing match-any 8q2t-in-q1
  Description: Classifier for ingress queue 1 of type 8q2t
  match cos 5-7

class-map type queuing match-any 8q2t-in-q2
  Description: Classifier for ingress queue 2 of type 8q2t
```

Send document comments to nexus7k-docfeedback@cisco.com

```

class-map type queuing match-any 8q2t-in-q3
  Description: Classifier for ingress queue 3 of type 8q2t

class-map type queuing match-any 8q2t-in-q4
  Description: Classifier for ingress queue 4 of type 8q2t

class-map type queuing match-any 8q2t-in-q5
  Description: Classifier for ingress queue 5 of type 8q2t

class-map type queuing match-any 8q2t-in-q6
  Description: Classifier for ingress queue 6 of type 8q2t

class-map type queuing match-any 8q2t-in-q7
  Description: Classifier for ingress queue 7 of type 8q2t

class-map type queuing match-any 8q2t-in-q-default
  Description: Classifier for ingress default queue of type 8q2t
  match cos 0-4

class-map type queuing match-any 1p3q4t-out-pq1
  Description: Classifier for egress priority queue of type 1p3q4t
  match cos 5-7

class-map type queuing match-any 1p3q4t-out-q2
  Description: Classifier for egress queue 2 of type 1p3q4t

class-map type queuing match-any 1p3q4t-out-q3
  Description: Classifier for egress queue 3 of type 1p3q4t

class-map type queuing match-any 1p3q4t-out-q-default
  Description: Classifier for egress default queue of type 1p3q4t
  match cos 0-4

class-map type queuing match-any 1p7q4t-out-pq1
  Description: Classifier for egress priority queue of type 1p7q4t
  match cos 5-7

class-map type queuing match-any 1p7q4t-out-q2
  Description: Classifier for egress queue 2 of type 1p7q4t

class-map type queuing match-any 1p7q4t-out-q3
  Description: Classifier for egress queue 3 of type 1p7q4t

class-map type queuing match-any 1p7q4t-out-q4
  Description: Classifier for egress queue 4 of type 1p7q4t

class-map type queuing match-any 1p7q4t-out-q5
  Description: Classifier for egress queue 5 of type 1p7q4t

class-map type queuing match-any 1p7q4t-out-q6
  Description: Classifier for egress queue 6 of type 1p7q4t

class-map type queuing match-any 1p7q4t-out-q7
  Description: Classifier for egress queue 7 of type 1p7q4t

class-map type queuing match-any 1p7q4t-out-q-default
  Description: Classifier for egress default queue of type 1p7q4t
  match cos 0-4

```

Related Commands

| Command | Description |
|------------------------|----------------------------------|
| <code>class-map</code> | Creates or modifies a class map. |

Send document comments to nexus7k-docfeedback@cisco.com

show interface priority-flow-control

To display the status of priority flow control (PFC) on all interfaces, use the **show interface priority-flow-control** command.

show interface priority-flow-control

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Any

SupportedUserRoles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display the status of PFC on all interfaces:

```
switch# show interface priority-flow-control
=====
Interface      Admin Oper
=====
Ethernet5/1    Auto  Off
Ethernet5/2    Auto  Off
Ethernet5/3    Auto  Off
Ethernet5/4    Auto  Off
Ethernet5/5    On     On
Ethernet5/6    Auto  Off
Ethernet5/7    Auto  Off
Ethernet5/8    Auto  Off
Ethernet5/9    Auto  Off
Ethernet5/10   Auto  Off
Ethernet5/11   Auto  Off
Ethernet5/12   Auto  Off
Ethernet5/13   Auto  Off
Ethernet5/14   Auto  Off
Ethernet5/15   Auto  Off
Ethernet5/16   Auto  Off
```


Send document comments to nexus7k-docfeedback@cisco.com

```
Ethernet5/17  Auto  Off
Ethernet5/18  Auto  Off
Ethernet5/19  Auto  Off
Ethernet5/20  Auto  Off
Ethernet5/21  Auto  Off
--More--
```

Related Commands

| Command | Description |
|------------------------------|---|
| priority-flow-control | Configures priority flow control (PFC) on an interface, |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show policy-map

To display policy maps and statistics, use the **show policy-map** command.

```
show policy-map [type {qos | queuing}] [policy-map-name | qos-dynamic]
```

| Syntax Description | Parameter | Description |
|--------------------|------------------------|---|
| | type | (Optional) Specifies the component type to display. |
| | qos | Specifies the policy maps of the type qos only. |
| | queuing | Specifies the policy maps of the type queuing only. |
| | <i>policy-map-name</i> | Named policy map. |
| | qos-dynamic | (Optional) Displays already configured policy maps. |

Defaults None

Command Modes Any command mode

Supported User Roles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|---|
| | 4.0 | This command was introduced. |
| | 4.0(3) | The WRR for the type queuing default-in-policy was changed from 50/50 to 80/20. |
| | 4.2(1) | The qos-dynamic variable was added. |

Usage Guidelines When you enter the command **show policy-map** with no arguments or keywords, the system also displays the Control Plane Policing (CoPP) information.

This command does not require a license.

Examples This example shows how to display a named policy map:

```
switch(config)# show policy-map abc

Type qos policy-maps
=====

policy-map type qos abc
  class abc
    set dscp 3
```

Send document comments to nexus7k-docfeedback@cisco.com

```

set qos-group 3
set cos dscp table cos-dscp-map
class class-default

```

This example shows how to display all type queuing policy maps:

```
switch(config)# show policy-map type queuing
```

```

Type queuing policy-maps
=====

policy-map type queuing q1
  class type queuing 8q2t-in-q-default
    set cos 4
policy-map type queuing default-in-policy
  class type queuing in-q1
    queue-limit percent 50
    bandwidth percent 80
  class type queuing in-q-default
    queue-limit percent 50
    bandwidth percent 20
policy-map type queuing default-out-policy
  class type queuing out-pq1
    priority level 1
    queue-limit percent 16
  class type queuing out-q2
    queue-limit percent 1
  class type queuing out-q3
    queue-limit percent 1
  class type queuing out-q-default
    queue-limit percent 82
    bandwidth remaining percent 25

```

Related Commands

| Command | Description |
|------------------|----------------------------------|
| class-map | Creates or modifies a class map. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show policy-map interface

To display policy maps and statistics for the interfaces, use the **show policy-map interface** command.

```
show policy-map interface [ethernet {slot/port} | port-channel {channel-number}] [input |
output] [type {qos | queuing}]
```

| Syntax Description | | |
|-----------------------|------------|---|
| ethernet | (Optional) | Specifies the policy maps that are assigned to Ethernet interfaces. |
| <i>slot/port</i> | | Policy maps that are assigned to a specified interface. |
| port-channel | (Optional) | Specifies the policy maps that are assigned to port channels. |
| <i>channel-number</i> | | Policy maps that are assigned to specified port channel. |
| input | (Optional) | Displays policy maps that are assigned to input traffic only. |
| output | (Optional) | Displays policy maps that are assigned to output traffic only. |
| type | (Optional) | Specifies the component type to display. |
| qos | | Specifies the policy maps of the type qos only. |
| queuing | | Specifies the policy maps of the type queuing only. |

Defaults None.

Command Modes Any command mode

Supported User Roles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines By default, statistics are set to On.
This command does not require a license.

Examples This example shows how to display policy maps that are assigned to a specified interface:

```
switch(config)# show policy-map interface ethernet 2/10

Global statistics status : enabled
```

Send document comments to nexus7k-docfeedback@cisco.com

```
Ethernet2/10

Service-policy (queuing) input:  default-in-policy
policy statistics status:  enabled

Class-map (queuing):  in-q1 (match-any)
queue-limit percent 50
bandwidth percent 50
queue dropped pkts : 0

Class-map (queuing):  in-q-default (match-any)
queue-limit percent 50
bandwidth percent 80
queue dropped pkts : 0

Service-policy (queuing) output:  default-out-policy
policy statistics status:  enabled

Class-map (queuing):  out-pq1 (match-any)
priority level 1
queue-limit percent 16
queue dropped pkts : 0

Class-map (queuing):  out-q2 (match-any)
queue-limit percent 1
queue dropped pkts : 0

Class-map (queuing):  out-q3 (match-any)
queue-limit percent 1
queue dropped pkts : 0

Class-map (queuing):  out-q-default (match-any)
queue-limit percent 82
bandwidth remaining percent 25
queue dropped pkts : 0
```

This example shows how to display policy maps that are assigned to a specified interface:

```
switch(config)# show policy-map interface ethernet 2/2 type qos

Global statistics status : enabled

Ethernet2/2

Service-policy (qos) input: pmap
policy statistics status: enabled

Class-map (qos): map (match-all)
1000000 packets
Match: dscp 46
police cir percent 20 bc 200 ms
conformed 78962304 bytes, 2725540 bps action: transmit
violated 49037696 bytes, 1692633 bps action: drop

Class-map (qos): class-default (match-any)
1000000 packets
police cir percent 10 bc 200 ms
conformed 39481856 bytes, 1362794 bps action: transmit
violated 88518144 bytes, 3055378 bps action: drop
```

■ show policy-map interface

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|-----------|----------------------------------|
| | class-map | Creates or modifies a class map. |

Send document comments to nexus7k-docfeedback@cisco.com

show policy-map interface brief

To display policy maps applied to interfaces in a brief format, use the **show policy-map interface brief** command.

show policy-map interface brief

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Any command mode

SupportedUserRoles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display assigned policy maps in a brief format:

```
switch(config)# show policy-map interface brief

Interface/VLAN [Status]:INP QOS      OUT QOS      INP QUE      OUT QUE
=====
port-channel5  [Active]:
port-channel20 [Active]:
port-channel30 [Active]:
port-channel37 [Active]:
port-channel50 [Active]:

Ethernet2/2    [Active]:
Ethernet2/3    [Active]:

=====
```

■ show policy-map interface brief

Send document comments to nexus7k-docfeedback@cisco.com

Related Commands

| Command | Description |
|------------------------|--------------------------------------|
| show policy-map | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

show policy-map system type network-qos

To display the active type network-qos policy maps, use the **show policy-map system type network-qos** command.

show policy-map system type network-qos

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Any

SupportedUserRoles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display the active type network-qos policy maps:

```
switch# show policy-map system type network-qos
Type network-qos policy-maps
=====
policy-map type network-qos default-nq-4e-policy
  class type network-qos c-nq-4e-drop
    match cos 0,5-7
    congestion-control tail-drop
    mtu 1500
  class type network-qos c-nq-4e-ndrop-fcoe
    match cos 3
    match protocol fcoe
    pause
    mtu 2112
  class type network-qos c-nq-4e-ndrop
    match cos 1-2,4
    pause
    mtu 1500
```

■ `show policy-map system type network-qos`

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|---|--|
| | <code>show policy-map type network-qos</code> | Displays the type network qos policy maps. |
| | <code>show policy-map</code> | Displays policy maps and statistics. |

Send document comments to nexus7k-docfeedback@cisco.com

show policy-map type network-qos

To display the type network-qos policy maps, use the **show policy-map system type network-qos** command.

show policy-map type network-qos

Syntax Description This command has no arguments or keywords.

Defaults None

Command Modes Any

SupportedUserRoles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display the type network-qos policy maps:

```
switch# show policy-map type network-qos
Type network-qos policy-maps
=====
policy-map type network-qos default-nq-4e-policy
  class type network-qos c-nq-4e-drop
    congestion-control tail-drop
    mtu 1500
  class type network-qos c-nq-4e-ndrop-fcoe
    pause
    mtu 2112
  class type network-qos c-nq-4e-ndrop
    pause
    mtu 1500
policy-map type network-qos default-nq-6e-policy
  class type network-qos c-nq-6e-drop
    congestion-control tail-drop
    mtu 1500
  class type network-qos c-nq-6e-ndrop-fcoe
    pause
    mtu 2112
  class type network-qos c-nq-6e-ndrop
```

■ `show policy-map type network-qos`

Send document comments to nexus7k-docfeedback@cisco.com

```

pause
mtu 1500
policy-map type network-qos default-nq-7e-policy
  class type network-qos c-nq-7e-drop
    congestion-control tail-drop
  mtu 1500
  class type network-qos c-nq-7e-ndrop-fcoe
    pause
    mtu 2112
policy-map type network-qos default-nq-8e-policy
  class type network-qos c-nq-8e
    congestion-control tail-drop
  mtu 1500

```

Related Commands

| Command | Description |
|------------------------------|--------------------------------------|
| <code>show policy-map</code> | Displays policy maps and statistics. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show policy-map vlan

To display policy maps for the VLANs, use the **show policy-map vlan** command.

```
show policy-map vlan [vlan-id] [input | output] [type {qos | queuing}]
```

| Syntax Description | |
|--------------------|---|
| <i>vlan-id</i> | (Optional) Policy maps assigned to specified VLAN. |
| input | (Optional) Displays policy maps that are assigned to input traffic only. |
| output | (Optional) Displays policy maps that are assigned to output traffic only. |
| type | (Optional) Specifies the component type to display. |
| qos | Specifies the policy maps of type qos only. |
| queuing | Specifies the policy maps of type queuing only. This keyword is not supported in Release 4.0.1. |

Defaults None

Command Modes Any command mode

Supported User Roles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display policy maps that are assigned to all VLANs:

```
switch(config)# show policy-map vlan

Global statistics status :   enabled

Vlan 1

  Service-policy (qos) input:   abc
    policy statistics status:   enabled

  Class-map (qos):   abc (match-all)
    Match: dscp 0-3
    set dscp 3
    set qos-group 3
```

■ show policy-map vlan

Send document comments to nexus7k-docfeedback@cisco.com

```
set cos dscp table cos-dscp-map

Class-map (qos):  class-default (match-any)

Service-policy (qos) output:  def
policy statistics status:  enabled
```

Related Commands

| Command | Description |
|------------------|----------------------------------|
| class-map | Creates or modifies a class map. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show qos dcbxp

To display the Data Center Bridging Capability Exchange Protocol (DCBXP) information on all interfaces, use the **show qos dcbxp** command.

```
show qos dcbxp {incompatibility [interface {ethernet slot/port-number} | info]}
```

| Syntax Description | Parameter | Description |
|--------------------|-------------------------|--|
| | incompatibility | (Optional) Specifies the DCBXP incompatibility. |
| | interface | (Optional) Specifies the Ethernet interface. |
| | <i>slot/port-number</i> | Module number and the port number for which you want to display the incompatibility information. |
| | info | (Optional) Specifies the DCBXP information. |

Command Default None

Command Modes Any

Supported User Roles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 5.1(1) | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display the status of DCBXP on all interfaces:

```
switch# show qos dcbxp info
Interface      PFC_rcvd/cmptble PG_rcvd/cmptble MTU_rcvd/cmptble FCOE_rcvd/cmptble
-----
Ethernet5/1    No/No             No/No             No/No             No/No
Ethernet5/2    No/No             No/No             No/No             No/No
Ethernet5/3    No/No             No/No             No/No             No/No
Ethernet5/4    No/No             No/No             No/No             No/No
Ethernet5/5    Yes/No            No/No             No/No             No/No
Ethernet5/6    No/No             No/No             No/No             No/No
Ethernet5/7    Yes/No            No/No             Yes/No            No/No
Ethernet5/8    No/No             No/No             No/No             No/No
Ethernet5/9    No/No             No/No             No/No             No/No
Ethernet5/10   No/No             No/No             No/No             No/No
Ethernet5/11   No/No             No/No             No/No             No/No
```

■ show qos dcbxp

Send document comments to nexus7k-docfeedback@cisco.com

```

Ethernet5/12      No/No           No/No           No/No           No/No
Ethernet5/13      No/No           No/No           No/No           No/No
Ethernet5/14      No/No           No/No           No/No           No/No
Ethernet5/15      No/No           No/No           No/No           No/No
Ethernet5/16      No/No           No/No           No/No           No/No
Ethernet5/17      No/No           No/No           No/No           No/No
Ethernet5/18      No/No           No/No           No/No           No/No
Ethernet5/19      No/No           No/No           No/No           No/No
Ethernet5/20      No/No           No/No           No/No           No/No
Ethernet5/21      No/No           No/No           No/No           No/No
Ethernet5/22      No/No           No/No           No/No           No/No
Ethernet5/23      No/No           No/No           No/No           No/No
Ethernet5/24      No/No           No/No           No/No           No/No
Ethernet5/25      No/No           No/No           No/No           No/No
Ethernet5/26      No/No           No/No           No/No           No/No
Ethernet5/27      No/No           No/No           No/No           No/No
Ethernet5/28      No/No           No/No           No/No           No/No
Ethernet5/29      No/No           No/No           No/No           No/No
Ethernet5/30      No/No           No/No           No/No           No/No
Ethernet5/31      No/No           No/No           No/No           No/No
Ethernet5/32      No/No           No/No           No/No           No/No
switch#

```

Related Commands

| Command | Description |
|---|---|
| show interface priority-flow-control | Displays the status of priority flow control (PFC) on all interfaces. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show qos shared-policer

To display qos shared policers, use the **show qos shared-policer** command.

```
show qos shared policer [type qos] [policer-name]
```

| Syntax Description | |
|---------------------|---|
| type qos | (Optional) Specifies the type qos policers. |
| policer-name | (Optional) Specified policer name. |

| Defaults | None |
|----------|------|
|----------|------|

| Command Modes | Any command mode |
|---------------|------------------|
|---------------|------------------|

| SupportedUserRoles | network-admin network-operator vdc-admin vdc-operator |
|--------------------|--|
|--------------------|--|

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

| Usage Guidelines | This command does not require a license. |
|------------------|--|
|------------------|--|

| Examples | This example shows how to display all type qos policers: <pre>switch(config)# show qos shared-policer</pre> <pre>switch(config)# qos shared-policer foo cir 300 mbps bc 200 ms conform transmit violate drop</pre> |
|----------|--|
|----------|--|

| Related Commands | Command | Description |
|------------------|------------------|----------------------------------|
| | class-map | Creates or modifies a class map. |

Send document comments to nexus7k-docfeedback@cisco.com

show queuing interface

To display queuing information on a specified interface, use the **show queuing interface** command.

```
show queuing interface {ethernet slot/port}
```

| Syntax Description | Parameter | Description |
|--------------------|------------------|--|
| | ethernet | Specifies the Ethernet interface. |
| | <i>slot/port</i> | Module number and the port number for which you want to display the queuing information. |

Defaults None

Command Modes Any command mode

Supported User Roles network-admin
network-operator
vdc-admin
vdc-operator

| Command History | Release | Modification |
|-----------------|---------|------------------------------|
| | 4.0 | This command was introduced. |

Usage Guidelines This command does not require a license.

Examples This example shows how to display the queuing information for a specified interface:

```
switch# show queuing interface ethernet 2/9
```

```
Interface Ethernet2/9 TX Queuing strategy: Weighted Round-Robin
Port QoS is enabled
  Queuing Mode in TX direction: mode-cos
  Transmit queues [type = 1p3q4t]
  Queue Id          Scheduling    Num of thresholds
-----
  1p3q4t-out-q-default  WRR           04
  1p3q4t-out-q2        WRR           04
  1p3q4t-out-q3        WRR           04
  1p3q4t-out-pq1       Priority       04

Configured WRR
  WRR bandwidth ratios:  25 [1p3q4t-out-q-default] 38 [1p3q4t-out-q2] 37 [1p3q
4t-out-q3]
  WRR configuration read from HW
  WRR bandwidth ratios:  24 [1p3q4t-out-q-default] 37 [1p3q4t-out-q2] 37 [1p3q
4t-out-q3]
```

Send document comments to nexus7k-docfeedback@cisco.com

```
Configured queue-limit ratios
queue-limit ratios:      82 [1p3q4t-out-q-default] 1 [1p3q4t-out-q2] 1 [1p3q4t
-out-q3] 16 [1p3q4t-out-pq1]
queue-limit ratios configuration read from HW
queue-limit ratios:      82 [1p3q4t-out-q-default] 1 [1p3q4t-out-q2] 1 [1p3q4t
-out-q3] 16 [1p3q4t-out-pq1]
```

Thresholds:

| COS | Queue | Threshold Type | Min | Max |
|-----|----------------------|----------------|-----|-----|
| 0 | 1p3q4t-out-q-default | DT | 100 | 100 |
| 1 | 1p3q4t-out-q-default | DT | 100 | 100 |
| 2 | 1p3q4t-out-q-default | DT | 100 | 100 |
| 3 | 1p3q4t-out-q-default | DT | 100 | 100 |
| 4 | 1p3q4t-out-q-default | DT | 100 | 100 |
| 5 | 1p3q4t-out-pq1 | DT | 100 | 100 |
| 6 | 1p3q4t-out-pq1 | DT | 100 | 100 |
| 7 | 1p3q4t-out-pq1 | DT | 100 | 100 |

Interface Ethernet2/9 RX Queuing strategy: Weighted Round-Robin

Queuing Mode in RX direction: mode-cos

Receive queues [type = 2q4t]

Port Cos not configured

| Queue Id | Scheduling | Num of thresholds |
|-------------------|------------|-------------------|
| 2q4t-in-q-default | WRR | 04 |
| 2q4t-in-q1 | WRR | 04 |

Configured WRR

WRR bandwidth ratios: 50 [2q4t-in-q-default] 50 [2q4t-in-q1]

WRR configuration read from HW

WRR bandwidth ratios: 50 [2q4t-in-q-default] 50 [2q4t-in-q1]

Configured queue-limit ratios

queue-limit ratios: 50 [2q4t-in-q-default] 50 [2q4t-in-q1]

queue-limit ratios configuration read from HW

queue-limit ratios: 50 [2q4t-in-q-default] 50 [2q4t-in-q1]

Thresholds:

| COS | Queue | Threshold Type | Min | Max |
|-----|-------------------|----------------|-----|-----|
| 0 | 2q4t-in-q-default | DT | 100 | 100 |
| 1 | 2q4t-in-q-default | DT | 100 | 100 |
| 2 | 2q4t-in-q-default | DT | 100 | 100 |
| 3 | 2q4t-in-q-default | DT | 100 | 100 |
| 4 | 2q4t-in-q-default | DT | 100 | 100 |
| 5 | 2q4t-in-q1 | DT | 100 | 100 |
| 6 | 2q4t-in-q1 | DT | 100 | 100 |
| 7 | 2q4t-in-q1 | DT | 100 | 100 |

Related Commands

| Command | Description |
|-------------------------------------|--|
| show class-map type queuing | Displays information about the class maps type queuing. |
| show policy-map type queuing | Displays information about the policy maps type queuing. |

[Send document comments to nexus7k-docfeedback@cisco.com](mailto:nexus7k-docfeedback@cisco.com)

show running-config ipqos

To display information about the running-system configuration for quality of service (QoS), use the **show running-config ipqos** command.

show running-config ipqos [all]

| Syntax Description | all (Optional) Displays configured and default information. | | | | |
|---------------------------|---|---------|--------------|-----|------------------------------|
| Defaults | None | | | | |
| Command Modes | Any command mode | | | | |
| SupportedUserRoles | network-admin vdc-admin | | | | |
| Command History | <table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>4.0</td> <td>This command was introduced.</td> </tr> </tbody> </table> | Release | Modification | 4.0 | This command was introduced. |
| Release | Modification | | | | |
| 4.0 | This command was introduced. | | | | |

Usage Guidelines This command does not require a license.

Examples This example shows how to display QoS information:

```
switch(config)# show running-config ipqos

version 4.0(3)
qos statistics
class-map type qos match-all abc
  match dscp 0-3
class-map type qos match-all qqg
class-map type qos match-all class1
class-map type qos match-all cmapdef
class-map type qos match-all my_test
  match cos 5
class-map type qos match-all my_class
  match discard-class 56
class-map type qos match-all class_acl
class-map type qos match-all class_protocol
class-map conform-color-in
class-map conform-color-out
class-map exceed-color-in
class-map exceed-color-out
class-map type queuing match-any 2q4t-in-q1
  match cos 5-7
class-map type queuing match-any 2q4t-in-q-default
  match cos 0-4
```

Send document comments to nexus7k-docfeedback@cisco.com

```

class-map type queuing match-any 8q2t-in-q1
  match cos 5-7
class-map type queuing match-any 8q2t-in-q2
class-map type queuing match-any 8q2t-in-q3
class-map type queuing match-any 8q2t-in-q4
class-map type queuing match-any 8q2t-in-q5
class-map type queuing match-any 8q2t-in-q6
class-map type queuing match-any 8q2t-in-q7
class-map type queuing match-any 8q2t-in-q-default
  match cos 0-4
class-map type queuing match-any 1p3q4t-out-pq1
  match cos 5-7
class-map type queuing match-any 1p3q4t-out-q2
class-map type queuing match-any 1p3q4t-out-q3
class-map type queuing match-any 1p3q4t-out-q-default
  match cos 0-4
class-map type queuing match-any 1p7q4t-out-pq1
  match cos 5-7
class-map type queuing match-any 1p7q4t-out-q2
class-map type queuing match-any 1p7q4t-out-q3
class-map type queuing match-any 1p7q4t-out-q4
class-map type queuing match-any 1p7q4t-out-q5
class-map type queuing match-any 1p7q4t-out-q6
class-map type queuing match-any 1p7q4t-out-q7
class-map type queuing match-any 1p7q4t-out-q-default
  match cos 0-4
table-map cir-markdown-map
  default copy
  from 10,12 to 12
  from 18,20 to 20
  from 26,28 to 28
  from 34,36 to 36
table-map pir-markdown-map
  default copy
  from 10,12 to 14
  from 18,20 to 22
  from 26,28 to 30
  from 34,36 to 38
table-map cos-dscp-map
  default copy
  from 0 to 2
table-map cos-precedence-map
  default copy
table-map cos-discard-class-map
  default copy
table-map dscp-cos-map
  default copy
table-map dscp-precedence-map
  default copy
table-map dscp-discard-class-map
  default copy
table-map precedence-cos-map
  default copy
table-map precedence-dscp-map
  default copy
table-map precedence-discard-class-map
  default copy
table-map discard-class-cos-map
  default copy
table-map discard-class-dscp-map
  default copy
table-map discard-class-precedence-map
  default copy
table-map t1

```

Send document comments to nexus7k-docfeedback@cisco.com

```

    default copy
table-map abc
    default copy
table-map my_table1
    default copy
table-map steve_tm2
    default 3
table-map steve_table_map
    default ignore
policy-map type queuing q
policy-map type queuing pq
    class type queuing 8q2t-in-q4
        queue-limit cos 3 1000 packets
        queue-limit cos 4 1000 packets
        queue-limit 10000 packets
policy-map type queuing q1
policy-map type queuing q2
    class type queuing 1p3q4t-out-pq1
policy-map type queuing p_q
    class type queuing 8q2t-in-q4
    class type queuing 8q2t-in-q-default
    set cos 4
policy-map type queuing abcq
    class type queuing 8q2t-in-q4
policy-map type queuing p_q2
    class type queuing 1p7q4t-out-q2
    shape average percent 10
policy-map type queuing steve_q
    class type queuing 1p7q4t-out-pq1
    class type queuing 1p7q4t-out-q4
    class type queuing 1p7q4t-out-q2
policy-map type queuing my_queue
    class type queuing 1p3q4t-out-pq1
policy-map type queuing steve_pq1
    class type queuing 1p3q4t-out-pq1
policy-map type qos abc
    class abc

switch# show running-config ipqos
version 4.0(3)
class-map type qos match-all abc
    match dscp 0-3
class-map type qos match-all qqq
class-map type qos match-all class1
class-map type qos match-all cmapdef
class-map type qos match-all my_test
    match cos 5
class-map type qos match-all my_class
    match discard-class 56
class-map type qos match-all class_acl
class-map type qos match-all class_protocol
table-map cos-dscp-map
    default copy
    from 0 to 2
table-map t1
    default copy
table-map abc
    default copy
table-map my_table1
    default copy
table-map steve_tm2
    default 3
table-map steve_table_map

```

Send document comments to nexus7k-docfeedback@cisco.com

```
default ignore
policy-map type queuing q
policy-map type queuing pq
  class type queuing 8q2t-in-q4
    queue-limit cos 3 1000 packets
    queue-limit cos 4 1000 packets
    queue-limit 10000 packets
policy-map type queuing q1
policy-map type queuing q2
  class type queuing 1p3q4t-out-pq1
policy-map type queuing p_q
  class type queuing 8q2t-in-q4
  class type queuing 8q2t-in-q-default
  set cos 4
policy-map type queuing abcq
  class type queuing 8q2t-in-q4
policy-map type queuing p_q2
  class type queuing 1p7q4t-out-q2
  shape average percent 10
policy-map type queuing steve_q
  class type queuing 1p7q4t-out-pq1
  class type queuing 1p7q4t-out-q4
  class type queuing 1p7q4t-out-q2
policy-map type queuing my_queue
  class type queuing 1p3q4t-out-pq1
policy-map type queuing steve_pq1
  class type queuing 1p3q4t-out-pq1
policy-map type qos abc
  class abc
    set dscp 3
    set qos-group 3
    set cos dscp table cos-dscp-map
  class class-default
policy-map type qos def
policy-map type qos policy1
  class class-default
  class class1
policy-map type qos polilcy1
policy-map type qos my_policy
  class class-default
policy-map type qos my_policy1
policy-map type queuing my_policy1
  class type queuing 1p7q4t-out-q2
policy-map type queuing shape_queue
  class type queuing 1p3q4t-out-pq1
    queue-limit 38984 packets
    random-detect cos-based
policy-map type queuing shape_queues
  class type queuing 1p3q4t-out-pq1
policy-map type queuing 1p3q4t-out-pq1
policy-map type queuing untrusted_port_cos
  class type queuing 2q4t-in-q-default

interface Ethernet2/4
  service-policy type qos input abc
  service-policy type qos output def
  service-policy type queuing output q1
```

■ show running-config ipqos

Send document comments to nexus7k-docfeedback@cisco.com

| Related Commands | Command | Description |
|------------------|-----------------|--|
| | show class-map | Displays information about class maps. |
| | show policy-map | Displays statistics and information about policy maps. |

Send document comments to nexus7k-docfeedback@cisco.com

show table-map

To display table maps, use the **show table-map** command.

```
show table-map [table-map-name | default-table-map-name]
```

| | | |
|-----------------------------|-------------------------------|--|
| Syntax Description | <i>table-map-name</i> | (Optional) User-defined named table map. |
| | <i>default-table-map-name</i> | (Optional) System-defined default table map. |
| Defaults | None | |
| Command Modes | Global configuration | |
| Supported User Roles | network-admin vdc-admin | |
| Command History | Release | Modification |
| | 4.0 | This command was introduced. |
| | 4.0.2 | Display was changed |

Usage Guidelines For a list of the system-defined table maps, see [Table 5](#).

In Cisco NX-OS Release 4.0.2 and later releases, the display shows only one of the following:

- The default copy if you have not configured any changes to the table map.
- The changes you configured to the table map.

This command does not require a license.

Examples

In the Cisco NX-OS Release 4.0.2 and later releases, the following example shows how to display a system-defined table map:

```
switch(config-pmap-c-qos)# show table-map cos-dscp-map
```

```
Table-map cos-dscp-map
  default copy
```

This example shows how to display a system-defined table map:

```
switch(config)# show table-map cos-dscp-map
```

```
Table-map cos-dscp-map
  from 0 to 0
  from 1 to 1
  from 2 to 2
```

■ show table-map

Send document comments to nexus7k-docfeedback@cisco.com

```
from 3 to 3
from 4 to 4
from 5 to 5
from 6 to 6
from 7 to 7
```

Related Commands

| Command | Description |
|------------------|----------------------------------|
| table-map | Creates or modifies a table map. |

Send document comments to nexus7k-docfeedback@cisco.com

table-map

To create or modify a table map and enter the table map configuration mode, use the **table-map** command. To remove a table map, use the **no** form of this command.

table-map {*table-map-name* | *default-table-map-name*}

no table-map {*table-map-name* | *default-table-map-name*}

Syntax Description

| | |
|-------------------------------|--|
| <i>table-map-name</i> | Name of an existing or new user-defined table map. |
| <i>default-table-map-name</i> | Name of a system-defined table map. |

Defaults

None

Command Modes

Global configuration

Supported User Roles

network-admin
vdc-admin

Command History

| Release | Modification |
|---------|------------------------------|
| 4.0 | This command was introduced. |

Usage Guidelines



Note

You cannot modify the system-defined table maps. For a list of the system-defined table maps, see [Table 5](#).

This command does not require a license.

Examples

This example shows how to create or modify a table map:

```
switch(config)# table-map my_table1
switch(config-tmap)#
```

This example shows how to remove a table map:

```
switch(config)# no table-map my_table1
switch(config)#
```

Related Commands

| Command | Description |
|-----------------------|----------------------|
| show table-map | Displays table maps. |

■ table-map

Send document comments to nexus7k-docfeedback@cisco.com