

# Table of Contents

<b><u>Configuring DLSw+ Peer Groups and Border Peers</u></b> .....	<b>1</b>
<u>Document ID: 12349</u> .....	1
<u>Introduction</u> .....	1
<u>Prerequisites</u> .....	1
<u>Requirements</u> .....	1
<u>Components Used</u> .....	1
<u>Conventions</u> .....	2
<u>Configure</u> .....	2
<u>Network Diagram</u> .....	2
<u>Configurations</u> .....	3
<u>Verify</u> .....	7
<u>Start the DSPU on Brachio</u> .....	7
<u>Troubleshoot</u> .....	8
<u>NetPro Discussion Forums – Featured Conversations</u> .....	8
<u>Related Information</u> .....	8

# Configuring DLSw+ Peer Groups and Border Peers

Document ID: 12349

---

## Introduction

### Prerequisites

- Requirements
- Components Used
- Conventions

### Configure

- Network Diagram
- Configurations

### Verify

- Start the DSPU on Brachio

### Troubleshoot

[NetPro Discussion Forums – Featured Conversations](#)

### Related Information

---

## Introduction

This document demonstrates how Data Link Switching Plus (DLSw+) peer groups and border peers can be used to provide any-to-any connectivity in large networks, with peer-on-demand. DLSw+ provides a hierarchical means to dynamically search for branch resources. Instead of a single branch router having to query every other branch router, the branch router sends a single broadcast to its border peer. The border peer checks its local, remote, and group cache before it forwards the explorer. If the resource is not found, the border peer propagates the broadcast within its group and to other border peers. Other border peers propagate the broadcast within their group. This method not only minimizes the broadcast replication on each line, it also minimizes the replication work done by any single router. End-to-end TCP connections (called peer-on-demand connections) are set up only when resources are found. DLSw+ border peer was introduced in Cisco IOS® Software Release 10.3.

## Prerequisites

### Requirements

There are no specific requirements for this document.

### Components Used

The information in this document is based on these software and hardware versions:

- Cisco IOS Software Releases 12.0(7)T, 12.1(2), and 12.1(5)T.

**Note:** It is recommended that you run the same Cisco IOS Software Release in all DLSw+ peering routers.

- Two Cisco 2500s, one Cisco 4700, and one Cisco 7500.
- For the Channel attachment, a Cisco 7206 with a Channel Port Adapter (CPA).

The information in this document was created from the devices in a specific lab environment. All of the



commonly established over serial WAN connections; however, they can be established over any arbitrary TCP topology.

All the routers are set up as promiscuous. This means that they will accept incoming requests to establish a peer connection. This is now enforced by the **group** parameter of the **dls w local-peer [peer-id ip-address] [group group] [border] [promiscuous]** command.

The remote routers Diplodocus, Rex, and Brachio are set up with a **dls w remote-peer** statement that points to their DLSw+ border peer routers Plesio and FEP, respectively. The DLSw+ border peer routers must be configured with a **dls w remote-peer** statement for every other border peer router to which they are supposed to forward traffic. Because they are both set up as promiscuous, however, the **dls w remote-peer** statement need only be configured in one of them. The Brachio router uses the Downstream Physical Unit (DSPU) feature to establish a DLSw+ circuit with the Diplodocus router, which has a CPA connection to a mainframe. This causes a DLSw+ peer connection to be established from Brachio to Diplodocus for the duration of the circuit only (see the DLSw+ circuit output on Brachio, in the Verify section).

## Configurations

This document uses these configurations:

- Border Router – Plesio
- Remote Router – Diplodocus (7206)
- Remote Router – Rex
- Border Peer Router – FEP
- Remote Router – Brachio

One other command that has not been mentioned here is **dls w peer-on-demand-defaults**. This command is used to change some characteristics for the on-demand peers. The most common option is to change the inactivity timeout after which the peer will be torn down. The default is ten minutes.

**Note:** Only relevant interfaces are provided.

```

                                Border Router – Plesio
-----
hostname plesio
!
!
source-bridge ring-group 1
DLSw local-peer peer-id 10.64.3.99 group 1 border promiscuous
DLSw remote-peer 0 tcp 10.64.3.194

!--- To border peer FEP.

!
!
!
interface Serial0
ip address 10.64.3.177 255.255.255.240

!--- WAN connection to FEP border peer.

no ip directed-broadcast
clockrate 64000
!
interface Serial1
ip address 10.64.3.161 255.255.255.240
```

```
!--- WAN connection to Rex DLSw remote router.
```

```
no ip directed-broadcast
clockrate 64000
!
interface TokenRing0
ip address 10.64.3.99 255.255.255.240
no ip directed-broadcast
ring-speed 16
!
router eigrp 1
network 10.0.0.0
!
!
ip classless
no ip http server
!
!
!
line con 0
transport input none
line aux 0
line vty 0 4
login
!
end
```

#### Remote Router – Diplodocus (7206)

```
hostname diplodocus
!
boot system flash slot0:c7200-a3js56i-mz.121-5.T1.bin
logging rate-limit console 10 except errors
enable password cisco
!
username cisco password 0 cisco
microcode pcpa slot0:xcpa28-2
microcode reload
clock timezone aest -9
ip subnet-zero
!
!
source-bridge ring-group 1
dlsw local-peer peer-id 10.64.3.97 group 1 promiscuous
dlsw remote-peer 0 tcp 10.64.3.99

!--- Connection to border peer, Plesio.

!
!
interface Channel2/0
no ip address
no keepalive
csna 0100 41
lan TokenRing 0
source-bridge 4 1 1
adapter 0 4000.0000.0001
!
interface TokenRing5/0
ip address 10.64.3.97 255.255.255.240
no ip route-cache
no ip mroute-cache
ring-speed 16
```

```

!
!
!
router eigrp 1
network 10.0.0.0
auto-summary
no eigrp log-neighbor-changes
!
ip classless
ip route 0.0.0.0 0.0.0.0 10.64.3.1
no ip http server
!
!

```

#### Remote Router – Rex

```

hostname rex
!
source-bridge ring-group 70
dlsw local-peer peer-id 10.64.3.162 group 1 promiscuous
dlsw remote-peer 0 tcp 10.64.3.99

!--- Connection to border peer, Plesio.

!
!
!
interface Serial1
ip address 10.64.3.162 255.255.255.240

!--- WAN connection to border peer, Plesio.

!
interface TokenRing0
ring-speed 16
source-bridge 30 1 70
source-bridge spanning
!
router eigrp 1
network 10.0.0.0
auto-summary
no eigrp log-neighbor-changes
!
no ip http server
ip classless
!
line con 0
transport input none
line aux 0
line vty 0 4
password cisco
login
!
end

```

#### Border Peer Router – FEP

```

!
version 12.1
service timestamps debug datetime
service timestamps log datetime
no service password-encryption
!

```

```

hostname FEP
!
!
source-bridge ring-group 60
dlsw local-peer peer-id 10.64.3.194 group 2 border promiscuous
!
!
interface TokenRing0/0
ip address 10.64.3.194 255.255.255.240
no ip mroute-cache ring-speed 16
!
!
interface Serial6/4
ip address 10.64.3.178 255.255.255.240

!--- WAN connection to border peer, Plesio.

!
!
router eigrp 1
network 10.0.0.0
!

```

### Remote Router – Brachio

```

!
version 12.1
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
!
hostname brachio
!
no logging buffered
!
!
!
!
!
ip subnet-zero
no ip domain-lookup
!
cns event-service server
!
source-bridge ring-group 2
dlsw local-peer peer-id 10.64.3.195 group 2 promiscuous
dlsw remote-peer 0 tcp 10.64.3.194

!--- Connection to border peer, FEP.

!
!
dspu vdlc 2 4000.cccc.dddd

!--- Local virtual ring and virtual MAC address for DSPU.

dspu vdlc enable-host lsap 12
!
dspu host PU5 xid-snd 01700005 rmac 4000.0000.0001 rsap 4 lsap 12

!--- XID to be sent to MAC address 4000.0000.0001,
!--- which is adapter 0 on the Channel Interface in Diplodocus.

```

```

dspu vdlc start PU5
!
!
interface TokenRing0
ip address 10.64.3.195 255.255.255.240
ring-speed 16
!
interface TokenRing1
ring-speed 16
source-bridge 200 1 2
source-bridge spanning
!
router eigrp 1
network 10.0.0.0

```

## Verify

This section shows example output of the establishment of the peer-on-demand, when the DSPU is started on Brachio. Initially, both Diplodocus and Brachio have only a single DLSw peer connection with their border peer routers.

**Note:** Certain **show** commands are supported by the Output Interpreter Tool (registered customers only), which allows you to view an analysis of **show** command output.

```
diplodocus# show dlsw peer
```

```

Peers:                state  pkts_rx  pkts_tx  type  drops  ckts  TCP  uptime
TCP 10.64.3.99        CONNECT  2         2  conf    0     0    0  00:00:20
Total number of connected peers: 1
Total number of connections: 1

```

```
brachio# show dlsw peer
```

```

Peers:                state  pkts_rx  pkts_TX  type  drops  ckts  TCP  uptime
TCP 10.64.3.194       CONNECT  12        10  conf    0     0    0  00:04:27
Total number of connected peers: 1
Total number of connections: 1

```

## Start the DSPU on Brachio

```
brachio# configure terminal
```

Enter configuration commands, one per line. End with CNTL/Z.

```
brachio(config)# dspu vdlc start pu5
```

```
brachio(config)# ^Z
```

```
brachio# show dspu
```

```

7w2d: %SYS-5-CONFIG_I: Configured from console by consolspu
dspu host PU5 Vdlc  PU STATUS Active
FRAMES RECEIVED 56 FRAMES SENT 56
LUs USED BY DSPU 0 LUs ACTIVE 0
LUs USED BY API 0 LUs ACTIVE 0
LUs ACTIVATED BY HOST BUT NOT USED 1

```

Notice that another peer is brought up to Diplodocus.

```
brachio# show dlsw peer
```

```
Peers:                state  pkts_rx  pkts_TX  type  drops  ckts  TCP  uptime
TCP 10.64.3.97        CONNECT  11        13       pod   0      1    0  00:00:34
```

*!--- pod means peer-on-demand.*

```
TCP 10.64.3.194      CONNECT  15        13       conf  0      0    0  00:05:26
Total number of connected peers: 2
Total number of connections: 2
```

There is also a circuit connected between the DSPU and adaptor 0 on the Channel Interface CPA.

```
brachio# show dlsw cir
```

```
Index          local addr(lsap)  remote addr(dsap)  state      uptime
3590324919    4000.cccc.dddd(0C) 4000.0000.0001(04) CONNECTED  00:00:21
Total number of circuits connected: 1
```

## Troubleshoot

There is currently no specific troubleshooting information available for this configuration.

## NetPro Discussion Forums – Featured Conversations

Networking Professionals Connection is a forum for networking professionals to share questions, suggestions, and information about networking solutions, products, and technologies. The featured links are some of the most recent conversations available in this technology.

NetPro Discussion Forums – Featured Conversations for IBM
---

Network Infrastructure: Enterprise Data Centers
---

## Related Information

- [DLSw Support Page](#)
- [Troubleshooting DLSw](#)
- [Technology Support](#)
- [Product Support](#)
- [Technical Support – Cisco Systems](#)

---

All contents are Copyright © 1992–2005 Cisco Systems, Inc. All rights reserved. Important Notices and Privacy Statement.

---

Updated: Sep 05, 2005

Document ID: 12349

---