

SNMP Counters: Frequently Asked Questions

Document ID: 26007

Questions

[Introduction](#)

[SNMP Counters Questions](#)

[SNMP Counters and show Command Equivalent Questions](#)

[NetPro Discussion Forums – Featured Conversations](#)

[Related Information](#)

Introduction

This document provides answers to commonly asked questions, and guides users to find helpful resources on SNMP, and SNMP issues as they relate to Cisco equipment.

SNMP Counters Questions

Q. Which MIB should I use for interface counters?

A. Interface management over SNMP is based on two tables: ifTable (registered customers only) and its extension, ifXTable (registered customers only) described in RFC1213/RFC2233. Interfaces can have several layers, which depends on the media, and each sub-layer is represented by a separate row in the table. The relationship between the higher layer and lower layers is described in the ifStackTable (registered customers only) . The ifTable defines 32-bit counters for inbound and outbound octets (ifInOctets (registered customers only) /ifOutOctets), packets (ifInUcastPkts (registered customers only) /ifOutUcastPkts (registered customers only) , ifInNUcastPkts (registered customers only) /ifOutNUcastPkts (registered customers only)), errors, and discards. The ifXTable provides similar 64-bit counters, also called high capacity (HC) counters: ifHCInOctets (registered customers only) /ifHCOutOctets (registered customers only) , and ifHCInUcastPkts (registered customers only) /ifHCOutUcastPkts (registered customers only) .

Q. When should 64-bit counters be used?

A. RFC 2233 adopted expanded 64-bit counters for high capacity interfaces in which 32-bit counters do not provide enough capacity and wrap too fast.

As the speed of network media increases, the minimum time in which a 32-bit counter wraps decreases. For example, a 10 Mbps stream of back-to-back, full-size packets causes ifInOctets to wrap in just over 57 minutes. At 100 Mbps, the minimum wrap time is 5.7 minutes, and at 1 Gbps, the minimum is 34 seconds.

Note: The SNMP counters wrap, the command line interface (CLI) counters do not.

For interfaces that operate at 20,000,000 (20 million) bits per second or less, you must use 32-bit byte and packet counters. For interfaces that operate faster than 20 million bits per second, and slower than 650,000,000 bits per second, you must use 32-bit packet counters

and 64-bit octet counters. For interfaces that operate at 650,000,000 bits/second or faster, 64-bit packet and octet counters must be used.

Correspondingly, Cisco IOS® Software does not support 64-bit counters for interface speeds of less than 20 Mbps. This means that 64-bit counters are not supported on 10 Mb Ethernet ports, only 100 Mb Fast-Ethernet and other high speed ports support 64-bit counters.

Q. Which version of SNMP is required to query 64-bit counters?

A. SNMPv2C or SNMPv3 is required to query 64-bit counters. SNMPv1 does not support 64-bit counters. Be aware that ifInOctets = .1.3.6.1.2.1.2.2.1.10 is a 32-bit counter while the 64-bit version is ifHCInOctets = .1.3.6.1.2.1.31.1.1.1.6.

For example:

Catalyst 5000 uses HP OpenView snmpget, which defaults to SNMPv1

```
# snmpget -c public 14.32.5.18 ifName.1

ifMIB.ifMIBObjects.ifXTable.ifXEntry.ifName.1 DISPLAY STRING- (ascii) sc0
```

Query with SNMPv1, default for HP OpenView snmpget

```
# snmpget -c public 14.32.5.18 ifHCInOctets.1

snmpget Agent reported error with variable #1.
.iso.org.dod.internet.mgmt.mib-2.ifMIB.ifMIBObjects.ifXTable.ifXEntry.
ifHCInOctets.1

SNMP Variable does not exist or access is denied.
```

Same query with SNMPv2C

```
# snmpget -v 2c -c public 14.32.5.18 ifHCInOctets.1

ifMIB.ifMIBObjects.ifXTable.ifXEntry.ifHCInOctets.1 Counter64 622366215
```

Q. Which Cisco devices implement 64-bit SNMP counters, especially for the IF-MIB?

A. These Cisco devices implement 64-bit SNMP counters:

Note: You must be a registered user and you must be logged in in order to visit the Cisco bug ID links and see detailed bug information.

- ◆ Cisco 2500, 2600 routers These routers do not support 64-bit counters.
- ◆ Catalyst 2950 and 3550 Support begins in Cisco IOS Software Release 12.1(11)EA1 since Cisco bug ID CSCdx67611 (registered customers only) and Cisco bug ID CSCdw52807 (registered customers only) .
- ◆ Catalyst 2900XL and 3500XL Support begins in Cisco IOS Software Release 12.0(5)WC3 since Cisco bug ID CSCds45300 (registered customers only) .
- ◆ Catalyst 5000 series Since Cisco IOS Software Release 3.x. On RSM/RSFC, support

begins in Cisco IOS Software Release 12.1(6)E1 since Cisco bug ID CSCds50549 (registered customers only) .

- ◆ Catalyst 5000/6000 ATM modules Since Cisco IOS Software Release 12.0(14)W05(20), refer to Cisco bug ID CSCds07238 (registered customers only) .
- ◆ Catalyst 6000 Gigabit Ethernet WAN OSM Since Cisco IOS Software Release 12.1.12E, refer to Cisco bug ID CSCdw64849 (registered customers only) .
- ◆ Catalyst 6000 series All Cisco IOS software releases. WS-F6K-MSFC and MSM support begins in Cisco IOS Software Release 12.1(8a)E4.
- ◆ Catalyst 8500 series Support begins as of Cisco IOS Software Release 12.0(5)W5(13).
- ◆ Cisco routers 3600, 4000, and higher platforms As of Cisco IOS Software 12.0(1) and Cisco IOS Software Release 12.0(1)T, refer to Cisco bug ID CSCdj93712 (registered customers only) and Cisco bug ID CSCdt58029 (registered customers only) .
- ◆ Frame Relay interfaces As of Cisco IOS Software Release 12.0(17)S and Cisco IOS Software Release 12.2(4)T3, refer to Frame Relay 64-Bit Counters.
- ◆ OC3 ATM interfaces As of Cisco IOS Software Release 12.0(6)T, refer to Cisco bug ID CSCdm45357 (registered customers only) .
- ◆ Tunnel interfaces As of Cisco IOS Software Release 12.0(16)S, refer to Cisco bug ID CSCdt58029 (registered customers only) .

Note: Cisco IOS Software does not support 64-bit counters for interface speeds of less than 20 Mbps. This means that 64-bit counters are not supported on 10 Mb Ethernet ports. Only 100 Mb Fast-Ethernet and other high speed ports support 64-bit counters.

Q. Are ifInOctets and ifOutOctets SNMP counters the same as the show interfaces In/Out counters?

A. Yes, but only when SNMP is enabled from boot time. If you power on a Cisco device, then enable SNMP, the SNMP counters start from 0. They do not automatically pick up their values from the CLI output.

Q. Do the ifInOctets and ifOutOctets counters include framing overhead (Point-to-Point Protocol, High-Level Data Link Control)?

A. Yes.

Q. On an Asynchronous Transfer Mode interface, do the counters include the cell header?

A. Asynchronous Transfer Mode (ATM) counters do not include ATM overhead (cell headers and AAL5 padding).

Q. Why do SNMP counters not return the same number as CLI show commands?

A. An SNMP object defined as a Counter must abide by RFC1155 :

"3.2.3.3. Counter

This application-wide type represents a non-negative integer which monotonically increases until it reaches a maximum value, when it wraps around and starts increasing again from zero. This memo specifies a maximum value of $2^{32}-1$ (4294967295 decimal) for counters."

There are no methods to reset an SNMP counter to zero without the need to reload the device.

The counter output from a CLI **show** command can be reset on interfaces since the SNMP restrictions are not present.

The original interface counters defined in MIB-2 are 32-bit counters. For a 10 Mbps interface, a 32-bit counter could theoretically wrap in 57 minutes. It is easy to avoid discontinuities with such a long period. But for 100 Mbps, the minimum theoretical wrap time is 5.7 minutes. For 1 Gbps interfaces, it falls to 34 seconds. Granted these times are for transmission of back-to-back full-sized packets, a theoretical ideal. Even so, the higher the interface speed, the harder it becomes to avoid missing a counter wrap. As a solution to this problem, SNMPv2 SMI defined a new object type, counter64, for 64-bit counters. Therefore, there are several new 64-bit counters defined in the extension interface table (ifxTable) defined in RFC 1573 (later superseded by RFC 2233). These are from the IF-MIB-V1SMI.my (registered customers only) .

ifHCInOctets (.1.3.6.1.2.1.31.1.1.6)	ifHCOutOctets (.1.3.6.1.2.1.31.1.1.10)
ifHCInUcastPkts (.1.3.6.1.2.1.31.1.1.7)	ifHCOutUcastPkts (.1.3.6.1.2.1.31.1.1.11)
ifHCInMulticastPkts (.1.3.6.1.2.1.31.1.1.8)	ifHCOutMulticastPkts (.1.3.6.1.2.1.31.1.1.12)
ifHCInBroadcastPkts (.1.3.6.1.2.1.31.1.1.9)	ifHCOutBroadcastPkts (.1.3.6.1.2.1.31.1.1.13)

Although basic support for 64-bit counters was written into Cisco IOS Software Release 11.3, which starts from Cisco IOS Software Release 12.0, only ifHCInOctets (.1.3.6.1.2.1.31.1.1.6) and ifHCOutOctets (.1.3.6.1.2.1.31.1.1.10) have been implemented for ATM LANE LEC sub-interfaces only. For Catalyst workgroup switches, 64-bit counter support has been implemented in version 3.1.

Note: You must use SNMPv2c or SNMPv3 protocol in order to retrieve any counter 64 objects.

SNMP Counters and show Command Equivalent Questions

Q. What do Cisco routers do for the following SNMP MIB variables: ifInOctets, ifInUcastPkts, ifInNUcastPkts, ifInDiscards, ifInErrors, ifInUnknownProtos, ifOutOctets, ifOutUcastPkts, ifOutNUcastPkts, ifOutDiscards, ifOutErrors, and ifOutQLen?

A. See this table for details. These are from the RFC1213-MIB (registered customers only) .

ifInNUcastPkts (.1.3.6.1.2.1.2.2.1.12)	These are counts of inbound broadcast and multicast packets.
ifInDiscards (.1.3.6.1.2.1.2.2.1.13)	These are counted as no buffers as reflected in the show interfaces command.

ifInErrors (.1.3.6.1.2.1.2.2.1.14)	These are counts of all input errors as reflected in the show interfaces command.
ifInUnknownProtos (.1.3.6.1.2.1.2.2.1.15)	These are counted as unclassified errors.
ifOutOctets (.1.3.6.1.2.1.2.2.1.16)	These are counts of the number of bytes output by the interface as shown in the show interfaces command.
ifOutUcastPkts (.1.3.6.1.2.1.2.2.1.17)	These are counts of outbound broadcast and multicast packets.
ifOutDiscards (.1.3.6.1.2.1.2.2.1.19)	These are counted as output drops as shown in the show interfaces command.
ifOutErrors (.1.3.6.1.2.1.2.2.1.20)	These are counted as output errors as shown in the show interfaces command.
ifOutQLen (.1.3.6.1.2.1.2.2.1.21)	This is the number of packets allowed to be on the output queue as shown in the show interfaces command.

The variables previously listed that do not say they appear in **show interfaces** are not available anywhere other than SNMP.

Examples

A. This example uses a 3640 that runs with Cisco IOS Software Release 12.2(2)T1. The Read-Only (RO) Community String used is public and the Read-Write (RW) Community String used is private. Refer to How to Configure SNMP Community Strings for more information on how to configure SNMP Community Strings on devices.

This output is typical of the **show ip interface brief** command executed in enable mode:

```
3600#show ip interface brief
Interface  IP-Address      OK? Method Status  Prol
BRI0/0    unassigned      YES NVRAM  administratively down dow
FastEthernet0/0  172.16.99.20   YES NVRAM  up      up
Serial0/0    unassigned      YES NVRAM  down    dow
Serial0/0.1  unassigned      YES unset  down    dow
BRI0/0:1    unassigned      YES unset  administratively down dow
BRI0/0:2    unassigned      YES unset  administratively down dow
Serial0/1    unassigned      YES NVRAM  administratively down dow
ATM1/0      unassigned      YES NVRAM  down    dow
ATM1/0.109  10.164.0.46    YES NVRAM  down    dow
Virtual-Template1  99.99.99.99   YES NVRAM  down    dow
Loopback0   10.1.10.1       YES NVRAM  up      up
Loopback1   unassigned      YES NVRAM  up      up
Loopback101 3.3.3.3        YES NVRAM  administratively down dow
Loopback200 4.4.4.14       YES NVRAM  administratively down dow
```

This output is the MIB Object **ifDescr** (.1.3.6.1.2.1.2.2.1.2) for the previous router, which is a text string that contains information about the interface. This gives the interface name and description as obtained, which uses the previous CLI command output. **ifName** (.1.3.6.1.2.1.31.1.1.1.1) can also be used but **ifDescr** gives the interface description along with the name, where **ifName** only gives the interface name.

```
snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.2
interfaces.ifTable.ifEntry.ifDescr.1 = ATM1/0
interfaces.ifTable.ifEntry.ifDescr.2 = BRI0/0
interfaces.ifTable.ifEntry.ifDescr.3 = FastEthernet0/0
interfaces.ifTable.ifEntry.ifDescr.4 = Serial0/0
interfaces.ifTable.ifEntry.ifDescr.5 = BRI0/0:1
interfaces.ifTable.ifEntry.ifDescr.6 = BRI0/0:2
interfaces.ifTable.ifEntry.ifDescr.7 = Serial0/1
interfaces.ifTable.ifEntry.ifDescr.8 = Null0
interfaces.ifTable.ifEntry.ifDescr.10 = Foreign Exchange Office 2/0/0
interfaces.ifTable.ifEntry.ifDescr.11 = Foreign Exchange Office 2/0/1
interfaces.ifTable.ifEntry.ifDescr.12 = recEive And transMit 3/0/0
interfaces.ifTable.ifEntry.ifDescr.13 = recEive And transMit 3/0/1
interfaces.ifTable.ifEntry.ifDescr.14 = Loopback0
interfaces.ifTable.ifEntry.ifDescr.15 = Loopback1
interfaces.ifTable.ifEntry.ifDescr.16 = Loopback101
interfaces.ifTable.ifEntry.ifDescr.17 = Loopback200
interfaces.ifTable.ifEntry.ifDescr.18 = Loopback201
interfaces.ifTable.ifEntry.ifDescr.19 = Serial0/0.1
interfaces.ifTable.ifEntry.ifDescr.20 = ATM1/0.109-atm subif
interfaces.ifTable.ifEntry.ifDescr.21 = ATM1/0.109-aal5 layer
interfaces.ifTable.ifEntry.ifDescr.22 = Virtual-Templatel
interfaces.ifTable.ifEntry.ifDescr.23 = Voice Encapsulation (POTS) Peer: 1
interfaces.ifTable.ifEntry.ifDescr.24 = Voice Over IP Peer: 2
interfaces.ifTable.ifEntry.ifDescr.25 = Voice Encapsulation (POTS) Peer: 111
interfaces.ifTable.ifEntry.ifDescr.26 = Voice Over IP Peer: 222
interfaces.ifTable.ifEntry.ifDescr.27 = Voice Over IP Peer: 1234
interfaces.ifTable.ifEntry.ifDescr.28 = Voice Over IP Peer: 300000
interfaces.ifTable.ifEntry.ifDescr.29 = Voice Over FR Peer: 3
interfaces.ifTable.ifEntry.ifDescr.30 = Voice Over IP Peer: 99
interfaces.ifTable.ifEntry.ifDescr.31 = Voice Encapsulation (POTS) Peer: 9
interfaces.ifTable.ifEntry.ifDescr.32 = BRI0/0-Physical
interfaces.ifTable.ifEntry.ifDescr.33 = BRI0/0-Signaling
interfaces.ifTable.ifEntry.ifDescr.34 = BRI0/0:1-Bearer Channel
interfaces.ifTable.ifEntry.ifDescr.35 = BRI0/0:2-Bearer Channel
```

1. ifInDiscards (.1.3.6.1.2.1.2.2.1.13):

```
snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.13
interfaces.ifTable.ifEntry.ifInDiscards.1 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.2 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.3 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.4 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.5 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.6 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.7 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.8 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.10 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.11 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.12 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.13 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.14 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.15 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.16 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.17 = Counter32: 0
```

```

interfaces.ifTable.ifEntry.ifInDiscards.18 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.19 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.20 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.21 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.22 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.23 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.24 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.25 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.26 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.27 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.28 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.29 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.30 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.31 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.32 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.33 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.34 = Counter32: 0
interfaces.ifTable.ifEntry.ifInDiscards.35 = Counter32: 0

```

The **ifInDiscards** is zero for all the interfaces of this router. If you compare this with the CLI result of the **show interfaces fastEthernet 0/0** command, this confirms the result:

```

3600#show interfaces fastEthernet 0/0
FastEthernet0/0 is up, line protocol is up
  Hardware is AmdFE, address is 0001.42b4.fe81 (bia 0001.42b4.fe81)
  Description: testme
  Internet address is 172.16.99.20/24
  MTU 1500 bytes, BW 100000 Kbit, DLY 100 usec,
    reliability 255/255, txload 1/255, rxload 1/255
  Encapsulation ARPA, loopback not set
  Keepalive set (10 sec)
  Full-duplex, 100Mb/s, 100BaseTX/FX
  ARP type: ARPA, ARP Timeout 04:00:00
  Last input 00:00:00, output 00:00:00, output hang never
  Last clearing of "show interface" counters never
  Queueing strategy: fifo
  Output queue 0/40, 0 drops; input queue 0/75, 323 drops
  5 minute input rate 1000 bits/sec, 2 packets/sec
  5 minute output rate 0 bits/sec, 0 packets/sec
    1767411 packets input, 178272010 bytes
      Received 1161500 broadcasts, 0 runts, 0 giants, 0 throttles
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
    0 watchdog
    0 input packets with dribble condition detected
7146925 packets output, 765049281 bytes, 0 underruns(0/0/0)
  0 output errors, 0 collisions, 1 interface resets
  0 babbles, 0 late collision, 461 deferred
  0 lost carrier, 0 no carrier
  0 output buffer failures, 0 output buffers swapped out

```

2. **ifInErrors** (.1.3.6.1.2.1.2.2.1.14):

```

snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.14

interfaces.ifTable.ifEntry.ifInErrors.1 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.2 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.3 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.4 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.5 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.6 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.7 = Counter32: 1
interfaces.ifTable.ifEntry.ifInErrors.8 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.10 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.11 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.12 = Counter32: 0

```

```

interfaces.ifTable.ifEntry.ifInErrors.13 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.14 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.15 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.16 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.17 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.18 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.19 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.20 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.21 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.22 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.23 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.24 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.25 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.26 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.27 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.28 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.29 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.30 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.31 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.32 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.33 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.34 = Counter32: 0
interfaces.ifTable.ifEntry.ifInErrors.35 = Counter32: 0

```

This output shows that there is only one input error for the interface

interfaces.ifTable.ifEntry.ifInErrors.7 = Counter32: 1.

In order to determine which interface this is, compare it with the output of **ifDescr** above, which shows that this is from **interfaces.ifTable.ifEntry.ifDescr.7 = Serial0/1**. Now execute the **show interfaces serial 0/1** command in enable mode in order to verify the previous result:

```

3600#show interfaces serial 0/1
Serial0/1 is administratively down, line protocol is down
  Hardware is DSCC4 Serial
  Description: atm-dxi test
  MTU 1500 bytes, BW 2048 Kbit, DLY 20000 usec,
    reliability 255/255, txload 1/255, rxload 1/255
  Encapsulation ATM-DXI, loopback not set
  Keepalive not set
  Last input never, output never, output hang never
  Last clearing of "show interface" counters 1w1d
  Queueing strategy: fifo
  Output queue 0/40, 0 drops; input queue 0/75, 0 drops
  5 minute input rate 0 bits/sec, 0 packets/sec
  5 minute output rate 0 bits/sec, 0 packets/sec
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
    1 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 1 abort
    0 packets output, 0 bytes, 0 underruns
    0 output errors, 0 collisions, 0 interface resets
    0 output buffer failures, 0 output buffers swapped out
    0 carrier transitions
  DCD=down DSR=down DTR=down RTS=down CTS=down

```

3. ifOutOctets (.1.3.6.1.2.1.2.2.1.16):

```

snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.16

interfaces.ifTable.ifEntry.ifOutOctets.1 = Counter32: 98
interfaces.ifTable.ifEntry.ifOutOctets.2 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.3 = Counter32: 765470674
interfaces.ifTable.ifEntry.ifOutOctets.4 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.5 = Counter32: 0

```

```

interfaces.ifTable.ifEntry.ifOutOctets.6 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.7 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.8 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.10 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.11 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.12 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.13 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.14 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.15 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.16 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.17 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.18 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.19 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.20 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.21 = Counter32: 98
interfaces.ifTable.ifEntry.ifOutOctets.22 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.23 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.24 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.25 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.26 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.27 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.28 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.29 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.30 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.31 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.32 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.33 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.34 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutOctets.35 = Counter32: 0

```

If you compare the previous result with the output of the **ifDescr**, this indicates:

- ◇ **interfaces.ifTable.ifEntry.ifOutOctets.1 = Counter32: 98** corresponds with **interfaces.ifTable.ifEntry.ifDescr.1 = ATM1/0**
- ◇ **interfaces.ifTable.ifEntry.ifOutOctets.3 = Counter32: 765470674** corresponds with **interfaces.ifTable.ifEntry.ifDescr.3 = FastEthernet0/0**
- ◇ **interfaces.ifTable.ifEntry.ifOutOctets.21 = Counter32: 98** corresponds with **interfaces.ifTable.ifEntry.ifDescr.21 = ATM1/0.109–aal5 layer**

This is the output of the CLI **show interfaces** command for each of the previous interfaces executed in enable mode:

```

3600#show interfaces atM 1/0
  ATM1/0 is down, line protocol is down
  Hardware is RS8234 ATMOC3
  MTU 4470 bytes, sub MTU 4470, BW 155000 Kbit, DLY 80 usec,
    reliability 5/255, txload 1/255, rxload 1/255
  Encapsulation ATM, loopback not set
  Encapsulation(s): AAL5
  1024 maximum active VCs, 1 current VCCs
  VC idle disconnect time: 300 seconds
  Last input never, output lwd, output hang never
  Last clearing of "show interface" counters never
  Input queue: 0/75/0/0 (size/max/drops/flushes); Total output drops: 0
  Queueing strategy: None
  5 minute input rate 0 bits/sec, 0 packets/sec
  5 minute output rate 0 bits/sec, 0 packets/sec
    0 packets input, 0 bytes, 0 no buffer
    Received 0 broadcasts, 0 runts, 0 giants, 0 throttles
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored, 0 abort
    2 packets output, 98 bytes, 0 underruns
    0 output errors, 0 collisions, 2 interface resets
    0 output buffer failures, 0 output buffers swapped out

3600#show interfaces fastEthernet 0/0

```

```

FastEthernet0/0 is up, line protocol is up
  Hardware is AmdFE, address is 0001.42b4.fe81 (bia 0001.42b4.fe81)
  Description: testme
  Internet address is 172.16.99.20/24
  MTU 1500 bytes, BW 100000 Kbit, DLY 100 usec,
    reliability 255/255, txload 1/255, rxload 1/255
  Encapsulation ARPA, loopback not set
  Keepalive set (10 sec)
  Full-duplex, 100Mb/s, 100BaseTX/FX
  ARP type: ARPA, ARP Timeout 04:00:00
  Last input 00:00:00, output 00:00:00, output hang never
  Last clearing of "show interface" counters never
  Queueing strategy: fifo
  Output queue 0/40, 0 drops; input queue 0/75, 323 drops
  5 minute input rate 2000 bits/sec, 3 packets/sec
  5 minute output rate 1000 bits/sec, 1 packets/sec
    1772214 packets input, 178767841 bytes
      Received 1164210 broadcasts, 0 runts, 0 giants, 0 throttles
      0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
0 watchdog
  0 input packets with dribble condition detected
  7149179 packets output, 765450524 bytes, 0 underruns(0/0/0)
  0 output errors, 0 collisions, 1 interface resets
  0 babbles, 0 late collision, 461 deferred
  0 lost carrier, 0 no carrier
  0 output buffer failures, 0 output buffers swapped out

```

The output of the **ifOutOctets** does not match the CLI output for the **show interfaces FastEthernet 0/0** command, but it is similar. This is because there might be a delay when the interfaces are polled and when the CLI command is executed.

```

3600#show interfaces atM 1/0.109
ATM1/0.109 is down, line protocol is down
  Hardware is RS8234 ATMOC3
  Description: pvc
  Internet address is 10.164.0.46/30
  MTU 4470 bytes, BW 2250 Kbit, DLY 80 usec,
    reliability 5/255, txload 1/255, rxload 1/255
  Encapsulation ATM
  0 packets input, 0 bytes
  2 packets output, 98 bytes
  0 OAM cells input, 77093 OAM cells output
  AAL5 CRC errors : 0
  AAL5 SAR Timeouts : 0
  AAL5 Oversized SDUs : 0
  AAL5 length violation : 0
  AAL5 CPI Error : 0

```

4. ifOutDiscards (.1.3.6.1.2.1.2.2.1.19):

```

snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.19

interfaces.ifTable.ifEntry.ifOutDiscards.1 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.2 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.3 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.4 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.5 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.6 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.7 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.8 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.10 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.11 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.12 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.13 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.14 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.15 = Counter32: 0

```

```

interfaces.ifTable.ifEntry.ifOutDiscards.16 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.17 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.18 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.19 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.20 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.21 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.22 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.23 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.24 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.25 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.26 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.27 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.28 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.29 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.30 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.31 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.32 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.33 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.34 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutDiscards.35 = Counter32: 0

```

The **ifOutDiscards** is zero for all the interfaces. With the **show interfaces fastEthernet 0/0** command as an example, this command produces this result:

```

3600#show interfaces fastEthernet 0/0
FastEthernet0/0 is up, line protocol is up
Hardware is AmdFE, address is 0001.42b4.fe81 (bia 0001.42b4.fe81)
Description: testme
Internet address is 172.16.99.20/24
MTU 1500 bytes, BW 100000 Kbit, DLY 100 usec,
    reliability 255/255, txload 1/255, rxload 1/255
Encapsulation ARPA, loopback not set
Keepalive set (10 sec)
Full-duplex, 100Mb/s, 100BaseTX/FX
ARP type: ARPA, ARP Timeout 04:00:00
Last input 00:00:00, output 00:00:00, output hang never
Last clearing of "show interface" counters never
Queueing strategy: fifo
Output queue 0/40, 0 drops; input queue 0/75, 323 drops
5 minute input rate 1000 bits/sec, 2 packets/sec
5 minute output rate 1000 bits/sec, 1 packets/sec
    1774581 packets input, 179005552 bytes
    Received 1165620 broadcasts, 0 runts, 0 giants, 0 throttles
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
    0 watchdog
    0 input packets with dribble condition detected
    7150259 packets output, 765645035 bytes, 0 underruns(0/0/0)
    0 output errors, 0 collisions, 1 interface resets
    0 babbles, 0 late collision, 461 deferred
    0 lost carrier, 0 no carrier
    0 output buffer failures, 0 output buffers swapped out

```

5. **ifOutErrors** (.1.3.6.1.2.1.2.2.1.20):

```

snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.20

interfaces.ifTable.ifEntry.ifOutErrors.1 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.2 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.3 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.4 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.5 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.6 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.7 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.8 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.10 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.11 = Counter32: 0

```

```

interfaces.ifTable.ifEntry.ifOutErrors.12 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.13 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.14 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.15 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.16 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.17 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.18 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.19 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.20 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.21 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.22 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.23 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.24 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.25 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.26 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.27 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.28 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.29 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.30 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.31 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.32 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.33 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.34 = Counter32: 0
interfaces.ifTable.ifEntry.ifOutErrors.35 = Counter32: 0

```

The **ifOutErrors** is zero for all the interfaces. With the **show interfaces fastEthernet 0/0** command as an example, this command produces this result:

```

3600#show interfaces fastEthernet 0/0
FastEthernet0/0 is up, line protocol is up
  Hardware is AmdFE, address is 0001.42b4.fe81 (bia 0001.42b4.fe81)
  Description: testme
  Internet address is 172.16.99.20/24
  MTU 1500 bytes, BW 100000 Kbit, DLY 100 usec,
    reliability 255/255, txload 1/255, rxload 1/255
  Encapsulation ARPA, loopback not set
  Keepalive set (10 sec)
  Full-duplex, 100Mb/s, 100BaseTX/FX
  ARP type: ARPA, ARP Timeout 04:00:00
  Last input 00:00:00, output 00:00:00, output hang never
  Last clearing of "show interface" counters never
  Queueing strategy: fifo
  Output queue 0/40, 0 drops; input queue 0/75, 323 drops
  5 minute input rate 0 bits/sec, 1 packets/sec
  5 minute output rate 0 bits/sec, 0 packets/sec
    1776187 packets input, 179154616 bytes
    Received 1166778 broadcasts, 0 runts, 0 giants, 0 throttles
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
    0 watchdog
    0 input packets with dribble condition detected
  7150781 packets output, 765744231 bytes, 0 underruns(0/0/0)
  0 output errors, 0 collisions, 1 interface resets
  0 babbles, 0 late collision, 461 deferred
  0 lost carrier, 0 no carrier
  0 output buffer failures, 0 output buffers swapped out

```

6. **ifOutQLen** (.1.3.6.1.2.1.2.2.1.21):

```

snmpwalk 172.16.99.20 public .1.3.6.1.2.1.2.2.1.21

interfaces.ifTable.ifEntry.ifOutQLen.1 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.2 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.3 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.4 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.5 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.6 = Gauge32: 0

```

```

interfaces.ifTable.ifEntry.ifOutQLen.7 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.8 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.10 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.11 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.12 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.13 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.14 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.15 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.16 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.17 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.18 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.19 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.20 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.21 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.22 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.23 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.24 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.25 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.26 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.27 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.28 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.29 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.30 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.31 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.32 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.33 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.34 = Gauge32: 0
interfaces.ifTable.ifEntry.ifOutQLen.35 = Gauge32: 0

```

The **ifOutQLen** is zero for all the interfaces. With the **show interfaces fastEthernet 0/0** command as an example:

```

3600#show interfaces fastEthernet 0/0
FastEthernet0/0 is up, line protocol is up
  Hardware is AmdFE, address is 0001.42b4.fe81 (bia 0001.42b4.fe81)
  Description: testme
  Internet address is 172.16.99.20/24
  MTU 1500 bytes, BW 100000 Kbit, DLY 100 usec,
    reliability 255/255, txload 1/255, rxload 1/255
  Encapsulation ARPA, loopback not set
  Keepalive set (10 sec)
  Full-duplex, 100Mb/s, 100BaseTX/FX
  ARP type: ARPA, ARP Timeout 04:00:00
  Last input 00:00:00, output 00:00:00, output hang never
  Last clearing of "show interface" counters never
  Queueing strategy: fifo
  Output queue 0/40, 0 drops; input queue 0/75, 323 drops
  5 minute input rate 0 bits/sec, 1 packets/sec
  5 minute output rate 0 bits/sec, 0 packets/sec
    1776912 packets input, 179225431 bytes
    Received 1167240 broadcasts, 0 runts, 0 giants, 0 throttles
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
    0 watchdog
    0 input packets with dribble condition detected
  7151102 packets output, 765796341 bytes, 0 underruns(0/0/0)
  0 output errors, 0 collisions, 1 interface resets
  0 babbles, 0 late collision, 461 deferred
  0 lost carrier, 0 no carrier
  0 output buffer failures, 0 output buffers swapped out

```

Q. What is the relationship between the show interfaces statements no buffers and input queue drops? Why do the inDiscards of SNMP give no buffers counts and not input queue drops, while the

outDiscards of SNMP do give output queue drops?

A. The locIfInputQueueDrops/ifInDiscards work differently than locIfOutputQueueDrops/ifOutDiscards. The ifInDiscards counts the number of packets that are thrown away for lack of a system resource such as a buffer. This is generally a subset of the locIfInputQueueDrops. You often see locIfInputQueueDrops = ifInDiscards. But, locIfInputQueueDrops also counts the number of packets dropped because they hit the input queue limit. So generally, you see locIfInputQueueDrops > ifInDiscards.

Summary

locIfInputQueueDrops = Queue Limit Drops + No Buffer Drops
ifInDiscards = No Buffer Drops (and is a subset of locIfInputQueueDrops)

The locIfOutputQueueDrops and ifOutDiscards are always equal when they count the same events. Those events hit the output queue limit, and do not have a hardware tx buffer when a packet is fastswitched from one interface to another. The OIDs of the previous MIB Objects are these:

From OLD-CISCO-INTERFACES-MIB (registered customers only)	From RFC1213-MIB (registered customers only)
locIfInputQueueDrops = .1.3.6.1.4.1.9.2.2.1.1.26	ifInDiscards = .1.3.6.1.2.1.2.2.1.13
locIfOutputQueueDrops = .1.3.6.1.4.1.9.2.2.1.1.27	ifOutDiscards = .1.3.6.1.2.1.2.2.1.19

Q. Can I poll no buffers on a router?

A. Yes. You can poll for ifInDiscards in order to poll no buffers.

Q. How do I poll queue limit drops on a router?

A. With the use of SNMP, there is no way for the **show interfaces** command to break out the individual elements that go into the output drops.

Consider this new information about what goes into the output drops counter:

Input drops = Queue limit drops + Throttling drops + SMT queue full drops + RSRB drops + no buffer drops

In addition, SNMP counters are never cleared, even if the interfaces are cleared.

NetPro Discussion Forums – Featured Conversations

Networking Professionals Connection is a forum for networking professionals to share questions, suggestions, and information about networking solutions, products, and technologies. The featured links are some of the most recent conversations available in this technology.

Network Infrastructure: Network Management
--

Virtual Private Networks: Network and Policy Management

Related Information

- [IP Application Services Technical Tips](#)
- [Technical Support & Documentation – Cisco Systems](#)

[Contacts & Feedback](#) | [Help](#) | [Site Map](#)

© 2007 – 2008 Cisco Systems, Inc. All rights reserved. [Terms & Conditions](#) | [Privacy Statement](#) | [Cookie Policy](#) | [Trademarks of Cisco Systems, Inc.](#)

Updated: Aug 24, 2007

Document ID: 26007
