



N Commands

- [name-lookup](#), on page 4
- [name-lookup](#), on page 5
- [name](#), on page 6
- [name](#), on page 7
- [name](#), on page 8
- [name](#), on page 9
- [name](#), on page 10
- [nat destination](#), on page 11
- [nbm bandwidth unicast](#), on page 12
- [nbm external-link](#), on page 13
- [nbm flow-definition](#), on page 14
- [nbm flow-definition](#), on page 15
- [nbm flow-policy](#), on page 16
- [nbm flow-policy](#), on page 17
- [nbm flow asm range](#), on page 18
- [nbm flow asm range](#), on page 19
- [nbm flow bandwidth immediate-recovery](#), on page 20
- [nbm flow bandwidth immediate-recovery](#), on page 21
- [nbm flow bandwidth kbps mbps gbps](#), on page 22
- [nbm flow bandwidth kbps mbps gbps](#), on page 23
- [nbm flow dscp](#), on page 24
- [nbm flow dscp](#), on page 25
- [nbm flow policer](#), on page 26
- [nbm flow policer](#), on page 27
- [nbm flow reserve-bandwidth receiver-only](#), on page 28
- [nbm flow reserve-bandwidth receiver-only](#), on page 29
- [nbm host-policy](#), on page 30
- [nbm host-policy](#), on page 31
- [nbm mode pim](#), on page 32
- [nbm reserve unicast fabric bandwidth](#), on page 33
- [nbm vrf](#), on page 34
- [nbm vrf default](#), on page 35
- [negotiate auto](#), on page 36

- negotiate auto 25000, on page 37
- neighbor-down fib-accelerate, on page 38
- neighbor, on page 39
- neighbor, on page 40
- neighbor, on page 41
- neighbor, on page 42
- neighbor, on page 43
- neighbor, on page 44
- neighbor, on page 45
- nemo config address port interval, on page 46
- net, on page 47
- net, on page 48
- network, on page 49
- network, on page 50
- next-hop-self, on page 51
- next-hop-third-party, on page 52
- nexthop route-map, on page 53
- nexthop suppress-default-resolution, on page 54
- nexthop trigger-delay critical non-critical, on page 55
- ngoam authentication-key, on page 56
- ngoam connect-check, on page 57
- ngoam install acl, on page 58
- ngoam loop-detection, on page 59
- ngoam loop-detection bringup vlan, on page 60
- ngoam loop-detection probe vlan, on page 61
- ngoam profile, on page 62
- ngoam xconnect hb-interval, on page 63
- no-more, on page 64
- no, on page 65
- no, on page 66
- no, on page 67
- no, on page 68
- no, on page 69
- no, on page 70
- no, on page 73
- no, on page 78
- no, on page 82
- no, on page 85
- no, on page 88
- no, on page 91
- no, on page 95
- no, on page 99
- no, on page 102
- no, on page 105
- no, on page 106
- no, on page 107

- no, on page 108
- no, on page 110
- node ip, on page 111
- node ip, on page 112
- npv auto-load-balance disruptive, on page 113
- npv traffic-map server-interface external-interface, on page 114
- nsf await-redist-proto-convergence, on page 115
- ntp access-group, on page 116
- ntp access-group match-all, on page 117
- ntp allow private, on page 118
- ntp authenticate, on page 119
- ntp authentication-key md5, on page 120
- ntp logging, on page 121
- ntp master, on page 122
- ntp passive, on page 123
- ntp peer, on page 124
- ntp server, on page 125
- ntp source-interface, on page 126
- ntp source, on page 127
- ntp sync-retry, on page 128
- ntp trusted-key, on page 129
- nv overlay evpn, on page 130
- nve interface remap-replication-servers, on page 131
- nve interface replication-server up, on page 132
- nve oam mode draft-pang, on page 133
- nwwn, on page 134
- nwwn vsan, on page 135
- nxapi certificate httpskey keyfile, on page 136
- nxapi client certificate authentication, on page 137
- nxapi http port, on page 138
- nxapi idle-timeout, on page 139
- nxapi ssl ciphers weak, on page 140
- nxapi ssl protocols, on page 141
- nxapi use-vrf management default, on page 142
- nx sdk profile, on page 143
- nx sdk remote port, on page 144
- nx sdk service-name, on page 145

name-lookup

[no] name-lookup

Syntax Description

no	(Optional) Negate a command or set its defaults
name-lookup	Enable Name Lookup for OSPFv3 Neighbors

Command Mode

- /exec/configure/router-ospf3 /exec/configure/router-ospf3/vrf

name-lookup

[no] name-lookup

Syntax Description

no	(Optional) Negate a command or set its defaults
name-lookup	Display OSPF router ids as DNS names

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

name

```
{ { name-server0 | name-server1 } <ip-addr> | no { name-server0 | name-server1 } [ <ip-addr> ] }
```

Syntax Description

no	Negate a command or set its defaults
name-server0	Name server IP Address
name-server1	Name server IP Address
<i>ip-addr</i>	Name server IP Address

Command Mode

- /exec/configure/app-hosting-appid

name

name <name-val> | no name [<name-val>]

Syntax Description

no	Negate a command or set its defaults
name	Set configuration name
<i>name-val</i>	Configuration name

Command Mode

- /exec/configure/spanning-tree/mst/configuration

name

name [<name>] | no name

Syntax Description

no	Negate a command or set its defaults
name	Redundancy name string
<i>name</i>	(Optional) name string

Command Mode

- /exec/configure/if-eth-any/hsrp_ipv4 /exec/configure/if-eth-any/hsrp_ipv6

name

name <vlan-name> | no name

Syntax Description

no	Negate a command or set its defaults
name	Ascii name of the VLAN
<i>vlan-name</i>	The ascii name for the VLAN

Command Mode

- /exec/configure/vlan

name

```
{ { name-server0-ipv6 | name-server1-ipv6 } <ipv6-addr> | no { name-server0-ipv6 | name-server1-ipv6 } [ <ipv6-addr> ] }
```

Syntax Description

no	Negate a command or set its defaults
name-server0-ipv6	Name server IPv6 Address
name-server1-ipv6	Name server IPv6 Address

Command Mode

- /exec/configure/app-hosting-appid

nat destination

{ nat destination } | { no nat destination }

Syntax Description

no	Negate a command or set its defaults
nat	Network Address Translation
destination	Destination NAT

Command Mode

- /exec/configure/itd

nbm bandwidth unicast

nbm bandwidth unicast

`nbm bandwidth unicast <percentage> | no nbm bandwidth unicast`

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
bandwidth	percentage of bandwidth set aside other than multicast
unicast	unicast
<i>percentage</i>	percentage value. 0 means no reservation for unicast on this link

Command Mode

- /exec/configure/if-igp

nbm external-link

[no] nbm external-link

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
external-link	link connected to external router. Configuring this will flap the interface

Command Mode

- /exec/configure/if-igp

nbm flow-definition

[no] nbm flow-definition <group> [<source>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-definition	Define a multicast flow
<i>group</i>	Multicast Group Address
<i>source</i>	(Optional) Source IP address to use

Command Mode

- /exec/configure

nbm flow-definition

[no] nbm flow-definition <group> [<source>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-definition	Define a multicast flow
<i>group</i>	Multicast Group Address
<i>source</i>	(Optional) Source IP address to use

Command Mode

- /exec/configure/nbm-vrf

nbm flow-policy

[no] nbm flow-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-policy	Flow Policy Characteristics

Command Mode

- /exec/configure

nbm flow-policy

[no] nbm flow-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-policy	Flow Policy Characteristics

Command Mode

- /exec/configure/nbm-vrf

nbm flow asm range

nbm flow asm range

[no] nbm flow asm range <group> +

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
asm	Any-Source Multicast (ASM) groups
range	Configure explicit group ranges
<i>group</i>	List of group range prefixes

Command Mode

- /exec/configure/nbm-vrf

nbm flow asm range

[no] nbm flow asm range <group> +

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
asm	Any-Source Multicast (ASM) groups
range	Configure explicit group ranges
<i>group</i>	List of group range prefixes

Command Mode

- /exec/configure

nbm flow bandwidth immediate-recovery

nbm flow bandwidth immediate-recovery

[no] nbm flow bandwidth immediate-recovery

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
immediate-recovery	Free up used BW immediately on last OIF removal

Command Mode

- /exec/configure/nbm-vrf

nbm flow bandwidth immediate-recovery

[no] nbm flow bandwidth immediate-recovery

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
immediate-recovery	Free up used BW immediately on last OIF removal

Command Mode

- /exec/configure

nbm flow bandwidth kbps mbps gbps

```
{ nbm flow bandwidth { <val_kbps> kbps | <val_mbps> mbps | <val_gbps> gbps } } | { no nbm flow bandwidth }
```

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
<i>val_kbps</i>	Per Flow Bandwidth in Kbps
kbps	Bandwidth value in Kbps
<i>val_mbps</i>	Per Flow Bandwidth in Mbps
mbps	Bandwidth value in Mbps
<i>val_gbps</i>	Per Flow Bandwidth in Gbps
gbps	Bandwidth value in Gbps

Command Mode

- /exec/configure

nbm flow bandwidth kbps mbps gbps

{ nbm flow bandwidth { <val_kbps> kbps | <val_mbps> mbps | <val_gbps> gbps } } | { no nbm flow bandwidth }

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
<i>val_kbps</i>	Per Flow Bandwidth in Kbps
kbps	Bandwidth value in Kbps
<i>val_mbps</i>	Per Flow Bandwidth in Mbps
mbps	Bandwidth value in Mbps
<i>val_gbps</i>	Per Flow Bandwidth in Gbps
gbps	Bandwidth value in Gbps

Command Mode

- /exec/configure/nbm-vrf

nbm flow dscp

nbm flow dscp

{ nbm flow dscp <val_dscp> } | { no nbm flow dscp }

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
dscp	DSCP for the flow
<i>val_dscp</i>	Integer value

Command Mode

- /exec/configure

nbm flow dscp

{ nbm flow dscp <val_dscp> } | { no nbm flow dscp }

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
dscp	DSCP for the flow
<i>val_dscp</i>	Integer value

Command Mode

- /exec/configure/nbm-vrf

nbm flow policer

[no] nbm flow policer

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
policer	Flow rate limiter installed in hardware

Command Mode

- /exec/configure

nbm flow policer

[no] nbm flow policer

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
policer	Flow rate limiter installed in hardware

Command Mode

- /exec/configure/nbm-vrf

nbm flow reserve-bandwidth receiver-only

nbm flow reserve-bandwidth receiver-only

[no] nbm flow reserve-bandwidth receiver-only

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
reserve-bandwidth	Reserve bandwidth
receiver-only	Configure explicit group ranges to restrict reserve bandwidth on receiver only

Command Mode

- /exec/configure

nbm flow reserve-bandwidth receiver-only

[no] nbm flow reserve-bandwidth receiver-only

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
reserve-bandwidth	Reserve bandwidth
receiver-only	Configure explicit group ranges to restrict reserve bandwidth on receiver only

Command Mode

- /exec/configure/nbm-vrf

nbm host-policy

[no] nbm host-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
host-policy	NBM SW Host Admission Policy

Command Mode

- /exec/configure/nbm-vrf

nbm host-policy

[no] nbm host-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
host-policy	NBM SW Host Admission Policy

Command Mode

- /exec/configure

nbm mode pim

nbm mode pim

nbm mode { pim-active | pim-passive } | no nbm mode [pim-active | pim-passive] [__readonly__ <output>]

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
mode	Set pmn mode
pim-active	Bandwidth engine running in fabric
pim-passive	API driven flow stitching
__readonly__	(Optional)
<i>output</i>	(Optional)

Command Mode

- /exec/configure /exec/configure/nbm-vrf

nbm reserve unicast fabric bandwidth

nbm reserve unicast fabric bandwidth <percentage> | no nbm reserve unicast fabric bandwidth

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
reserve	reserve bandwidth
unicast	unicast
fabric	fabric
bandwidth	percentage of bandwidth for unicast flow
<i>percentage</i>	percentage value

Command Mode

- /exec/configure /exec/configure/nbm-vrf

nbm vrf

[no] nbm vrf <vrf-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
vrf	Display per-VRF information
<i>vrf-name</i>	VRF name

Command Mode

- /exec/configure

nbm vrf default

[no] nbm vrf default

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
vrf	Display per-VRF information
default	Default VRF

Command Mode

- /exec/configure /exec/configure/nbm-vrf

negotiate auto

negotiate auto

negotiate auto | no negotiate auto

Syntax Description

no	Negate a command or set its defaults
negotiate	Configure link negotiation parameters
auto	Configure auto-negotiation

Command Mode

- /exec/configure/if-ether-all /exec/configure/if-eth-non-member /exec/configure/if-port-channel

negotiate auto 25000

[no] negotiate auto 25000

Syntax Description

no	(Optional) Negate a command or set its defaults
negotiate	Configure link negotiation parameters
auto	Configure auto-negotiation
25000	Force auto-negotiate to only 25000 and change fec to auto

Command Mode

- /exec/configure/if-ethernet-all /exec/configure/if-eth-non-member /exec/configure/if-port-channel

neighbor-down fib-accelerate

neighbor-down fib-accelerate

[no] neighbor-down fib-accelerate

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor-down	Handle BGP neighbor down event, due to various reasons
fib-accelerate	Accelerate the hardware updates for IP/IPv6 adjacencies for neighbor

Command Mode

- /exec/configure/router-bgp/vrf-cmds

neighbor

```
neighbor [ vrf { <vrf-name> | <vrf-known-name> } ] <ipaddr> { implicit-withdraw | labels accept <pfx-list>
| targeted } | no neighbor [ vrf { <vrf-name> | <vrf-known-name> } ] <ipaddr> [ implicit-withdraw | labels
accept | targeted ]
```

Syntax Description

no	Negate a command or set its defaults
neighbor	Configure neighbor parameters
vrf	(Optional) VRF Routing/Forwarding instance information
<i>vrf-name</i>	(Optional) VPN Routing/Forwarding instance name
<i>vrf-known-name</i>	(Optional) Known VRF name
<i>ipaddr</i>	IP address for LDP neighbor
implicit-withdraw	Enable LDP Implicit Withdraw Label
labels	Configure label binding exchange controls
accept	Specify label bindings to accept
<i>pfx-list</i>	Name of prefix list
targeted	Establish targeted session

Command Mode

- /exec/configure/ldp

neighbor

[no] neighbor { <neighbor-id> | <ipv6-neighbor-id> } [remote-as { <asn> | external | internal }]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-id</i>	IP address of the neighbor
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type

Command Mode

- /exec/configure/router-bgp

neighbor

[no] neighbor { <neighbor-id> | <ipv6-neighbor-id> } [remote-as { <asn> | external | internal }]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-id</i>	IP address of the neighbor
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

[no] neighbor { <neighbor-prefix> | <ipv6-neighbor-prefix> } [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-prefix</i>	IP prefix for neighbors
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match prefix peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp

neighbor

[no] neighbor { <neighbor-prefix> | <ipv6-neighbor-prefix> } [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-prefix</i>	IP prefix for neighbors
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match prefix peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

[no] neighbor <interface> [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>interface</i>	Interface name for BGP interface peering
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match interface peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp

neighbor

[no] neighbor <interface> [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>interface</i>	Interface name for BGP interface peering
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match interface peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

nemo config address port interval

nemo config address port interval

[no] nemo config address <ip_address> port <portnum> interval <interval-num>

Syntax Description

no	(Optional) Negate a command or set its defaults
nemo	Nemo switch onboarding enabler
config	Configure Nemo for switch onboarding
address	IP address of the Nemo platform
<i>ip_address</i>	IP Address
port	Port number of the Nemo platform
<i>portnum</i>	Port number
interval	Config interval in millisecond
<i>interval-num</i>	Config interval in millisecond

Command Mode

- /exec/configure

net

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/otv-isis

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/router-isis/router-isis-vrf-common

network

[no] network <ipv6-prefix> [route-map <rmap-name> | summarize] +

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Configure an IPv6 prefix to advertise
route-map	(Optional) Apply route-map to modify attributes
<i>rmap-name</i>	(Optional) Route-map name
summarize	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv6 /exec/configure/router-bgp/router-bgp-vrf-af-ipv6

network

[no] network { <ip-addr> mask <ip-mask> | <ip-prefix> } [route-map <rmap-name> | summarize | evpn] +

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Configure an IP prefix to advertise
<i>ip-addr</i>	IP network to advertise
mask	Configure the mask of the IP prefix to advertise
<i>ip-mask</i>	Dotted 4-octet mask
<i>ip-prefix</i>	IP prefix in CIDR format
route-map	(Optional) Apply route-map to modify attributes
<i>rmap-name</i>	(Optional) Route-map name
summarize	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
evpn	(Optional) Only advertise route towards evpn side

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv4 /exec/configure/router-bgp/router-bgp-vrf-af-ipv4

next-hop-self

[no | default] next-hop-self [all]

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-self	Set our address as nexthop (non-reflected)
all	(Optional) Set our address as nexthop for all routes

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv4
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpnv6
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mdt

next-hop-third-party

[no | default] next-hop-third-party

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-third-party	Compute a third-party nexthop if possible

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-label

nexthop route-map

[no] nexthop route-map <rmap-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
nexthop	Nexthop tracking
route-map	Route map for valid nexthops
<i>rmap-name</i>	Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-af /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn
/exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-ipv4-mvpn
/exec/configure/router-bgp/router-bgp-af-ipv6-mvpn /exec/configure/router-bgp/router-bgp-af-ipv4-mdt
/exec/configure/router-bgp/router-bgp-af-l2vpn-vpls

nexthop suppress-default-resolution

nexthop suppress-default-resolution

[no] nexthop suppress-default-resolution

Syntax Description

no	(Optional) Negate a command or set its defaults
nexthop	Nexthop resolution options
suppress-default-resolution	Prohibit use of default route for nexthop address resolution

Command Mode

- /exec/configure/router-bgp

nexthop trigger-delay critical non-critical

```
{ nexthop trigger-delay critical <criticaldelay> non-critical <noncriticaldelay> } | { no nexthop trigger-delay }
```

Syntax Description

no	Negate a command or set its defaults
nexthop	Nexthop tracking
trigger-delay	Set the delay to trigger nexthop tracking
critical	Nexthop changes affecting reachability
non-critical	Other nexthop changes
<i>noncriticaldelay</i>	Delay value (milliseconds)
<i>criticaldelay</i>	Delay value (milliseconds)

Command Mode

- /exec/configure/router-bgp/router-bgp-af /exec/configure/router-bgp/router-bgp-af-ipv4-mdt
 /exec/configure/router-bgp/router-bgp-af-vpnv4 /exec/configure/router-bgp/router-bgp-af-vpnv6
 /exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-l2vpn-vpls
 /exec/configure/router-bgp/router-bgp-af-ipv4-mvpn /exec/configure/router-bgp/router-bgp-af-ipv6-mvpn
 /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn

ngoam authentication-key

ngoam authentication-key

{ ngoam authentication-key <value> } | { no ngoam authentication-key [<value>] }

Syntax Description

no	Negate a command or set its defaults
ngoam	Configure ngoam
authentication-key	Ngoam authentication-key
<i>value</i>	authentication key

Command Mode

- /exec/configure

ngoam connect-check

[no] ngoam connect-check <id>

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
connect-check	Configure ngoam oam connectivity check
<i>id</i>	connect check id

Command Mode

- /exec/configure

ngoam install acl

ngoam install acl

[no] ngoam install acl

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
install	Ngoam install
acl	Ngoam install acl

Command Mode

- /exec/configure

ngoam loop-detection

[no] ngoam loop-detection

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
loop-detection	Configure Loop Detection

Command Mode

- /exec/configure

ngoam loop-detection bringup vlan

ngoam loop-detection bringup vlan

ngoam loop-detection bringup { vlan <vlan-range> } [port <port-range>]

Syntax Description

ngoam	Configure ngoam
loop-detection	Configure Loop Detection
bringup	Bringup the ports,if disabled
vlan	Vlan
port	(Optional) Ports to bringup if disabled
<i>vlan-range</i>	vlan range max span 1024, Example: 2000-3000,400,500
<i>port-range</i>	(Optional) Interface for loop detection

Command Mode

- /exec

ngoam loop-detection probe vlan

ngoam loop-detection probe { vlan <vlan-range> } [port <port-range>]

Syntax Description

ngoam	Configure ngoam
loop-detection	Configure Loop Detection
probe	Probe for loop detection
vlan	Start probing on vlan for loop detection
port	(Optional) start probing on port for loop detection
<i>vlan-range</i>	vlan range max span 1024, Example: 2000-3000,400,500
<i>port-range</i>	(Optional) Interface for loop detection

Command Mode

- /exec

ngoam profile

[no] ngoam profile <profile-id>

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
profile	Configure ngoam oam profile
<i>profile-id</i>	ngoam profile id

Command Mode

- /exec/configure

ngoam xconnect hb-interval

{ ngoam xconnect hb-interval <ms> } | { no ngoam xconnect hb-interval [<ms>] }

Syntax Description

no	Negate a command or set its defaults
ngoam	Configure ngoam
xconnect	Configure xconnect parameters
hb-interval	Configure xconnect heartbeat interval
<i>ms</i>	interval in ms, 3 failures triggers failure default is 190

Command Mode

- /exec/configure

no-more

| no-more

Syntax Description

	Pipe command output to filter
no-more	Turn-off pagination for command output

Command Mode

- /output

no

[no] { userprofile | trustedCert | CRLLookup | user-switch-bind | user-certdn-match | user-pubkey-match }

Syntax Description

no	Negate a command or set its defaults
userprofile	Delete the userprofile
trustedCert	Delete the trustedCert
CRLLookup	Delete the CRLLookup
user-switch-bind	Delete the user-switch-bind
user-certdn-match	Delete the certificate matching
user-pubkey-match	Delete the pubkey matching

Command Mode

- /exec/configure/ldap/search

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/arpacl /exec/configure/ipgroup /exec/configure/ipv6group /exec/configure/portgroup /exec/configure/timerange

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/macacl

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/mplsacl

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/ipacl /exec/configure/ipv6acl

no

no

```
{ [ <seqno> ] | no } <permitdeny> { { { { ethertype <ethertypeid> } | { { ip | <proto> | <ip_other_proto> } { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { capture session <session-id> } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] | { udf { <udf_name> <udf_val> <udf_mask> } + } ] { [ <action> <actionid> ] } + [ load-share ] { [ <action> <actionid> ] } + [ log ] { [ <action> <actionid> ] } + [ telemetry_queue ] { [ <action> <actionid> ] } + [ telemetry_path ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>ip</i>	Any IP protocol
<i>proto</i>	A protocol number
<i>ip_other_proto</i>	ip_other_proto
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits

<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>time-range</i>	(Optional) Specify a time range

no

<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
<i>load-share</i>	(Optional) load share amoung the ports specified in redirect list

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { ethertype <ethertypeid> } | { <proto_tcp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> } ] { { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] <dscp_str> } } | { http-method { <opt_num> | <opt_str> } } | { tcp-option-length <tcp_opt_len> } | { tcp-flags-mask <tcp_flags_mask> } | { ttl <ttl_num> } ] } + | { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + | { udf { <udf_name> <udf_val> <udf_mask> } + } } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } | { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } | { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] <dscp_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { [ [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + | { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] <dscp_str> } } | { http-method { <opt_num> | <opt_str> } } | { tcp-option-length <tcp_opt_len> } | { tcp-flags-mask <tcp_flags_mask> } | { ttl <ttl_num> } ] } + | { [ urg | ack | psh | rst | syn | fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + | { udf { <udf_name> <udf_val> <udf_mask> } + } ] [ capture session <session-id> ] { [ <action> <actionid> ] } + [ load-share ] { [ <action> <actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value

<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_tcp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) TCP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) TCP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) TCP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address

<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) TCP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) TCP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) TCP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name

no

packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
ttl	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
tcp-option-length	(Optional) Specify TCP Options size
<i>tcp_opt_len</i>	(Optional) TCP option length (multiples of 4 bytes)
tcp-flags-mask	(Optional) Specify TCP Flags
<i>tcp_flags_mask</i>	(Optional) TCP flags mask
http-method	(Optional) Match packets based on http-method
<i>opt_num</i>	(Optional) http_option value
<i>opt_str</i>	(Optional) http_option_param
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
urg	(Optional) Match on the URG bit
ack	(Optional) Match on the ACK bit
psh	(Optional) Match on the PSH bit
rst	(Optional) Match on the RST bit
syn	(Optional) Match on the SYN bit
fin	(Optional) Match on the FIN bit
established	(Optional) Match established connections
udf	(Optional) User defined field match

<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share amoung the ports specified in redirect list

Command Mode

- /exec/configure/ipacl

no

no

```
{ [ <seqno> ] | no } <permitdeny> { { ethertype <ethertypeid> } | { <proto_udp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> ] { { [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } ] } + | { [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] [ nve vni <vni-id> ] } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + | { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + } [ nve vni <vni-id> ] } | { [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } ] } + | { [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] # 2384 ..//feature/acl_mngr/cli/aclmgr.cmd [ capture session <session-id> ] { [ <action> <actionid> ] } + [ load-share ] { [ <action> <actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number

<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_udp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) UDP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) UDP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) UDP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group

<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) UDP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) UDP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) UDP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<itos></itos>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length

<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>nve</i>	(Optional) VNI ID <0-16777215>
<i>vni</i>	(Optional) VNI ID <0-16777215>
<i>vni-id</i>	(Optional) VNI ID <0-16777215>
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
<i>load-share</i>	(Optional) load share amoung the ports specified in redirect list

Command Mode

- /exec/configure/ipacl

no

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_igmp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr>
<dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [
[ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | <igmp_num> | packet-length
{ <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask>
] | <dscp_str> } } ] + | [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] |
<igmp_str> | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num>
[ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] + | [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] | <igmp_num> | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2>
} | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } ] + | [ [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | <igmp_str> | packet-length {
<plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence {
<prec_num> | <prec_str> } } ] + } } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host
<src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } |
<dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ fragments ]
| [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op>
<plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } | { ttl <ttl_num> } ] + | [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos {
<tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] + } } [ capture
session <session-id> ] { [ <action> <actionid> ] } + [ load-share ] { [ <action> <actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_igmp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address

<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length

no

<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>igmp_num</i>	(Optional) IGMPv1 message type
<i>igmp_str</i>	(Optional) IGMP type
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
<i>load-share</i>	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { { ethertype <ethertypeid> } | { <proto_icmp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | { <icmp_type> [ <icmp_code> ] } | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] + | [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | <icmp_str> | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] + | [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | { <icmp_type> [ <icmp_code> ] } | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } ] + | [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | <icmp_str> | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } ] + } } | { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } ] } + | [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op><plen0> | <plen_range><plen1><plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | wlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] { [ <action><actionid> ] + [ load-share ] { [ <action><actionid> ] } + [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ethertype</i>	Configure match based on ethertype
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_icmp</i>	Protocol

<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<itos< i=""></itos<>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry

telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
ttl	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>icmp_type</i>	(Optional) ICMP message type
<i>icmp_code</i>	(Optional) ICMP message code
<i>icmp_str</i>	(Optional) ICMP label
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipacl

no

no

```
{ [ <seqno> ] | no } <permitdeny> { { ipv6 | <proto> | <ipv6_other_proto> } { <src_any> | { <src_addr>
<src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } {
<dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp
<dst_addrgrp_name> } } { [ { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] [
flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ { udf {
<udf_name> <udf_val> <udf_mask> } + } ] } + [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } |
vlan_priority <vlanpriorityid> ] + [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] [ capture session
<session-id> ] { [ <actionv6> <actionidv6> ] } + [ load-share ] { [ <actionv6> <actionidv6> ] [ log ] | { udf
{ <udf_name> <udf_val> <udf_mask> } + } }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>ipv6</i>	Any IPV6 protocol
<i>proto</i>	A protocol number
<i>ipv6_other_proto</i>	ipv6_other_proto
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
<i>src_key_host</i>	A single source host
<i>src_key_addrgrp</i>	Source address group

<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>flow-label</i>	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6

no

<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share amoung the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_tcp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } } | [ { flow-label <flow_num> } ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] | [ urg | ack | psh | rst | syn | fin | established ] | { tcp-flags-mask <tcp_flags_mask> } |
[ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] } + [ { udf { <udf_name><udf_val>
<udf_mask> } + } } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host>
} | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { dscp { <dscp_num> [ [ dscp-mask
] <dscp_mask> ] | <dscp_str> } } } | { flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [
telemetry_path ] [ time-range <time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range>
<plen1> <plen2> } ] [ { udf { <udf_name><udf_val><udf_mask> } + } ] } + } } [ vlan <vlanid> | ingress_intf
{ <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] { [ <actionv6>
<actionidv6> ] } { [ <actionv6><actionidv6> ] } + [ load-share ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_tcp</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority

<i>src_any</i>	Any
<i>src_key_host</i>	A single source host
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) TCP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) TCP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) TCP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) TCP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) TCP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) TCP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask

dscp-mask	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
tcp-flags-mask	Specify TCP Flags
<i>tcp_flags_mask</i>	TCP flags mask
urg	(Optional) Match on the URG bit
ack	(Optional) Match on the ACK bit
psh	(Optional) Match on the PSH bit
rst	(Optional) Match on the RST bit
syn	(Optional) Match on the SYN bit
fin	(Optional) Match on the FIN bit
established	(Optional) Match established connections
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session

no

<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
<i>load-share</i>	(Optional) load share amoung the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_udp> { { { <src_any> | { <src_addr><src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } [ { flow-label <flow_num> } ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] } + { udf
{ <udf_name> <udf_val> <udf_mask> } + } } [ nve vni <vni-id> ] | { { <src_any> | { <src_addr><src_wild>
} | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | {
<dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name>
} } { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } [ { flow-label <flow_num>
} ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ { udf { <udf_name> <udf_val> <udf_mask>
} + } ] + } } [ nve vni <vni-id> ] [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority
<vlanpriorityid> ] + [ capture session <session-id> ] { [ <actionv6> <actionidv6> ] } { [ <actionv6>
<actionidv6> ] } + [ load-share ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_udp</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority

<i>src_any</i>	Any
<i>src_key_host</i>	A single source host
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) UDP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) UDP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) UDP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) UDP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) UDP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) UDP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask

dscp-mask	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
nve	(Optional) VNI ID <0-16777215>
vni	(Optional) VNI ID <0-16777215>
<i>vni-id</i>	(Optional) VNI ID <0-16777215>
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share amoung the ports specified in redirect list

Command Mode

no

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_sctp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> } ] { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } [ { flow-label <flow_num> } ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] } + } | { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } [ { flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_sctp</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
<i>src_key_host</i>	A single source host

no

<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) SCTP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) SCTP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) SCTP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) SCTP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) SCTP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) SCTP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value

<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>flow-label</i>	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session

Command Mode

- /exec/configure/ipv6acl

no

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_icmpv6> { { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { { <icmpv6_type> [ <icmpv6_code> ] } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { flow-label <flow_num> } | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] + | [ <icmpv6_str> | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { flow-label <flow_num> } | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] + } } | { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { flow-label <flow_num> } | [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] | { udf { <udf_name> <udf_val> <udf_mask> } + } } + } | [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + | capture session <session-id> | [ <actionv6> <actionidv6> ] | [ <actionv6> <actionidv6> ] | [ load-share ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_icmpv6</i>	Protocol
<i>vlan</i>	(Optional) Configure match based on vlan
<i>ingress_intf</i>	(Optional) Configure match based on ingress interface
<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any

src_key_host	A single source host
src_key_addrgrp	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
dst_key_host	A single destination host
dst_key_addrgrp	Destination address group
<i>dst_addrgrp_name</i>	Address group name
dscp	(Optional) Match packets with given dscp value and Mask
dscp-mask	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>icmpv6_type</i>	(Optional) ICMPv6 message type
<i>icmpv6_code</i>	(Optional) ICMPv6 message code
<i>icmpv6_str</i>	(Optional) ICMPv6 label

no

capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

{ [<seqno>] | no } { <addr> <wild> | <prefix> | host <hostaddr> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>addr</i>	A.B.C.D Network address of object-group member
<i>wild</i>	A.B.C.D wildcard
<i>prefix</i>	A.B.C.D/nn Network prefix of the object-group member
host	Host address of the object-group member
<i>hostaddr</i>	A.B.C.D Host address

Command Mode

- /exec/configure/ipgroup

no

{ [<seqno>] | no } { <addr> <wild> | <prefix> | host <hostaddr> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
host	Host address of the object-group member

Command Mode

- /exec/configure/ipv6group

no

{ [<seqno>] | no } { <_port_op> <port0_num> | <_port_range> <port1_num> <port2_num> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>_port_op</i>	Port operator
<i>_port_range</i>	Port range
<i>port0_num</i>	Port number
<i>port1_num</i>	Port number
<i>port2_num</i>	Port number

Command Mode

- /exec/configure/portgroup

no

no

```
{ [ <seqno> ] | no } <permitdeny> { <src_any> | { <src_addr> <src_wild> } } { <dst_any> | { <dst_addr> <dst_wild> } } [ <mac_proto> | <mac_proto_str> ] [ vlan <vlan> | cos <cos> ] + [ time-range <time_range_name> ] [ capture session <session-id> ] { [ <macaction> <macactionid> ] } + [ load-share ] { [ <macaction> <macactionid> ] } + [ { udf { <udf_name> <udf_val> <udf_mask> } + } ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
<i>no</i>	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>src_any</i>	Any
<i>src_addr</i>	Source MAC address
<i>src_wild</i>	Source wildcard bits
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination MAC address
<i>dst_wild</i>	Destination wildcard bits
<i>mac_proto</i>	(Optional) MAC protocol number
<i>mac_proto_str</i>	(Optional) MAC protocol name
<i>vlan</i>	(Optional) VLAN number
<i>cos</i>	(Optional) CoS value
<i>vlan</i>	(Optional) VLAN number
<i>cos</i>	(Optional) CoS value
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>macaction</i>	(Optional) MAC ACL Action
<i>macactionid</i>	(Optional) redirect: Ethernet1/1,port-channel1
<i>udf</i>	(Optional) User defined field match

<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
load-share	(Optional) load share amoung the ports specified in redirect list

Command Mode

- /exec/configure/macacl

no

no

Syntax Description

no	Negate a command or set its defaults
----	--------------------------------------

Command Mode

- /exec/configure/vsan-db

node ip

[no] node { ip <ip-addr> | IPv6 <ip-addrv6> }

Syntax Description

no	(Optional) Negate a command or set its defaults
node	ITD node
ip	ITD node IPv4 address
<i>ip-addr</i>	ITD node IP4 prefix in format i.i.i.i
IPv6	ITD node IPv6 address

Command Mode

- /exec/configure/itd-session-device-group

node ip

[no] node { ip <ip-addr> | IPv6 <ip-addrv6> }

Syntax Description

no	(Optional) Negate a command or set its defaults
node	ITD node
ip	ITD node IPv4 address
<i>ip-addr</i>	ITD node IP4 prefix in format i.i.i.i
IPv6	ITD node IPv6 address

Command Mode

- /exec/configure/itd-device-group

npv auto-load-balance disruptive

[no] npv auto-load-balance disruptive

Syntax Description

no	(Optional) Negate a command or set its defaults
npv	Config commands for FC N_port Virtualizer
auto-load-balance	configure auto load balancing among preferred external links
disruptive	enable disruptive auto load balancing among external links

Command Mode

- /exec/configure

npv traffic-map server-interface external-interface

[no] npv traffic-map server-interface <if1> external-interface <interface>

Syntax Description

no	(Optional) Negate a command or set its defaults
npv	Config commands for FC N_port Virtualizer
traffic-map	Configure NPV traffic engineering
server-interface	Configure server interface based traffic engineering
<i>if1</i>	
external-interface	Configure preferred external interface(s)
<i>interface</i>	

Command Mode

- /exec/configure

nsf await-redist-proto-convergence

{ [no] nsf await-redist-proto-convergence }

Syntax Description

no	(Optional) Negate a command or set its defaults
nsf	Non-stop forwarding
await-redist-proto-convergence	Specify whether EIGRP should wait for other protocols to converge before advertising routes

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-common

ntp access-group

ntp access-group

[no] ntp access-group { peer | serve-only | serve | query-only } <acl-name>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
access-group	NTP access-group
peer	access-group peer
serve	access-group serve
serve-only	access-group serve-only
query-only	access-group query-only
<i>acl-name</i>	Name of access list

Command Mode

- /exec/configure

ntp access-group match-all

[no] ntp access-group match-all

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
access-group	NTP access-group
match-all	Scan ACLs present in all ntp access groups

Command Mode

- /exec/configure

ntp allow private

ntp allow private

[no] ntp allow { private | control [rate-limit <delay>] }

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
allow	Enable/Disable the packets
private	Enable/Disable Private mode packets
control	Enable/Disable Control mode packets
rate-limit	(Optional) Rate-limit the control packets
delay	(Optional) Rate-limit delay (Default 3)

Command Mode

- /exec/configure

ntp authenticate

[no] ntp authenticate

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
authenticate	Enable/Disable authentication

Command Mode

- /exec/configure

ntp authentication-key md5

ntp authentication-key md5

[no] ntp authentication-key <number> md5 <md5> [0 | 7]

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
authentication-key	NTP authentication key
<i>number</i>	authentication key number (range 1-65535)
md5	use md5 authentication scheme
<i>md5</i>	MD5 string
0	(Optional) clear text
7	(Optional) encrypted

Command Mode

- /exec/configure

ntp logging

[no] ntp logging

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
logging	Enable/Disable logging of NTPD Events

Command Mode

- /exec/configure

ntp master

ntp master

[no] ntp master [<stratum-no>]

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
master	Act as NTP master clock
<i>stratum-no</i>	(Optional) Stratum number

Command Mode

- /exec/configure

ntp passive

[no] ntp passive

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
passive	NTP passive command

Command Mode

- /exec/configure

ntp peer

[no] ntp peer <host0> [prefer | key <keyid> | use-vrf { <vrf-name> | <vrf-known-name> } | minpoll <minpoll> | maxpoll <maxpoll>] +

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
peer	NTP Peer address
<i>host0</i>	Hostname/IP address of the NTP Peer
prefer	(Optional) Preferred Server
key	(Optional) Keyid to be used while communicating to this server
<i>keyid</i>	(Optional) Value of keyid 1-65535
use-vrf	(Optional) Display per-VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
minpoll	(Optional) Minimum interval to poll a peer
<i>minpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 4]
maxpoll	(Optional) Maximum interval to poll a peer
<i>maxpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 6]

Command Mode

- /exec/configure

ntp server

[no] ntp server <host0> [prefer | key <keyid> | use-vrf { <vrf-name> | <vrf-known-name> } | minpoll <minpoll> | maxpoll <maxpoll>] +

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
server	NTP server address
<i>host0</i>	Hostname/IP address of the NTP Server
prefer	(Optional) Preferred Server
key	(Optional) Keyid to be used while communicating to this server
<i>keyid</i>	(Optional) Value of keyid 1-65535
use-vrf	(Optional) Display per-VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
minpoll	(Optional) Minimum interval to poll a server
<i>minpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 4]
maxpoll	(Optional) Maximum interval to poll a server
<i>maxpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 6]

Command Mode

- /exec/configure

ntp source-interface

ntp source-interface

[no] ntp source-interface <interface>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
source-interface	Source interface sending NTP packets
<i>interface</i>	Source interface

Command Mode

- /exec/configure

ntp source

[no] ntp source <ip-addr>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP Configuration
source	Source of NTP packets
<i>ip-addr</i>	IPv4/IPv6 address

Command Mode

- /exec/configure

ntp sync-retry

ntp sync-retry

ntp sync-retry

Syntax Description

ntp	NTP configuration
sync-retry	Retry synchronization with configured servers

Command Mode

- /exec

ntp trusted-key

[no] ntp trusted-key <number>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
trusted-key	NTP trusted-key
<i>number</i>	trusted-key number

Command Mode

- /exec/configure

nv overlay evpn

[no] nv overlay evpn

Syntax Description

no	(Optional) Negate a command or set its defaults
nv	Command to enable/disable features
overlay	Command to enable/disable features
evpn	Enable/Disable Ethernet VPN (EVPN)

Command Mode

- /exec/configure

nve interface remap-replication-servers

nve interface <nve-if> remap-replication-servers

Syntax Description

nve	Configure NVE information
interface	Interface
<i>nve-if</i>	NVE interface
remap-replication-servers	Remap Replication servers to VNIs

Command Mode

- /exec

nve interface replication-server up

nve interface <nve-if> replication-server <rep-addr> { up | down }

Syntax Description

nve	Configure NVE information
interface	Interface
<i>nve-if</i>	NVE interface
replication-server	Configure a replication server
<i>rep-addr</i>	Replication Server IP Address
up	mark replication-server up
down	mark replication-server down

Command Mode

- /exec

nve oam mode draft-pang

[no] nve oam mode draft-pang

Syntax Description

no	(Optional) Negate a command or set its defaults
nve	VxLAN functionality
oam	VxLAN OAM functionality
mode	Choose operation mode for OAM
draft-pang	OAM implementation as per Draft Pang

Command Mode

- /exec/configure

nwwn

[no] nwwn <wwn0>

Syntax Description

no	(Optional) Negate a command or set its defaults
nwwn	Node WWN of the platform
<i>wwn0</i>	Node WWN

Command Mode

- /exec/configure/fcs-register/attrib

nwwn vsan

[no] nwwn <wwn0> vsan <i1>

Syntax Description

no	(Optional) Negate a command or set its defaults
nwwn	Device NWWN
<i>wwn0</i>	NWWN of the Device
vsan	VSAN id for device
<i>i1</i>	vsan id

Command Mode

- /exec/configure/dpvm-db

nxapi certificate httpskey keyfile

```
{ nxapi certificate { { httpskey { keyfile <uri0> [ password <passphrase> ] } } | { httpscert { certfile <uri1> } } | { enable } | { trustpoint <trustpoint-name> } | { sudi } } } | { no nxapi certificate { sudi | trustpoint <trustpoint-name> } }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
certificate	Https certificate configuration
httpskey	Https private key
httpscert	Https certificate
keyfile	Https key file
certfile	Https certificate file
password	(Optional) Https encrypted key passphrase
enable	Enable the current certificate
trustpoint	Trustpoint configuration
<i>trustpoint-name</i>	trustpoint name to use for Identity
sudi	sudi configuration
<i>uri0</i>	File containing https private key for the user
<i>passphrase</i>	(Optional) Https encrypted private key passphrase
<i>uri1</i>	File containing https certificate

Command Mode

- /exec/configure

nxapi client certificate authentication

```
{ nxapi client certificate authentication [ <verification-setting> ] } | { no nxapi client certificate authentication }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
client	Configure NX-API client management properties
certificate	Configure NX-API client certificate authentication functionality
authentication	Enable/Disable client certificate authentication
<i>verification-setting</i>	(Optional) Configure nxapi client-certificate authentication verification restriction setting

Command Mode

- /exec/configure

nxapi http port

{ nxapi { http | https } port <s0> } | { no nxapi { http | https } } | { no nxapi { http | https } port <s0> }

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
http	Http configuration
https	Https configuration
port	Port number
s0	Port number. Please do not use well-known protocol ports

Command Mode

- /exec/configure

nxapi idle-timeout

[no] nxapi idle-timeout <i0>

Syntax Description

no	(Optional) Negate a command or set its defaults
nxapi	Configure nxapi
idle-timeout	duration until idle session expires
<i>i0</i>	Length of time, in minutes

Command Mode

- /exec/configure

nxapi ssl ciphers weak

nxapi ssl ciphers weak

{ [no] nxapi ssl ciphers weak }

Syntax Description

no	(Optional) Negate a command or set its defaults
nxapi	Configure nxapi
ssl	Configure ssl parameters
ciphers	Configure allowed ciphers for ssl
weak	Allow weak ciphers

Command Mode

- /exec/configure

nxapi ssl protocols

{ nxapi ssl protocols <prot_string> } | { no nxapi ssl protocols }

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
ssl	Configure ssl parameters
protocols	Configure allowed ssl protocols
<i>prot_string</i>	String of supported protocols, Ex: TLSv1 TLSv1.1 TLSv1.2

Command Mode

- /exec/configure

nxapi use-vrf management default

```
{ nxapi use-vrf { management | default | <vrf_name> } } | { no nxapi use-vrf { management | default | <vrf_name> } }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
use-vrf	vrf to be used for nxapi communication
management	management vrf
default	default vrf
<i>vrf_name</i>	name of the vrf

Command Mode

- /exec/configure

nxSDK profile

[no] nxSDK profile <nxSDK-profile-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
nxSDK	NXOS SDK
profile	service profile
<i>nxSDK-profile-name</i>	NxSDK service profile name

Command Mode

- /exec/configure

nx sdk remote port

[no] nx sdk remote port <port> [namespace { <vrf-name> | <vrf-known-name> }] [certificate <cert-id>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nx sdk	NXOS SDK
remote	To run NX-SDK service as a remote service
port	Port to accept remote NX-SDK connections
<i>port</i>	Port
namespace	(Optional) Namespace to run the remote server on. Default is Vrf: Default
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
certificate	(Optional) Specify certificate id to be used for the remote session
<i>cert-id</i>	(Optional) Certificate identification

Command Mode

- /exec/configure

nx sdk service-name

[no] nx sdk service-name <nx sdk-service-name> [profile <nx sdk-profile-name>]

Syntax Description

nx sdk	NXOS SDK
service-name	Complete path and name of file to execute
<i>nx sdk-service-name</i>	Service name
profile	(Optional) Service profile
<i>nx sdk-profile-name</i>	(Optional) Name of the profile

Command Mode

- /exec/configure

```
nxSDK service-name
```