



N Commands

- [name-lookup](#), on page 4
- [name-lookup](#), on page 5
- [name](#), on page 6
- [name](#), on page 7
- [name](#), on page 8
- [name](#), on page 9
- [name](#), on page 10
- [nat destination](#), on page 11
- [nbm bandwidth capacity](#), on page 12
- [nbm bandwidth unicast](#), on page 13
- [nbm external-link](#), on page 14
- [nbm flow-definition](#), on page 15
- [nbm flow-definition](#), on page 16
- [nbm flow-policy](#), on page 17
- [nbm flow-policy](#), on page 18
- [nbm flow asm range](#), on page 19
- [nbm flow asm range](#), on page 20
- [nbm flow bandwidth immediate-recovery](#), on page 21
- [nbm flow bandwidth immediate-recovery](#), on page 22
- [nbm flow bandwidth kbps mbps gbps](#), on page 23
- [nbm flow bandwidth kbps mbps gbps](#), on page 24
- [nbm flow dscp](#), on page 25
- [nbm flow dscp](#), on page 26
- [nbm flow policer](#), on page 27
- [nbm flow policer](#), on page 28
- [nbm flow reserve-bandwidth receiver-only](#), on page 29
- [nbm flow reserve-bandwidth receiver-only](#), on page 30
- [nbm host-policy](#), on page 31
- [nbm host-policy](#), on page 32
- [nbm mode pim](#), on page 33
- [nbm reserve unicast fabric bandwidth](#), on page 34
- [nbm vrf](#), on page 35
- [nbm vrf default](#), on page 36

- negotiate auto, on page 37
- negotiate auto 25000, on page 38
- neighbor-down fib-accelerate, on page 39
- neighbor, on page 40
- neighbor, on page 41
- neighbor, on page 42
- neighbor, on page 43
- neighbor, on page 44
- neighbor, on page 45
- neighbor, on page 46
- nemo config address port interval, on page 47
- net, on page 48
- net, on page 49
- network, on page 50
- network, on page 51
- next-hop-self, on page 52
- next-hop-third-party, on page 53
- nexthop load-balance egress multisite, on page 54
- nexthop route-map, on page 55
- nexthop suppress-default-resolution, on page 56
- nexthop trigger-delay critical non-critical, on page 57
- ngoam authentication-key, on page 58
- ngoam connect-check, on page 59
- ngoam install acl, on page 60
- ngoam loop-detection, on page 61
- ngoam loop-detection bringup vlan, on page 62
- ngoam loop-detection probe vlan, on page 63
- ngoam profile, on page 64
- ngoam xconnect hb-interval, on page 65
- no-more, on page 66
- no, on page 67
- no, on page 68
- no, on page 69
- no, on page 70
- no, on page 71
- no, on page 75
- no, on page 80
- no, on page 85
- no, on page 89
- no, on page 93
- no, on page 96
- no, on page 100
- no, on page 104
- no, on page 107
- no, on page 110
- no, on page 111

- no, on page 112
- no, on page 113
- no, on page 115
- no, on page 116
- node ip, on page 117
- node ip, on page 118
- npv auto-load-balance disruptive, on page 119
- npv traffic-map server-interface external-interface, on page 120
- nsf await-redis-proto-convergence, on page 121
- ntp access-group, on page 122
- ntp access-group match-all, on page 123
- ntp allow private, on page 124
- ntp authenticate, on page 125
- ntp authentication-key md5, on page 126
- ntp logging, on page 127
- ntp master, on page 128
- ntp passive, on page 129
- ntp peer, on page 130
- ntp server, on page 131
- ntp source-interface, on page 132
- ntp source, on page 133
- ntp sync-retry, on page 134
- ntp trusted-key, on page 135
- nv overlay evpn, on page 136
- nve interface remap-replication-servers, on page 137
- nve interface replication-server up, on page 138
- nve oam mode draft-pang, on page 139
- nwwn, on page 140
- nwwn vsan, on page 141
- nxapi certificate httpskey keyfile, on page 142
- nxapi client certificate authentication, on page 143
- nxapi http port, on page 144
- nxapi idle-timeout, on page 145
- nxapi ssl ciphers weak, on page 146
- nxapi ssl protocols, on page 147
- nxapi use-vrf management default, on page 148
- nxsdk profile, on page 149
- nxsdk remote port, on page 150
- nxsdk service-name, on page 151

name-lookup

[no] name-lookup [use-vrf <dns-vrf-name>]

Syntax Description

no	(Optional) Negate a command or set its defaults
name-lookup	Display OSPF router ids as DNS names
use-vrf	(Optional) Optional use vrf parameter
<i>dns-vrf-name</i>	(Optional) VRF name

Command Mode

- /exec/configure/router-ospf /exec/configure/router-ospf/vrf

name-lookup

[no] name-lookup

Syntax Description

no	(Optional) Negate a command or set its defaults
name-lookup	Enable Name Lookup for OSPFv3 Neighbors

Command Mode

- /exec/configure/router-ospf3 /exec/configure/router-ospf3/vrf

name

```
{ { name-server0-ipv6 | name-server1-ipv6 } <ipv6-addr> | no { name-server0-ipv6 | name-server1-ipv6 } [ <ipv6-addr> ] }
```

Syntax Description

no	Negate a command or set its defaults
name-server0-ipv6	Name server IPv6 Address
name-server1-ipv6	Name server IPv6 Address

Command Mode

- /exec/configure/app-hosting-appid

name

name <name-val> | no name [<name-val>]

Syntax Description

no	Negate a command or set its defaults
name	Set configuration name
<i>name-val</i>	Configuration name

Command Mode

- /exec/configure/spanning-tree/mst/configuration

name

name [<name>] | no name

Syntax Description

no	Negate a command or set its defaults
name	Redundancy name string
<i>name</i>	(Optional) name string

Command Mode

- /exec/configure/if-eth-any/hsrp_ipv4 /exec/configure/if-eth-any/hsrp_ipv6

name

name <vlan-name> | no name

Syntax Description

no	Negate a command or set its defaults
name	Ascii name of the VLAN
<i>vlan-name</i>	The ascii name for the VLAN

Command Mode

- /exec/configure/vlan

name

{ { name-server0 | name-server1 } <ip-addr> | no { name-server0 | name-server1 } [<ip-addr>] }

Syntax Description

no	Negate a command or set its defaults
name-server0	Name server IP Address
name-server1	Name server IP Address
<i>ip-addr</i>	Name server IP Address

Command Mode

- /exec/configure/app-hosting-appid

nat destination

{ nat destination } | { no nat destination }

Syntax Description

no	Negate a command or set its defaults
nat	Network Address Translation
destination	Destination NAT

Command Mode

- /exec/configure/itd

nbm bandwidth capacity

nbm bandwidth capacity <percentage> | no nbm bandwidth capacity

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
bandwidth	bandwidth
capacity	capacity
<i>percentage</i>	percentage value, 0 means no reservation for BW purpose

Command Mode

- /exec/configure/if-igp

nbm bandwidth unicast

nbm bandwidth unicast <percentage> | no nbm bandwidth unicast

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
bandwidth	percentage of bandwidth set aside other than multicast
unicast	unicast
<i>percentage</i>	percentage value. 0 means no reservation for unicast on this link

Command Mode

- /exec/configure/if-igp

nbm external-link

[no] nbm external-link

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
external-link	link connected to external router. Configuring this will flap the interface

Command Mode

- /exec/configure/if-igp

nbm flow-definition

[no] nbm flow-definition <group> [<source>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-definition	Define a multicast flow
<i>group</i>	Multicast Group Address
<i>source</i>	(Optional) Source IP address to use

Command Mode

- /exec/configure

nbm flow-definition

[no] nbm flow-definition <group> [<source>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-definition	Define a multicast flow
<i>group</i>	Multicast Group Address
<i>source</i>	(Optional) Source IP address to use

Command Mode

- /exec/configure/nbm-vrf

nbm flow-policy

[no] nbm flow-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-policy	Flow Policy Characteristics

Command Mode

- /exec/configure/nbm-vrf

nbm flow-policy

[no] nbm flow-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow-policy	Flow Policy Characteristics

Command Mode

- /exec/configure

nbm flow asm range

[no] nbm flow asm range <group> +

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
asm	Any-Source Multicast (ASM) groups
range	Configure explicit group ranges
<i>group</i>	List of group range prefixes

Command Mode

- /exec/configure/nbm-vrf

nbm flow asm range

[no] nbm flow asm range <group> +

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
asm	Any-Source Multicast (ASM) groups
range	Configure explicit group ranges
<i>group</i>	List of group range prefixes

Command Mode

- /exec/configure

nbm flow bandwidth immediate-recovery

[no] nbm flow bandwidth immediate-recovery

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
immediate-recovery	Free up used BW immediately on last OIF removal

Command Mode

- /exec/configure

nbm flow bandwidth immediate-recovery

[no] nbm flow bandwidth immediate-recovery

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
immediate-recovery	Free up used BW immediately on last OIF removal

Command Mode

- /exec/configure/nbm-vrf

nbm flow bandwidth kbps mbps gbps

```
{ nbm flow bandwidth { <val_kbps> kbps | <val_mbps> mbps | <val_gbps> gbps } } | { no nbm flow bandwidth }
```

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
<i>val_kbps</i>	Per Flow Bandwidth in Kbps
kbps	Bandwidth value in Kbps
<i>val_mbps</i>	Per Flow Bandwidth in Mbps
mbps	Bandwidth value in Mbps
<i>val_gbps</i>	Per Flow Bandwidth in Gbps
gbps	Bandwidth value in Gbps

Command Mode

- /exec/configure/nbm-vrf

nbm flow bandwidth kbps mbps gbps

```
{ nbm flow bandwidth { <val_kbps> kbps | <val_mbps> mbps | <val_gbps> gbps } } | { no nbm flow bandwidth }
```

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
bandwidth	Bandwidth per flow
<i>val_kbps</i>	Per Flow Bandwidth in Kbps
kbps	Bandwidth value in Kbps
<i>val_mbps</i>	Per Flow Bandwidth in Mbps
mbps	Bandwidth value in Mbps
<i>val_gbps</i>	Per Flow Bandwidth in Gbps
gbps	Bandwidth value in Gbps

Command Mode

- /exec/configure

nbm flow dscp

{ nbm flow dscp <val_dscp> } | { no nbm flow dscp }

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
dscp	DSCP for the flow
<i>val_dscp</i>	Integer value

Command Mode

- /exec/configure

nbm flow dscp

```
{ nbm flow dscp <val_dscp> } | { no nbm flow dscp }
```

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
dscp	DSCP for the flow
<i>val_dscp</i>	Integer value

Command Mode

- /exec/configure/nbm-vrf

nbm flow policer

[no] nbm flow policer

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
policer	Flow rate limiter installed in hardware

Command Mode

- /exec/configure

nbm flow policer

[no] nbm flow policer

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
policer	Flow rate limiter installed in hardware

Command Mode

- /exec/configure/nbm-vrf

nbm flow reserve-bandwidth receiver-only

[no] nbm flow reserve-bandwidth receiver-only

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
reserve-bandwidth	Reserve bandwidth
receiver-only	Configure explicit group ranges to restrict reserve bandwidth on receiver only

Command Mode

- /exec/configure/nbm-vrf

nbm flow reserve-bandwidth receiver-only

[no] nbm flow reserve-bandwidth receiver-only

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
flow	Flow Characteristics
reserve-bandwidth	Reserve bandwidth
receiver-only	Configure explicit group ranges to restrict reserve bandwidth on receiver only

Command Mode

- /exec/configure

nbm host-policy

[no] nbm host-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
host-policy	NBM SW Host Admission Policy

Command Mode

- /exec/configure

nbm host-policy

[no] nbm host-policy

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
host-policy	NBM SW Host Admission Policy

Command Mode

- /exec/configure/nbm-vrf

nbm mode pim

```
nbm mode { pim-active | pim-passive } | no nbm mode [ pim-active | pim-passive ] [ __readonly__ <output> ]
```

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
mode	Set pmn mode
pim-active	Bandwidth engine running in fabric
pim-passive	API driven flow stitching
__readonly__	(Optional)
<i>output</i>	(Optional)

Command Mode

- /exec/configure /exec/configure/nbm-vrf

nbm reserve unicast fabric bandwidth

nbm reserve unicast fabric bandwidth <percentage> | no nbm reserve unicast fabric bandwidth

Syntax Description

no	Negate a command or set its defaults
nbm	Non Blocking Multicast
reserve	reserve bandwidth
unicast	unicast
fabric	fabric
bandwidth	percentage of bandwidth for unicast flow
<i>percentage</i>	percentage value

Command Mode

- /exec/configure /exec/configure/nbm-vrf

nbm vrf

[no] nbm vrf <vrf-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
vrf	Display per-VRF information
<i>vrf-name</i>	VRF name

Command Mode

- /exec/configure

nbm vrf default

[no] nbm vrf default

Syntax Description

no	(Optional) Negate a command or set its defaults
nbm	Non Blocking Multicast
vrf	Display per-VRF information
default	Default VRF

Command Mode

- /exec/configure /exec/configure/nbm-vrf

negotiate auto

negotiate auto | no negotiate auto

Syntax Description

no	Negate a command or set its defaults
negotiate	Configure link negotiation parameters
auto	Configure auto-negotiation

Command Mode

- /exec/configure/if-ethernet-all /exec/configure/if-eth-non-member /exec/configure/if-port-channel

negotiate auto 25000

[no] negotiate auto 25000

Syntax Description

no	(Optional) Negate a command or set its defaults
negotiate	Configure link negotiation parameters
auto	Configure auto-negotiation
25000	Force auto-negotiate to only 25000 and change fec to auto

Command Mode

- /exec/configure/if-ethernet-all /exec/configure/if-eth-non-member /exec/configure/if-port-channel

neighbor-down fib-accelerate

[no] neighbor-down fib-accelerate

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor-down	Handle BGP neighbor down event, due to various reasons
fib-accelerate	Accelerate the hardware updates for IP/IPv6 adjacencies for neighbor

Command Mode

- /exec/configure/router-bgp/vrf-cmds

neighbor

[no] neighbor <interface> [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>interface</i>	Interface name for BGP interface peering
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match interface peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

```
neighbor [ vrf { <vrf-name> | <vrf-known-name> } ] <ipaddr> { implicit-withdraw | labels accept <px-list>
| targeted } | no neighbor [ vrf { <vrf-name> | <vrf-known-name> } ] <ipaddr> [ implicit-withdraw | labels
accept | targeted ]
```

Syntax Description

no	Negate a command or set its defaults
neighbor	Configure neighbor parameters
vrf	(Optional) VRF Routing/Forwarding instance information
<i>vrf-name</i>	(Optional) VPN Routing/Forwarding instance name
<i>vrf-known-name</i>	(Optional) Known VRF name
<i>ipaddr</i>	IP address for LDP neighbor
implicit-withdraw	Enable LDP Implicit Withdraw Label
labels	Configure label binding exchange controls
accept	Specify label bindings to accept
<i>px-list</i>	Name of prefix list
targeted	Establish targeted session

Command Mode

- /exec/configure/ldp

neighbor

[no] neighbor { <neighbor-id> | <ipv6-neighbor-id> } [remote-as { <asn> | external | internal }]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-id</i>	IP address of the neighbor
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type

Command Mode

- /exec/configure/router-bgp

neighbor

[no] neighbor { <neighbor-id> | <ipv6-neighbor-id> } [remote-as { <asn> | external | internal }]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-id</i>	IP address of the neighbor
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

```
[no] neighbor { <neighbor-prefix> | <ipv6-neighbor-prefix> } [ remote-as [ { <asn> | external | internal } | route-map <rmap-name> ] ]
```

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-prefix</i>	IP prefix for neighbors
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match prefix peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp

neighbor

[no] neighbor { <neighbor-prefix> | <ipv6-neighbor-prefix> } [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>neighbor-prefix</i>	IP prefix for neighbors
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match prefix peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-vrf

neighbor

[no] neighbor <interface> [remote-as [{ <asn> | external | internal } | route-map <rmap-name>]]

Syntax Description

no	(Optional) Negate a command or set its defaults
neighbor	Configure a BGP neighbor
<i>interface</i>	Interface name for BGP interface peering
remote-as	(Optional) Specify Autonomous System Number of the neighbor
<i>asn</i>	(Optional) Autonomous System Number
external	(Optional) eBGP session type
internal	(Optional) iBGP session type
route-map	(Optional) Route-map to match interface peer AS number
<i>rmap-name</i>	(Optional) Route-map name

Command Mode

- /exec/configure/router-bgp

nemo config address port interval

[no] nemo config address <ip_address> port <portnum> interval <interval-num>

Syntax Description

no	(Optional) Negate a command or set its defaults
nemo	Nemo switch onboarding enabler
config	Configure Nemo for switch onboarding
address	IP address of the Nemo platform
<i>ip_address</i>	IP Address
port	Port number of the Nemo platform
<i>portnum</i>	Port number
interval	Config interval in millisecond
<i>interval-num</i>	Config interval in millisecond

Command Mode

- /exec/configure

net

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/router-isis/router-isis-vrf-common

net

[no] net <net>

Syntax Description

no	(Optional) Negate a command or set its defaults
net	Configure Network Entity Title for IS-IS
<i>net</i>	NET in form of XX.XXXX.XXXX[.00]

Command Mode

- /exec/configure/otv-isis

network

[no] network <ipv6-prefix> [route-map <rmap-name> | summarize] +

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Configure an IPv6 prefix to advertise
route-map	(Optional) Apply route-map to modify attributes
<i>rmap-name</i>	(Optional) Route-map name
summarize	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv6 /exec/configure/router-bgp/router-bgp-vrf-af-ipv6

network

[no] network { <ip-addr> mask <ip-mask> | <ip-prefix> } [route-map <rmap-name> | summarize | evpn] +

Syntax Description

no	(Optional) Negate a command or set its defaults
network	Configure an IP prefix to advertise
<i>ip-addr</i>	IP network to advertise
mask	Configure the mask of the IP prefix to advertise
<i>ip-mask</i>	Dotted 4-octet mask
<i>ip-prefix</i>	IP prefix in CIDR format
route-map	(Optional) Apply route-map to modify attributes
<i>rmap-name</i>	(Optional) Route-map name
summarize	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
evpn	(Optional) Only advertise route towards evpn side

Command Mode

- /exec/configure/router-bgp/router-bgp-af-ipv4 /exec/configure/router-bgp/router-bgp-vrf-af-ipv4

next-hop-self

[no | default] next-hop-self [all]

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-self	Set our address as nexthop (non-reflected)
all	(Optional) Set our address as nexthop for all routes

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpn4
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-vpn6
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-mdt

next-hop-third-party

[no | default] next-hop-third-party

Syntax Description

no	(Optional) Negate a command or set its defaults
default	(Optional) Inherit values from a peer template
next-hop-third-party	Compute a third-party nexthop if possible

Command Mode

- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv4-label
- /exec/configure/router-bgp/router-bgp-neighbor/router-bgp-neighbor-af-ipv6-label

nexthop load-balance egress multisite

[no] nexthop load-balance egress multisite

Syntax Description

no	(Optional) Negate a command or set its defaults
nexthop	Next hop egress load balancing that are specific to multisite
load-balance	load-balance
egress	egress
multisite	multisite routes

Command Mode

- /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn

nexthop route-map

[no] nexthop route-map <rmap-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
nexthop	Nexthop tracking
route-map	Route map for valid nexthops
<i>rmap-name</i>	Route-map name

Command Mode

- /exec/configure/router-bgp/router-bgp-af /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn
/exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-ipv4-mvpn
/exec/configure/router-bgp/router-bgp-af-ipv6-mvpn /exec/configure/router-bgp/router-bgp-af-ipv4-mdt
/exec/configure/router-bgp/router-bgp-af-l2vpn-vpls

nexthop suppress-default-resolution

[no] nexthop suppress-default-resolution

Syntax Description

no	(Optional) Negate a command or set its defaults
nexthop	Nexthop resolution options
suppress-default-resolution	Prohibit use of default route for nexthop address resolution

Command Mode

- /exec/configure/router-bgp

nexthop trigger-delay critical non-critical

```
{ nexthop trigger-delay critical <criticaldelay> non-critical <noncriticaldelay> } | { no nexthop trigger-delay }
}
```

Syntax Description

no	Negate a command or set its defaults
nexthop	Nexthop tracking
trigger-delay	Set the delay to trigger nexthop tracking
critical	Nexthop changes affecting reachability
non-critical	Other nexthop changes
<i>noncriticaldelay</i>	Delay value (milliseconds)
<i>criticaldelay</i>	Delay value (milliseconds)

Command Mode

- /exec/configure/router-bgp/router-bgp-af /exec/configure/router-bgp/router-bgp-af-ipv4-mdt /exec/configure/router-bgp/router-bgp-af-ipv6-mdt /exec/configure/router-bgp/router-bgp-af-ipv4-vpnv4 /exec/configure/router-bgp/router-bgp-af-ipv6-vpnv6 /exec/configure/router-bgp/router-bgp-af-link-state /exec/configure/router-bgp/router-bgp-af-l2vpn-vpls /exec/configure/router-bgp/router-bgp-af-ipv4-mvpn /exec/configure/router-bgp/router-bgp-af-ipv6-mvpn /exec/configure/router-bgp/router-bgp-af-l2vpn-evpn

ngoam authentication-key

{ ngoam authentication-key <value> } | { no ngoam authentication-key [<value>] }

Syntax Description

no	Negate a command or set its defaults
ngoam	Configure ngoam
authentication-key	Ngoam authentication-key
<i>value</i>	authentication key

Command Mode

- /exec/configure

ngoam connect-check

[no] ngoam connect-check <id>

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
connect-check	Configure ngoam oam connectivity check
<i>id</i>	connect check id

Command Mode

- /exec/configure

ngoam install acl

[no] ngoam install acl

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
install	Ngoam install
acl	Ngoam install acl

Command Mode

- /exec/configure

ngoam loop-detection

[no] ngoam loop-detection

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
loop-detection	Configure Loop Detection

Command Mode

- /exec/configure

ngoam loop-detection bringup vlan

```
ngoam loop-detection bringup { vlan <vlan-range> } [ port <port-range> ]
```

Syntax Description

ngoam	Configure ngoam
loop-detection	Configure Loop Detection
bringup	Bringup the ports,if disabled
vlan	Vlan
port	(Optional) Ports to bringup if disabled
<i>vlan-range</i>	vlan range max span 1024, Example: 2000-3000,400,500
<i>port-range</i>	(Optional) Interface for loop detection

Command Mode

- /exec

ngoam loop-detection probe vlan

```
ngoam loop-detection probe { vlan <vlan-range> } [ port <port-range> ]
```

Syntax Description

ngoam	Configure ngoam
loop-detection	Configure Loop Detection
probe	Probe for loop detection
vlan	Start probing on vlan for loop detection
port	(Optional) start probing on port for loop detection
<i>vlan-range</i>	vlan range max span 1024, Example: 2000-3000,400,500
<i>port-range</i>	(Optional) Interface for loop detection

Command Mode

- /exec

ngoam profile

[no] ngoam profile <profile-id>

Syntax Description

no	(Optional) Negate a command or set its defaults
ngoam	Configure ngoam
profile	Configure ngoam oam profile
<i>profile-id</i>	ngoam profile id

Command Mode

- /exec/configure

ngoam xconnect hb-interval

{ ngoam xconnect hb-interval <ms> } | { no ngoam xconnect hb-interval [<ms>] }

Syntax Description

no	Negate a command or set its defaults
ngoam	Configure ngoam
xconnect	Configure xconnect parameters
hb-interval	Configure xconnect heartbeat interval
<i>ms</i>	interval in ms, 3 failures triggers failure default is 190

Command Mode

- /exec/configure

no-more

| no-more

Syntax Description

	Pipe command output to filter
no-more	Turn-off pagination for command output

Command Mode

- /output

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/ipacl /exec/configure/ipv6acl

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/arpacl /exec/configure/ipgroup /exec/configure/ipv6group /exec/configure/portgroup /exec/configure/timerange

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/macac1

no

[no] <seqno>

Syntax Description

no	Negate a command or set its defaults
<i>seqno</i>	Sequence number

Command Mode

- /exec/configure/mplsac1

no

```
{ [ <seqno> ] | no } <permitdeny> { { { { ethertype <ethertypeid> } | { ip | <proto> | <ip_other_proto> } {
<src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp
<src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host>
} | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ fragments ] | [ log ] | [ telemetry_queue ] | [ telemetry_path
] | [ time-range <time_range_name> ] | all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } | { udf
{ <udf_name> <udf_val> <udf_mask> } + } ] } + [ [ [ fragments ] | [ log ] | [ telemetry_queue ] | [ telemetry_path
] | [ time-range <time_range_name> ] | all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num>
} | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + [ capture session <session-id> ] } } [ vlan <vlanid>
| ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ { udf { <udf_name> <udf_val>
<udf_mask> } + } ] | { udf { <udf_name> <udf_val> <udf_mask> } + } } { [ <action> <actionid> ] } + [
load-share ] { [ <action> <actionid> ] } + [ { set-vlan <wf_set_vlan_actionid> | strip-vlan ] [ log ] [ wideflow
[ srcmac { <wfsrc_any> | { <wfsrc_addr> <wfsrc_wild> } } ] [ dstmac { <wfdst_any> | { <wfdst_addr>
<wfdst_wild> } } ] [ vlan <wf_vlan> ] ] | { [ <action> <actionid> ] } } + [ telemetry_queue ] | { [ <action>
<actionid> ] } } + [ telemetry_path ] [ all ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
ethertype	Configure match based on ethertype
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
ip	Any IP protocol
<i>proto</i>	A protocol number
<i>ip_other_proto</i>	ip_other_proto
<i>src_any</i>	Any
<i>src_addr</i>	Source network address

<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled

all	(Optional) Filter all traffic (data + control) that matches this rule
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
ttl	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list
set-vlan	(Optional) tag vlan value for traffic egressing via redirect ports(s)
<i>wf_set_vlan_actionid</i>	(Optional) VLAN number
strip-vlan	(Optional) send vlan untagged packet from redirect port(s)
wideflow	(Optional) flow redirect ACL options, NDB ACL special NXAPI options
srmac	(Optional) Source MAC Address
<i>wfsrc_any</i>	(Optional) Any
<i>wfsrc_addr</i>	(Optional) Source MAC address

<i>wfsrc_wild</i>	(Optional) Source wildcard bits
<i>dstmac</i>	(Optional) Destination MAC Address
<i>wfdst_any</i>	(Optional) Any
<i>wfdst_addr</i>	(Optional) Destination MAC address
<i>wfdst_wild</i>	(Optional) Destination wildcard bits
<i>vlan</i>	(Optional) Vlan number
<i>wf_vlan</i>	(Optional) VLAN number

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { ethertype <ethertypeid> } | { <proto_tcp> { { { <src_any> | {
<src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name>
} } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> |
<src_port1_str> } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> } ] { <dst_any> | {
<dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name>
} } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> |
<dst_port1_str> } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> } ] { { [ urg | ack |
psh | rst | syn | fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name>
] [ all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [
dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { http-method { <opt_num> | <opt_str> } } | { tcp-option-length
<tcp_opt_len> } | { tcp-flags-mask <tcp_flags_mask> } | { ttl <ttl_num> } } ] } + [ { [ urg | ack | psh | rst | syn
| fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] |
packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } |
{ precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + ] { { udf { <udf_name> <udf_val>
<udf_mask> } + } ] } | { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host>
} | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { { [ [ fragments ] | [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length { <plen_op>
<plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + ] { [ [ fragments ] | [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length { <plen_op>
<plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num>
| <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } + } ] } + } } } } [ vlan
<vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + { { [ urg | ack | psh | rst
| syn | fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all
] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [ dscp-mask
] <dscp_mask> ] | <dscp_str> } } | { http-method { <opt_num> | <opt_str> } } | { tcp-option-length
<tcp_opt_len> } | { tcp-flags-mask <tcp_flags_mask> } | { ttl <ttl_num> } ] } + [ { [ urg | ack | psh | rst | syn
| fin | established | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] |
packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } |
{ precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + ] { { udf { <udf_name> <udf_val>
<udf_mask> } + } ] [ capture session <session-id> ] { [ <action> <actionid> ] } + [ load-share ] { [ <action>
<actionid> ] } + [ set-vlan <wf_set_vlan_actionid> ] | strip-vlan ] [ log ] [ wideflow [ srcmac { <wfsrc_any>
| { <wfsrc_addr> <wfsrc_wild> } } ] [ dstmac { <wfdst_any> | { <wfdst_addr> <wfdst_wild> } } ] [ vlan
<wf_vlan> ] ] ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
ethertype	Configure match based on ethertype
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface

<i>vlan_priority</i>	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_tcp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) TCP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) TCP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) TCP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix

<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) TCP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) TCP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) TCP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled

all	(Optional) Filter all traffic (data + control) that matches this rule
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
ttl	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
tcp-option-length	(Optional) Specify TCP Options size
<i>tcp_opt_len</i>	(Optional) TCP option length (multiples of 4 bytes)
tcp-flags-mask	(Optional) Specify TCP Flags
<i>tcp_flags_mask</i>	(Optional) TCP flags mask
http-method	(Optional) Match packets based on http-method
<i>opt_num</i>	(Optional) http_option value
<i>opt_str</i>	(Optional) http_option_param
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
urg	(Optional) Match on the URG bit
ack	(Optional) Match on the ACK bit
psh	(Optional) Match on the PSH bit
rst	(Optional) Match on the RST bit
syn	(Optional) Match on the SYN bit

<i>fin</i>	(Optional) Match on the FIN bit
<i>established</i>	(Optional) Match established connections
<i>udf</i>	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-prot: <1-65535> redirect_all: Ethernet1/1,port-channel1
<i>load-share</i>	(Optional) load share among the ports specified in redirect list
<i>set-vlan</i>	(Optional) tag vlan value for traffic egressing via redirect ports(s)
<i>wf_set_vlan_actionid</i>	(Optional) VLAN number
<i>strip-vlan</i>	(Optional) send vlan untagged packet from redirect port(s)
<i>wideflow</i>	(Optional) flow redirect ACL options, NDB ACL special NXAPI options
<i>srcmac</i>	(Optional) Source MAC Address
<i>wfsrc_any</i>	(Optional) Any
<i>wfsrc_addr</i>	(Optional) Source MAC address
<i>wfsrc_wild</i>	(Optional) Source wildcard bits
<i>dstmac</i>	(Optional) Destination MAC Address
<i>wfdst_any</i>	(Optional) Any
<i>wfdst_addr</i>	(Optional) Destination MAC address
<i>wfdst_wild</i>	(Optional) Destination wildcard bits
<i>vlan</i>	(Optional) Vlan number
<i>wf_vlan</i>	(Optional) VLAN number

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] no } <permitdeny> { { ethertype <ethertypeid> } | { <proto_udp> { { { <src_any> | {
<src_addr><src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name>
} } [ { { <src_port_op> { <src_port0> | <src_port0_str> } } | { <src_port_range> { <src_port1> |
<src_port1_str> } } { <src_port2> | <src_port2_str> } } | src_portgroup <src_port_group> } ] } <dst_any> | {
<dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name>
} } [ { { <dst_port_op> { <dst_port0> | <dst_port0_str> } } | { <dst_port_range> { <dst_port1> |
<dst_port1_str> } } { <dst_port2> | <dst_port2_str> } } | dst_portgroup <dst_port_group> } ] } { [ [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length { <plen_op>
<plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } | { ttl <ttl_num> } } ] } + [ [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name>
] [ all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str>
} } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } } ] } + [ { udf { <udf_name> <udf_val>
<udf_mask> } } + ] [ nve vni <vni-id> ] } | { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | {
src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } } { <dst_any> | { <dst_addr> <dst_wild>
} | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } } { [ [ fragments
] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length {
<plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask>
] | <dscp_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } } + ] } ] } + [ [ [ fragments
] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length {
<plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence {
<prec_num> | <prec_str> } } | { ttl <ttl_num> } | { udf { <udf_name> <udf_val> <udf_mask> } } + ] } ] } +
} } [ nve vni <vni-id> ] } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority
<vlanpriorityid> ] + { [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [
all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [
dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } } ] } + [ [ [ log ] [ telemetry_queue ] [
telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length { <plen_op> <plen0> | <plen_range>
<plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl
<ttl_num> } } ] } + [ { udf { <udf_name> <udf_val> <udf_mask> } } + ] [ capture session <session-id> ] {
[ <action> <actionid> ] } + [ load-share ] { [ <action> <actionid> ] } + [ { set-vlan <wf_set_vlan_actionid>
} | strip-vlan ] [ log ] [ wideflow [ srcmac { <wfsrc_any> | { <wfsrc_addr> <wfsrc_wild> } } ] [ dstmac {
<wfdst_any> | { <wfdst_addr> <wfdst_wild> } } ] [ vlan <wf_vlan> ] ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
ethertype	Configure match based on ethertype
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value

<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>proto_udp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) UDP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) UDP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) UDP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address

<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) UDP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) UDP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) UDP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>all</i>	(Optional) Filter all traffic (data + control) that matches this rule
<i>time-range</i>	(Optional) Specify a time range

<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
ttl	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
nve	(Optional) VNI ID <0-16777215>
vni	(Optional) VNI ID <0-16777215>
<i>vni-id</i>	(Optional) VNI ID <0-16777215>
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list
set-vlan	(Optional) tag vlan value for traffic egressing via redirect ports(s)
<i>wf_set_vlan_actionid</i>	(Optional) VLAN number
strip-vlan	(Optional) send vlan untagged packet from redirect port(s)
wideflow	(Optional) flow redirect ACL options, NDB ACL special NXAPI options
srcmac	(Optional) Source MAC Address
<i>wfsrc_any</i>	(Optional) Any

<i>wfsrc_addr</i>	(Optional) Source MAC address
<i>wfsrc_wild</i>	(Optional) Source wildcard bits
<i>dstmac</i>	(Optional) Destination MAC Address
<i>wfdst_any</i>	(Optional) Any
<i>wfdst_addr</i>	(Optional) Destination MAC address
<i>wfdst_wild</i>	(Optional) Destination wildcard bits
<i>vlan</i>	(Optional) Vlan number
<i>wf_vlan</i>	(Optional) VLAN number

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_igmp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr>
<dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [
[ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | <igmp_num> |
packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { dscp { <dscp_num> [ [ dscp-mask
] <dscp_mask> ] | <dscp_str> } } ] + [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] | <igmp_str> | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] + [ [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | <igmp_num> | packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence
{ <prec_num> | <prec_str> } } ] + [ [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] | <igmp_str> | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } ] + } } | { {
<src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp
<src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host>
} | { dst_key_addrgrp <dst_addrgrp_name> } } { [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path
] [ time-range <time_range_name> ] [ all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { ttl <ttl_num> } ] } + |
{ [ [ fragments ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] |
packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } | { tos { <tos_num> | <tos_str> } } |
{ precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } ] } + } } [ capture session <session-id> ] { [
<action> <actionid> ] } + [ load-share ] { [ <action> <actionid> ] } + [ set-vlan <wf_set_vlan_actionid> ]
| strip-vlan ] [ log ] [ wideflow [ srcmac { <wfsrc_any> | { <wfsrc_addr> <wfsrc_wild> } } ] [ dstmac {
<wfdst_any> | { <wfdst_addr> <wfdst_wild> } } ] [ vlan <wf_vlan> ] ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_igmp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
src_key_host	A single source host
<i>src_host</i>	Source address
src_key_addrgrp	Source address group
<i>src_addrgrp_name</i>	Address group name

<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>all</i>	(Optional) Filter all traffic (data + control) that matches this rule
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range

<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>ttl</i>	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>igmp_num</i>	(Optional) IGMPv1 message type
<i>igmp_str</i>	(Optional) IGMP type
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
<i>load-share</i>	(Optional) load share among the ports specified in redirect list
<i>set-vlan</i>	(Optional) tag vlan value for traffic egressing via redirect ports(s)
<i>wf_set_vlan_actionid</i>	(Optional) VLAN number
<i>strip-vlan</i>	(Optional) send vlan untagged packet from redirect port(s)
<i>widelflow</i>	(Optional) flow redirect ACL options, NDB ACL special NXAPI options
<i>srcmac</i>	(Optional) Source MAC Address
<i>wfsrc_any</i>	(Optional) Any
<i>wfsrc_addr</i>	(Optional) Source MAC address
<i>wfsrc_wild</i>	(Optional) Source wildcard bits
<i>dstmac</i>	(Optional) Destination MAC Address
<i>wfdst_any</i>	(Optional) Any
<i>wfdst_addr</i>	(Optional) Destination MAC address
<i>wfdst_wild</i>	(Optional) Destination wildcard bits
<i>vlan</i>	(Optional) Vlan number
<i>wf_vlan</i>	(Optional) VLAN number

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { { ethertype <ethertypeid> } | { <proto_icmp> { { { <src_any> | {
<src_addr><src_wild> } | <src_prefix> | { src_key_host<src_host> } | { src_key_addrgrp <src_addrgrp_name>
} } } { <dst_any> | { <dst_addr><dst_wild> } | <dst_prefix> | { dst_key_host<dst_host> } | { dst_key_addrgrp
<dst_addrgrp_name> } } } { [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name>
] [ all ] | { <icmp_type> [ <icmp_code> ] } | packet-length { <plen_op> <plen0> | <plen_range> <plen1>
<plen2> } } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } } ] + | [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | <icmp_str> | packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask>
] | <dscp_str> } } } ] + | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all
] | { <icmp_type> [ <icmp_code> ] } | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2>
} } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } } ] + | [ log ] [
telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | <icmp_str> | packet-length
{ <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } | { tos { <tos_num> | <tos_str> } } | { precedence
{ <prec_num> | <prec_str> } } } ] + } | { { <src_any> | { <src_addr><src_wild> } | <src_prefix> | {
src_key_host<src_host> } | { src_key_addrgrp <src_addrgrp_name> } } } { <dst_any> | { <dst_addr><dst_wild>
} | <dst_prefix> | { dst_key_host<dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } } { { [ fragments
] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] | packet-length {
<plen_op> <plen0> | <plen_range> <plen1> <plen2> } } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask>
] | <dscp_str> } } } | { ttl <ttl_num> } } } ] + | { [ [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [
time-range <time_range_name> ] [ all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2>
} } | { tos { <tos_num> | <tos_str> } } | { precedence { <prec_num> | <prec_str> } } | { ttl <ttl_num> } } } ] +
} } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture
session <session-id> ] [ [ <action> <actionid> ] ] + [ load-share ] [ { <action> <actionid> } ] + [ { set-vlan
<wf_set_vlan_actionid> } | strip-vlan ] [ log ] [ wideflow [ srmac { <wfsrc_any> | { <wfsrc_addr>
<wfsrc_wild> } } ] [ dstmac { <wfdst_any> | { <wfdst_addr> <wfdst_wild> } } ] [ vlan <wf_vlan> ] ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
ethertype	Configure match based on ethertype
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
<i>ethertypeid</i>	Configure the ethertype value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority

<i>proto_icmp</i>	Protocol
<i>src_any</i>	Any
<i>src_addr</i>	Source network address
<i>src_wild</i>	Source wildcard bits
<i>src_prefix</i>	Source network prefix
<i>src_key_host</i>	A single source host
<i>src_host</i>	Source address
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination network address
<i>dst_wild</i>	Destination wildcard bits
<i>dst_prefix</i>	Destination network prefix
<i>dst_key_host</i>	A single destination host
<i>dst_host</i>	Destination address
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>tos</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_num</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>tos_str</i>	THIS KEYWORD OR VARIABLE IS NOT SUPPORTED
<i>precedence</i>	(Optional) Match packets with given precedence value
<i>prec_num</i>	(Optional) Precedence value
<i>prec_str</i>	(Optional) Precedence label
<i>fragments</i>	(Optional) Check non-initial fragments

log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
all	(Optional) Filter all traffic (data + control) that matches this rule
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
ttl	(Optional) Match Packets with a given TTL value
<i>ttl_num</i>	(Optional)
<i>icmp_type</i>	(Optional) ICMP message type
<i>icmp_code</i>	(Optional) ICMP message code
<i>icmp_str</i>	(Optional) ICMP label
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>action</i>	(Optional) Action
<i>actionid</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-PROTO: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list
set-vlan	(Optional) tag vlan value for traffic egressing via redirect ports(s)
<i>wf_set_vlan_actionid</i>	(Optional) VLAN number
strip-vlan	(Optional) send vlan untagged packet from redirect port(s)
widelflow	(Optional) flow redirect ACL options, NDB ACL special NXAPI options
srcmac	(Optional) Source MAC Address

<i>wfsrc_any</i>	(Optional) Any
<i>wfsrc_addr</i>	(Optional) Source MAC address
<i>wfsrc_wild</i>	(Optional) Source wildcard bits
<i>dstmac</i>	(Optional) Destination MAC Address
<i>wfdst_any</i>	(Optional) Any
<i>wfdst_addr</i>	(Optional) Destination MAC address
<i>wfdst_wild</i>	(Optional) Destination wildcard bits
<i>vlan</i>	(Optional) Vlan number
<i>wf_vlan</i>	(Optional) VLAN number

Command Mode

- /exec/configure/ipacl

no

```
{ [ <seqno> ] | no } <permitdeny> { { ipv6 | <proto> | <ipv6_other_proto> } { <src_any> | { <src_addr>
<src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } {
<dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp
<dst_addrgrp_name> } } { [ { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] [ {
flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ {
udf { <udf_name> <udf_val> <udf_mask> } + } ] } + [ vlan <vlanid> | ingress_intf { <intfid> | <intfname>
} | vlan_priority <vlanpriorityid> ] + [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] [ capture session
<session-id> ] [ { <actionv6> <actionidv6> } ] + [ load-share ] [ { <actionv6> <actionidv6> } ] [ log ] [ { udf
{ <udf_name> <udf_val> <udf_mask> } + } ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
ipv6	Any IPV6 protocol
<i>proto</i>	A protocol number
<i>ipv6_other_proto</i>	ipv6_other_proto
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
src_key_host	A single source host
src_key_addrgrp	Source address group

<i>src_addrgrp_name</i>	Address group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
<i>flow-label</i>	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
<i>fragments</i>	(Optional) Check non-initial fragments
<i>log</i>	(Optional) Log matches against this entry
<i>telemetry_queue</i>	(Optional) Flow of interest for BDC/HDC
<i>telemetry_path</i>	(Optional) IPT enabled
<i>all</i>	(Optional) Filter all traffic (data + control) that matches this rule
<i>time-range</i>	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
<i>packet-length</i>	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
<i>capture</i>	(Optional) Enable packet capture on this filter for session
<i>session</i>	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6

<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] no } <permitdeny> <proto_tcp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] [ { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } ] | [ { flow-label <flow_num> } ] | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] | [ urg | ack | psh | rst | syn | fin | established ] | { tcp-flags-mask <tcp_flags_mask>
} ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] ] + [ { udf { <udf_name>
<udf_val> <udf_mask> } + } ] | { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host
<src_host> } | { src_key_addrgrp <src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } |
<dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } { [ { dscp {
<dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] | [ { flow-label <flow_num> } ] [ fragments
] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] [ packet-length {
<plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ { udf { <udf_name> <udf_val> <udf_mask> } +
} ] ] + } ] [ vlan <vlanid> | ingress_intf { <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture
session <session-id> ] [ [ <actionv6> <actionidv6> ] ] [ [ <actionv6> <actionidv6> ] ] + [ load-share ] [ log
]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_tcp</i>	Protocol
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority

<i>src_any</i>	Any
<i>src_key_host</i>	A single source host
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) TCP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) TCP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) TCP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) TCP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) TCP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) TCP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask

dscp-mask	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
all	(Optional) Filter all traffic (data + control) that matches this rule
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
tcp-flags-mask	Specify TCP Flags
<i>tcp_flags_mask</i>	TCP flags mask
urg	(Optional) Match on the URG bit
ack	(Optional) Match on the ACK bit
psh	(Optional) Match on the PSH bit
rst	(Optional) Match on the RST bit
syn	(Optional) Match on the SYN bit
fin	(Optional) Match on the FIN bit
established	(Optional) Match established connections
capture	(Optional) Enable packet capture on this filter for session

<code>session</code>	(Optional) Session ID <1-48> for this session
<code>session-id</code>	(Optional) Session ID <1-48> for this session
<code>actionv6</code>	(Optional) ActionV6
<code>actionidv6</code>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
<code>load-share</code>	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] no } <permitdeny> <proto_udp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] [ { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } ] [ { flow-label <flow_num> } ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] ] + [
{ udf { <udf_name> <udf_val> <udf_mask> } + } ] [ nve vni <vni-id> ] | { { <src_any> | { <src_addr>
<src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } {
<dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp
<dst_addrgrp_name> } } { [ { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } ] [ {
flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ {
udf { <udf_name> <udf_val> <udf_mask> } + } ] + } ] [ nve vni <vni-id> ] [ vlan <vlanid> | ingress_intf
{ <intfid> | <intfname> } | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] [ { <actionv6>
<actionidv6> } ] } [ <actionv6> <actionidv6> } ] + [ load-share ] [ log ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_udp</i>	Protocol
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority

<i>src_any</i>	Any
<i>src_key_host</i>	A single source host
<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) UDP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) UDP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) UDP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) UDP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) UDP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) UDP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask

dscp-mask	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value
<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
all	(Optional) Filter all traffic (data + control) that matches this rule
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
nve	(Optional) VNI ID <0-16777215>
vni	(Optional) VNI ID <0-16777215>
<i>vni-id</i>	(Optional) VNI ID <0-16777215>
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_sctp> { { { <src_any> | { <src_addr> <src_wild> } | <src_prefix>
| { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } [ { { <src_port_op> { <src_port0>
| <src_port0_str> } } | { <src_port_range> { <src_port1> | <src_port1_str> } { <src_port2> | <src_port2_str>
} } | src_portgroup <src_port_group> } ] { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | {
dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name> } } [ { { <dst_port_op> { <dst_port0>
| <dst_port0_str> } } | { <dst_port_range> { <dst_port1> | <dst_port1_str> } { <dst_port2> | <dst_port2_str>
} } | dst_portgroup <dst_port_group> } ] [ { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str>
} } ] [ { flow-label <flow_num> } ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] } +
} | { { <src_any> | { <src_addr> <src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp
<src_addrgrp_name> } } { <dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host>
} | { dst_key_addrgrp <dst_addrgrp_name> } } { [ { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] |
<dscp_str> } } ] [ { flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [
time-range <time_range_name> ] [ all ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2>
} ] ] [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] + } [ vlan <vlanid> | ingress_intf { <intfid> |
<intfname> } | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_sctp</i>	Protocol
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any
src_key_host	A single source host

<i>src_key_addrgrp</i>	Source address group
<i>src_addrgrp_name</i>	Address group name
<i>src_port_op</i>	(Optional) Port operator
<i>src_port_range</i>	(Optional) Port range
<i>src_port0</i>	(Optional) Port number
<i>src_port0_str</i>	(Optional) SCTP port
<i>src_port1</i>	(Optional) Port number
<i>src_port1_str</i>	(Optional) SCTP port
<i>src_port2</i>	(Optional) Port number
<i>src_port2_str</i>	(Optional) SCTP port
<i>src_portgroup</i>	(Optional) src port group
<i>src_port_group</i>	(Optional) Port group name
<i>dst_any</i>	Any
<i>dst_key_host</i>	A single destination host
<i>dst_key_addrgrp</i>	Destination address group
<i>dst_addrgrp_name</i>	Address group name
<i>dst_port_op</i>	(Optional) Port operator
<i>dst_port_range</i>	(Optional) Port range
<i>dst_port0</i>	(Optional) Port number
<i>dst_port0_str</i>	(Optional) SCTP port
<i>dst_port1</i>	(Optional) Port number
<i>dst_port1_str</i>	(Optional) SCTP port
<i>dst_port2</i>	(Optional) Port number
<i>dst_port2_str</i>	(Optional) SCTP port
<i>dst_portgroup</i>	(Optional) dst port group
<i>dst_port_group</i>	(Optional) Port group name
<i>dscp</i>	(Optional) Match packets with given dscp value and Mask
<i>dscp-mask</i>	(Optional) DSCP wildcard Mask
<i>dscp_num</i>	(Optional) Differentiated services codepoint value

<i>dscp_mask</i>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<i>dscp_str</i>	(Optional) Differentiated services codepoint label
flow-label	(Optional) Flow label
<i>flow_num</i>	(Optional) Flow label value
fragments	(Optional) Check non-initial fragments
log	(Optional) Log matches against this entry
telemetry_queue	(Optional) Flow of interest for BDC/HDC
telemetry_path	(Optional) IPT enabled
all	(Optional) Filter all traffic (data + control) that matches this rule
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
packet-length	(Optional) Match packets based on layer 3 packet length
<i>plen_op</i>	(Optional) Packet-length operator
<i>plen_range</i>	(Optional) Packet-length range
<i>plen0</i>	(Optional) Packet length
<i>plen1</i>	(Optional) Lower packet length
<i>plen2</i>	(Optional) Higher packet length
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session

Command Mode

- /exec/configure/ipv6acl

no

```
{ [ <seqno> ] | no } <permitdeny> <proto_icmpv6> { { { { <src_any> | { <src_addr> <src_wild> } |
<src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } } { <dst_any> | {
<dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp <dst_addrgrp_name>
} } } { { { <icmpv6_type> [ <icmpv6_code> ] } | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] |
<dscp_str> } } } | { flow-label <flow_num> } } [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] | packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } ] + [
<icmpv6_str> | { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } | { flow-label
<flow_num> } | [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range <time_range_name> ] [ all ] |
packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } } ] + } | { { <src_any> | { <src_addr>
<src_wild> } | <src_prefix> | { src_key_host <src_host> } | { src_key_addrgrp <src_addrgrp_name> } } } {
<dst_any> | { <dst_addr> <dst_wild> } | <dst_prefix> | { dst_key_host <dst_host> } | { dst_key_addrgrp
<dst_addrgrp_name> } } } { { { dscp { <dscp_num> [ [ dscp-mask ] <dscp_mask> ] | <dscp_str> } } } | [ {
flow-label <flow_num> } ] [ fragments ] [ log ] [ telemetry_queue ] [ telemetry_path ] [ time-range
<time_range_name> ] [ all ] [ packet-length { <plen_op> <plen0> | <plen_range> <plen1> <plen2> } ] [ {
udf { <udf_name> <udf_val> <udf_mask> } + } ] + } } [ vlan <vlanid> | ingress_intf { <intfid> | <intfname>
} | vlan_priority <vlanpriorityid> ] + [ capture session <session-id> ] { [ <actionv6> <actionidv6> } ] { [
<actionv6> <actionidv6> ] } + [ load-share ] [ log ] }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>proto_icmpv6</i>	Protocol
vlan	(Optional) Configure match based on vlan
ingress_intf	(Optional) Configure match based on ingress interface
vlan_priority	(Optional) Configure match based on priority
udf	(Optional) User defined field match
<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
<i>vlanid</i>	(Optional) VLAN number
<i>intfid</i>	(Optional) Interface index
<i>intfname</i>	(Optional) Interface name
<i>vlanpriorityid</i>	(Optional) Vlan Priority
<i>src_any</i>	Any

<code>src_key_host</code>	A single source host
<code>src_key_addrgrp</code>	Source address group
<code>src_addrgrp_name</code>	Address group name
<code>dst_any</code>	Any
<code>dst_key_host</code>	A single destination host
<code>dst_key_addrgrp</code>	Destination address group
<code>dst_addrgrp_name</code>	Address group name
<code>dscp</code>	(Optional) Match packets with given dscp value and Mask
<code>dscp-mask</code>	(Optional) DSCP wildcard Mask
<code>dscp_num</code>	(Optional) Differentiated services codepoint value
<code>dscp_mask</code>	(Optional) Differentiated services codepoint mask - 0 to 0x3F
<code>dscp_str</code>	(Optional) Differentiated services codepoint label
<code>flow-label</code>	(Optional) Flow label
<code>flow_num</code>	(Optional) Flow label value
<code>fragments</code>	(Optional) Check non-initial fragments
<code>log</code>	(Optional) Log matches against this entry
<code>telemetry_queue</code>	(Optional) Flow of interest for BDC/HDC
<code>telemetry_path</code>	(Optional) IPT enabled
<code>all</code>	(Optional) Filter all traffic (data + control) that matches this rule
<code>time-range</code>	(Optional) Specify a time range
<code>time_range_name</code>	(Optional) Time range name
<code>packet-length</code>	(Optional) Match packets based on layer 3 packet length
<code>plen_op</code>	(Optional) Packet-length operator
<code>plen_range</code>	(Optional) Packet-length range
<code>plen0</code>	(Optional) Packet length
<code>plen1</code>	(Optional) Lower packet length
<code>plen2</code>	(Optional) Higher packet length
<code>icmpv6_type</code>	(Optional) ICMPv6 message type
<code>icmpv6_code</code>	(Optional) ICMPv6 message code

<i>icmpv6_str</i>	(Optional) ICMPv6 label
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>actionv6</i>	(Optional) ActionV6
<i>actionidv6</i>	(Optional) redirect: Ethernet1/1,port-channel1 set-erspan-dscp: <1-63> set-erspan-gre-proto: <1-65535> redirect_all: Ethernet1/1,port-channel1
load-share	(Optional) load share among the ports specified in redirect list

Command Mode

- /exec/configure/ipv6acl

no

{ [<seqno>] | no } { <addr> <wild> | <prefix> | host <hostaddr> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>addr</i>	A.B.C.D Network address of object-group member
<i>wild</i>	A.B.C.D wildcard
<i>prefix</i>	A.B.C.D/nn Network prefix of the object-group member
host	Host address of the object-group member
<i>hostaddr</i>	A.B.C.D Host address

Command Mode

- /exec/configure/ipgroup

no

{ [<seqno>] | no } { <addr> <wild> | <prefix> | host <hostaddr> }

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
host	Host address of the object-group member

Command Mode

- /exec/configure/ipv6group

no

```
{ [ <seqno> ] | no } { <_port_op> <port0_num> | <_port_range> <port1_num> <port2_num> }
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>_port_op</i>	Port operator
<i>_port_range</i>	Port range
<i>port0_num</i>	Port number
<i>port1_num</i>	Port number
<i>port2_num</i>	Port number

Command Mode

- /exec/configure/portgroup

no

```
{ [ <seqno> ] | no } <permitdeny> { <src_any> | { <src_addr> <src_wild> } } { <dst_any> | { <dst_addr>
<dst_wild> } } [ <mac_proto> | <mac_proto_str> ] [ vlan <vlan> | cos <cos> ] + [ time-range
<time_range_name> ] [ capture session <session-id> ] { [ <macaction> <macactionid> ] } + [ load-share ] {
[ <macaction> <macactionid> ] } + [ { udf { <udf_name> <udf_val> <udf_mask> } + } ] [ all ]
```

Syntax Description

<i>seqno</i>	(Optional) Sequence number
no	Negate a command or set its defaults
<i>permitdeny</i>	Permit/deny
<i>src_any</i>	Any
<i>src_addr</i>	Source MAC address
<i>src_wild</i>	Source wildcard bits
<i>dst_any</i>	Any
<i>dst_addr</i>	Destination MAC address
<i>dst_wild</i>	Destination wildcard bits
<i>mac_proto</i>	(Optional) MAC protocol number
<i>mac_proto_str</i>	(Optional) MAC protocol name
vlan	(Optional) VLAN number
cos	(Optional) CoS value
<i>vlan</i>	(Optional) VLAN number
<i>cos</i>	(Optional) CoS value
time-range	(Optional) Specify a time range
<i>time_range_name</i>	(Optional) Time range name
capture	(Optional) Enable packet capture on this filter for session
session	(Optional) Session ID <1-48> for this session
<i>session-id</i>	(Optional) Session ID <1-48> for this session
<i>macaction</i>	(Optional) MAC ACL Action
<i>macactionid</i>	(Optional) redirect: Ethernet1/1,port-channel1
udf	(Optional) User defined field match

<i>udf_name</i>	(Optional) UDF name
<i>udf_val</i>	(Optional) UDF value to match
<i>udf_mask</i>	(Optional) Mask to apply to UDF value
load-share	(Optional) load share among the ports specified in redirect list
all	(Optional) Filter all traffic (data + control) that matches this rule

Command Mode

- /exec/configure/macac1

no

[no] { userprofile | trustedCert | CRLLookup | user-switch-bind | user-certdn-match | user-pubkey-match }

Syntax Description

no	Negate a command or set its defaults
userprofile	Delete the userprofile
trustedCert	Delete the trustedCert
CRLLookup	Delete the CRLLookup
user-switch-bind	Delete the user-switch-bind
user-certdn-match	Delete the certificate matching
user-pubkey-match	Delete the pubkey matching

Command Mode

- /exec/configure/ldap/search

no

no

Syntax Description

no	Negate a command or set its defaults
----	--------------------------------------

Command Mode

- /exec/configure/vsan-db

node ip

[no] node { ip <ip-addr> | IPv6 <ip-addrv6> }

Syntax Description

no	(Optional) Negate a command or set its defaults
node	ITD node
ip	ITD node IPv4 address
<i>ip-addr</i>	ITD node IP4 prefix in format i.i.i.i
IPv6	ITD node IPv6 address

Command Mode

- /exec/configure/itd-device-group

node ip

[no] node { ip <ip-addr> | IPv6 <ip-addrv6> }

Syntax Description

no	(Optional) Negate a command or set its defaults
node	ITD node
ip	ITD node IPv4 address
<i>ip-addr</i>	ITD node IP4 prefix in format i.i.i.i
IPv6	ITD node IPv6 address

Command Mode

- /exec/configure/itd-session-device-group

npv auto-load-balance disruptive

[no] npv auto-load-balance disruptive

Syntax Description

no	(Optional) Negate a command or set its defaults
npv	Config commands for FC N_port Virtualizer
auto-load-balance	configure auto load balancing among preferred external links
disruptive	enable disruptive auto load balancing among external links

Command Mode

- /exec/configure

npv traffic-map server-interface external-interface

[no] npv traffic-map server-interface <if1> external-interface <interface>

Syntax Description

no	(Optional) Negate a command or set its defaults
npv	Config commands for FC N_port Virtualizer
traffic-map	Configure NPV traffic engineering
server-interface	Configure server interface based traffic engineering
<i>if1</i>	
external-interface	Configure preferred external interface(s)
<i>interface</i>	

Command Mode

- /exec/configure

nsf await-redist-proto-convergence

{ [no] nsf await-redist-proto-convergence }

Syntax Description

no	(Optional) Negate a command or set its defaults
nsf	Non-stop forwarding
await-redist-proto-convergence	Specify whether EIGRP should wait for other protocols to converge before advertising routes

Command Mode

- /exec/configure/router-eigrp/router-eigrp-vrf-common /exec/configure/router-eigrp/router-eigrp-af-common

ntp access-group

[no] ntp access-group { peer | serve-only | serve | query-only } <acl-name>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
access-group	NTP access-group
peer	access-group peer
serve	access-group serve
serve-only	access-group serve-only
query-only	access-group query-only
<i>acl-name</i>	Name of access list

Command Mode

- /exec/configure

ntp access-group match-all

[no] ntp access-group match-all

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
access-group	NTP access-group
match-all	Scan ACLs present in all ntp access groups

Command Mode

- /exec/configure

ntp allow private

```
[no] ntp allow { private | control [ rate-limit <delay> ] }
```

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
allow	Enable/Disable the packets
private	Enable/Disable Private mode packets
control	Enable/Disable Control mode packets
rate-limit	(Optional) Rate-limit the control packets
<i>delay</i>	(Optional) Rate-limit delay (Default 3)

Command Mode

- /exec/configure

ntp authenticate

[no] ntp authenticate

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
authenticate	Enable/Disable authentication

Command Mode

- /exec/configure

ntp authentication-key md5

[no] ntp authentication-key <number> { md5 | aes128cmac } <password> [0 | 7 | 6]

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
authentication-key	NTP authentication key
<i>number</i>	authentication key number (range 1-65535)
md5	Use MD5 authentication scheme.
aes128cmac	Use AES-128-CMAC authentication scheme.
<i>password</i>	Password string. Maximum size is 32 characters for clear text and type 7, 128 characters for type 6.
0	(Optional) Type 0 (clear text) encryption. (default)
7	(Optional) Type 7 encryption.
6	(Optional) Type 6 encryption.

Command Mode

- /exec/configure

ntp logging

[no] ntp logging

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
logging	Enable/Disable logging of NTPD Events

Command Mode

- /exec/configure

ntp master

[no] ntp master [<stratum-no>]

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
master	Act as NTP master clock
<i>stratum-no</i>	(Optional) Stratum number

Command Mode

- /exec/configure

ntp passive

[no] ntp passive

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
passive	NTP passive command

Command Mode

- /exec/configure

ntp peer

[no] ntp peer <host0> [prefer | key <keyid> | use-vrf { <vrf-name> | <vrf-known-name> } | minpoll <minpoll> | maxpoll <maxpoll>] +

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
peer	NTP Peer address
<i>host0</i>	Hostname/IP address of the NTP Peer
prefer	(Optional) Preferred Server
key	(Optional) Keyid to be used while communicating to this server
<i>keyid</i>	(Optional) Value of keyid 1-65535
use-vrf	(Optional) Display per-VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
minpoll	(Optional) Minimum interval to poll a peer
<i>minpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 4]
maxpoll	(Optional) Maximum interval to poll a peer
<i>maxpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 6]

Command Mode

- /exec/configure

ntp server

```
[no] ntp server <host0> [ prefer | key <keyid> | use-vrf { <vrf-name> | <vrf-known-name> } | minpoll <minpoll> | maxpoll <maxpoll> ] +
```

Syntax Description

no	(Optional) Negate a command or set its defaults
ntp	NTP Configuration
server	NTP server address
<i>host0</i>	Hostname/IP address of the NTP Server
prefer	(Optional) Preferred Server
key	(Optional) Keyid to be used while communicating to this server
<i>keyid</i>	(Optional) Value of keyid 1-65535
use-vrf	(Optional) Display per-VRF information
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
minpoll	(Optional) Minimum interval to poll a server
<i>minpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 4]
maxpoll	(Optional) Maximum interval to poll a server
<i>maxpoll</i>	(Optional) Poll interval in secs to a power of 2 [default 6]

Command Mode

- /exec/configure

ntp source-interface

[no] ntp source-interface <interface>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
source-interface	Source interface sending NTP packets
<i>interface</i>	Source interface

Command Mode

- /exec/configure

ntp source

[no] ntp source <ip-addr>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP Configuration
source	Source of NTP packets
<i>ip-addr</i>	IPv4/IPv6 address

Command Mode

- /exec/configure

ntp sync-retry

ntp sync-retry

Syntax Description

ntp	NTP configuration
sync-retry	Retry synchronization with configured servers

Command Mode

- /exec

ntp trusted-key

[no] ntp trusted-key <number>

Syntax Description

no	(Optional) Negate a command or set its default
ntp	NTP configuration
trusted-key	NTP trusted-key
<i>number</i>	trusted-key number

Command Mode

- /exec/configure

nv overlay evpn

[no] nv overlay evpn

Syntax Description

no	(Optional) Negate a command or set its defaults
nv	Command to enable/disable features
overlay	Command to enable/disable features
evpn	Enable/Disable Ethernet VPN (EVPN)

Command Mode

- /exec/configure

nve interface remap-replication-servers

nve interface <nve-if> remap-replication-servers

Syntax Description

nve	Configure NVE information
interface	Interface
<i>nve-if</i>	NVE interface
remap-replication-servers	Remap Replication servers to VNIs

Command Mode

- /exec

nve interface replication-server up

```
nve interface <nve-if> replication-server <rep-addr> { up | down }
```

Syntax Description

nve	Configure NVE information
interface	Interface
<i>nve-if</i>	NVE interface
replication-server	Configure a replication server
<i>rep-addr</i>	Replication Server IP Address
up	mark replication-server up
down	mark replication-server down

Command Mode

- /exec

nve oam mode draft-pang

[no] nve oam mode draft-pang

Syntax Description

no	(Optional) Negate a command or set its defaults
nve	VxLAN functionality
oam	VxLAN OAM functionality
mode	Choose operation mode for OAM
draft-pang	OAM implementation as per Draft Pang

Command Mode

- /exec/configure

nwwn

[no] nwwn <wwn0>

Syntax Description

no	(Optional) Negate a command or set its defaults
nwwn	Node WWN of the platform
<i>wwn0</i>	Node WWN

Command Mode

- /exec/configure/fcs-register/attrib

nwwn vsan

[no] nwwn <wwn0> vsan <i1>

Syntax Description

no	(Optional) Negate a command or set its defaults
nwwn	Device NWWN
<i>wwn0</i>	NWWN of the Device
vsan	VSAN id for device
<i>i1</i>	vsan id

Command Mode

- /exec/configure/dpvm-db

nxapi certificate httpskey keyfile

```
{ nxapi certificate { { httpskey { keyfile <uri0> [ password <passphrase> ] } } | { httpsert { certfile <uri1> } } | { enable } | { trustpoint <trustpoint-name> } | { sudi } } } | { no nxapi certificate { sudi | trustpoint <trustpoint-name> } }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
certificate	Https certificate configuration
httpskey	Https private key
httpsert	Https certificate
keyfile	Https key file
certfile	Https certificate file
password	(Optional) Https encrypted key passphrase
enable	Enable the current certificate
trustpoint	Trustpoint configuration
<i>trustpoint-name</i>	trustpoint name to use for Identity
sudi	sudi configuration
<i>uri0</i>	File containing https private key for the user
<i>passphrase</i>	(Optional) Https encrypted private key passphrase
<i>uri1</i>	File containing https certificate

Command Mode

- /exec/configure

nxapi client certificate authentication

```
{ nxapi client certificate authentication [ <verification-setting> ] } | { no nxapi client certificate authentication }  
}
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
client	Configure NX-API client management properties
certificate	Configure NX-API client certificate authentication functionality
authentication	Enable/Disable client certificate authentication
<i>verification-setting</i>	(Optional) Configure nxapi client-certificate authentication verification restriction setting

Command Mode

- /exec/configure

nxapi http port

```
{ nxapi { http | https } port <s0> } | { no nxapi { http | https } } | { no nxapi { http | https } port <s0> }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
http	Http configuration
https	Https configuration
port	Port number
s0	Port number. Please do not use well-known protocol ports

Command Mode

- /exec/configure

nxapi idle-timeout

[no] nxapi idle-timeout <i0>

Syntax Description

no	(Optional) Negate a command or set its defaults
nxapi	Configure nxapi
idle-timeout	duration until idle session expires
<i>i0</i>	Length of time, in minutes

Command Mode

- /exec/configure

nxapi ssl ciphers weak

```
{ [ no ] nxapi ssl ciphers weak }
```

Syntax Description

no	(Optional) Negate a command or set its defaults
nxapi	Configure nxapi
ssl	Configure ssl parameters
ciphers	Configure allowed ciphers for ssl
weak	Allow weak ciphers

Command Mode

- /exec/configure

nxapi ssl protocols

{ nxapi ssl protocols <prot_string> } | { no nxapi ssl protocols }

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
ssl	Configure ssl parameters
protocols	Configure allowed ssl protocols
<i>prot_string</i>	String of supported protocols, Ex: TLSv1 TLSv1.1 TLSv1.2 TLSv1.3

Command Mode

- /exec/configure

nxapi use-vrf management default

```
{ nxapi use-vrf { management | default | <vrf_name> } } | { no nxapi use-vrf { management | default | <vrf_name> } }
```

Syntax Description

no	Negate a command or set its defaults
nxapi	Configure nxapi
use-vrf	vrf to be used for nxapi communication
management	management vrf
default	default vrf
<i>vrf_name</i>	name of the vrf

Command Mode

- /exec/configure

nxsdk profile

[no] nxsdk profile <nxsdk-profile-name>

Syntax Description

no	(Optional) Negate a command or set its defaults
nxsdk	NXOS SDK
profile	service profile
<i>nxsdk-profile-name</i>	NxSDK service profile name

Command Mode

- /exec/configure

nxsdk remote port

[no] nxsdk remote port <port> [namespace { <vrf-name> | <vrf-known-name> }] [certificate <cert-id>]

Syntax Description

no	(Optional) Negate a command or set its defaults
nxsdk	NXOS SDK
remote	To run NX-SDK service as a remote service
port	Port to accept remote NX-SDK connections
<i>port</i>	Port
namespace	(Optional) Namespace to run the remote server on. Default is Vrf: Default
<i>vrf-name</i>	(Optional) VRF name
<i>vrf-known-name</i>	(Optional) Known VRF name
certificate	(Optional) Specify certificate id to be used for the remote session
<i>cert-id</i>	(Optional) Certificate identification

Command Mode

- /exec/configure

nxsdk service-name

[no] nxsdk service-name <nxsdk-service-name> [profile <nxsdk-profile-name>]

Syntax Description

nxsdk	NXOS SDK
service-name	Complete path and name of file to execute
<i>nxsdk-service-name</i>	Service name
profile	(Optional) Service profile
<i>nxsdk-profile-name</i>	(Optional) Name of the profile

Command Mode

- /exec/configure

