



Extended NAS-Port-Type and NAS-Port Support

Last Updated: April 18, 2012

The Extended NAS-Port-Type and NAS-Port Support feature allows you to identify what service type is taking place on specific ports with non-RADIUS RFC supported types. You have the flexibility to use your own coding mechanism to track users or to track shared resources, such as Ethernet or ATM interfaces, as you identify traffic based on the service type.

RADIUS attributes are used to define specific authentication, authorization, and accounting (AAA) elements in a user profile. NAS-Port-Type (RADIUS IETF attribute 61) indicates the type of physical port the network access server (NAS) is using to authenticate the user. NAS-Port-ID (RADIUS IETF attribute 87) contains a text string that identifies the NAS port that is authenticating the user.

- [Finding Feature Information, page 1](#)
- [Prerequisites for Extended NAS-Port-Type and NAS-Port Support, page 2](#)
- [Information About Extended NAS-Port-Type and NAS-Port Support, page 2](#)
- [How to Configure Extended NAS-Port-Type and NAS-Port Support, page 4](#)
- [Configuration Examples for Extended NAS-Port-Type and NAS-Port Support, page 7](#)
- [Additional References, page 9](#)
- [Feature Information for Extended NAS-Port-Type and NAS-Port Support, page 9](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the Feature Information Table at the end of this document.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Prerequisites for Extended NAS-Port-Type and NAS-Port Support

- The device must have RADIUS and AAA enabled.

Information About Extended NAS-Port-Type and NAS-Port Support

- [Extended NAS-Port-Type \(RADIUS Attribute 61\), page 2](#)
- [NAS-Port \(RADIUS Attribute 5\), page 3](#)
- [Relationship Between NAS-Port-Type \(RADIUS Attribute 61\) and NAS-Port \(RADIUS Attribute 5\), page 3](#)
- [NAS-Port-ID \(RADIUS Attribute 87\), page 4](#)

Extended NAS-Port-Type (RADIUS Attribute 61)

Prior to the attribute 61 extension, attribute 61 allowed you to identify virtual or Ethernet resources only. Now, by enabling the extended attribute 61 you can also do the following:

- Track specific service port information for broadband environments.
- Identify service port type sessions PPP over ATM (PPPoA), PPP over Ethernet (PPPoE) over Ethernet (PPPoEoE), PPPoE over ATM (PPPoEoA), PPPoE over VLAN (PPPoEoVLAN), and PPPoE over Q-in-Q (PPPoEoQinQ) with a corresponding RADIUS value, which allows you to identify physical NAS port types based on service types.
- [Benefits of Using the Extended NAS-Port-Type Attribute, page 2](#)

Benefits of Using the Extended NAS-Port-Type Attribute

The benefits of using the extended attribute 61 are as follows:

- Establishing your own coding scheme to track users on specific physical ports. For example, service providers may want to track customers using shared resources such as Ethernet or ATM interfaces that have virtual LANs (VLANs), stacked VLAN (Q-in-Q), or virtual circuits (VCs) connected to certain customers.
- Allowing additional granularity for subinterfaces such as VLAN, Q-in-Q, VC, or VC ranges by overriding the attribute 61 value to be sent on any session that resides on the port. For example, this capability provides an extra level of detail for service providers in managing their end users and allows for further detail of different customer usage.

The value for the extended 61 attribute can be any number you choose. Customizing your own value is useful when you need to distinguish between NAS port types based on the type of end client using a port. For example, if you want to track mobile clients behind a specific private virtual connection (PVC), you can define your own attribute 61 value for mobile clients.

The non-RFC compliant broadband service port types with their corresponding values that can be set with the extended attribute 61 are shown in the table below.

Table 1 Service Port Types and Corresponding RADIUS Values

Service Port Type	RADIUS Value
Wireless - IEEE 802.16	27
PPPoA	30
PPPoEoA	31
PPPoEoE	32
PPPoEoVLAN	33
PPPoEoQinQ	34

NAS-Port (RADIUS Attribute 5)

NAS-Port (RADIUS attribute 5) indicates the physical NAS port number that is authenticating the user. A logical port can be represented by the virtual path identifier (VPI) and virtual channel identifier (VCI) for an ATM interface, or by the VLAN ID or Q-in-Q ID for an Ethernet interface.

Each platform and service may have different port information, which is relevant to its environment; therefore there is no unique way to populate this attribute. There are four service-specific non configurable formats (**a**, **b**, **c**, and **d**) and one configurable format (**e**) that can be tailored to customer and platform needs.

Format **e** allowed customization of only one global format for all call types on a device, which had limitations for devices that contained multiple services. With the extended attribute 5 support, it is possible to configure a custom format **e** string for any service type based on the value of attribute 61. When building the RADIUS access or accounting request, the encoding routine will apply the specific format **e** string defined for the session of the value of attribute 61.



Note

Setting a specific format **e** string for the value of attribute 61 overrides the default global format **e** string.

Relationship Between NAS-Port-Type (RADIUS Attribute 61) and NAS-Port (RADIUS Attribute 5)

The **radius-server attribute nas-port format** command supports the custom format **e** string with the **type nas-port-type** keyword and argument. The **type** keyword allows you to specify format strings to represent physical port types for any of the extended NAS-Port-Type values.

The relationship between extended attribute 61 and extended attribute 5 support is that the format **e** string chosen by the encoding routine will depend on the value of attribute 61 for the session. If you use the extended attribute 61 values (values 30-34) and want to further customize the NAS port type, configure a different format string.

For example, you can specify the string "SSSSAAAAPPPPIIIIIICCCCCCCCCCCC" for type 30 (all PPPoA ports), and you can also specify string "SSSSAPPPVVVVVVVVVVVVVVVVVVVVVVVVVVVVVV" for type 33 (all PPPoAoVLAN ports). In this case, you can track VPI/VCI-specific information for a PPPoA user and VLAN-specific information for a PPPoEoVLAN user.

**Note**

If you enable the extended attribute 61, format **e** with either type 5 (Virtual) or type 15 (Ethernet) will not function, because these types require an additional value to be set (extended attribute 61 values 30-34).

NAS-Port-ID (RADIUS Attribute 87)

The NAS-Port-ID (RADIUS attribute 87) contains the character text string identifier of the NAS port that is authenticating the user. This text string typically matches the interface description found under the CLI configuration. This attribute is sent by default under IETF attribute 87, it was previously under Cisco vendor-specific-attribute (VSA) Cisco-NAS-Port.

How to Configure Extended NAS-Port-Type and NAS-Port Support

- [Configuring Extended NAS-Port-Type Attribute and NAS-Port Attribute Support, page 4](#)
- [Overriding Global NAS-Port-Type Configuration, page 6](#)

Configuring Extended NAS-Port-Type Attribute and NAS-Port Attribute Support

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **radius-server attribute 61 extended**
4. **radius-server attribute nas-port format *format* [*string*]**
5. **radius-server attribute nas-port format *format* [*string*] [**type** *nas-port-type*]**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable	Enables privileged EXEC mode.
	Example:	
	Device> enable	<ul style="list-style-type: none"> • Enter your password if prompted.

Command or Action	Purpose
<p>Step 5 radius-server attribute nas-port format <i>format</i> [<i>string</i>] [<i>type nas-port-type</i>]</p> <p>Example:</p> <pre>Device(config)# radius-server attribute nas-port format e SSSSAAAAPPPPIIIIIIIICCCCCCCCCC type 30</pre>	<p>Configures a specific service port type for extended attribute 61 support.</p> <p>This command does customize a specific service port type value.</p> <ul style="list-style-type: none"> The <i>format</i> argument indicates the specific NAS port format. The <i>string</i> argument represents all of a specific port type. The characters supported for format e are shown in the radius-server attribute nas-port format command page. The type keyword allows you to specify different format strings to represent different physical port types. The <i>nas-port-type</i> argument can be set to one of the extended attribute 61 values. <p>Note You must explicitly define the usage of the 32-bit attribute 5 to use format e. The usage is defined with a given parser character for each NAS port field of interest for a given bit field.</p>

Overriding Global NAS-Port-Type Configuration

You can override attribute 61 configured globally on the router at an interface or subinterface level.

Use the following task to override all global options on how the extended attribute 61 is sent to any subinterface such as Ethernet, VLAN, Q-in-Q, VC, or VC ranges.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface atm** *interface-number* [*subinterface-number*{**mpls**|**multipoint**|**point-to-point**}]
4. **pvc** [*name*] *vpi* / *vci* [**ces**|**ilmi**|**qsaal**|**smds**|**l2transport**]
5. **radius attribute nas-port-type** *port-number*
6. **end**

DETAILED STEPS

Command or Action	Purpose
<p>Step 1 enable</p> <p>Example:</p> <pre>Device> enable</pre>	<p>Enables privileged EXEC mode.</p> <ul style="list-style-type: none"> Enter your password if prompted.

Command or Action	Purpose
<p>Step 2 <code>configure terminal</code></p> <p>Example:</p> <pre>Device# configure terminal</pre>	Enters global configuration mode.
<p>Step 3 <code>interface atm interface-number [subinterface-number {mpls multipoint point-to-point}]</code></p> <p>Example:</p> <pre>Device(config)# interface atm 5/0/0.1</pre>	Enters ATM subinterface mode.
<p>Step 4 <code>pvc [name] vpi / vci [ces ilmi qsaal smds l2transport]</code></p> <p>Example:</p> <pre>Device(config-subif)# pvc 1/33</pre>	Enters PVC subinterface mode.
<p>Step 5 <code>radius attribute nas-port-type port-number</code></p> <p>Example:</p> <pre>Device(config-if-atm-vc)# radius attribute nas-port-type 7</pre>	<p>Sets a specific extended attribute 61 value for an interface or subinterface, select a value for a port type to override the NAS-Port type configured globally.</p> <ul style="list-style-type: none"> • The range for the <i>port-number</i> is 0-2147483647. • The <i>value</i> argument must be assigned a number 1-40 to set a customized extended NAS port type and configure a specific service port type. If you choose a number outside of this range, the default global NAS port format e string is used to configure the NAS port value that is sent for the session. • You can set a specific service port type with the radius-server attribute nas-port format command. This setting overrides a global NAS port type session format.
<p>Step 6 <code>end</code></p> <p>Example:</p> <pre>Device(config-if-atm-vc)# end</pre>	Ends the configuration session and returns to privileged EXEC mode.

Configuration Examples for Extended NAS-Port-Type and NAS-Port Support

- [Example: Configuring Global Support for Extended NAS-Port-Type Attribute, page 8](#)

Table 2 *Feature Information for Extended NAS-Port-Type and NAS-Port Support*

Feature Name	Releases	Feature Information
Extended NAS-Port-Type and NAS-Port Support	12.3(7)XI1 12.2(28)SB 12.2(33)SRC 15.0(1)M Cisco IOS Release XE 3.3SG	<p>The Extended NAS-Port-Type and NAS-Port Support feature allows you to identify what service type is taking place on specific ports with non-RADIUS RFC supported types.</p> <p>This feature was introduced to support the Cisco 10000 series router in Cisco IOS Release 12.3(7)XI1.</p> <p>The following commands were introduced or modified: radiusattributenas-port-type,radius-serverattribute61extended,radius-serverattributenas-portformat.</p>

© 2012 Cisco Systems, Inc. All rights reserved.