



DiffServ Compliant WRED

DiffServ Compliant WRED extends the functionality of Weighted Random Early Detection to enable support for DiffServ and Assured Forwarding (AF) per hop behavior (PHB). This feature enables customers to implement AF PHB by coloring packets according to Differentiated Services Code Point (DSCP) values and then assigning preferential drop probabilities to those packets.



Note

This feature can be used with IP packets only. It is not intended for use with Multiprotocol Label Switching (MPLS)-encapsulated packets.

- [Information About DiffServ Compliant WRED, page 1](#)
- [How to Configure DiffServ Compliant WRED, page 2](#)
- [Configuration Examples for DiffServ Compliant WRED, page 5](#)

Information About DiffServ Compliant WRED

Differentiated Services for WRED

Differentiated Services is a multiple service model that can satisfy differing Quality of Service (QoS) requirements. With Differentiated Services, the network tries to deliver a particular kind of service based on the QoS specified by each packet. This specification can occur in different ways. The DiffServ Compliant WRED feature enables WRED to use either the 6-bit differentiated services code point (DSCP) or the IP Precedence setting in IP packets when it calculates the drop probability for a packet. The DSCP value is the first six bits of the IP type of service (ToS) byte.

Usage Guidelines for DiffServ Compliant WRED

To configure the DiffServ Compliant WRED feature, first specify the policy map, add the class, and configure the bandwidth or shape for the class. If you want WRED to use the DSCP value when it calculates the drop probability, use the *dscp-based* argument with the **random-detect** command to specify the DSCP value and then use the **random-detect dscp** command to modify the default minimum and maximum thresholds for the

DSCP value. If you want WRED to use the IP Precedence value when it calculates the drop probability, use the *precedence-based* argument with the **random-detect** command to specify the IP Precedence value. This configuration can then be applied wherever policy maps are attached (for example, at the interface level, the per-VC level, or the shaper level).

Remember the following points when using the commands included with this feature:

- If you use the *dscp-based* argument, WRED will use the DSCP value to calculate the drop probability.
- If you use the *precedence-based* argument, WRED will use the IP Precedence value to calculate the drop probability.
- The *dscp-based* and *precedence-based* arguments are mutually exclusive.
- If you do not specify either argument, WRED will use the IP Precedence value to calculate the drop probability (the default method).

How to Configure DiffServ Compliant WRED

Configuring DiffServ Compliant WRED

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface** *type number* [**name-tag**]
4. **class-map** *class-map-name*
5. **match** *match-criterion*
6. **policy-map** *policy-map-name*
7. **class** {*class-name* | **class-default**}
8. **bandwidth** {*kbps* | **remaining percentage** | **percent percentage**}
9. **random-detect** [**dscp-based** | **precedence-based** | **cos-based** | **discard-class based**]
10. **random-detect dscp** *dscp-value min-threshold max-threshold* [*mark-probability-denominator*]
11. **exit**
12. **exit**
13. **interface** *type number* [**name-tag**]
14. **service-policy output** *policy-map-name*
15. **end**
16. **show policy-map interface** *type number*
17. **exit**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	interface <i>type number</i> [name-tag] Example: Device(config)# interface GigabitEthernet 0/0/0	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and number.
Step 4	class-map <i>class-map-name</i> Example: Device(config-if)# class-map diffservclass	Specifies the name of the class map to be created and enters QoS class-map configuration mode.
Step 5	match <i>match-criterion</i> Example: Device(config-cmap)# match any	Configures the match criteria for a class map.
Step 6	policy-map <i>policy-map-name</i> Example: Device(config-cmap)# policy-map diffservpm	Creates or modifies a policy map that can be attached to one or more interfaces to specify a service policy, and enters QoS policy-map configuration mode.
Step 7	class { <i>class-name</i> class-default } Example: Device(config-pmap)# class diffservclass	Specifies the name of the class whose policy you want to create or change or specifies the default class (commonly known as the class-default class) before you configure its policy. <ul style="list-style-type: none"> • Enters QoS policy-map class configuration mode.
Step 8	bandwidth { <i>kpbs</i> remaining percentage percent percentage } Example: Device(config-pmap-c)# bandwidth percent 30	Specifies the bandwidth allocated for a class belonging to a policy map.

	Command or Action	Purpose
Step 9	random-detect [dscp-based precedence-based cos-based discard-class based] Example: <pre>Device(config-pmap-c)# random-detect dscp-based</pre>	Configures WRED for a class in a policy map.
Step 10	random-detect dscp <i>dscp-value min-threshold max-threshold</i> [<i>mark-probability-denominator</i>] Example: <pre>Device(config-pmap-c)# random-detect dscp af11 10000 30000 25</pre>	Changes the minimum and maximum packet thresholds for the differentiated services code point (DSCP) value.
Step 11	exit Example: <pre>Device(config-pmap-c)# exit</pre>	Exits QoS policy-map class configuration mode.
Step 12	exit Example: <pre>Device(config-pmap)# exit</pre>	Exits QoS policy-map configuration mode.
Step 13	interface <i>type number</i> [name-tag] Example: <pre>Device(config)# interface GigabitEthernet 0/0/0</pre>	Configures an interface type and enters interface configuration mode. <ul style="list-style-type: none"> • Enter the interface type and number.
Step 14	service-policy output <i>policy-map-name</i> Example: <pre>Device(config-if)# service-policy output policy1</pre>	Attaches a policy map to an output interface. <ul style="list-style-type: none"> • Enter the policy map name. <p>Note Policy maps can be configured on ingress or egress routers. They can also be attached in the input or output direction of an interface. The direction (input or output) and the router (ingress or egress) to which the policy map should be attached varies according your network configuration. When using the service-policy command to attach the policy map to an interface, be sure to choose the router and the interface direction that are appropriate for your network configuration.</p>

	Command or Action	Purpose
Step 15	end Example: Device(config-if)# end	Returns to privileged EXEC mode.
Step 16	show policy-map interface <i>type number</i> Example: Device# show policy-map interface GigabitEthernet 0/0/0	(Optional) Displays the traffic statistics of all classes that are configured for all service policies either on the specified interface or subinterface or on a specific PVC on the interface. <ul style="list-style-type: none"> • Enter the interface type and number.
Step 17	exit Example: Device# exit	(Optional) Exits privileged EXEC mode.

Configuration Examples for DiffServ Compliant WRED

Example: DiffServ compliant WRED

The following example enables WRED to use the DSCP value 8 for the class c1. The minimum threshold for the DSCP value 8 is 24 and the maximum threshold is 40. The last line attaches the traffic policy to the output interface or VC p1.

```
Device(config)# interface GigabitEthernet 0/0/0
Device(config-if)# class-map c1
Device(config-cmap)# match ip precedence 1
Device(config-cmap)# policy-map p1
Device(config-pmap)# class c1
Device(config-pmap-c)# bandwidth 48
Device(config-pmap-c)# random-detect dscp-based
Device(config-pmap-c)# random-detect dscp 8 24 40
Device(config-if)# service-policy output p1
```

