



1-Port ADSL WAN Interface Card

Feature History

Release	Modification
12.1(3)XJ	This feature was introduced on the Cisco 1700 series routers.
12.2(2)T	This feature was integrated into Cisco IOS Release 12.2(2)T.
12.2(13)ZH	This feature was expanded to include the WIC-1ADSL-I-DG interface card on Cisco 1700 series modular access routers, to support ADSL over ISDN WAN. For specific platforms supported, see Table 26 on page 3 .
12.2(15)ZJ	This feature was expanded to include the WIC-1ADSL-I-DG interface card on Cisco 2600 series, Cisco 3600 series, and Cisco 3700 series modular access routers. For specific platforms supported, see Table 26 on page 3 .
12.3(4)T	Support was added for the WIC-1ADSL-I-DG interface card on Cisco 2600 series, Cisco 3600 series, and Cisco 3700 series modular access routers. For specific platforms supported, see Table 26 on page 3 .

This feature module describes the 1-port Asymmetric Digital Subscriber Line (ADSL) Wide Area Network (WAN) Interface Card (WIC) feature. It describes the benefits of the feature, supported platforms, configuration, related documents, and provides command reference information.

This document includes the following sections:

- [Feature Overview, page 2](#)
- [Supported Platforms, page 3](#)
- [Configuring the Cisco ADSL WAN Interface Cards, page 4](#)
- [Configuration Example, page 4](#)
- [Additional References, page 5](#)
- [Command List, page 5](#)



Feature Overview

The Cisco ADSL WAN interface cards are 1-port WAN interface cards (WIC) for Cisco modular access routers. These cards provide high-speed ADSL digital data transfer between a single customer premises equipment (CPE) subscriber and a central office.

**Note**

ADSL is a last-mile access technology that uses an asymmetrical data rate over a single copper wire pair.

The ADSL WICs are available in two variations: ADSL over POTS (WIC-1ADSL), and ADSL over ISDN WAN with Dying Gasp support (WIC-1ADSL-I-DG). The following bullets summarize the features of each card:

- Cisco WIC-1ADSL—Provides ADSL services over ordinary telephone lines. It is compatible with the Alcatel Digital Subscriber Loop Access Multiplexer (DSLAM), the Cisco 6260 DSLAM with Flexi-line cards, and the Cisco 6130 DSLAM with Flexi-line cards.
- Cisco WIC-1ADSL-I-DG—Provides ADSL services in areas of the world that have extensive ISDN backbones already in place. It is compatible with ECI, Siemens, Alcatel, and Cisco DSLAMs that support ISDN.

All Cisco ADSL WICs support Asynchronous Transfer Mode (ATM) Adaptation Layer 2 (AAL2) for the Cisco 2600, Cisco 3600, and Cisco 3700 series only, and AAL5 for the those models as well as for the Cisco 1700. The cards support various classes of Quality of Service (QoS) for both voice and data.

Benefits

Both Cisco ADSL WAN interface cards provide the following benefits:

- Enable business-class broadband service with voice integration, scalable performance, flexibility, and security
- Aggregate both ADSL and other transport options into a single box
- Provide ADSL high-speed digital data transmissions between CPE and the central office (CO)
- Support ATM AAL5 services and applications, ATM class of service (constant bit rate [CBR], variable bit rate-nonreal time [VBR-NRT], variable bit rate-real time [VBR-rt], and unspecified bit rate [UBR]), as well as up to 23 virtual circuits on a WIC in Cisco routers
- Provide ATM traffic management and QoS features to enable service providers to manage their core ATM network infrastructure.

The following benefits are specific to each card:

- Cisco WIC-1ADSL—Supports and complies with ANSI T1.413 Issue 2, and ITU G.992.1, Annex A (G.DMT for full-rate ADSL over POTS)
- Cisco WIC-1ADSL-I-DG—Allows the coexistence of ADSL and ISDN on the same local loop; supports and complies with ITU G.992.1, Annex B (G.DMT for full-rate ADSL over ISDN), ETSI 101-388, and the Deutsche Telekom U-R2 specification

Restrictions

The Cisco ADSL WAN interface cards do not support dual latency, ADSL2, or ADSL2plus. When the ADSL link is intended to support both voice and data traffic simultaneously, the link should be configured for either all fast-path data or all interleave data, with an interleave depth of zero to ensure that latency is minimized. In addition, the total supported data rate must be reduced to adjust for the reduced coding gain, which is usually present with high-latency traffic.

Related Documents

- *Release Notes for the Cisco 1700 Series Routers for Cisco IOS Release 12.3(4)T*
- *Caveats for Cisco IOS Release 12.3 T*
- *Cisco Interface Cards Hardware Installation Guide*
- *Enhanced Voice and QoS for ADSL and G.SHDSL on Cisco 1700 Series, Cisco 2600 Series, and Cisco 3600 Series Routers*
- *Configuring an ADSL WAN Interface Card on Cisco 1700 Series Routers*

Supported Platforms

Table 26 details the specific platforms that each card supports.

Table 26 **Platforms Supported by Each Cisco ADSL WAN Card**

Cisco WIC-1ADSL	Cisco WIC-1ADSL-I-DG
Cisco 1720, Cisco 1721, Cisco 1751, Cisco 1760, Cisco 2600, Cisco 2600XM, Cisco 2691, Cisco 3600, Cisco 3700	Cisco 1721, Cisco 1751, Cisco 1760, Cisco 2600XM, Cisco 2691, Cisco 3700

Determining Platform Support Through Cisco Feature Navigator

Cisco IOS software is packaged in feature sets that support specific platforms. To get updated information regarding platform support for this feature, access Cisco Feature Navigator. Cisco Feature Navigator dynamically updates the list of supported platforms as new platform support is added for the feature.

Cisco Feature Navigator is a web-based tool that enables you to determine which Cisco IOS software images support a specific set of features and which features are supported in a specific Cisco IOS image. You can search by feature or release. Under the release section, you can compare releases side by side to display both the features unique to each software release and the features in common.

Use Cisco Feature Navigator to find information about platform support and Cisco IOS and Catalyst OS software image support. To access Cisco Feature Navigator, go to <http://tools.cisco.com/ITDIT/CFN/jsp/index.jsp>. An account on Cisco.com is not required.

Availability of Cisco IOS Software Images

Platform support for particular Cisco IOS software releases is dependent on the availability of the software images for those platforms. Software images for some platforms may be deferred, delayed, or changed without prior notice. For updated information about platform support and availability of software images for each Cisco IOS software release, refer to the online release notes or, if supported, Cisco Feature Navigator.

Configuring the Cisco ADSL WAN Interface Cards

- [Configuration Example, page 4](#)
- [Command List, page 5](#)

Configuration Example

The following sample shows a Cisco 1700 series router configured for bridging on the ATM interface with a Cisco ADSL WIC:

Current configuration:

```
!  
version 12.2  
service timestamps debug uptime  
service timestamps log uptime  
no service password-encryption  
!  
hostname meltrack  
!  
no ip routing  
!  
interface ATM0  
no ip address  
atm vc-per-vp 256  
    pvc 8/35  
        encapsulation aal5snap  
!  
dsl operating-mode auto  
bridge-group 1  
!  
interface FastEthernet0  
no ip address  
speed auto  
bridge-group 1  
!  
ip classless  
no ip http server  
!  
bridge 1 protocol ieee  
!  
line con 0  
transport input none  
line aux 0  
line vty 0 4  
login  
!  
end
```

Additional References

The following section provides a reference related to the ADSL WAN interface card.

Related Documents

Related Topic	Document Title
	<p>All other commands used to configure that feature are documented in the following publications:</p> <ul style="list-style-type: none"> • Configuring an ADSL WAN Interface Card on Cisco 1700 Series Routers • The “Configuring ATM” section of the <i>Cisco IOS Wide-Area Networking Configuration Guide</i> <p>The “ATM Commands” section of the <i>Cisco IOS Wide-Area Networking Command Reference</i></p>
ADSL WAN interface card on Cisco 1700 series routers	Configuring an ADSL WAN Interface Card on Cisco 1700 Series Routers

Command List

The following command is pertinent to this feature. To see the command pages for this and other commands used with this feature, go to the *Cisco IOS Master Commands List*, Release 12.4, at <http://www.cisco.com/univercd/cc/td/doc/product/software/ios124/124mindx/124index.htm>.

- **dsl operating-mode**

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Copyright © 2005 Cisco Systems, Inc. All rights reserved.

