



Service Manager

To access Service management tasks, log into the system (see “[Logging In](#)” section on page 2-23). Then, from the Home page, click the **Tools** tab. The Tools page appears.

From the Tools Page, click **Service Manager**. The Service Manager page appears showing:

- Edit Service Properties
- Edit IMGW Device and Hop Types

Editing Service Properties

Step 1 From the Service Manager Functional Overview page, click **Edit Service Properties**. The Edit Service Properties page appears (see [Figure 15-1](#)).

Figure 15-1 *Edit Service Properties*

Edit Service Properties

Select Service:	<input checked="" type="radio"/> CNS Image Service
<input type="button" value="Edit Properties"/> <input type="button" value="Cancel"/>	

101540

Step 2 From the Edit Service Properties page, select Image Service by clicking the associated radio button. The service properties page for Image Service appears (see [Figure 15-2](#)).

Figure 15-2 Image Service Properties

Edit Service Properties

Image Service Configurable Properties:

Name	Value
Image Types	<div style="border: 1px solid gray; padding: 5px;"> <p>Removed Image Types:</p> <div style="border: 1px solid gray; height: 40px; width: 100%;"></div> <p style="text-align: center;"> <input type="button" value="<<"/> <input type="button" value=">>"/> </p> <p>Image Types:</p> <div style="border: 1px solid gray; padding: 2px;"> IOS PDM Pix-image ASDM ASA-image Other </div> <p style="text-align: right;"> <input type="button" value="Add New"/> </p> </div>
Boot Timeout	<input type="text" value="300"/> seconds
Check Server Msg Timeout	<input type="text" value="600"/> seconds
>Check Server Msg Retry	<input type="text" value="6"/> times

20080804

- Step 3** To Edit Image Types: Click the move button (<<) to move an image type to the Removed Image Types column.
- Step 4** To Edit Boot Timeout: Enter a new value in the text box.
- Step 5** To Edit Check Server Msg Timeout: Enter a new value in the text box.
- Step 6** To Edit Check Server Msg Retry: Enter a new value in the text box.
- Step 7** To cancel this task, click **Cancel**.
- Step 8** To submit the changes, click **OK**.

Editing IMGW Device and Hop Types

- Step 1** From the Service Manager Functional Overview page, click **Edit IMGW Device and Hop Types**. The IMGW Device and Hop Types page appears (see [Figure 15-3](#)).

Figure 15-3 IMGW Device and Hop Types

Add and Remove IMGW Device Types and Hop Types:

Device Types	CATIOS CATOS CE CSS	Remove	New DeviceType	Add to list
Hop Types	AP_LOGIN CATALYST_EN CATALYST_LOGIN CATIOS_EN	Remove	New HopType	Add to list

Edit Reset

129600

- Step 2** To remove a Device Type or Hop Type, click the item, then click **Remove**.
- Step 3** To add a new Device Type or Hop Type, enter the item in the dialog box, then click **Add to list**.
- Step 4** When complete, so save your changes, click **Edit**.

