



# Compatibility Matrix and Web UI System Requirements

- [Compatibility Matrix](#), on page 1
- [Web UI System Requirements](#), on page 8

## Compatibility Matrix

The following table provides software compatibility information between Cisco Catalyst 9200 Series Switches, Cisco Identity Services Engine, and Cisco Prime Infrastructure.

| Catalyst 9200  | Cisco Identity Services Engine                         | Cisco Prime Infrastructure  |
|----------------|--|---|
| 17.14.1        | 3.2<br>3.1 + Patch 3<br>3.0 + Patch 6<br>2.7 + Patch 7 | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| 17.13.1        | 3.2<br>3.1 + Patch 3<br>3.0 + Patch 6<br>2.7 + Patch 7 | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Dublin 17.12.3 | 3.2<br>3.1 + Patch 3<br>3.0 + Patch 6<br>2.7 + Patch 7 | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |

| Catalyst 9200    | Cisco Identity Services Engine   | Cisco Prime Infrastructure  |
|------------------|--|---|
| Dublin 17.12.2   | 3.2<br>3.1 + Patch 3<br>3.0 + Patch 6<br>2.7 + Patch 7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Dublin 17.12.1   | 3.2<br>3.1 + Patch 3<br>3.0 + Patch 6<br>2.7 + Patch 7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Dublin 17.11.1   | 3.2<br>3.1 + Patch 3<br>3.0 + Patch 6<br>2.7 + Patch 7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Dublin 17.10.1   | 3.2<br>3.1 + Patch 1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Cupertino 17.9.5 | 3.2<br>3.1 + Patch 1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Cupertino 17.9.4 | 3.2<br>3.1 + Patch 1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |

| Catalyst 9200    | Cisco Identity Services Engine   | Cisco Prime Infrastructure  |
|------------------|--|---|
| Cupertino 17.9.3 | 3.2<br>3.1 + Patch 1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Cupertino 17.9.2 | 3.2<br>3.1 + Patch 1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Cupertino 17.9.1 | 3.2<br>3.1 + Patch 1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Cupertino 17.8.1 | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch                  | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Cupertino 17.7.1 | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch                  | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |

| Catalyst 9200     | Cisco Identity Services Engine  | Cisco Prime Infrastructure  |
|-------------------|---|---|
| Bengaluru 17.6.7  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Bengaluru 17.6.6a | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Bengaluru 17.6.6  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Bengaluru 17.6.5  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Bengaluru 17.6.4  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Bengaluru 17.6.3  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |

| Catalyst 9200     | Cisco Identity Services Engine  | Cisco Prime Infrastructure  |
|-------------------|---|---|
| Bengaluru 17.6.2  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Bengaluru 17.6.1  | 3.1<br>3.0 latest patch<br>2.7 latest patch<br>2.6 latest patch<br>2.4 latest patch | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> .     |
| Bengaluru 17.5.1  | 3.0 Patch 1<br>2.7 Patch 2<br>2.6 Patch 7<br>2.4 Patch 13                           | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> .     |
| Bengaluru 17.4.1  | 3.0<br>2.7 Patch 2  | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> .     |
| Amsterdam 17.3.8a | 2.7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Amsterdam 17.3.8  | 2.7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Amsterdam 17.3.7  | 2.7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Amsterdam 17.3.6  | 2.7   | C9200 and C9200L: PI 3.10 + PI 3.10 latest maintenance release + PI 3.10 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.10</a> → <b>Downloads</b> . |
| Amsterdam 17.3.5  | 2.7   | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br><br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> .     |

| Catalyst 9200      | Cisco Identity Services Engine | Cisco Prime Infrastructure  |
|--------------------|--------------------------------|---|
| Amsterdam 17.3.4b  | 2.7                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> . |
| Amsterdam 17.3.4   | 2.7                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> . |
| Amsterdam 17.3.3   | 2.7                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> . |
| Amsterdam 17.3.2a  | 2.7                            | C9200 and C9200L: PI 3.8 + PI 3.8 latest maintenance release + PI 3.8 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.8</a> → <b>Downloads</b> . |
| Amsterdam 17.3.1   | 2.7                            | C9200 and C9200L: PI 3.8 + PI 3.8 latest maintenance release + PI 3.8 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.8</a> → <b>Downloads</b> . |
| Amsterdam 17.2.1   | 2.7                            | C9200 and C9200L: PI 3.7 + PI 3.7 latest maintenance release + PI 3.7 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.7</a> → <b>Downloads</b> . |
| Amsterdam 17.1.1   | 2.7                            | C9200 and C9200L: PI 3.6 + PI 3.6 latest maintenance release + PI 3.6 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.6</a> → <b>Downloads</b> . |
| Gibraltar 16.12.8  | 2.6                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → Downloads.         |
| Gibraltar 16.12.7  | 2.6                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → Downloads.         |
| Gibraltar 16.12.6  | 2.6                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → Downloads.         |
| Gibraltar 16.12.5b | 2.6                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → Downloads.         |

| Catalyst 9200      | Cisco Identity Services Engine | Cisco Prime Infrastructure  |
|--------------------|--------------------------------|---|
| Gibraltar 16.12.5  | 2.6                            | C9200 and C9200L: PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → Downloads.         |
| Gibraltar 16.12.4  | 2.6                            | C9200 and C9200L: PI 3.8 + PI 3.8 latest maintenance release + PI 3.8 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.8</a> → Downloads.         |
| Gibraltar 16.12.3a | 2.6                            | C9200 and C9200L: PI 3.5 + PI 3.5 latest maintenance release + PI 3.5 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.5</a> → <b>Downloads</b> . |
| Gibraltar 16.12.3  | 2.6                            | C9200 and C9200L: PI 3.5 + PI 3.5 latest maintenance release + PI 3.5 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.5</a> → <b>Downloads</b> . |
| Gibraltar 16.12.2  | 2.6                            | C9200 and C9200L: PI 3.5 + PI 3.5 latest maintenance release + PI 3.5 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.5</a> → <b>Downloads</b> . |
| Gibraltar 16.12.1  | 2.6                            | C9200 and C9200L: PI 3.5 + PI 3.5 latest maintenance release + PI 3.5 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.5</a> → <b>Downloads</b> . |
| Gibraltar 16.11.1  | 2.6<br>2.4 Patch 5             | C9200 and C9200L: PI 3.4 + PI 3.4 latest maintenance release + PI 3.4 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → <b>Downloads</b> . |
| Gibraltar 16.10.1  | 2.4                            | C9200: PI 3.4 + Device Pack 9<br>C9200L: PI 3.4 + Device Pack 7<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → <b>Downloads</b> .                          |
| Fuji 16.9.8        | 2.5<br>2.1                     | PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> .                   |
| Fuji 16.9.7        | 2.5<br>2.1                     | PI 3.9 + PI 3.9 latest maintenance release + PI 3.9 latest device pack<br>See <a href="#">Cisco Prime Infrastructure 3.9</a> → <b>Downloads</b> .                   |
| Fuji 16.9.6        | 2.4                            | PI 3.4 + Device Pack 7<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → <b>Downloads</b> .   |

| Catalyst 9200            | Cisco Identity Services Engine | Cisco Prime Infrastructure  |
|--------------------------|--------------------------------|---|
| Fuji 16.9.5              | 2.4                            | PI 3.4 + Device Pack 7<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → Downloads. |
| Fuji 16.9.4              | 2.4                            | PI 3.4 + Device Pack 7<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → Downloads. |
| Fuji 16.9.3              | 2.4                            | PI 3.4 + Device Pack 7<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → Downloads. |
| Fuji 16.9.2 <sup>1</sup> | 2.4                            | PI 3.4 + Device Pack 7<br>See <a href="#">Cisco Prime Infrastructure 3.4</a> → Downloads. |

<sup>1</sup> The compatibility information for Fuji 16.9.2 applies only to the C9200L SKUs.

## Web UI System Requirements

The following subsections list the hardware and software required to access the Web UI:

### Minimum Hardware Requirements

| Processor Speed              | DRAM                | Number of Colors | Resolution           | Font Size |
|------------------------------|---------------------|------------------|----------------------|-----------|
| 233 MHz minimum <sup>2</sup> | 512 MB <sup>3</sup> | 256              | 1280 x 800 or higher | Small     |

<sup>2</sup> We recommend 1 GHz

<sup>3</sup> We recommend 1 GB DRAM

### Software Requirements

#### Operating Systems

- Windows 10 or later
- Mac OS X 10.9.5 or later

#### Browsers

- Google Chrome—Version 59 or later (On Windows and Mac)
- Microsoft Edge
- Mozilla Firefox—Version 54 or later (On Windows and Mac)
- Safari—Version 10 or later (On Mac)