



Troubleshooting Cisco Unity Connection SRSV

- [Troubleshooting Cisco Unity Connection SRSV, on page 1](#)

Troubleshooting Cisco Unity Connection SRSV

Error Message Appears When Testing the Connectivity of Unity Connection with Branch

You may receive the following error messages on the Edit Branch page of Cisco Unity Connection Administration when you test the connectivity of Unity Connection with the branch:

- “Authentication failed. Incorrect Username and Password”: If you receive the “Authentication failed. Incorrect Username and Password.” error message on the Edit Branch page when you test the connectivity of the central Unity Connection server with the branch, make sure that the username and password of the branch entered on the Edit Branch page are correct.
- “Branch is unreachable”: If you receive the “Branch is unreachable” error message on the Edit Branch page when you test the connectivity of the central Unity Connection server with the branch, make sure that the PAT port number specified on the Edit Branch page is correct.
- “Server Address is Invalid”: If you receive the “Server Address is Invalid” error on the Edit Branch page, make sure that the FQDN/IP address of the branch entered on the Edit Branch page is correct. In case DNS is configured, make sure that the IP address of the branch is added to it.

Certificate Mismatch Error Message for Appears on the Central Unity Connection Server

If you are getting the “Unable to start provisioning.” error on the Edit Branch page of Connection Administration page, make sure that the hostname of the branch mentioned in the certificate installed on the central Unity Connection server is correct.

- Make sure that the name of an administrator on the branch is not same as the name of a subscriber on the central Unity Connection server associated with the branch.
- Make sure that the extension of a call handler at the branch is not used as the extension of a branch user at the central Unity Connection server.
- Make sure that the deleted user on the central Unity Connection server is not used on the branch. For example, if a branch user on Unity Connection is used as operator on Connection SRSV, make sure to change the operator at branch before deleting the user at central Unity Connection server.
- Make sure that the deleted distribution list on the central Unity Connection server is not used on the branch. For example, if a distribution list is used in a call handler template on the branch, make sure to change the distribution list in the template before deleting the distribution list.

Provisioning/Voicemail Upload Remains in Scheduled state for a Long Time

If the provisioning of the users or voicemail upload remains in the Scheduled state for a long time, make sure that the Unity Connection Branch Sync Service is active on the central Unity Connection server.

Unable to Reach a Branch User through Telephony User Interface (TUI)

If you are not able to reach a branch user through TUI, make sure that the associated partition is added in the Search Space of the central Unity Connection server.

Unable to Send a Voice Message to a Branch User During WAN Outage

If you are unable to send a voice message to a branch user during WAN outage, make sure that Visual VoiceMail (VVM) is not installed on your phone. For more information, contact your phone service provider.

Error Messages Appear on the Branch Sync Results Page

If the username and password of the branch is not entered correctly on the Edit Branch page, the provisioning of the users and the voicemail upload does not work and you receive the following error messages or status in the Description field of the Branch Sync Results page of Cisco Unity Connection Administration:

- Unable to start Provisioning of the branch:: Message = Authentication failed.
- Unable to fetch voice mail summary of the branch:: Message = Authentication failed.

If you receive the “Unable to start provisioning of the branch:: Message=Central Server is not Configured on CUCE” error message on the Branch Sync Results page of Cisco Unity Connection Administration when you start provisioning of the branch, enter the correct FQDN/ IP address of the central Unity Connection server on Cisco Unity Connection SRSV Administration to resolve the problem.

Logs are Not Created or SRSV feature Not Working Properly

If the logs for the branch are not generated or the SRSV feature is not working properly, you may restart the Unity Connection Branch Sync Service and the REST APIs on both the branch and Unity Connection sites to resolve this issue.

Unable to Perform Backup/Restore Operation on the Branch

If you are unable to perform the backup/restore operation on the branch, make sure that the backup server is configured correctly on the branch.

Central Unity Connection Server Moves to Violation State

If the central Unity Connection server moves to the Violation state, make sure that the number of licenses for the Unity Connection features, such as SpeechView and Connection SRSV, does not exceed its maximum limit. For more information on licensing, see the “[Managing Licenses](#)” chapter of the Install, Upgrade, and Maintenance Guide for Cisco Unity Connection, Release 11.x, available at https://www.cisco.com/c/en/us/td/docs/voice_ip_comm/connection/11x/install_upgrade/guide/b_11xcuciumg.html.

Non-Delivery Receipts (NDR) on the Central Unity Connection Server

If you are getting NDR on the central Unity Connection server but the same email is delivered on the branch, check the NDR code and take action accordingly. For example, if user A sends email to user B from the branch, the email gets successfully delivered to user B on the branch. However, on the central Unity Connection server, user A receives “4.2.2” NDR code stating that the mailbox quota of user B has exceeded its maximum limit. In this case, user B needs to take appropriate action, such as delete existing emails or get the mailbox quota increased to receive further emails. For more information on NDR codes, refer to the [Troubleshooting Non-Delivery Receipts](#) chapter of this guide.