



# Service Chain Configuration Mode Commands

---

The Service Chain configuration mode is a sub-mode of the Global Configuration mode. This sub-mode associates nsh-format to service-chain.

---

## Command Modes

Exec > Global Configuration > Service Chain Configuration

**configure > service-chain**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain) #
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [end, on page 2](#)
- [exit, on page 3](#)
- [nsh-format, on page 4](#)

**end**

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Return to the Exec mode.

# exit

Exits the current configuration mode and returns to the global configuration mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>exit</b>
<b>Usage Guidelines</b>	Returns to the global configuration mode.

# nsh-format

This command associates nsh format with service-chain.

---

## Product

P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Service Chain Configuration  
**configure > service-chain**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain)#
```

---

## Syntax Description

**[ no ] nsh-format** *<nsh\_format\_name>*

### **no**

Disassociates nsh format with the service-chain configuration.

### **nsh-format**

Associates nsh format with service chain.

### ***nsh\_format\_name***

Specifies the name of nsh-format. This is entered as an alphanumeric string of 1 through 63 characters.

---

## Usage Guidelines

Use this command to associate nsh-format with service-chain.

### **Example**

The following commands associates a nsh-format to service-chain:

```
nsh-format ns1
```

The following commands disassociates the nsh-format with service-chain:

```
no nsh-format
```