



Enabling EMM and ESM Cause Code Mapping

- [Feature Summary and Revision History, on page 1](#)
- [Feature Description, on page 2](#)
- [Enabling EMM/ESM Cause Code Mapping \(Cause Code 27\) under MME-Service , on page 2](#)
- [Enabling EMM/ESM Cause Code Mapping \(Cause Code 27\) under Call Control Profile, on page 2](#)
- [Show Commands and Outputs, on page 3](#)

Feature Summary and Revision History

Summary Data

Applicable Product(s) or Functional Area	MME
Applicable Platform(s)	<ul style="list-style-type: none"> • ASR 5500 • VPC-DI • VPC-SI
Feature Default	Enabled - Always On
Related Changes in This Release	Not applicable
Related Documentation	<ul style="list-style-type: none"> • <i>MME Administration Guide</i> • <i>Statistics and Counters Reference</i>

Revision History

Revision Details	Release
First Introduced	21.22

Feature Description

The User Equipment (UE) suffers failure, during attach process with an `EMM Attach Reject` message sent from MME to UE. When UE attach request is sent from MME to P-GW, the DNS server responds back with "Server failure", causing the MME to reject the UE attach request with the following error messages:

1. `EMM Cause Code 17 Network Failure`
2. `ESM PDN Connectivity Reject Container` message with `ESM Cause Code 31 Request Rejected Unspecified`.

To overcome the impact in MME 4G attach SR calculations, the Cause Codes introduced in the `EMM Attach Reject/ESM PDN Connectivity Reject` message to be `EMM Cause Code 19 ESM Failure` and `ESM Cause Code 27 Missing or Unknown APN`, instead of the current cause codes `EMM 17` and `ESM 31`.

To overcome the UE attach request failure, the following new configuration commands are introduced:

1. `ESM-failure` with `EMM Cause Code`
2. `ESM-cause-code` with `ESM Cause Code option missing-or-unknown-apn`

Enabling EMM/ESM Cause Code Mapping (Cause Code 27) under MME-Service

Use the following configuration commands to enable cause code mapping under `mme-service`:

```
configure
  context context_name
    mme-service service_name { local-cause-code-mapping{
pgw-selection-failure( emm-cause-code ){ esm-failure ( esm-cause-code ) (
  unknown-apn ) }}}
```

Enabling EMM/ESM Cause Code Mapping (Cause Code 27) under Call Control Profile

Use the following configuration commands to enable cause code mapping under call control profile:

```
configure
  call-control-profile profile_name { local-cause-code-mapping{
pgw-selection-failure( emm-cause-code ){ esm-failure ( esm-cause-code )
( unknown-apn ) }}}
```

Show Commands and Outputs

show mme-service all

The output of this command displays the following newly introduced field:

ESM Failure (EMM-19)	Displays the EMM Cause Code of EMM Attach Reject/ESM PDN Connectivity Reject message.
Missing-or-Unknown-APN (ESM-27)	Displays the ESM Cause Code of EMM Attach Reject/ESM PDN Connectivity Reject message.

show call-control-profile full all

The output of this command displays the following newly introduced field:

ESM Failure (EMM-19)	Displays the EMM Cause Code of EMM Attach Reject/ESM PDN Connectivity Reject message.
Missing-or-Unknown-APN (ESM-27)	Displays the ESM Cause Code of EMM Attach Reject/ESM PDN Connectivity Reject message.

