



Finding Feature Information

Last Updated: December 4, 2012

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table at the end of this module.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

© 2012 Cisco Systems, Inc. All rights reserved.



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA



RADIUS Vendor-Specific Attributes

Last Updated: December 4, 2012

The table below lists the supported vendor-specific options (subtype numbers from 3 through 21) that use IETF RADIUS attribute 26 and the Cisco vendor-ID company code of 9. These attributes are used with store-and-forward fax.

For more information, refer to the RADIUS Vendor-Specific Attributes appendix of the *Cisco IOS Security Configuration Guide*.

Table 1 *RADIUS Vendor-Specific Attributes*

Subtype Number	Attribute	Description
3	Cisco-Fax-Account-Id-Origin	Account ID origin as defined by the system administrator for the mmoip aaa receive-id or mmoip aaa send-id command.
4	Cisco-Fax-Msg-Id=	Unique fax message identification number assigned by store-and-forward fax.
5	Cisco-Fax-Pages	Number of pages sent or received during a fax session including cover pages.
6	Cisco-Fax-Coverpage-Flag	True/false flag that indicates whether a cover page was generated by the off-ramp gateway for this fax session. True indicates that a cover page was generated, and false indicates that a cover page was not generated.

Subtype Number	Attribute	Description
7	Cisco-Fax-Modem-Time	Number of seconds it takes to send fax data (x) and to complete the entire fax session (y), which includes both fax-mail and PSTN time, in the form x/y. For example, 10/15 means that the transfer time took 10 seconds and that the full fax session took 15 seconds.
8	Cisco-Fax-Connect-Speed	Modem speed at which this fax mail was initially sent or received. Possible values are 1200, 4800, 9600, and 14400.
9	Cisco-Fax-Recipient-Count	Number of recipients for this fax transmission. Until e-mail servers support session mode, the number should be 1.
10	Cisco-Fax-Process-Abort-Flag	True/false flag that indicates whether the fax session was aborted or successful. True indicates that the session was aborted, and false indicates that the session was successful.
11	Cisco-Fax-Dsn-Address	Address to which DSNs are sent.
12	Cisco-Fax-Dsn-Flag	True/false flag to indicate whether DSN is enabled. True indicates that DSN is enabled, and false indicates that DSN is not enabled.
13	Cisco-Fax-Mdn-Address	Address to which MDNs are sent.
14	Cisco-Fax-Mdn-Flag	True/Flash flag to indicate whether MDN is enabled. True indicates that MDN is enabled, and false indicates that MDN is not enabled.
15	Cisco-Fax-Auth-Status	Indicates whether or not authentication for this fax session was successful. Possible values for this field are success, failed, bypassed, or unknown.

Subtype Number	Attribute	Description
16	Cisco-Email-Server-Address	IP address of the e-mail server handling the on-ramp fax-mail message.
17	Cisco-Email-Server-Ack-Flag	Indicates that the on-ramp gateway has received a positive acknowledgment from the e-mail server accepting the fax-mail message.
18	Cisco-Gateway-Id	Name of the gateway that processed the fax session. The name appears in the following format: hostname.domain-name.
19	Cisco-Call-Type	Type of call activity: fax receive or fax send.
20	Cisco-Port-Used	Slot/port number used to send or receive this fax mail.
21	Cisco-Abort-Cause	If the fax session aborts, indicates the system component that signaled the abort. Examples of system components that could trigger an abort are FAP (Fax Application Process), TIFF (the TIFF reader or the TIFF writer), fax-mail client, fax-mail server, ESMTP client, or ESMTP server.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks

Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

© 2012 Cisco Systems, Inc. All rights reserved.



Last Updated: December 4, 2012

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2012 Cisco Systems, Inc. All rights reserved.



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA