



Using Performance Routing to Control EIGRP Routes with mGRE DMVPN Hub-and-Spoke Support

First Published: October 2, 2009

Last Updated: November 20, 2009

The PfR EIGRP mGRE DMVPN Hub-and-Spoke Support feature introduces the ability to inject routes into the EIGRP routing table, which allows Performance Routing (PfR) to control prefixes and applications over EIGRP routes. This feature also adds support for multicast Generic Routing Encapsulation (mGRE) Dynamic Multipoint Virtual Private Network (DMVPN) deployments that follow a hub- and-spoke network design.

Performance Routing is an extension of the Optimized Edge Routing (OER) technology and many of the commands and command modes still use the OER naming conventions. All of the original OER features are incorporated into the Performance Routing technology. Some of the early OER features have been superseded by newer techniques, and the more recent configuration module titles now use Performance Routing naming.

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the [“Feature Information for Using PfR to Control EIGRP Routes”](#) section on page 11.

Use Cisco Feature Navigator to find information about platform support and Cisco IOS and Catalyst OS software image support. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.



Americas Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Contents

- [Prerequisites for Using PfR to Control EIGRP Routes, page 2](#)
- [Restrictions for Using PfR to Control EIGRP Routes, page 2](#)
- [Information About Using PfR to Control EIGRP Routes, page 2](#)
- [How to Configure PfR to Control EIGRP Routes, page 4](#)
- [Configuration Examples for Using PfR to Control EIGRP Routes, page 8](#)
- [Additional References, page 9](#)
- [Feature Information for Using PfR to Control EIGRP Routes, page 11](#)

Prerequisites for Using PfR to Control EIGRP Routes

This feature assumes that EIGRP is already configured in your network and that basic OER functionality is also configured. See the [“Cisco IOS Optimized Edge Routing Overview”](#) and [“Setting Up OER Network Components”](#) modules for more details. For other OER and PfR features, see the [“Where to Go Next”](#) section on page 9 or the [“Additional References”](#) section on page 9 for more details.

Restrictions for Using PfR to Control EIGRP Routes

If you are deploying EIGRP in an mGRE DMVPN topology in your network, it must conform to a hub-and-spoke network design.

Information About Using PfR to Control EIGRP Routes

To use PfR to control EIGRP routes, you should understand the following concepts:

- [PfR EIGRP Route Control, page 2](#)
- [PfR and mGRE Dynamic Multipoint VPN, page 3](#)

PfR EIGRP Route Control

The PfR EIGRP mGRE DMVPN Hub-and-Spoke Support feature introduces PfR route control for EIGRP. When enabled, a parent route check is performed in the EIGRP database for controlling PfR prefixes and routes in addition to the existing BGP and static route databases.

PfR can only optimize paths for prefixes, which have an exact matching route or a less specific route (also called as parent route) in the routing protocols. The route being controlled by PfR can be an exact match of the parent route or can be a more specific one. For example, if PfR wants to control 10.1.1.0/24 but the EIGRP routing table has only 10.1.0.0/16 then the parent route is 10.1.0.0/16 and PfR will inject 10.1.1.0/24 in the EIGRP routing table.

If an exact matching parent route in the EIGRP routing table is found, PfR will attempt to install a route on an exit selected by the master controller by influencing the metric. If an exact match parent is not found, then PfR introduces a new route in the EIGRP table that matches the attributes of the parent. If

the route installation in the EIGRP table is successful, PfR saves the EIGRP parent and registers for any updates to the parent route. If the parent route is removed, PfR will uncontrol any routes it has installed in the EIGRP table based on this parent route.

PfR monitors traffic performance for prefixes it is controlling either passively using NetFlow or actively using IP SLA probes. Performance statistics such as delay, loss, and reachability are gathered and compared against a set of policies configured for the prefixes. If the traffic performance does not conform to the policies, the prefix is said to be out-of-policy (OOP). PfR tries to find an alternate path when the prefix goes into the OOP state.

While both BGP and static route control are enabled by default, EIGRP route control must be configured. PfR always attempts to control a prefix using BGP first. If BGP route control fails, static route control is tried. When EIGRP route control is enabled, PfR will attempt to control a prefix using BGP first. If no parent route is found, PfR will try to use EIGRP route control. If EIGRP route control fails, static route control is tried.

To find an alternate path for a prefix, PfR tries to send active probes from all the external interfaces on the border routers to a set of hosts in the destination prefix network. Before an active probe can be sent on an external interface, a parent route lookup is performed in routing protocol tables. When the PfR EIGRP mGRE DMVPN Hub-and-Spoke Support feature is enabled, PfR checks EIGRP routing tables, in addition to BGP and static routing tables, for a parent route, before sending active probes on external interfaces. Active probes are initiated on all the external interfaces that have a parent route in the EIGRP routing table. When the probe activity completes and the timer expires, statistics are sent from the border router to the master controller for policy decision and selection of an optimal exit.

When an exit is selected, a control prefix command is sent to the border router with the selected exit, specifying EIGRP as the protocol to install or modify the route. When the border router receives the command, it checks the EIGRP table to find a parent route. If a parent route is found, OER will install or modify the route in the EIGRP table and will notify the master controller about the route control status.

If an EIGRP route is successfully installed and advertised into the domain, OER continues to monitor traffic performance for this prefix and takes further action as mentioned above if the prefix goes OOP.

For more details about the PfR control mode and details about other PfR exit link selection control techniques including BGP, static routes, policy-based routing, and Protocol Independent Route Optimization (PIRO), see the [“Using OER to Control Traffic Classes and Verify the Route Control Changes”](#) module.

PfR and mGRE Dynamic Multipoint VPN

Dynamic Multipoint VPN (DMVPN) enables zero-touch deployment of IPsec encrypted VPN networks. The DMVPN topology leverages protocols like multipoint GRE (mGRE) for hub-to-spoke functionality, and for spoke-to-spoke functionality it utilizes the Next Hop Resolution Protocol (NHRP). Many DMVPN deployments use EIGRP networks, and support was added to PfR to allow DMVPN network deployments to use EIGRP route control within the DMVPN network. In the PfR EIGRP route control implementation, only hub-to-spoke network designs are supported.

For more details about configuring mGRE DMVPN networks, see the [Dynamic Multipoint VPN](#) module. For general information about DMVPN, go to <http://www.cisco.com/go/dmvpn>.

How to Configure PfR to Control EIGRP Routes

- [Enabling PfR EIGRP Route Control and Setting a Community Value, page 4](#)
- [Disabling PfR EIGRP Route Control, page 5](#)
- [Manually Verifying the PfR EIGRP-Controlled Routes, page 6](#)

Enabling PfR EIGRP Route Control and Setting a Community Value

Perform this task on the master controller to enable EIGRP route control. While both BGP and static route control are enabled by default, EIGRP route control must be enabled using a command-line interface (CLI) command, **mode route metric eigrp**. PfR always attempts to control a prefix using BGP first. If BGP route control fails, static route control is tried. When EIGRP route control is enabled, PfR will attempt to control a prefix using BGP first. If no parent route is found, PfR will try to use EIGRP route control. If EIGRP route controls fails, static route control is tried.

This task can also set an extended community value for an injected EIGRP route to allow the routes to be uniquely identified. An EIGRP route may be injected by PfR to control the traffic defined by a traffic class when it goes out-of-policy (OOP). In this task, the PfR route control mode is configured globally with the **mode route control** command in OER master controller configuration mode, and any injected EIGRP routes will be tagged with a value of 700.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **oer master**
4. **mode route control**
5. **mode route metric eigrp tag *community***
6. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	oer master Example: Router(config)# oer master	Enters OER master controller configuration mode to configure a router as a master controller and to configure global operations and policies.

	Command or Action	Purpose
Step 4	<pre>mode route control</pre> <p>Example: Router(config-oer-mc)# mode route control</p>	<p>Configures the OER route control mode on a master controller.</p> <ul style="list-style-type: none"> The route and control keywords enable route control mode. In control mode, the master controller analyzes monitored traffic classes and implements changes based on policy parameters. <p>Note Only the syntax applicable to this task is shown. For more details, see the Cisco IOS Optimized Edge Routing Command Reference.</p>
Step 5	<pre>mode route metric eigrp tag community</pre> <p>Example: Router(config-oer-mc)# mode route metric eigrp tag 7000</p>	<p>Enables EIGRP route control and sets an EIGRP tag and community number value for injected EIGRP routes.</p> <ul style="list-style-type: none"> Use the tag keyword to apply a tag to an EIGRP route under OER control. The <i>community</i> argument is a number from 1 to 65535. <p>Note Only the syntax applicable to this task is shown. For more details about setting metrics for BGP and static routes, see the Cisco IOS Optimized Edge Routing Command Reference.</p>
Step 6	<pre>end</pre> <p>Example: Router(config-oer-mc)# end</p>	<p>Exits OER master controller configuration mode and returns to privileged EXEC mode.</p>

Disabling PfR EIGRP Route Control

Perform this task on the master controller to disable EIGRP route control.



Note

When this task is complete, PfR withdraws all the routes that are being controlled using the EIGRP protocol.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **oer master**
4. **no mode route metric eigrp**
5. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	<code>enable</code> Example: <code>Router> enable</code>	Enables privileged EXEC mode. <ul style="list-style-type: none">Enter your password if prompted.
Step 2	<code>configure terminal</code> Example: <code>Router# configure terminal</code>	Enters global configuration mode.
Step 3	<code>oer master</code> Example: <code>Router(config)# oer master</code>	Enters OER master controller configuration mode to configure a router as a master controller and to configure global operations and policies.
Step 4	<code>no mode route metric eigrp</code> Example: <code>Router(config-oer-mc)# no mode route metric eigrp</code>	Disables EIGRP route control and removes all the routes that are being controlled using the EIGRP protocol.
Step 5	<code>end</code> Example: <code>Router(config-oer-mc)# end</code>	Exits OER master controller configuration mode and returns to privileged EXEC mode.

Manually Verifying the PfR EIGRP-Controlled Routes

PfR automatically verifies route control changes in the network using NetFlow output. PfR monitors the NetFlow messages and uncontrols a traffic class if a message does not appear to verify the route control change. Perform the steps in this optional task if you want to manually verify that the traffic control implemented in the PfR control phase actually changes the traffic flow, and brings the OOP event to be in-policy.

All the steps in this task are optional and are not in any order. The information from these steps can verify that a specific prefix associated with a traffic class has been moved to another exit or entrance link interface, or that it is being controlled by PfR. The first two commands are entered at the master controller, the last two commands are entered at a border router.

Only partial command syntax for some of the **show** commands used in this task is displayed. For more details about OER **show** commands, see the [Cisco IOS Optimized Edge Routing Command Reference](#).

Prerequisites

- This task assumes that you have previously enabled EIGRP route control using PfR. To enable PfR EIGRP route control, see the [“Enabling PfR EIGRP Route Control and Setting a Community Value” section on page 4](#).

SUMMARY STEPS

1. **enable**
2. **show oer master prefix *prefix* [detail]**
3. Move to a border router to enter the next step.
4. **enable**
5. **show oer border routes eigrp [parent]**

DETAILED STEPS

Step 1 enable

Enables privileged EXEC mode. Enter your password if prompted.

```
Router> enable
```

Step 2 show oer master prefix *prefix* [detail]

This command is used to display the status of monitored prefixes. The output from this command includes information about the source border router, current exit interface, protocol, prefix delay, and egress and ingress interface bandwidth. In this example, the protocol displayed for the prefix 10.1.0.0/16 is EIGRP, which means that the parent route for the traffic class exists in the EIGRP routing table and EIGRP community values are used to control the prefix. Only syntax relevant to this task is shown in this step.

```
Router# show oer master prefix 10.1.0.0
```

OER Prefix Statistics:

Pas - Passive, Act - Active, S - Short term, L - Long term, Dly - Delay (ms),
 P - Percentage below threshold, Jit - Jitter (ms),
 MOS - Mean Opinion Score
 Los - Packet Loss (packets-per-million), Un - Unreachable (flows-per-million),
 E - Egress, I - Ingress, Bw - Bandwidth (kbps), N - Not applicable
 U - unknown, * - uncontrolled, + - control more specific, @ - active probe all
 # - Prefix monitor mode is Special, & - Blackholed Prefix
 % - Force Next-Hop, ^ - Prefix is denied

Prefix	State	Time	Curr BR	CurrI/F		Protocol				
				PasSDly	PasLDly		PasSUn	PasLUn	PasSLos	PasLLos
				ActSDly	ActLDly		ActSUn	ActLUn	EBw	IBw
				ActSJit	ActPMOS					
10.1.0.0/16	DEFAULT*	@69	10.1.1.1	Gi1/22		EIGRP				
	U	U	0	0	0	0				
	U	U	0	0	22	8				
	N	N								

Step 3 Move to a border router to enter the next step.

The next command is entered on a border router, not the master controller.

Step 4 enable

Enables privileged EXEC mode. Enter your password if prompted.

```
Router> enable
```

Step 5 show oer border routes eigrp [parent]

This command is entered on a border router. Use this command to display information about EIGRP routes controlled by PfR on a border router. In this example, the output shows that prefix 10.1.2.0/24 is being controlled by OER. This command is used to show parent route lookup and route changes to existing parent routes when the parent route is identified from the EIGRP routing table.

```
Router# show oer border routes eigrp
```

```
Flags: C - Controlled by oer, X - Path is excluded from control,
       E - The control is exact, N - The control is non-exact
```

Flags	Network	Parent	Tag
CE	10.1.2.0/24	10.0.0.0/8	5000

In this example, the **parent** keyword is used and more details are shown about the parent route lookup.

```
Router# show oer border routes eigrp parent
```

Network	Gateway	Intf	Flags
10.0.0.0/8	10.40.40.2	Ethernet4	1

Child Networks

Network	Flag
10.1.2.0/24	6

Troubleshooting Tips

If the **show** commands are not displaying output that verifies the EIGRP route control, use the **debug oer border routes eigrp** command with the optional **detail** keyword for more information. Debugging must be enabled before entering the required commands, and the debug output depends on which commands are subsequently entered.

Configuration Examples for Using PfR to Control EIGRP Routes

This section provides the following configuration example:

- [Enabling PfR EIGRP Route Control and Setting a Community Value: Example, page 8](#)

Enabling PfR EIGRP Route Control and Setting a Community Value: Example

In the following configuration example, PfR route control is enabled first, and then the EIGRP route control is enabled and configured to set an extended community value of 700 to any injected EIGRP routes:

```
oer master
 mode route control
 mode route metric eigrp tag 700
end
```

Where to Go Next

This module covers PfR EIGRP route control. To learn more about PfR, start with the “[Cisco IOS Optimized Edge Routing Overview](#)” and the “[Setting Up OER Network Components](#)” modules. To learn more about the OER phases (same as Performance Routing phases) identified in the “[Cisco IOS Optimized Edge Routing Overview](#)” module, read through the other modules in the following list:

- [Using Performance Routing to Profile the Traffic Classes](#)
- [Measuring the Traffic Class Performance and Link Utilization Using OER](#)
- [Configuring and Applying OER Policies](#)
- [Configuring Performance Routing Cost Policies](#)
- [Using OER to Control Traffic Classes and Verify the Route Control Changes](#)

Additional References

The following sections provide references related to the PfR EIGRP mGRE DMVPN Hub-and-Spoke Support feature.

Related Documents

Related Topic	Document Title
Cisco PfR technology overview	“ Cisco IOS Optimized Edge Routing Overview ” module
Concepts and configuration tasks required to set up PfR network components	“ Setting Up OER Network Components ” module
Cisco OER commands: complete command syntax, command mode, command history, defaults, usage guidelines and examples	Cisco IOS Optimized Edge Routing Command Reference
EIGRP Routing Protocol commands	Cisco IOS IP Routing: EIGRP Command Reference
Configuring mGRE DMVPN networks	Dynamic Multipoint VPN
General information about the DMVPN technology	http://www.cisco.com/go/dmvpn
Command Lookup Tool	http://tools.cisco.com/Support/CLILookup
<i>Cisco IOS Master Command List</i>	http://www.cisco.com/en/US/docs/ios/mcl/allreleasemcl/all_book.html

Standards

Standard	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	—

MIBs

MIB	MIBs Link
No new or modified MIBs are supported by this feature, and support for existing MIBs has not been modified by this feature.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

RFCs

RFC	Title
No new or modified RFCs are supported by this feature, and support for existing RFCs has not been modified by this feature.	—

Technical Assistance

Description	Link
<p>The Cisco Support website provides extensive online resources, including documentation and tools for troubleshooting and resolving technical issues with Cisco products and technologies.</p> <p>To receive security and technical information about your products, you can subscribe to various services, such as the Product Alert Tool (accessed from Field Notices), the Cisco Technical Services Newsletter, and Really Simple Syndication (RSS) Feeds.</p> <p>Access to most tools on the Cisco Support website requires a Cisco.com user ID and password.</p>	http://www.cisco.com/cisco/web/support/index.html

Feature Information for Using PfR to Control EIGRP Routes

Table 1 lists the release history for this feature.

Table 1 lists the features in this module and provides links to specific configuration information. Only features that were introduced or modified in Cisco IOS Release 15.0(1)M, or a later release appear in the table.

For information on a feature in this technology that is not documented here, see the “[Optimized Edge Routing Roadmap](#).”

Not all commands may be available in your Cisco IOS software release. For release information about a specific command, see the command reference documentation.

Use Cisco Feature Navigator to find information about platform support and software image support. Cisco Feature Navigator enables you to determine which Cisco IOS and Catalyst OS software images support a specific software release, feature set, or platform. To access Cisco Feature Navigator, go to <http://www.cisco.com/go/cfn>. An account on Cisco.com is not required.



Note

Table 1 lists only the Cisco IOS software release that introduced support for a given feature in a given Cisco IOS software release train. Unless noted otherwise, subsequent releases of that Cisco IOS software release train also support that feature.

Table 1 Feature Information for Using PfR to Control EIGRP Routes

Feature Name	Releases	Feature Information
PfR EIGRP mGRE DMVPN Hub-and-Spoke Support	12.2(33)SRE 15.0(1)M	The PfR EIGRP feature introduces PfR route control capabilities based on EIGRP by performing a route parent check on the EIGRP database. The following commands were introduced or modified: debug oer border routes, mode (OER), show oer border routes, and show oer master prefix.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2009 Cisco Systems, Inc. All rights reserved.

