



X.25 Call Confirm Packet Address Control

The X.25 Call Confirm Packet Address Control feature provides options for controlling the source and destination addresses that are encoded in outgoing Call Confirm packets. You can suppress the addresses completely or specify that the addresses originally proposed in the received Call packet be encoded in the Call Confirm packet. This feature may be necessary when connecting to equipment that implements a nonstandard or proprietary X.25 service.

Feature Specifications for the X.25 Call Confirm Packet Address Control Feature

Feature History

Release	Modification
12.3(2)T	This feature was introduced.

Supported Platforms

Cisco 1400 series, Cisco 1710, Cisco 2500 series, Cisco 2691, Cisco 3631, Cisco 3640, Cisco 3660, Cisco 3725, Cisco 3745, Cisco 4500 series, Cisco 7100 series, Cisco 7200 series, Cisco 7400 series, Cisco 800 series, Cisco AS5300, Cisco AS5350, Cisco AS5400, Cisco AS5800, Cisco AS5850, Cisco UBR720

Finding Support Information for Platforms and Cisco IOS Software Images

Use Cisco Feature Navigator to find information about platform support and Cisco IOS software image support. Access Cisco Feature Navigator at <http://www.cisco.com/go/fn>. You must have an account on Cisco.com. If you do not have an account or have forgotten your username or password, click **Cancel** at the login dialog box and follow the instructions that appear.

Contents

- [Information About X.25 Call Confirm Packet Address Control, page 2](#)
- [How to Configure X.25 Call Confirm Packet Address Control, page 3](#)
- [Configuration Examples for X.25 Call Confirm Packet Address Control, page 5](#)
- [Additional References, page 6](#)
- [Command Reference, page 7](#)



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

© 2007 Cisco Systems, Inc. All rights reserved.

Information About X.25 Call Confirm Packet Address Control

To configure X.25 Call Confirm packet address control, you should understand the following concepts:

- [Address Encoding in X.25 Call Confirm Packets, page 2](#)
- [X.25 Call Confirm Packet Address Control, page 2](#)
- [Benefits of X.25 Call Confirm Packet Address Control, page 3](#)

Address Encoding in X.25 Call Confirm Packets



Note

This document refers to Call packets and Call Confirm packets. These names differ from those standardized by X.25. The standard distinguishes between a Call packet sent by the data terminal equipment (DTE) station (a Call Request) and one sent by the data communications equipment (DCE) station (an Incoming Call), and similarly between a Call Confirm packet sent by the DTE (a Call Accepted) and one sent by the DCE (a Call Connected).

The packets are encoded identically, and in many cases the processing that X.25 does is identical; however, there are cases where the behavior is predicated on the station type that is receiving or sending the packet.

An X.25 switched virtual circuit (SVC) is established between two stations through the exchange of a Call and a Call Confirm packet. The X.25 standards specify that Call packets include source and destination addresses. Call Confirm packets might also encode source and destination addresses, depending on the circumstances. When the source address is encoded in a Call Confirm packet, the X.25 standards require that it be the same address that was specified in the Call packet. When the destination address is encoded in a Call Confirm packet and is different from the destination address in the Call packet, the newer X.25 standards (those after ITU-T 1980 X.25) require that the reason for the difference be signaled by the encoding of the Called Line Address Modified Notification (CLAMN) facility.

For example, when an X.25 Call is routed through a configured hunt group, a Call Redirection/Call Deflection Notification (CRCDN) facility is encoded in the forwarded call along with the original destination address. This encoding notifies the receiver that the Call packet was redistributed by a hunt group. If such a Call is accepted by a returned Call Confirm packet, a CLAMN facility and the destination address of the accepting station will be encoded in the Call Confirm packet. This encoding notifies the originator that the accepting destination was reached by distribution through a hunt group.

X.25 Call Confirm Packet Address Control

Network devices that implement nonstandard X.25 service may have different requirements for address encoding in the Call Confirm packet. The **no x25 security call-confirm address out** command enables you to control the source and destination addresses that are encoded in outgoing Call Confirm packets. You can suppress the addresses completely, or you can specify that the addresses originally presented in the received Call packet be encoded unmodified in the Call Confirm packet. When address suppression is configured, any address block in the Call Confirm packet will specify the null address (zero digits) for the suppressed addresses.

**Caution**

X.25 specifies address signaling behavior as a security measure to ensure that connecting devices are given clear notice of a Call setup that encountered redirection, deflection, or distribution to an alternate destination. Disabling these security features should be done only when the risks of doing so are understood and acceptable.

X.25 Call Confirm packet address control can be configured on an interface or in an X.25 profile. When the feature is configured on an interface, all Call Confirm packets sent over the services that use that interface will be affected, including SVCs that use a configuration from a subinterface. When the feature is configured in an X.25 profile, all services using that profile will be affected.

Benefits of X.25 Call Confirm Packet Address Control

Users implementing nonstandard X.25 service may have specific requirements for the encoding of source and destination addresses in Call Confirm packets. The X.25 Call Confirm Packet Address Control feature enables you to control the source and destination addresses that are encoded in outgoing Call Confirm packets. This feature allows you to suppress the addresses completely or specify that the addresses originally proposed in the received Call packet be encoded in the Call Confirm packet.

How to Configure X.25 Call Confirm Packet Address Control

Perform one of the following tasks to configure X.25 Call Confirm packet control:

- [Configuring X.25 Call Confirm Packet Address Control on an Interface, page 3](#)
- [Configuring X.25 Call Confirm Packet Address Control in an X.25 Profile, page 4](#)

Configuring X.25 Call Confirm Packet Address Control on an Interface

To suppress the addresses in a Call Confirm packet, or to specify that the addresses presented in the original Call packet are to be encoded in the Call Confirm packet, perform the following steps:

SUMMARY STEPS

1. enable
2. **configure terminal**
3. **interface serial** *number*
4. **encapsulation x25**
5. **no x25 security call-confirm address out source** {suppress | unmodified} **dest** {suppress | unmodified}
6. end

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> Enter your password if prompted.
Step 2	configure terminal Example: Router# configure terminal	Enters global configuration mode.
Step 3	interface serial number Example: Router(config)# interface serial 0	Specifies an interface and enters interface configuration mode.
Step 4	encapsulation x25 Example: Router(config-if)# encapsulation x25	Enables the default X.25 DTE operation mode.
Step 5	no x25 security call-conf address out source {suppress unmodified} dest {suppress unmodified} Example: Router(config-if)# no x25 security call-conf address out source suppress dest suppress	Suppresses the addresses in transmitted X.25 Call Confirm packets or specifies that the addresses originally received in a Call packet are to be encoded in the Call Confirm packet.
Step 6	exit Example: Router(config-if)# exit	Returns to global configuration mode.

Troubleshooting Tips

Use the **debug x25 events** command to determine when the source and destination addresses in Call Confirm packets have been suppressed or configured to remain unmodified from the addresses proposed in the original Call packet.

Configuring X.25 Call Confirm Packet Address Control in an X.25 Profile

To suppress the addresses in a Call Confirm packet, or to specify that the addresses presented in the original Call packet are to be encoded in the Call Confirm packet, perform the following steps:

SUMMARY STEPS

1. **enable**
2. **configure terminal**

3. `x25 profile name {dce | dte | dxe}`
4. `no x25 security call-conf address out source {suppress | unmodified} dest {suppress | unmodified}`
5. `exit`

DETAILED STEPS

	Command or Action	Purpose
Step 1	<code>enable</code> Example: Router> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	<code>configure terminal</code> Example: Router# configure terminal	Enters global configuration mode.
Step 3	<code>x25 profile name {dce dte dxe}</code> Example: x25 profile NetworkNodeA dce	Configures an X.25 profile.
Step 4	<code>no x25 security call-conf address out source {suppress unmodified} dest {suppress unmodified}</code> Example: Router(config-if)# no x25 security call-conf address out source suppress dest suppress	Suppresses the addresses in transmitted X.25 Call Confirm packets or specifies that the addresses originally received in a Call packet are to be encoded in the Call Confirm packet.
Step 5	<code>exit</code> Example: Router(config-if)# exit	Returns to global configuration mode.

Troubleshooting Tips

Use the `debug x25 events` command to determine when the source and destination addresses in Call Confirm packets have been suppressed or configured to remain unmodified from the addresses proposed in the original Call packet.

Configuration Examples for X.25 Call Confirm Packet Address Control

- [Suppressing Addresses in Call Confirm Packets: Example, page 6](#)
- [Using Addresses from Original Call Packets in the Call Confirm Packets: Example, page 6](#)

Suppressing Addresses in Call Confirm Packets: Example

The following example shows how to suppress both the source and destination addresses in Call Confirm packets:

```
interface serial 0
  no ip address
  encapsulation x25
  no x25 security call-conf address out source suppress dest suppress
```

Using Addresses from Original Call Packets in the Call Confirm Packets: Example

The following example show how to specify that the addresses presented in the original Call packet are encoded in the Call Confirm packet:

```
interface serial 0
  no ip address
  encapsulation x25
  no x25 security call-conf address out source unmodified dest unmodified
```

Additional References

For additional information related to X.25 call confirm packet address control, consult the references in the following sections.

Related Documents

Related Topic	Document Title
X.25 commands	<i>Cisco IOS Wide-Area Networking Command Reference, Release 12.3</i>
X.25 configuration tasks and examples	<i>Cisco IOS Wide-Area Networking Configuration Guide, Release 12.3</i>
Commands and tasks for configuring suppression of CRCND and CLAMN security signaling facilities	<i>X.25 Suppression of Security Signaling Facilities, 12.2(13)T new feature document</i>

Standards

Standards ¹	Title
ITU-T X.25	<ul style="list-style-type: none"> • <i>ITU-T 1980 X.25 Recommendation</i> • <i>ITU-T 1984 X.25 Recommendation</i> • <i>ITU-T 1988 X.25 Recommendation</i> • <i>ITU-T 1993 X.25 Recommendation</i>

1. Not all supported standards are listed.

MIBs

MIBs ¹	MIBs Link
None	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

1. Not all supported MIBs are listed.

RFCs

RFCs	Title
None	—

Technical Assistance

Description	Link
Technical Assistance Center (TAC) home page, containing 30,000 pages of searchable technical content, including links to products, technologies, solutions, technical tips, and tools. Registered Cisco.com users can log in from this page to access even more content.	http://www.cisco.com/public/support/tac/home.shtml

Command Reference

The following commands are introduced or modified in the feature or features documented in this module. For information about these commands, see the *Cisco IOS Wide-Area Networking Command Reference* at http://www.cisco.com/en/US/docs/ios/wan/command/reference/wan_book.html. For information about all Cisco IOS commands, go to the Command Lookup Tool at <http://tools.cisco.com/Support/CLILookup> or to the *Cisco IOS Master Commands List*.

- **x25 security call-conf address out**

CCVP, the Cisco logo, and Welcome to the Human Network are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, iQuick Study, LightStream, Linksys, MeetingPlace, MGX, Networkers, Networking Academy, Network Registrar, PIX, ProConnect, ScriptShare, SMARTnet, StackWise, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0711R)

Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.

© 2007 Cisco Systems, Inc. All rights reserved.