



# Supported Device Tables for the Cisco Application Networking Manager 2.0

---

**Revised: September 28, 2009**

The following sections show the Cisco devices supported by Cisco Application Networking Manager (ANM) 2.0:

- [Supported Cisco Application Control Engine \(ACE\) Modules and Appliances, page 2](#)
- [Supported Switches, page 4](#)
- [Supported Routers, page 4](#)
- [Supported Supervisor Engines, page 5](#)
- [Supported Content Switching Modules, page 5](#)
- [Supported Content Services Switch and Global Site Selector, page 5](#)
- [Supported Browsers, page 6](#)

You can find updated information about new device support on Cisco.com, at [http://www.cisco.com/en/US/docs/net\\_mgmt/application\\_networking\\_manager/2.0/device\\_support/table/sdt.html](http://www.cisco.com/en/US/docs/net_mgmt/application_networking_manager/2.0/device_support/table/sdt.html).



---

**Americas Headquarters:**  
**Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA**

© 2009 Cisco Systems, Inc. All rights reserved.

# Supported Cisco Application Control Engine (ACE) Modules and Appliances

The following sections identify the supported ACE devices:

- [Supported ACE Modules, page 2](#)
- [Supported ACE Appliances, page 2](#)

## Supported ACE Modules

ANM 2.0 supports Cisco ACE modules ACE10-6500-K9 and ACE20-MOD-K9 running these software versions:

- A2(1.6)
- A2(1.5a)
- A2(1.5)
- A2(1.4a)
- A2(1.4)
- A2(1.3)
- A2(1.2)
- A2(1.1a)
- A2(1.1)
- A2(1.0a)
- A2(1.0)
- 3.0(0)A1(6.3b)
- 3.0(0)A1(6.3a)
- 3.0(0)A1(6.3)

## Supported ACE Appliances

ANM 2.0 supports Cisco ACE 4710 appliances running these software versions, organized by major release:

- A3(2.3)
- A3(2.2)
- A3(2.1)
- A3(2.0)
- A3(1.0)
- A1(8.0a)
- A1(8.0)
- A1(7b)
- A1(7a)

For more information about ACE appliances and available software versions, see ACE product literature at <http://www.cisco.com/en/US/products/ps6906/index.html>.

## Supported Switches

ANM 2.0 supports Cisco Catalyst 6500 series switches with Cisco Supervisor 720 modules and Multilayer Switch Feature Cards (MSFC3).

Table 1 lists the switches and sysObjectIDs that ANM 2.0 supports.

**Table 1** ANM 2.0 Supported Switches and sysObjectIDs

Switch	sysObjectID
Cisco Catalyst 6506 switch	1.3.6.1.4.1.9.1.282
Cisco Catalyst 6509 switch	1.3.6.1.4.1.9.1.283
Cisco Catalyst 6509SP switch	1.3.6.1.4.1.9.1.310
Cisco Catalyst WS-C6503 switch	1.3.6.1.4.1.9.1.449
Cisco Catalyst WS-C6504-E switch	1.3.6.1.4.1.9.1.657
Cisco Catalyst WS-C6509-NEBA switch	1.3.6.1.4.1.9.1.534
Cisco Catalyst WS-C6513 switch	1.3.6.1.4.1.9.1.400

Cisco Catalyst 6500 series switches require IOS software version 12.2(18)SXF4 or later.

For more information about Cisco Catalyst 6500 series switches and supported software, refer to the product literature at <http://www.cisco.com/en/US/products/hw/switches/ps708/index.html>.

## Supported Routers

Table 2 lists the Cisco 7600 series routers and the sysObjectIDs that ANM 2.0 supports.

**Table 2** ANM 2.0 Supported Routers and sysObjectIDs

Routers	sysObjectID
Cisco OSR-7603 router	1.3.6.1.4.1.9.1.401
Cisco 7606 router	1.3.6.1.4.1.9.1.402
Cisco 7609 router	1.3.6.1.4.1.9.1.509
Cisco 7613 router	1.3.6.1.4.1.9.1.528
Cisco 7604 router	1.3.6.1.4.1.9.1.658
Cisco 7603-S router	1.3.6.1.4.1.9.1.862
Cisco 7606-S router	1.3.6.1.4.1.9.1.863
Cisco 7609-S router	1.3.6.1.4.1.9.1.864

The Cisco 7600 series router requires either IOS software version 12.2(18)SXF4 or 12.2(33)SR8 or later. Note that IOS release 12.2(33)SXH runs only on the Cisco Catalyst 6500 switch.

For more information about Cisco 7600 series routers and supported software, refer to the product literature at <http://www.cisco.com/en/US/products/hw/routers/ps368/>.

## Supported Supervisor Engines

Table 3 identifies the Cisco Supervisor Engines and software versions that ANM 2.0 supports.

**Table 3** ANM 2.0 Supported Supervisor Engines

Models	IOS Software Versions
WS-Sup720-3B	12.2(18)SXF4 or later <sup>1</sup>
WS-Sup720-3BXL	12.2(18)SXF4 or later <sup>2</sup>

1. IOS release 12.2(33)SXH runs only on the Cisco Catalyst 6500 switch.
2. IOS release 12.2(33)SXH runs only on the Cisco Catalyst 6500 switch.

For more information about Cisco Catalyst 6500 series switches and supported software, refer to the product literature at <http://www.cisco.com/en/US/products/hw/switches/ps708/index.html>.

## Supported Content Switching Modules

Table 4 identifies the Content Switching Modules and their software versions that ANM 2.0 supports.

**Table 4** ANM 2.0 Supported CSMs and Software Versions

Device	Version
Cisco Content Switching Module (CSM)	4.2(4), 4.3(1)
Cisco Content Switching Module with SSL (CSM-S)	2.1

## Supported Content Services Switch and Global Site Selector

Table 5 identifies the Cisco Content Services Switch (CSS) and the Cisco Global Site Selector (GSS) software versions that ANM 2.0 supports.

**Table 5** ANM 2.0 Supported CSS and GSS Software Versions

Device	Version
Cisco Content Services Switch	8.10, 8.20
Cisco Global Site Selector	3.0(2), 3.1(0)

# Supported Browsers

Table 6 identifies the browsers that ANM 2.0 supports. All browsers must have cookies, Javascript/scripting, and popup windows enabled.

**Table 6** ANM 2.0 Supported Browsers

Browser	Version	Client Platform
Microsoft Internet Explorer	6.0 with Service Pack 2 or 7.0 with Service Pack 2	Windows XP and Windows Vista
Firefox	2.0	<ul style="list-style-type: none"><li>Windows XP and Windows Vista</li><li>Red Hat Enterprise Linux 4.x/5.x</li></ul>