



CHAPTER 13

Using the Program Options

Changing the Date and Time Format

To change the date and time format:

-
- Step 1** From the Cisco netManager console, select **Configure > Program Options**.
 - Step 2** Select the **Regional** section.
For each of the three date formats, select the one that best suits your needs.
 - Step 3** Click **OK**.
These formats can be seen in use on several of the reports available on the Reports view.
-

Changing how Long Report Data is Stored

Ping Active Monitor data is stored in the Cisco netManager database to populate the Performance reports available in the application.

-
- Step 1** From the Cisco netManager console, select **Configure > Program Options**.
 - Step 2** In Program Options, select **Report Data**.
On the Report Data section, you can change the settings for raw data, hourly data, and daily data.
 - Step 3** Click **OK** to save the changes.
You can see how many rows in the database that the data takes up by viewing the numbers under the time settings.
-

Changing the Device State Colors or Icons

To change the device state colors or icons:

-
- Step 1** From the Cisco netManager console, select **Configure > Program Options**.

- Step 2** In Program Options, select **Device States**.
To change an existing icon or state, select the entry from the list and click **Edit**.
- Step 3** Adjust the shape and color of the icon using the settings in the **Device State Editor**.
- Step 4** Click **OK** to save changes.
If the default settings do not fit your needs, click **Add** to create a new device state, using the internal state and state time that you need.
-

Stopping and Starting the Secure Web Server

To stop and restart the secure web server:

- Step 1** From the Cisco netManager console, select **Configure > Program Options**.
- Step 2** In **Program Options**, select **Web server**.
- Step 3** Select **Use SSL access** to start the server with SSL.
- Step 4** Click **OK**.
You can change the port that the SSL server runs on by changing the port number next to the **Enable SSL web server on port** option.
-

Stopping and Starting the Web Server

To stop and restart the Web server:

- Step 1** On the Cisco netManager console, select **Configure > Program Options**.
- Step 2** On the Program Options dialog, select **Web Server**.
Select **Enable web server on port:** to start the server, then clear the option to stop the server.
- Step 3** Click **OK** to save your changes.
You can change the port that the server runs on by changing the port number next to the **Enable web server on port:** option.
-

Changing Clock/Regional Preferences

To use a 24-hour clock instead of the default 12-hour clock:

- Step 1** From the Cisco netManager console, select **Configure > Program Options**.
- Step 2** Select the **Regional** section.

Step 3 Select the **Use 24 hour clock** option.

Step 4 Click **OK**.
