



Read Me First (Solaris)

You must install the software in this package on a system that meets specific requirements. You need to configure client systems and some applications before use.

The contents of the LAN Management Solutions Bundle are listed in the suggested installation order:

1. CiscoWorks2000 CD One Second Edition (CD One)—CiscoWorks2000 Server, CiscoView 5.1, and the Network Management Integration Module that supports third-party Network Management systems.
2. Resource Manager Essentials 3.1 (Essentials)—Web-based administration tool for collecting the monitoring, fault, and availability information needed to track devices critical to the network.
3. Campus Manager 3.0 (Campus)—Web-enabled version of the CWSI Campus product providing topology services and ATM, LANE, and VLAN utilities.
4. TrafficDirector 5.8 (TD)—RMON-based reporting tool for network traffic analysis.
5. Content Flow Monitor 1.0 (CFM)—Web-based performance monitoring application for managing Cisco server load-balancing devices.



Note

You must install CiscoWorks2000 CD One Second Edition first.

Minimum Server System Requirements

Table 1 shows the minimum server system requirements for each application and combinations of applications.

Table 1 Minimum Server System Requirements

Requirement Type	CD One Only	CD One and Campus	CD One and Essentials	CD One and CFM	CD One and TD	Entire LAN Bundle
Processor	Ultra 10	Ultra 10	Ultra 10	Ultra 10	Ultra 10	Ultra 60MP
Memory (RAM)	256 MB	256 MB	256 MB	256 MB	256 MB	512 MB
Swap space ¹	512 MB	512 MB	512 MB	512 MB	512 MB	1 GB



Corporate Headquarters: Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Copyright © 2000. Cisco Systems, Inc. All rights reserved.

Table 1 Minimum Server System Requirements (continued)

Requirement Type	CD One Only	CD One and Campus	CD One and Essentials	CD One and CFM	CD One and TD	Entire LAN Bundle
Available drive space	2 GB	4 GB	4 GB and space for software management files	4 GB	3 GB	6 GB and space for software management files
Additional hardware	CD-ROM drive and 17-inch color monitor					
System software	Solaris 2.6 with patches ² 105181-11, 105210-17, 105490-05 ³ , 105529-07, and 105568-13					
Browser	If system is also used as a client, a browser is required (refer to Table 2)					

1. Swap space should be double the amount of RAM. If your server has more than the minimum recommended RAM, set the swap space to double your servers RAM.
2. Make sure patch 106292-03 is not installed on your system. Otherwise CD One will not install.
3. Or patch 107733-05.

Minimum Client System Requirements

Table 2 shows the minimum client system requirements for a network with 950 or fewer devices. For information about configuring client systems, refer to *Installing and Setting Up CiscoWorks2000 CD One Second Edition*.

Table 2 Minimum Client System Requirements

Requirement Type	Minimum Requirement
System software and hardware	<ul style="list-style-type: none"> • Client system: <ul style="list-style-type: none"> – IBM PC-compatible system with 300 MHz Pentium III processor running Windows NT 4.0, Windows 95, or Windows 98. – Sun SPARCstation or Sun Ultra 10 running Solaris 2.5.1 or Solaris 2.6. – IBM RS/6000 workstation running AIX 4.3.3. – HP-UX workstation running HP-UX 10.20 or 11.0. • Color monitor with video card set to 256 colors.
Memory (RAM)	128 MB
Browser	One of the following browsers: <ul style="list-style-type: none"> • Microsoft Internet Explorer 5.0 or 5.01 (Windows NT, Windows 95/98). Microsoft Java Virtual Machine (JVM) versions 5.0.0.3186 or later. To verify the JVM version, select View > Java Console. • Netscape Navigator 4.6.1 or 4.7 (Windows NT, Windows 95/98, Solaris 2.5.1 or 2.6, HP-UX 10.20 or 11.0, AIX 4.33).