



Supported Devices Table for Campus Manager 3.3

Revised: June 27, 2007

The following table lists the Cisco devices supported by Campus Manager 3.3 with Incremental Device Update 11.0 (IDU 11.0):

[Table 1, Devices Supported in IDU 11.0 on Campus Manager 3.3](#)

Incremental Device Update 11.0 contains updated files necessary for Campus Manager 3.3 to support the Cisco devices listed in [Table 1](#). If you are a registered user, you can download IDU for Campus.

An IDU is a software package that enables an application to support new devices. IDU might also contain bug fixes. IDU 11.0 requires one file, *CM33.IDU.v11-0.sol.zip* (for Solaris) or *CM33.IDU.v11-0.win.exe* (for Windows), to be downloaded and installed. You can download IDUs for Campus and their readme files from Cisco.com. To access it, log into Cisco.com and download it from:

<http://www.cisco.com/cgi-bin/tablebuild.pl/cw2000-campus>

The following tables show the Cisco devices supported by Campus Manager 3.3:

- [Table 2, Devices Supported in IDU 10.0 on Campus 3.3](#)
- [Table 3, Devices Supported in IDU 9.0 on Campus 3.3](#)
- [Table 4, Devices Supported in IDU 8.0 on Campus 3.3](#)
- [Table 5, Devices Supported in IDU 7.0 on Campus 3.3](#)
- [Table 6, Devices Supported in IDU 6.0 on Campus 3.3](#)
- [Table 7, Devices Supported in IDU 5.0 on Campus 3.3](#)
- [Table 8, Devices Supported in IDU 4.0 on Campus 3.3](#)
- [Table 9, Cisco Routers](#)
- [Table 10, Cisco Fast Hubs](#)
- [Table 11, Cisco Access Servers](#)
- [Table 12, Cisco Switches](#)
- [Table 13, Cisco Content Networking Devices](#)
- [Table 14, Cisco Wireless LAN Products](#)
- [Table 15, Cisco Voice Gateways](#)



Corporate Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Copyright © 2005 Cisco Systems, Inc. All rights reserved.

- [Table 16, Network Switch Probes](#)
- [Table 17, IP Telephony Devices](#)
- [sysObjectID for Devices Supported in Campus Manager 3.3](#)

To see a list of packages installed on your CiscoWorks server, select **Server Configuration >About the Server >Applications and Versions**. Then, click the application name in the Applications Installed table.

Table 1 *Devices Supported in IDU 11.0 on Campus Manager 3.3*

Device Type	Devices/ Modules Supported	Sys ObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco Aironet AP/BR Series	AP 1130	1.3.6.1.4.1.9.1.618	Yes	—	—	—	Yes	Yes	12.2(13)JA
Cisco Catalyst 6500/7600 Series Supervisor Modules	SUP 720-3BXL	—	Yes	Yes	—	—	Yes ^{1, 2}	Yes	12.2(17a)SXA
Cisco Catalyst 7600 Series Switches	Catalyst 7609	1.3.6.1.4.1.9.5.55	Yes	Yes	—	—	Yes ^{1, 2}	Yes	8.1(3)
Cisco Content Engine Series	CE 511	1.3.6.1.4.1.9.1.595	Yes	—	—	—	—	Yes	5.2.1.5
Cisco Gigabit Ethernet Switching Module	CGESM	1.3.6.1.4.1.11.2.3.7.11.33.3.1.1	Yes	Yes	—	—	Yes	Yes	12.2(25)SE
Cisco MDS 9200 Series Multi-layer Fabric Switches	9216A	1.3.6.1.4.1.9.12.3.1.3.442	Yes ²	—	—	—	—	Yes ²	2.0(2b)
Cisco Small Business Routers	SB 101	1.3.6.1.4.1.9.1.627	Yes	—	—	—	—	Yes	12.3(8)YG
	SB 106	1.3.6.1.4.1.9.1.628							
	SB 107	1.3.6.1.4.1.9.1.629							

1. Support for IP Phones has been provided.
2. Support for this device has not been tested.

Table 2 *Devices Supported in IDU 10.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysobjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco 1800 Series Routers	1841	1.3.6.1.4.1.9.1.620	Yes	—	—	—	Yes ¹	Yes	12.3(8)T4
Cisco 1900 Mobile Wireless Routers	MWR 1900	1.3.6.1.4.1.9.1.398	Yes	—	—	—	Yes ¹	Yes	12.2(15)MC1
Cisco 2800 Series Routers	2801	1.3.6.1.4.1.9.1.619	Yes	—	—	—	Yes ¹	Yes	12.3(8)T4
	2811	1.3.6.1.4.1.9.1.576							
	2821	1.3.6.1.4.1.9.1.577							
	2851	1.3.6.1.4.1.9.1.578							
Cisco 3800 Series Routers	3825	1.3.6.1.4.1.9.1.543	Yes	—	—	—	Yes ¹	Yes	12.3(11)T
	3845	1.3.6.1.4.1.9.1.544							
Cisco Catalyst 4900 Series Switches	4948	1.3.6.1.4.1.9.1.626	Yes	Yes	—	—	Yes ²	Yes	12.2(20)EWA
Cisco Intelligent Gigabit Ethernet Switch Module	IGESM	1.3.6.1.4.1.9.1.592	Yes	Yes	—	—	Yes ²	Yes	12.1(14)AY1
Cisco Catalyst 3550 Series Switches	3560G-24PS	1.3.6.1.4.1.9.1.614	Yes	Yes	—	—	Yes ²	Yes	12.2(20)SE3
	3560G-24TS	1.3.6.1.4.1.9.1.615							
	3560G-48PS	1.3.6.1.4.1.9.1.616							
	3560G-48TS	1.3.6.1.4.1.9.1.617							
Cisco Catalyst 3750 Series Switches	C3750-24ME	1.3.6.1.4.1.9.1.574	Yes	Yes	—	—	Yes ²	Yes	12.1(14)AX1
	3750G-24PS	1.3.6.1.4.1.9.1.516							12.2(20)SE3
	3750G-48TS								
	3750G-24TS-1U								
	3750G-48PS								
Cisco Catalyst 4000 Series Supervisor Module	SUP 2 Plus (20G)	—	Yes	Yes	—	—	Yes ²	Yes	12.2(20)EWA

1. User tracking will be provided using ARP.
2. Support for IP phones is also provided.

Table 3 *Devices Supported in IDU 9.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysobjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco Aironet Devices	WMIC Bridge 3201	1.3.6.1.4.1.9.1.581	Yes	—	—	—	Yes	Yes	12.2(15)JK
	BR 1300	1.3.6.1.4.1.9.1.565							12.2(15)JA
Cisco Catalyst 6500 and 7600 Service Modules	CMM ¹	1.3.6.1.4.1.9.1.573	Yes	—	—	—	—	Yes	12.1(20)E ² , 12.2(17)SX ³
Cisco 7000 Series Routers	RPM-PR	1.3.6.1.4.1.9.1.457	Yes	—	—	—	—	Yes	12.2(15) MC1
Cisco Catalyst 6500 Series Switches	6509-NEB-A-I OS	1.3.6.1.4.1.9.1.534	Yes	Yes	—	—	Yes ⁴	Yes	12.1(20) E3
Cisco 7600 Series Routers	7613-IOS	1.3.6.1.4.1.9.1.528	Yes	Yes	—	—	Yes ⁴	Yes	12.2(17b)SXA2
Cisco Mobile Wireless Routers 1900 Series	MWR 1941	1.3.6.1.4.1.9.1.520	Yes	—	—	—	—	Yes	12.2(15) MC1a

1. Communication Media Module.
2. Minimum supported version for SUP I and SUP II.
3. Minimum supported version for SUP III.
4. Support for IP phones is also provided.

Table 4 *Devices Supported in IDU 8.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysobjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco Content Engines	CE-590	1.3.6.1.4.1.9.1.411	Yes	—	—	—	—	Yes	ACNS 4.2
Cisco IAD Series Routers	IAD 2431- 1T1E1	1.3.6.1.4.1.9.1.548	Yes	—	—	—	Yes ¹	Yes	12.3(7)T
	IAD 2431- 8FXS	1.3.6.1.4.1.9.1.546							
	IAD 2431- 16FXS	1.3.6.1.4.1.9.1.547							
	IAD 2432- 24FXS	1.3.6.1.4.1.9.1.549							

Table 4 *Devices Supported in IDU 8.0 on Campus 3.3 (Continued)*

Device Type	Devices/ Modules Supported	sysobjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco IP Phones	7902, 7905, 7912	—	—	—	—	—	Yes	Yes	—
Cisco SOHO Series Routers	SOHO 78	1.3.6.1.4.1.9.1.383	Yes ²	—	—	—	Yes ¹	Yes	12.2.1- XE2
Cisco Storage Switches	MDS 9216	1.3.6.1.4.1.9.12.3. 1.3.380	Yes	—	—	—	—	Yes	SAN OS 1.0.5
	MDS 9509	1.3.6.1.4.1.9.12.3. 1.3.376							
Cisco 3750 Series Stack Switches	3750-24PS	1.3.6.1.4.1.9.1.516	Yes	Yes	—	—	Yes	Yes ³	12.2.18-SE (ED)
	3750-48PS								
	3750-16TD								
Network Analysis Module for Cisco 2600 Series	NAM	1.3.6.1.4.1.9.1.467	Yes ⁴	—	—	—	—	—	3.2(1A)

1. User Tracking will be provided using ARP.
2. Since this device does not support CDP MIB, Topology is partially supported. Because of this, the device cannot be used as a seed device and cannot discover other devices that are further behind this device.
3. Support for IP Phones is also provided.
4. IDU is supporting NAM as a module on Cisco 2600 series routers rather than as an individual device, due to lack of CDP MIB support.

Table 5 *Devices Supported in IDU 7.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco AP Aironet Devices	AP 350 IOS	1.3.6.1.4.1.9.1.552	Yes	—	—	—	Yes ¹	Yes	12.2 (13) JA1
Cisco Catalyst 2900 Series Devices	C2948G-GE-TX	1.3.6.1.4.1.9.5.62	Yes	Yes	—	—	Yes ¹	Yes	8.2 (1) GLX
Cisco Catalyst 4000 Series Devices	C4510R SUP V IOS	1.3.6.1.4.1.9.1.537	Yes	Yes	—	—	Yes ¹	Yes	12.2 (18) EW (1.12)

Table 5 *Devices Supported in IDU 7.0 on Campus 3.3 (Continued)*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco DSL Switches	6015 IP DSL	1.3.6.1.4.1.9.1.299	Yes	—	—	—	No	Yes	12.2 (12) DA5
	6160 IP DSL	1.3.6.1.4.1.9.1.297							
	6260 IP DSL	1.3.6.1.4.1.9.1.253							
Cisco 3560 Series Switches	3560-24PS-S	1.3.6.1.4.1.9.1.563	Yes	Yes	—	—	Yes ¹	Yes	12.1 (19) EA1
	3560-24PS-E	1.3.6.1.4.1.9.1.563							
	3560-48PS-E	1.3.6.1.4.1.9.1.564							
	3560-48PS-S	1.3.6.1.4.1.9.1.564							
Cisco 3700 Series Switches	C3750 Stack (12 SFP)	1.3.6.1.4.1.9.1.516	Yes	Yes	—	—	Yes ¹	Yes	12.1 (19) EA1a
Cisco 7600 Series Routers	Cisco 7609	1.3.6.1.4.1.9.1.509	Yes	Yes	—	—	No	Yes	12.2 (14) SX1

1. Support for IP Phones are also provided.

Table 6 *Devices Supported in IDU 6.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco SOHO Series Routers	SOHO 91	1.3.6.1.4.1.9.1.498	Yes ¹	—	—	—	Yes ²	Yes	12.2(8) YN
	SOHO 96	1.3.6.1.4.1.9.1.500		—	—	—	Yes ²	Yes	12.2(11) YV
	SOHO 97	1.3.6.1.4.1.9.1.496		—	—	—	Yes ²	Yes	12.2(8) YN
Cisco 3200 Series Mobile Access Routers	3220	1.3.6.1.4.1.9.1.553	Yes	—	—	—	—	Yes	12.3(2) XA1
Cisco Catalyst 2950 Series	2950-48T	1.3.6.1.4.1.9.1.559	Yes	Yes ³	—	—	Yes ³	Yes	12.1(19)
	2950-48SX	1.3.6.1.4.1.9.1.560							
Cisco Catalyst 2970 Series Switch	C2970G-24TS	1.3.6.1.4.1.9.1.561	Yes	Yes ³	—	—	Yes ³	Yes	12.1(14)EA1
Cisco Catalyst 4000 Series Supervisor Module	Sup II-Plus	1.3.6.1.4.1.9.5.59	Yes	Yes	—	—	Yes ³	Yes	12.1(19)EW1
Cisco IAD 2400 Series	IAD 2430	1.3.6.1.4.1.9.1.545	Yes	—	—	—	—	Yes	12.2(15)ZJ3

Table 6 *Devices Supported in IDU 6.0 on Campus 3.3 (Continued)*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco Catalyst 6000 Modules	MWAM	1.3.6.1.4.1.9.12.3.1.9 .17.39	Yes	—	—	—	—	Yes	1.2(1.0)
	VPN IPSec	1.3.6.1.4.1.9.5.44	Yes	—	—	—	—	—	12.2(9)Y04
	CSG		Yes	—	—	—	—	—	3.1(3)C4
Cisco MDS 9000 Series Switches	MDS 9120	1.3.6.1.4.1.9.12.3.1.3 .414	Yes	—	—	—	—	Yes	SAN-OS 1.2
	MDS 9140	1.3.6.1.4.1.9.12.3.1.3 .411							
Cisco Content Engine	CE-510	1.3.6.1.4.1.9.1.505	Yes	—	—	—	—	Yes	ACNS 5.1.1
	CE-565	1.3.6.1.4.1.9.1.491	Yes	—	—	—	—	Yes	ACNS 5.1.0
Cisco Content Server Switch	CSS 11501	1.3.6.1.4.1.2467.4.7	Yes	—	—	—	—	Yes	7.20
Cisco Route Processor Module	RPM-PR	1.3.6.1.4.1.9.1.199	Yes	—	—	—	—	Yes	12.1

1. Since Cisco SOHO series routers do not support CDP MIB, Topology is partially supported. Because of this, the devices cannot be used as seed devices and cannot discover other devices that are further behind these device.
2. User Tracking will be provided using ARP.
3. Support for IP Phones is also provided.

Table 7 *Devices Supported in IDU 5.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco 800 ¹ Series	831	1.3.6.1.4.1.9.1.497	Yes	—	—	—	Yes ²	Yes	12.2(8r)YN
	836	1.3.6.1.4.1.9.1.499							12.2(11) YV
	837	1.3.6.1.4.1.9.1.495							12.2(8r) YN
Cisco 1700 Series	1701	1.3.6.1.4.1.9.1.550	Yes	—	—	—	Yes ²	Yes	12.2(7r) XM1
	1711	1.3.6.1.4.1.9.1.538							
	1712	1.3.6.1.4.1.9.1.539							
Cisco Aironet Series	AP 1200-IOS	1.3.6.1.4.1.9.1.474	Yes	—	—	—	Yes	Yes	12.2
	BR1410	1.3.6.1.4.1.9.1.533	Yes	—	—	—	—	Yes	12.2(11) JA
Cisco Catalyst 2940 Series Switches	2940-8TF	1.3.6.1.4.1.9.1.542	Yes	Yes	—	—	Yes ³	Yes ³	12.1(13) AY
	2940-8TT	1.3.6.1.4.1.9.1.540	Yes	Yes	—				
Cisco Catalyst 2970 Series Switches	2970-24	1.3.6.1.4.1.9.1.527	Yes	Yes	—	—	Yes ³	Yes ³	12.1(11) EA1

Table 7 *Devices Supported in IDU 5.0 on Campus 3.3 (Continued)*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco Catalyst 6500 Series Service Modules	FWSM	1.3.6.1.4.1.9.1.522	Yes	—	—	—	—	—	1.1(2)
	CSM	—	Yes	—	—	—	—	—	3.1(3)
	SSL	—	Yes	—	—	—	—	—	1.1(2)
	WS-SUP 720 (MSFC3)	1.3.6.1.4.1.9.1.557	Yes	—	—	—	Yes ⁴	Yes	12.2
Cisco Content Engines	CE 7305	1.3.6.1.4.1.9.1.504	Yes	—	—	—	—	Yes	ACNS 5.0
	CE 7325	1.3.6.1.4.1.9.1.492							
Cisco Storage Switch	MDS 9506	1.3.6.1.4.1.9.12.3.1 .3.375	Yes	—	—	—	—	Yes	1.1
Cisco ONS 15500 Series	ONS15540ESP	1.3.6.1.4.1.9.1.406	Yes	—	—	—	—	Yes	12.1(10) EV1
	ONS15540ESPx	1.3.6.1.4.1.9.1.481							
	ONS15530ETSI	1.3.6.1.4.1.9.1.462							
	ONS15530 NEBS	1.3.6.1.4.1.9.1.461							

1. Since Cisco 800 series routers do not support CDP MIB, Topology is partially supported. Because of this, the devices cannot be used as seed devices and cannot discover other devices that are further behind these device.
2. Cisco routers provide User Tracking application with ARP Table information.
3. Support for IP Phones also provided.
4. Cisco Routers provide User Tracking with ARP Table information.

Table 8 *Devices Supported in IDU 4.0 on Campus 3.3*

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco Catalyst 2900 XL-LRE Series	2912-XL-LRE	1.3.6.1.4.1.9.1.219	Yes	Yes	—	—	Yes ¹	Yes ¹	12.0(5) WC6
	2924-XL-LRE	1.3.6.1.4.1.9.1.183							
Cisco Catalyst 2950 LRE Series	2950-ST-8	1.3.6.1.4.1.9.1.483	Yes	Yes	—	—	Yes ¹	Yes ¹	12.(11)YJ
	2950-ST-24	1.3.6.1.4.1.9.1.482							
Cisco Catalyst 2955 Series	2955-C12	1.3.6.1.4.1.9.1.489	Yes	Yes	—	—	Yes ¹	Yes ¹	12.1(13)EA1
	2955-S12	1.3.6.1.4.1.9.1.508							
	2955-T12	1.3.6.1.4.1.9.1.488							
Cisco Catalyst 3550 Series	3550-24PWR	1.3.6.1.4.1.9.1.485	Yes ²	Yes	—	—	Yes ¹	Yes ¹	12.1(13)EA1

Table 8 **Devices Supported in IDU 4.0 on Campus 3.3 (Continued)**

Device Type	Devices/ Modules Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	Minimum Software
Cisco 3750 Series	3750-Stack (3750-24, 3750-48, 3750-24T, 3750-24TS)	1.3.6.1.4.1.9.1.516	Yes	Yes ³	—	—	Yes ¹	Yes ¹	12.1(11) AX
Cisco 4000 Series Modules	SUP-III, SUP-IV	1.3.6.1.4.1.9.5.59	Yes	Yes	—	—	Yes ¹	Yes ¹	12.1(13)EW1
Cisco Catalyst 6000 Series Module	SUP 720 ⁴	1.3.6.1.4.1.9.5.44	Yes	Yes	—	—	Yes	Yes	IOS12.2.14-SX
			Yes	Yes	—	—	Yes	Yes	Catalyst 8.1(0.71)
Cisco Catalyst 6500 Series	6503 ⁴	1.3.6.1.4.1.9.1.449	Yes	Yes	—	—	Yes	Yes	IOS 12.1(11b)E
		1.3.6.1.4.1.9.5.56	Yes	Yes	—	—	Yes	Yes	Catalyst OS 7.5(1)
Cisco 10700 Series	10720	1.3.6.1.4.1.9.1.397	Yes	—	—	—	Yes ⁵	Yes	12.0(19)SP
Cisco 800 ⁶ Series	806	1.3.6.1.4.1.9.1.384	Yes	—	—	—	Yes ⁵	Yes	12.2(4)YA
	811	1.3.6.1.4.1.9.1.295							
	804J	1.3.6.1.4.1.9.1.296							
	826	1.3.6.1.4.1.9.1.321							
	827-H	1.3.6.1.4.1.9.1.446							
	828	1.3.6.1.4.1.9.1.382							
Cisco 1700 Series	1710	1.3.6.1.4.1.9.1.200	Yes	—	—	—	Yes ⁵	Yes	12.2(8)T
	1721	1.3.6.1.4.1.9.1.444	Yes						
	1751	1.3.6.1.4.1.9.1.326	Yes						
	1760	1.3.6.1.4.1.9.1.416	Yes						
Cisco 7300 Series	7301	1.3.6.1.4.1.9.1.476	Yes	—	—	—	Yes ⁵	Yes	12.2(15)B

1. Support for IP Phones also provided.
2. Topology Services does not support Gigastack adapter that is attached to these devices.
3. Support for VLAN Port Assignment not provided.
4. Supports Cisco IOS and CatOS.
5. Cisco routers provide User Tracking with ARP Table information.
6. Since Cisco 800 series routers do not support CDP MIB, Topology is partially supported. Because of this, the devices cannot be used as seed devices and cannot discover other devices that are further behind these device.

Table 9 Cisco Routers

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco Universal Broadband Routers	uBR904	1.3.6.1.4.1.9.1.191	Yes	—	—	—	Yes ¹	Yes
	uBR905	1.3.6.1.4.1.9.1.351						
	uBR924	1.3.6.1.4.1.9.1.255						
	uBR925	1.3.6.1.4.1.9.1.316						
	uBR7100	1.3.6.1.4.1.9.1.309						
	uBR7111	1.3.6.1.4.1.9.1.344						
	uBR7111E	1.3.6.1.4.1.9.1.345						
	uBR7114	1.3.6.1.4.1.9.1.346						
	uBR7114E	1.3.6.1.4.1.9.1.347						
	uBR7223	1.3.6.1.4.1.9.1.210						
	uBR7246	1.3.6.1.4.1.9.1.179						
	uBR10012	1.3.6.1.4.1.9.1.317						
Cisco Gigabit Switch Router (GSR) 12000 Series	12008	1.3.6.1.4.1.9.1.182	Yes	—	No	Yes	Yes ¹	Yes
	12010	1.3.6.1.4.1.9.1.348						
	12012	1.3.6.1.4.1.9.1.173						
	12016	1.3.6.1.4.1.9.1.273						
	12004	1.3.6.1.4.1.9.1.181	Yes	—	—	—	—	Yes
Cisco Gigabit Switch Router (GSR) 12400 Series	12404	1.3.6.1.4.1.9.1.423	Yes	—	—	Yes	Yes ¹	Yes
	12406	1.3.6.1.4.1.9.1.388						
	12410	1.3.6.1.4.1.9.1.394						
	12416	1.3.6.1.4.1.9.1.385						

Table 9 Cisco Routers (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco 7000 Series	7000	1.3.6.1.4.1.9.1.8	Yes	—	Yes	Yes	Yes ¹	Yes
	7010	1.3.6.1.4.1.9.1.12						
	7120	1.3.6.1.4.1.9.1.259						
	7140-2FE	1.3.6.1.4.1.9.1.277						
	7140-8T	1.3.6.1.4.1.9.1.276						
	7150-2FE	1.3.6.1.4.1.9.1.355						
	7150-8T	1.3.6.1.4.1.9.1.356						
	7150-8T1							
	7150-2T3	1.3.6.1.4.1.9.1.357						
	7202	1.3.6.1.4.1.9.1.194						
	7204	1.3.6.1.4.1.9.1.125						
	7206	1.3.6.1.4.1.9.1.108						
	7505	1.3.6.1.4.1.9.1.48						
	7507	1.3.6.1.4.1.9.1.45						
	7507MX	1.3.6.1.4.1.9.1.290						
	7507Z	1.3.6.1.4.1.9.1.288						
	7513	1.3.6.1.4.1.9.1.46						
	7513MX	1.3.6.1.4.1.9.1.291						
	7513Z	1.3.6.1.4.1.9.1.289						
	7576	1.3.6.1.4.1.9.1.204						
	7204VXR	1.3.6.1.4.1.9.1.223						
	7206VXR	1.3.6.1.4.1.9.1.222						
	7246VXR	1.3.6.1.4.1.9.1.271						
	7120-AE3	1.3.6.1.4.1.9.1.263						
7120-AT3	1.3.6.1.4.1.9.1.262							
7120-E3	1.3.6.1.4.1.9.1.261							
7120-SMI3	1.3.6.1.4.1.9.1.264							
7120-T3	1.3.6.1.4.1.9.1.260							
7140-2AE3	1.3.6.1.4.1.9.1.268							
7140-2AT3	1.3.6.1.4.1.9.1.267							
7140-2E3	1.3.6.1.4.1.9.1.266							
7140-2MM3	1.3.6.1.4.1.9.1.269							
7140-2T3	1.3.6.1.4.1.9.1.265							

Table 9 Cisco Routers (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco 4000 Series	4000	1.3.6.1.4.1.9.1.7	Yes	—	Yes ²	Yes ²	Yes ¹	Yes
	4000-M							
	4500	1.3.6.1.4.1.9.1.14						
	4500-M							
	4700	1.3.6.1.4.1.9.1.50						
	4700-M							
Cisco 3200 Series Mobile Access Router	3251	1.3.6.1.4.1.9.1.479	Yes	—	—	—	Yes ¹	Yes
Cisco 3700 Series Multi Service Access Routers	3725	1.3.6.1.4.1.9.1.414	Yes	—	—	—	Yes ¹	Yes ³
	3745	1.3.6.1.4.1.9.1.436						
Cisco 7300 Series	7304	1.3.6.1.4.1.9.1.439	Yes	—	—	—	Yes ¹	Yes
Cisco 7400 Series	7401	1.3.6.1.4.1.9.1.403	Yes	—	—	—	Yes ¹	Yes
Cisco 7600 Series ^{4,5}	7603	1.3.6.1.4.1.9.5.53	Yes	Yes	Yes	Yes	Yes ⁶	Yes ^{6,3}
	7603-IOS	1.3.6.1.4.1.9.1.401						
	7606	1.3.6.1.4.1.9.5.54						
	7606-IOS	1.3.6.1.4.1.9.1.402						
	7609	1.3.6.1.4.1.9.5.44						
Cisco Switching Access Concentrator	MC3810	1.3.6.1.4.1.9.1.157	Yes	—	—	—	Yes	Yes
	MC3810-V3	1.3.6.1.4.1.9.1.286						
Cisco 3000 Series	3000	1.3.6.1.4.1.9.1.6	Yes	—	—	—	—	Yes
Cisco 3600 Series	3620	1.3.6.1.4.1.9.1.122	Yes	—	—	No	Yes ¹	Yes
	3640	1.3.6.1.4.1.9.1.110						
	3660	1.3.6.1.4.1.9.1.205						
	3661AC	1.3.6.1.4.1.9.1.338						
	3661DC	1.3.6.1.4.1.9.1.339						
	3662AC	1.3.6.1.4.1.9.1.340						
	3662DC	1.3.6.1.4.1.9.1.341						
	3662AC-CO	1.3.6.1.4.1.9.1.342						
	3662DC-CO	1.3.6.1.4.1.9.1.343						

Table 9 Cisco Routers (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco 2600 Series	2610	1.3.6.1.4.1.9.1.185	Yes	—	—	No	Yes ¹	Yes
	2611	1.3.6.1.4.1.9.1.186						
	2612	1.3.6.1.4.1.9.1.187						
	2613	1.3.6.1.4.1.9.1.195						
	2620	1.3.6.1.4.1.9.1.208						
	2621	1.3.6.1.4.1.9.1.209						
	2650	1.3.6.1.4.1.9.1.319						
	2651	1.3.6.1.4.1.9.1.320						
	2691	1.3.6.1.4.1.9.1.413	Yes	—	—	—	Yes ¹	Yes
Cisco 2600XM Series	2610XM	1.3.6.1.4.1.9.1.466	Yes	—	—	—	Yes ¹	Yes
	2611XM	1.3.6.1.4.1.9.1.467						
	2620XM	1.3.6.1.4.1.9.1.468						
	2621XM	1.3.6.1.4.1.9.1.469						
	2650XM	1.3.6.1.4.1.9.1.470						
	2651XM	1.3.6.1.4.1.9.1.471						
Cisco 2500 Series	2500-2525	—	Yes	—	—	—	Yes ¹	Yes
	2501CF	1.3.6.1.4.1.9.1.165						
	2501LF	1.3.6.1.4.1.9.1.166						
	2502LF	1.3.6.1.4.1.9.1.167						
	AccessProEC	1.3.6.1.4.1.9.1.39	Yes	—	—	—	—	Yes
Cisco 2000 Series	2102	1.3.6.1.4.1.9.1.15	Yes	—	—	—	—	Yes
	2202	1.3.6.1.4.1.9.1.16						
Cisco 1700 Series	1720 VPN	1.3.6.1.4.1.9.1.201	Yes	—	—	—	Yes ¹	Yes
	1750	1.3.6.1.4.1.9.1.216						
	1751	1.3.6.1.4.1.9.1.326	Yes	—	—	—	—	Yes
Cisco 1600 Series	1601	1.3.6.1.4.1.9.1.113	Yes	—	—	—	Yes ¹	Yes
	1602	1.3.6.1.4.1.9.1.114						
	1603	1.3.6.1.4.1.9.1.115						
	1604	1.3.6.1.4.1.9.1.116						
	1605	1.3.6.1.4.1.9.1.172						
Cisco 1400 Series	1401	1.3.6.1.4.1.9.1.206	Yes	—	—	—	—	Yes
	1407	1.3.6.1.4.1.9.1.249						
	1417	1.3.6.1.4.1.9.1.250						

Table 9 Cisco Routers (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco 1000 Series	1000	1.3.6.1.4.1.9.1.40	Yes	—	—	—	Yes ¹	Yes
	1003	1.3.6.1.4.1.9.1.41						
	1004	1.3.6.1.4.1.9.1.44						
	1005	1.3.6.1.4.1.9.1.49						
	1020	1.3.6.1.4.1.9.1.43						
Cisco 800 Series ⁷	801	1.3.6.1.4.1.9.1.212	Yes	—	—	—	Yes ¹	Yes
	802	1.3.6.1.4.1.9.1.213						
	802J	1.3.6.1.4.1.9.1.295						
	803	1.3.6.1.4.1.9.1.214						
	804	1.3.6.1.4.1.9.1.215						
	804J	1.3.6.1.4.1.9.1.296						
	827	1.3.6.1.4.1.9.1.284						
	827-4V	1.3.6.1.4.1.9.1.270						
	826-4V	1.3.6.1.4.1.9.1.321	Yes	—	—	—	—	Yes
	805	1.3.6.1.4.1.9.1.245	Yes	—	—	—	Yes ¹	Yes
Cisco 700 Series	761	1.3.6.1.4.1.9.1.98	Yes	—	—	—	Yes ¹	Yes
	762	1.3.6.1.4.1.9.1.99						
	765	1.3.6.1.4.1.9.1.102						
	766	1.3.6.1.4.1.9.1.103						
	771	1.3.6.1.4.1.9.1.126						
	772	1.3.6.1.4.1.9.1.127						
	775	1.3.6.1.4.1.9.1.128						
	776	1.3.6.1.4.1.9.1.129						
Cisco AGSplus Router	AGSplus	1.3.6.1.4.1.9.1.11	Yes	—	—	—	—	Yes
Edge Services Router	10400	1.3.6.1.4.1.9.1.272	Yes	—	—	—	Yes ¹	Yes
CPA1000 Series	CPA1003	1.3.6.1.4.1.9.1.51	Yes	—	—	—	—	Yes
	CPA1004	1.3.6.1.4.1.9.1.52						
	CPA1005	1.3.6.1.4.1.9.1.53						
CPA1600 Series	CPA1601	1.3.6.1.4.1.9.1.117	Yes	—	—	—	—	Yes
	CPA1602	1.3.6.1.4.1.9.1.118						
	CPA1603	1.3.6.1.4.1.9.1.119						
	CPA1604	1.3.6.1.4.1.9.1.120						

Table 9 Cisco Routers (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
CPA2500 Series	CPA2501	1.3.6.1.4.1.9.1.56	Yes	—	—	—	—	Yes
	CPA2502	1.3.6.1.4.1.9.1.130						
	CPA2503	1.3.6.1.4.1.9.1.57						
	CPA2504	1.3.6.1.4.1.9.1.131						
	CPA2505	1.3.6.1.4.1.9.1.58						
	CPA2506	1.3.6.1.4.1.9.1.132						
	CPA2507	1.3.6.1.4.1.9.1.59						
	CPA2508	1.3.6.1.4.1.9.1.133						
	CPA2509	1.3.6.1.4.1.9.1.60						
	CPA2510	1.3.6.1.4.1.9.1.134						
	CPA2511	1.3.6.1.4.1.9.1.61						
	CPA2512	1.3.6.1.4.1.9.1.135						
	CPA2513	1.3.6.1.4.1.9.1.136						
	CPA2514	1.3.6.1.4.1.9.1.62						
	CPA2515	1.3.6.1.4.1.9.1.137						
	CPA2516	1.3.6.1.4.1.9.1.63						
	CPA2517	1.3.6.1.4.1.9.1.138						
		1.3.6.1.4.1.9.1.67						
	CPA2518	1.3.6.1.4.1.9.1.139						
		1.3.6.1.4.1.9.1.68						
	CPA2519	1.3.6.1.4.1.9.1.64						
		1.3.6.1.4.1.9.1.69						
	CPA2520	1.3.6.1.4.1.9.1.104						
	CPA2521	1.3.6.1.4.1.9.1.65						
	CPA2522	1.3.6.1.4.1.9.1.105						
CPA2523	1.3.6.1.4.1.9.1.140							
CPA2524	1.3.6.1.4.1.9.1.106							
CPA2525	1.3.6.1.4.1.9.1.141							
CPA 3600 Series	CPA3620	1.3.6.1.4.1.9.1.123	Yes	—	—	—	—	Yes
	CPA3640	1.3.6.1.4.1.9.1.124						
CPA 4500 Series	CPA4500	1.3.6.1.4.1.9.1.66	Yes	—	—	—	—	Yes
CPA 4700 Series	CPA4700	1.3.6.1.4.1.9.1.142	Yes	—	—	—	—	Yes

Table 9 Cisco Routers (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
CPA 700 Series	CPA761	1.3.6.1.4.1.9.1.88	Yes	—	—	—	—	Yes
	CPA762	1.3.6.1.4.1.9.1.89						
	CPA763	—						
	CPA764	—						
	CPA765	1.3.6.1.4.1.9.1.92						
	CPA766	1.3.6.1.4.1.9.1.93						
Cisco SOHO Series	SOHO 76	1.3.6.1.4.1.9.1.354	Yes ⁷	—	—	—	—	Yes
	SOHO 77	1.3.6.1.4.1.9.1.353						
Gateway Server	Gateway Server	1.3.6.1.4.1.9.1.1	Yes	—	—	—	—	Yes
Cisco IGS Series	IGS	1.3.6.1.4.1.9.1.5	Yes	—	—	—	—	Yes
Cisco Catalyst 3011 Router	WSX3011	1.3.6.1.4.1.9.1.112	Yes	—	—	—	—	Yes
Cisco Trouter	Trouter	1.3.6.1.4.1.9.1.3	Yes	—	—	—	—	Yes

1. Cisco routers supply the User Tracking application with ARP Table information.
2. Provided only on the 4500 and 4700 series.
3. Support for Analog Voice Gateway (FXS/FXO port) provided.
4. Supports Cisco IOS and Catalyst IOS.
5. All Optical Services Routers.
6. Support for IP phones provided.
7. Since these devices do not support CDP MIB, Topology is partially supported. Because of this, the devices cannot be used as seed devices and cannot discover other devices that are further behind these device.

Table 10 Cisco Fast Hubs

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco FastHub Series	FastHub 100	1.3.6.1.4.1.9.1.226	Yes	—	—	—	—	—
	FastHub 400							
	FastHub1116	1.3.6.1.4.1.9.1.152	Yes	—	—	—	Not tested	
	FastHub116C	1.3.6.1.4.1.9.1.151						
	FastHub116T	1.3.6.1.4.1.9.1.150						
	FastHub216T	1.3.6.1.4.1.9.1.169						
	FastHub3116	1.3.6.1.4.1.9.1.149						
	FastHub316C	1.3.6.1.4.1.9.1.148						
	FastHub316T	1.3.6.1.4.1.9.1.147						
	FastHubBMMFX	1.3.6.1.4.1.9.1.178						
	FastHubBMMTX	1.3.6.1.4.1.9.1.177						

Table 10 Cisco Fast Hubs (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco MicroHub Series	MicroHub 1502	1.3.6.1.4.1.9.1.161	Yes	—	—	—	—	Not tested
	MicroHub 1503	1.3.6.1.4.1.9.1.160						

Table 11 Cisco Access Servers

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco AS5000 Series Access Servers	AS5200	1.3.6.1.4.1.9.1.109	Yes	—	—	—	Yes ¹	Yes
	AS5300	1.3.6.1.4.1.9.1.162						
	AS5400	1.3.6.1.4.1.9.1.274						
	AS5800	1.3.6.1.4.1.9.1.188						
	AS5850	1.3.6.1.4.1.9.1.308						
	AS5350	1.3.6.1.4.1.9.1.313	Yes	—	—	—	—	Yes
Cisco 2500 Series Access Servers	2509RJ	1.3.6.1.4.1.9.1.153	Yes	—	—	—	Yes ¹	Yes
	2511RJ	1.3.6.1.4.1.9.1.154						

1. Cisco routers supply the User Tracking application with ARP Table information.

Table 12 Cisco Switches

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco Catalyst 8500 MSR Series	8510 MSR	1.3.6.1.4.1.9.1.230	Yes	—	Yes	Yes	—	Yes
	8540 MSR	1.3.6.1.4.1.9.1.202						
	8515 MSR	1.3.6.1.4.1.9.1.231						
Lightstream Series	LS1010	1.3.6.1.4.1.9.5.11	Yes	—	Yes	Yes	—	Yes
		1.3.6.1.4.1.9.1.107						
	LS1015	1.3.6.1.4.1.9.1.164						
Multiservice Switch	IGX 8400	1.3.6.1.4.1.351.100	Yes	—	—	No	—	No
	IGX 8410	1.3.6.1.4.1.9.1.232						
	IGX 8420	1.3.6.1.4.1.9.1.233						
	IGX 8430	1.3.6.1.4.1.9.1.234						
Cisco Catalyst 8500 CSR Series	8510 CSR	1.3.6.1.4.1.9.1.190	Yes	—	—	—	Yes ¹	Yes
	8540 CSR	1.3.6.1.4.1.9.1.203						

Table 12 Cisco Switches (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco Catalyst 6000 Series	6006	1.3.6.1.4.1.9.5.38	Yes	Yes	Yes	Yes	Yes	Yes
	6006-IOS	1.3.6.1.4.1.9.1.280						
	6009	1.3.6.1.4.1.9.5.39						
	6506	1.3.6.1.4.1.9.5.45						
	6506-IOS	1.3.6.1.4.1.9.1.282						
	6509	1.3.6.1.4.1.9.5.44						
	6009-IOS	1.3.6.1.4.1.9.1.281						
	6509-IOS	1.3.6.1.4.1.9.1.283						
	6513	1.3.6.1.4.1.9.5.50						
	6513-IOS	1.3.6.1.4.1.9.1.400						
	6509 with NEBS chassis—running Catalyst operating system	1.3.6.1.4.1.9.5.47						
	6509 with NEBS chassis—running IOS	1.3.6.1.4.1.9.1.310	Yes	Yes	—	—	Yes	Yes
	WS-X6302 (MSM)	1.3.6.1.4.1.9.1.256	Yes	—	—	—	Yes ¹	Yes
	WS-F6K (MSFC)	1.3.6.1.4.1.9.1.258						
MSFC2	1.3.6.1.4.1.9.1.301							
WS-SUP 720 (MSFC3)	1.3.6.1.4.1.9.1.557							
Cisco Catalyst 6000 Series Modules	NAM-2	1.3.6.1.4.1.9.5.1.3.1.1.2.291	Yes	—	—	—	—	—
Cisco Catalyst 5000 Series	5000	1.3.6.1.4.1.9.5.7	Yes ²	Yes ²	Yes	Yes ²	Yes	Yes
	5002	1.3.6.1.4.1.9.5.29						
	5500	1.3.6.1.4.1.9.5.17						
	5505	1.3.6.1.4.1.9.5.34						
	5509	1.3.6.1.4.1.9.5.36						
	WS-X5302 (RSM)	1.3.6.1.4.1.9.1.168	Yes	—	—	—	Yes ¹	Yes
	WS-F5541 (RSFC)	1.3.6.1.4.1.9.1.257						

Table 12 Cisco Switches (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis	
Cisco Catalyst 4000 Series	4003	1.3.6.1.4.1.9.5.40	Yes	Yes	—	—	Yes	Yes	
	4006	1.3.6.1.4.1.9.5.46							
	4000-IOS ^{3,4}	1.3.6.1.4.1.9.1.448							
	4912G	1.3.6.1.4.1.9.5.41							
	Cisco Catalyst 4500 Series	WS-X4232-L3	1.3.6.1.4.1.9.1.300	Yes	—	—	—	Yes ¹	Yes
		WS-X4604-GWY	1.3.6.1.4.1.9.1.318						
		4840G-L3	1.3.6.1.4.1.9.1.312						
		4908G-L3	1.3.6.1.4.1.9.1.298						
		4224	1.3.6.1.4.1.9.1.399						
Cisco Catalyst 3900 Series	4503 ⁵	1.3.6.1.4.1.9.5.58	Yes	Yes ⁶	—	—	Yes	Yes	
	4503-IOS	1.3.6.1.4.1.9.1.503							
	4506 ⁵	1.3.6.1.4.1.9.5.59							
	4506-IOS	1.3.6.1.4.1.9.1.502							
	4507 ⁷	1.3.6.1.4.1.9.1.501							
	4507-IOS	1.3.6.1.4.1.9.1.501							
Cisco Catalyst 3500XL Series ⁸	3900	1.3.6.1.4.1.9.5.33	Yes	Yes	No	Yes	Yes	Yes	
	3920	1.3.6.1.4.1.9.5.37							
Cisco Catalyst 3550 Series	3508GXL	1.3.6.1.4.1.9.1.246	Yes ⁹	Yes	—	—	Yes ¹⁰	Yes	
	3512XL	1.3.6.1.4.1.9.1.247							
	3524PWR-XL	1.3.6.1.4.1.9.1.287							
	3524XL	1.3.6.1.4.1.9.1.248							
	3548XL	1.3.6.1.4.1.9.1.278							
Cisco Catalyst 3000 Series	3550-24	1.3.6.1.4.1.9.1.366	Yes ⁹	Yes	—	—	Yes ¹⁰	Yes	
	3550-48	1.3.6.1.4.1.9.1.367							
	3550-12T	1.3.6.1.4.1.9.1.368							
	3550-12G	1.3.6.1.4.1.9.1.431							
	3550-24DC	1.3.6.1.4.1.9.1.452	Yes ⁹	Yes	—	—	Yes ¹¹	Yes ¹¹	
	3550-24FX	1.3.6.1.4.1.9.1.453							
Cisco Catalyst 3000 Series	3000	1.3.6.1.4.1.9.5.10	Yes	Yes	Yes	Yes	Yes ¹²	Yes	
		1.3.6.1.4.1.9.5.26							
	3100	1.3.6.1.4.1.9.5.23							
	3200	1.3.6.1.4.1.9.5.15							

Table 12 Cisco Switches (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco Catalyst 2900 Series	2900	1.3.6.1.4.1.9.5.12	Yes	Yes	—	—	Yes	Yes
	2926	1.3.6.1.4.1.9.5.35						
	2948G	1.3.6.1.4.1.9.5.42						
	2948G-L3	1.3.6.1.4.1.9.1.275	Yes	—	—	—	Yes ¹	Yes
	2980G	1.3.6.1.4.1.9.5.49	Yes	Yes	—	—	Yes	Yes
	2980GA	1.3.6.1.4.1.9.5.51						
Cisco Catalyst 2950 Series	2950-12	1.3.6.1.4.1.9.1.323	Yes	Yes	—	—	Yes	Yes
	2950-24	1.3.6.1.4.1.9.1.324						
	2950C-24	1.3.6.1.4.1.9.1.325						
	2950T-24	1.3.6.1.4.1.9.1.359						
	2950G-24	1.3.6.1.4.1.9.1.428						
	2950G-12	1.3.6.1.4.1.9.1.427						
	2950G-24DC	1.3.6.1.4.1.9.1.472						
	2950G-48	1.3.6.1.4.1.9.1.429						
	2950-24SX	1.3.6.1.4.1.9.1.480						
Cisco Catalyst 2900XL Series	2908XL	1.3.6.1.4.1.9.1.170	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ²	Yes
	2916M-XL	1.3.6.1.4.1.9.1.171						
	2912XL	1.3.6.1.4.1.9.1.217						
	2912MF-XL	1.3.6.1.4.1.9.1.218						
	2924C-XL-V	1.3.6.1.4.1.9.1.219						
	2924M-XL	1.3.6.1.4.1.9.1.220						
	2924XL-V	1.3.6.1.4.1.9.1.221						
	2924XL	—						
	2924C-XL	1.3.6.1.4.1.9.1.184						
Cisco Catalyst 2800 Series ¹⁴	2820	1.3.6.1.4.1.9.5.20	Yes	Yes	Yes	Yes	Yes	Yes
Cisco Catalyst 2200 Series	2200	1.3.6.1.4.1.9.5.13	Yes	Yes	—	—	Yes	Yes
Cisco Catalyst 1900 Series ¹⁵	1912	1.3.6.1.4.1.9.5.31	Yes	Yes	—	—	Yes	Yes
	1924	1.3.6.1.4.1.9.5.18						
Cisco Catalyst 1200 Series	1200	1.3.6.1.4.1.9.5.5	Yes	No	—	—	No	Yes
Cisco CPW16	CPW16	1.3.6.1.4.1.9.5.25	Yes	—	—	—	—	—
		1.3.6.1.4.1.9.5.9						

1. Cisco Routers provide User Tracking application with ARP Table information.
2. IOS version 3.2(7), 3.2(9), 3.2(12), 3.2(13), and 3.2(15) are compatible code bases for Cisco Catalyst 5000 ATM interface.
3. VLAN management supported in IOS 12.1(13)EW1.

4. User Tracking not supported in Cisco IOS 12.1(13)EW1.
5. Supports Cisco IOS and Catalyst operating system.
6. Supported with Catalyst operating system only.
7. Supports Cisco IOS only.
8. 3500XL series is supported in IP Mode only. Clustered devices not assigned an IP address are not supported.
9. Topology Services does not support Gigastack adapter that is attached to these devices.
10. User Tracking will not discover end-hosts connected to Cisco Catalyst 2900XL or Cisco Catalyst 3500XL devices running IOS 12.0(5)XP.
11. Support for IP Phones also provided.
12. Cisco Catalyst 3000, 3100, and 3200 may erroneously indicate duplicate MAC addresses after each User Tracing Acquisition (Bug ID CSCdk20561).
13. Enterprise editions only.
14. Cisco Catalyst 2800 devices must run Cisco IOS Software Release 8.0 (Enterprise), or later.
15. Cisco Catalyst 1900 devices must run Cisco IOS Software Release 8.0 (Enterprise), or later.

Table 13 *Cisco Content Networking Devices*

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco CSS 11000 Series Content Services Switches	CSS11503	1.3.6.1.4.1.2467.4.5	Yes	—	—	—	—	Yes
	CSS11506	1.3.6.1.4.1.2467.4.6						
HSE Series	HSE 1105	1.3.6.1.4.1.9.1.405	Yes	—	—	—	—	Yes

Table 14 *Cisco Wireless LAN Products*

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
WLSE Series	WLSE	1.3.6.1.4.1.9.1.459	Yes	—	—	—	—	Yes
Cisco Aironet Series Access Points	AP340	1.3.6.1.4.1.9.1.379	Yes	—	—	—	No	Yes
	AP350	1.3.6.1.4.1.9.1.380						
	AP1200	—	Yes	—	—	—	Yes	Yes
	AP1200-IOS	1.3.6.1.4.1.9.1.525	Yes	No	No	No	Yes	Yes
	AP1100	1.3.6.1.4.1.9.1.507	Yes	No	—	—	Yes	Yes

Table 15 *Cisco Voice Gateways*

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
VG 200 Series	VG 200	1.3.6.1.4.1.9.1.279	Yes	—	—	—	—	Yes
	VG 248	1.3.6.1.4.1.9.1.404						
DPA 7600 Series	DPA 7630	1.3.6.1.4.1.9.1.365	Yes	—	—	—	—	Yes
	DPA 7610	1.3.6.1.4.1.9.1.381						

Table 16 Network Switch Probes

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Network Switch Probes ¹	NetScout Probe 5100	1.3.6.1.4.1.141.1.1.5100	Yes	—	—	—	—	Yes
	NetScout Probe 6010	1.3.6.1.4.1.141.1.1.6010						
	NetScout Probe 6020	1.3.6.1.4.1.141.1.1.6020						
	NetScout Probe 6030	1.3.6.1.4.1.141.1.1.6030						
	NetScout Probe 6040	1.3.6.1.4.1.141.1.1.6040						
	NetScout Probe 6050	1.3.6.1.4.1.141.1.1.6050						
	NetScout Probe 6060	1.3.6.1.4.1.141.1.1.6060						
	NetScout Probe 6070	1.3.6.1.4.1.141.1.1.6070						
	NetScout Probe 7101	1.3.6.1.4.1.141.1.1.7101						
Network Switch Probes (Continued)	NetScout Probe 7102	1.3.6.1.4.1.141.1.1.7102	Yes	—	—	—	—	Yes
	NetScout Probe 7103	1.3.6.1.4.1.141.1.1.7103						
	NetScout Probe 7201	1.3.6.1.4.1.141.1.1.7201						
	NetScout Probe 7203	1.3.6.1.4.1.141.1.1.7203						
	NetScout Probe 7211	1.3.6.1.4.1.141.1.1.7211						
	NetScout Probe 7223	1.3.6.1.4.1.141.1.1.7223						
	NetScout Probe 7301	1.3.6.1.4.1.141.1.1.7301						
	NetScout Probe 7302	1.3.6.1.4.1.141.1.1.7302						
	NetScout Probe 7303	1.3.6.1.4.1.141.1.1.7303						
	NetScout Probe 7401	1.3.6.1.4.1.141.1.1.7400 1.3.6.1.4.1.141.1.1.7401						
	NetScout Probe 7500	1.3.6.1.4.1.141.1.1.7500						
	NetScout Probe 7501	1.3.6.1.4.1.141.1.1.7501						
	NetScout Probe 7502	1.3.6.1.4.1.141.1.1.7502						
	NetScout Probe 7503	1.3.6.1.4.1.141.1.1.7503						
	NetScout Probe 7504	1.3.6.1.4.1.141.1.1.7504						
	NetScout Probe 8110	1.3.6.1.4.1.141.1.1.8100 1.3.6.1.4.1.141.1.1.8110						
	NetScout Probe 8150	1.3.6.1.4.1.141.1.1.8150						
	NetScout Probe 8241	1.3.6.1.4.1.141.1.1.8241						
	NetScout Probe 8243	1.3.6.1.4.1.141.1.1.8243						
	NetScout Probe 8281	1.3.6.1.4.1.141.1.1.8281						

Table 16 Network Switch Probes (Continued)

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Network Switch Probes (Continued)	NetScout Probe 8283	1.3.6.1.4.1.141.1.1.8283	Yes	—	—	—	—	Yes
	NetScout Probe 8700	1.3.6.1.4.1.141.1.1.87, 1.3.6.1.4.1.141.1.1.8700						
	NetScout Probe 8704	1.3.6.1.4.1.141.1.1.8704						
	NetScout Probe 8712	1.3.6.1.4.1.141.1.1.8712						
	NetScout Probe 8722	1.3.6.1.4.1.141.1.1.8722						
	NetScout Probe 8724	1.3.6.1.4.1.141.1.1.8724						
	NetScout Probe 8800	1.3.6.1.4.1.141.1.1.8800						
	NetScout Probe 8812	1.3.6.1.4.1.141.1.1.8812						
	NetScout Probe 8822	1.3.6.1.4.1.141.1.1.8822						
	NetScout Probe 8911	1.3.6.1.4.1.141.1.1.8911						
	NetScout Probe 8912	1.3.6.1.4.1.141.1.1.8912						

1. Management interface only, for WAN Switch Probes.

Table 17 IP Telephony Devices

Series	Devices Supported	sysObjectID	Topology	VLAN Mgmt	LANE Mgmt	ATM Mgmt	User Tracking	Path Analysis
Cisco Integrated Communications System (ICS) Device	ICS7750MRP	1.3.6.1.4.1.9.1.302	Yes	—	—	—	Yes	Yes
	ICS7750SPE	1.3.6.1.4.1.9.1.314						
	ICS7750SSP	1.3.6.1.4.1.9.1.303						
Media Convergence Server (MCS)	MCS-7800 Series	1.3.6.1.4.1.311.1.1.3.1.2	Yes	—	—	—	Yes	Yes
Cisco IP Conference Station	7935	—	—	—	—	—	Yes	Yes
IP Phones	7960	—	—	—	—	—	Yes	Yes
	7940	—						
Application Server	Application Server	1.3.6.1.4.1.311.1.1.3.1.2	Yes	—	—	—	Yes	Yes

sysObjectID for Devices Supported in Campus Manager 3.3

The following tables show the sysObjectID for the Cisco devices supported when Campus Manager 3.3 was released:

- [Table 18, sysObjectID for Routers](#)
- [Table 19, sysObjectID for Switch Probe and Network Analysis Modules](#)

Table 18 *sysObjectID for Routers*

Device Type	Devices Supported	sysObjectID
Cisco 2500 Series	2500	1.3.6.1.4.1.9.1.13
	2501	1.3.6.1.4.1.9.1.17
	2502	1.3.6.1.4.1.9.1.18
	2503	1.3.6.1.4.1.9.1.19
	2504	1.3.6.1.4.1.9.1.20
	2505	1.3.6.1.4.1.9.1.21
	2506	1.3.6.1.4.1.9.1.22
	2507	1.3.6.1.4.1.9.1.23
	2508	1.3.6.1.4.1.9.1.24
	2509	1.3.6.1.4.1.9.1.25
	2510	1.3.6.1.4.1.9.1.26
	2511	1.3.6.1.4.1.9.1.27
	2512	1.3.6.1.4.1.9.1.28
	2513	1.3.6.1.4.1.9.1.29
	2514	1.3.6.1.4.1.9.1.30
	2515	1.3.6.1.4.1.9.1.31
	2516	1.3.6.1.4.1.9.1.42
	2517	1.3.6.1.4.1.9.1.67
	2518	1.3.6.1.4.1.9.1.68
	2519	1.3.6.1.4.1.9.1.69
	2520	1.3.6.1.4.1.9.1.70
	2521	1.3.6.1.4.1.9.1.71
	2522	1.3.6.1.4.1.9.1.72
	2523	1.3.6.1.4.1.9.1.73
	2524	1.3.6.1.4.1.9.1.74
2525	1.3.6.1.4.1.9.1.75	

Table 19 *sysObjectID for Switch Probe and Network Analysis Modules*

Device Type	Devices Supported	sysObjectID
Network Switch Probes	NetScout Probe7213	1.3.6.1.4.1.141.1.1.7213
	NetScout Probe7221	1.3.6.1.4.1.141.1.1.7221
	NetScout Probe8702	1.3.6.1.4.1.141.1.1.8702
	NetScout Probe8714	1.3.6.1.4.1.141.1.1.8714