



Vendor Specific Attributes

This appendix lists all vendor-specific attributes (VSAs) supported by Cisco Access Registrar 3.1.

Cisco VSAs

Table A-1 lists the Cisco VSAs.

Table A-1 Cisco VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	Cisco-AVPair	String	0-253
2	Cisco-NAS-Port	String	0-253
3	Cisco-Fax-Account-ID-Origin	String	0-253
4	Cisco-Fax-Message-ID	String	0-253
5	Cisco-Fax-Pages	String	0-253
6	Cisco-FAX Cover Page Flag	String	0-253
7	Cisco-Fax-Modem-Time	String	0-253
8	Cisco-Fax-Connect-Speed	String	0-253
9	Cisco-Fax-Recipient-Count	String	0-253
10	Cisco-Fax-Process-Abort-Flag	String	0-253
11	Cisco-Fax-DSN-Address	String	0-253
12	Cisco-Fax-DSN-Flag	String	0-253
13	Cisco-Fax-MDN-Address	String	0-253
14	Cisco-Fax-MDN-Flag	String	0-253
15	Cisco-Fax-Auth-Status	String	0-253
16	Cisco-Email-Server-Address	IP Address	
17	Cisco-Email-Server-ACK Flag	String	0-253
18	Cisco-Gateway-ID	String	0-253
19	Cisco-Call-Type	String	0-253
20	Cisco-Port-Used	String	0-253
21	Cisco-Abort-Cause	String	0-253

Table A-1 Cisco VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
22	Cisco-CRS-Info	String	0-253
23	Cisco-h323-Remote-Address	String	0-253
24	Cisco-h323-Conf-ID	String	0-253
25	Cisco-h323-Setup-Time	String	0-253
26	Cisco-h323-Call-Origin	String	0-253
27	Cisco-h323-Call-Type	String	0-253
28	Cisco-h323-Connect-Time	String	0-253
29	Cisco-h323-Disconnect-Time	String	0-253
30	Cisco-h323-Disconnect-Cause	String	0-253
31	Cisco-h323-Voice-Quality	String	0-253
32	Cisco-h323-Generic-IVR-Out	String	0-253
33	Cisco-h323-Gateway-ID	String	0-253
34	Cisco-3GPP2-AVPair	String	0-253
35	Cisco Connection ID-h323-incoming-connection-ID	String	0-253
100	Cisco-h323-Generic-IVR-In	String	0-253
101	Cisco-h323-Amount-Balance		
102	Cisco-h323-Time-Balance	String	0-253
103	Cisco-h323-Return-Code	String	0-253
104	Cisco-h323-Prompt-ID	String	0-253
105	Cisco-h323-Time-of-Day	String	0-253
106	Cisco-h323-Redirect-Number	String	0-253
107	Cisco-h323-Preferred-Language	String	0-253
108	Cisco-h323-Redirect-IP-Address	String	0-253
109	Cisco-h323-Billing-Model	ENUM: postpaid prepaid	0-1
110	Cisco-h323-Currency	String	0-253
128	Cisco-UCP-IP-Pool-ID	String	0-253
129	Cisco-UCP-User-Max-Sessions	String	0-253
130	Cisco-UCP-User-Session-Count	String	0-253
131	Cisco-UCP-Next-Session-ID	String	0-253
132	Cisco-UCP-VPDN-Max-Sessions	String	0-253
133	Cisco-UCP-VPDN-Session-Count	String	0-253
134	Cisco-UCP-B-Channel-Max-Sessions	String	0-253
135	Cisco-UCP-B-Channel-Session-Coun	String	0-253
136	Cisco-UCP-Status	String	0-253
137	Cisco-UCP-BLOB-Attribute-Length	String	0-253

Table A-1 Cisco VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
138	Cisco-UCP-Disable-Statu	String	0-253
139	Cisco-UCP-Block-Access-Range	String	0-253
140	Cisco-UCP-Home-POP-ID	String	0-253
175	Cisco-UCP-IP-Addresses	IP Address	0-253
176	Cisco-UCP-Session-Info	String	0-253
211	Cisco-Ascend AV pairs	String	0-253
250	Cisco-SSG-Account-Info	String	0-253
251	Cisco-SSG-Service-Info	String	0-253
252	Cisco-SSG-Command-Code	String	0-253
253	Cisco-SSG-Control-Info	String	0-253

Ascend VSAs

Table A-2 lists the Ascend VSAs.

Table A-2 Ascend VSAs

SubAttr	VSA Name	Type	Min-Max Value
17	Ascend-Change-Password	String	0 - 253
18	Ascend-Session-Type	ENUM: Unused Unknown G711-Ulaw G711-Alaw G723 G729 G723-64KPS G728 RT24	0 - 8
19	Ascend-H323-Gatekeeper	IP Address	0 - 253
21	Ascend-H323-Conference-ID	String	0-253
22	Ascend-H323-Destination-NAS-ID	IP Address	0-65535
23	Ascend-H323-Dialed-Time	UINT32	0-253
24	Ascend-H323-Dialed-Number	String	0-253
25	Ascend-Inter-Arrival-Jitter	UINT32	0-253
26	Ascend-Dropped-Octets	UINT32	0-253
27	Ascend-Dropped-Packets	UINT32	0-253

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
48	Ascend-Call-Direction	ENUM: Incoming Outgoing	0-1
49	Ascend-Service-Type	ENUM	0 - 23; NotUsed None EuUi Telnet TelnetBin RawTcp TermServer MP VirtualConn X25DChan PseuTunPPP IpFax Other ATM HdleNrm VoIp Visa2 PPP Slip MPP X25 Combinet FR EuRaw
68	Ascend-Tunnel-ID	String	0 - 253
126	Ascend-Route-Preference	ENUM: Interface, OSPF-Internal, RIP, Down-WAN, OSPF-ASE, Infinite, ICMP	0-225
132	Ascend-Client-Gateway	IP Address	0 - 253
144	Ascend-Assign-IP-Client	IP Address	0-0
145	Ascend-Assign-IP-Server	IP Address	0-0
152	Ascend-Multicast-Rate-Limit	UINT32	0-65535
162	Ascend-FR-DCE-N392	UINT32	0-65535
163	Ascend-FR-DTE-N392	UINT32	0-65535
164	Ascend-FR-DCE-N393	UINT32	0-65535

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
165	Ascend-FR-DTE-N393	UINT32	0-65535
166	Ascend-FR-T391	UINT32	0-65535
167	Ascend-FR-T392	UINT32	0-65535
168	Ascend-Bridge-Address	UINT32	1-253
169	Ascend-TS-Idle-Limit	UINT32	0-65535
170	Ascend-TS-Idle-Mode	ENUM; TS-Idle-None TS-Idle-Input TS-Idle-Input-Output	0-2
171	Ascend-DBA-Monitor	ENUM; Transmit Transmit-Receive None	0-2
172	Ascend-Base-Channel-Count	UINT32	0-65535
173	Ascend-Minimum-Channels	UINT32	0-65535
174	Ascend-IPX-Route	String	1-253
175	Ascend-FT1-Caller	ENUM; FT1-No FT1-Yes	0-1
176	Ascend-Backup	String	1-253
177	Ascend-Call-Type	ENUM; Nailed Nailed/MPP Perm/Switched	0-2
178	Ascend-Group	String	1-253
179	Ascend-FR-DLCI	UINT32	0-65535
180	Ascend-FR-Profile-Name	String	1-253
181	Ascend-Ara-PW	String	1-253
182	Ascend-IPX-Node-Address	String	1-253
183	Ascend-Home-Agent-IP-Addr	IP Address	0-0
184	Ascend-Home-Agent-Password	String	1-253
185	Ascend-Home-Network-Name	String	1-253
186	Ascend-Home-Agent-UDP-Port	UINT32	0-65535
187	Ascend-Multilink-ID	UINT32	0-65535
188	Ascend-Num-In-Multilink	UINT32	0-65535
189	Ascend-First-Dest	IP Address	0-0
190	Ascend-Pre-Input-Octets	UINT32	0-65535
191	Ascend-Pre-Output-Octets	UINT32	0-65535

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
192	Ascend-Pre-Input-Packets	UINT32	0-65535
193	Ascend-Pre-Output-Packets	UINT32	0-65535
194	Ascend-Maximum-Time	UINT32	0-65535
195	vAscend-Pre-Output-Packets (continued)	ENUM: No-Reason, Not-Applicable, Modem-No-DCD, Session-Timeout, Invalid-Incoming-User, Disconnect-Due-To-Callback, DCD-Detected-Then-Inactive, Modem-Invalid-Result-Codes, Protocol-Disabled-Or-Unsuppor, Disconnect-Req-By-RADIUS, Disconnect-Req-By-Local-Admin, V110-Timeout-Or-Sync-Retry-Ex, PPP-Auth-Timeout-Exceeded, User-Executed-Do-Hangup, Remote-End-Hung-Up, Resource-Has-Been-Quiesced, Max-Call-Duration-Reached, Unknown, (continued)	0-195
195	vAscend-Pre-Output-Packets	ENUM: TermSrv-User-Quit, TermSrv-Idle-Timeout, TermSrv-Exit-Telnet, TermSrv-No-IPaddr, TermSrv-Exit-Raw-TCP, TermSrv-Exit-Login-Failed, TermSrv-Exit-Raw-TCP-Disabled, TermSrv-CTRL-C-In-Login, TermSrv-Destroyed, TermSrv-User-Closed-VCon, Call-Disconnected, TermSrv-VCon-Destroyed, TermSrv-Exit-Rlogin, TermSrv-Bad-Rlogin-Option, TermSrv-Not-Enough-Resources, MPP-No-NULL-Msg-Timeout, CLID-Authentication-Failed, (continued)	0-195

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
195	vAscend-Pre-Output-Packets	ENUM: PPP-LCP-Timeout, PPP-LCP-Negotion-Failed, PPP-PAP-Auth-Failed, PPP-CHAP-Auth-Failed, PPP-Rmt-Auth-Failed, PPP-Rcv-Terminate-Req, PPP-Rcv-Close-Event, PPP-No-NCPs-Open, PPP-MP-Bundle-Unknown,, PPP-LCP-Close-MP-Add-Fail, CLID-RADIUS-Timeout (continued)	0-195
195	vAscend-Pre-Output-Packets (continued)	Out-Of-Resources, Invalid-IP-Address, Hostname-Resolution-Failed, Bad-Or-Missing-Port-Number, Host-Reset, Connection-Refused, Connection-Timeout, Connection-Closed, Network-Unreachable, Host-Unreachable, Network-Unreachable-Admin, Host-Unreachable-Admin, Port-Unreachable,	
196	Ascend-Connect-Progress	ENUM: No-Progress, unknown1, Call-Up, unknown2, Modem-Up, Modem-Awaiting-DCD, Modem-Awaiting-Codes, TermSrv-Started, TermSrv-Raw-TCP-Started, TermSrv-Telnet-Started, TermSrv-Raw-TCP-Connected, TermSrv-Telnet-Connected, TermSrv-Rlogin-Started, TermSrv-Rlogin-Connected, TermSrv-Authentication-Begin, Modem-Outdial-Call-Up	0-94

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
196	Ascend-Connect-Progress	ENUM: LAN-Session-Up, LCP-Opening, CCP-Opening, IPNCP-Opening, NCP-Opening, LCP-Opened, CCP-Opened, IPNCP-Opened, BNCP-Opened, LCP-State-Initial, LCP-State-Starting, LCP-State-Closed, LCP-State-Stopped, BACP-Opened, LCP-State-Stopping, LCP-State-Request-Sent, LCP-State-Ack-Received, LCP-State-Ack-Sent, IPXNCP-Opened, ATNCP-Opened, BACP-Opening, V110-Up, V110-State-Opened, V110-State-Carrier, V110-State-Reset, V110-State-Closed	0-94
197	Ascend-Data-Rate	UINT32	0-65535
198	Ascend-PreSession-Time	UINT32	0-65535
199	Ascend-Token-Idle	UINT32	0-65535
200		ENUM: Tok-Imm-No, Tok-Imm-Yes	0-1

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
201	Ascend-Require-Auth	ENUM: Not-Require-Auth Require-Auth Pap-Only Pap-Only Pap-Login-Only Pap-Framed-Only Pap-Outbound-Only CHAP-Only CHAP-Only CHAP-Login-Only CHAP-Framed-Only CHAP-Outbound-Only MS-CHAP-Only MS-CHAP-Only MS-CHAP-Login-Only MS-CHAP-Framed-Only MS-CHAP-Outbound-Only	0-55
210	Ascend-PPP-VJ-Slot-Comp	ENUM: VJ-Slot-Comp-No	1-1
211	Ascend-PPP-VJ-1172	ENUM: PPP-VJ-1172	1-1
212	Ascend-PPP-Async-Map	UINT32	0-65535
213	Ascend-Third-Prompt	String	1-253
214	Ascend-Send-Secret	String	1-253
215	Ascend-Receive-Secret	String	1-253
216	Ascend-IPX-Peer-Mode	ENUM: IPX-Peer-Router, IPX-Peer-Dialin	1-1
217	Ascend-IP-Pool-Definition	String	1-253
218	Ascend-Assign-IP-Pool	UINT32	0-65535
219	Ascend-FR-Direct	ENUM: FR-Direct-No, FR-Direct-Yes	1-1
220	Ascend-FR-Direct-Profile	String	1-253
221	Ascend-FR-Direct-DLCI	UINT32	0-65535
222	Ascend-Handle-IPX	ENUM: Handle-IPX-None, Handle-IPX-Client, Handle-IPX-Server	0-2
223	Ascend-Netware-timeout	UINT32	0-65535
224	Ascend-IPX-Alias	UINT32	0-65535
225	Ascend-Metric	UINT32	0-65535

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
226	Ascend-PRI-Number-Type	ENUM: Unknown-Number, Intl-Number, National-Number, Local-Number Abbrev-Number	0-5
227	Ascend-Dial-Number	String	1-253
228	Ascend-Route-IP	ENUM: Unknown-Number, Intl-Number, National-Number, Local-Number, Abbrev-Number	0-5
229	Ascend-Route-IPX	ENUM: Route-IPX-No Route-IPX-Yes	0-1
230	Ascend-Bridge	ENUM: Bridge-No, Bridge-Yes	0-1
231	Ascend-Send-Auth	ENUM: Send-Auth-None, end-Auth-PAP, Send-Auth-CHAP	0-2
232	Ascend-Send-Passwd	String	1-253
233	Ascend-Link-Compression	ENUM: Link-Comp-None, Link-Comp-Stac, Link-Comp-Stac-Draft-9, Link-Comp-MS-Stac	0-3
234	Ascend-Target-Util	UINT32	0-65535
235	Ascend-Maximum-Channels	UINT32	0-65535
236	Ascend-Inc-Channel-Count	UINT32	0-65535
237	Ascend-Dec-Channel-Count	UINT32	0-65535
238	Ascend-Seconds-Of-History	UINT32	0-65535
239	Ascend-History-Weigh-Type	ENUM: History-Constant, History-Linear, History-Quadratic	0-2
240	Ascend-Add-Seconds	UINT32	0-65535
241	Ascend-Remove-Seconds	UINT32	0-65535
242	Ascend-Data-Filter	String	1-253
243	Ascend-Call-Filter	String	1-253
244	Ascend-Idle-Limit	UINT32	0-65535

Table A-2 Ascend VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
245	Ascend-Idle-Limit	UINT32	0-65535
246	Ascend-Callback	ENUM: Callback-No, Callback-Yes	0-1
247	Ascend-Data-Svc	ENUM: Switched-Voice-Bearer, Switched-56KR, Switched-192K, Switched-256K, Switched-320K, Switched-384K-MR, Switched-448K, Switched-512K, Switched-566K, Switched-640K, Switched-704K, Switched-768K, Switched-64K, Switched-832K, Switched-896K, Switched-960K, Switched-1024K, Switched-1088K, Switched-1152K, Switched-1216K,. Switched-1280K, Switched-1344K, Switched-1408K, Switched-64KR, Switched-1472K, Switched-1600K, Switched-1664K, Switched-1728K, Switched-1792K, Switched-1856K, Switched-1920K, Switched-inherited, Switched-restricted-bearer-x3, Switched-clear-bearer-v110, Switched-56K, Switched-restricted-64-x30, Switched-clear-56-v110, Switched-modem, Switched-atmodem, Switched-384KR, Switched-384K, Switched-1536K, Switched-1536KR, Switched-128K	0-43
248	Ascend-Force-56	ENUM: Force-56-No, Force-56-Yes	0-1
249	Ascend-Billing-Number	String	1-253
250	Ascend-Call-By-Call	UINT32	0-65535
251	Ascend-Transit-Number	String	1-253
252	Ascend-Host-Info	String	1-253
253	Ascend-PPP-Address	IP Address	0-0
254	Ascend-MPP-Idle-Percent	UINT32	0-65535

Microsoft VSAs

Table A-3 lists the Microsoft VSAs.

Table A-3 Microsoft VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	MS-CHAP-Response	String	50-50
2	MS-CHAP-Error	String	0-253
3	MS-CHAP-CPW1	String	70-70
4	MS-CHAP-CPW2	String	84-84
5	MS-CHAP-LM-Enc-PW	String	4-253
6	MS-CHAP-NT-Enc-PW	String	4-253
7	MS-MPPE-Encryption-Policy	ENUM: Encryption-Allowed Encryption-Required	1-2
8	MS-MPPE-Encryption-Types	String	0-4
9	MS-RAS-Vendor	UINT32	0-253
10	MS-CHAP-Domain	String	0-253
11	MS-CHAP-Challenge	String	0-253
12	MS-CHAP-MPPE-Keys	String	32-32
13	MS-BAP-Usage	ENUM: Not allowed Allowed Required	0-2
14	MS-Link-Utilization-Threshold	UINT32	0-253
15	MS-Link-Drop-Time-Limit	String	0-253
16	MS-MPPE-Send-Key	String	0-253
17	MS-MPPE-Recv-Key	String	0-253
18	MS-RAS-Version	String	0-253
19	MS-Old-ARAP-Password	String	0-253
20	MS-New-ARAP-Password	String	0-253
21	MS-ARAP-Password-Change-Reason	ENUM: Just-Change-Password Expired-Password Admin-Requires-Password-Chang Password-Too-Short	1-4
22	MS-Filter	String	0-253
23	MS-Acct-Auth-Type	ENUM: PAP CHAP MS-CHAP-1 MS-CHAP-2 EAP	1-5
26	MS-CHAP2-Success	String	43-43
27	MS-CHAP2-CPW8	String	68-68

Table A-3 Microsoft VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
29	MS-Secondary-DNS-Server	IP Address	68-68
31	MS-Secondary-NBNS-Server	IP Address	70-70
33	MS-ARAP-Challenge	String	8-8

Cabletron VSAs

Table A-4 lists the Cabletron VSAs.

Table A-4 Cabletron VSAs

SubAttr	VSA Name	Type	Min-Max Value
192	Cabletron-Framed-Data-Rate	ENUM: Rate-56KB Rate-64KB Rate-112KB Rate-128KB	0-4
193	Cabletron-Phone-Number	String	0-253
194	Cabletron-Caller-Id	String	0-253
196	Cabletron-Connection-Reference	UINT32	0-253
198	Cabletron-Initial-Rate	UINT32	0-253
199	Cabletron-Maximum-Rate	UINT32	0-253
192	Cabletron-Framed-Data-Rate	Enum: Rate-56KB Rate-64KB Rate-112KB Rate-128KB	192

Compatible VSAs

Table A-5 lists the Compatible VSAs.

Table A-5 Compatible VSAs

SubAttr	VSA Name	Type	Min-Max Value
0	Compatible-Tunnel-Delay	UNIT32	0-253
1	Compatible-Tunnel-Throughput	UNIT32	0-253
3	Compatible-Tunnel-Server-Endpoint	IP Address	0-253
4	Compatible-Tunnel-Group-Info	String	0-253
5	Compatible-Tunnel-Password	String	0-253

Table A-5 Compatible VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
6	Compatible-Echo	UNIT32	0-253
7	Compatible-Tunnel-Client-IPX	UNIT32	0-253

Nomadix VSAs

Table A-6 lists the Nomadix VSAs.

Table A-6 Nomadix VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	Nomadix-Bw-Up 0 253	UINT32	0-253
2	Nomadix-Dw-Down	UINT32	0-253

RedCreek VSAs

Table A-7 lists the RedCreek VSAs.

Table A-7 RedCreek VSAs

SubAttr	VSA Name	Type	Min-Max Value
6	RedCreek-Tunneled-IP-Netmask	IP Address	0-253
7	RedCreek-Tunneled-Gateway	IP Address	0-253
9	RedCreek-Tunneled-WINS-Server1	String	0-253
10	RedCreek-Tunneled-WINS-Server2	String	0-253
11	RedCreek-Tunneled-HostName	String	0-253
12	RedCreek-Tunneled-DomainName	String	0-253
13	RedCreek-Tunneled-Search-List	String	0-253

USR VSAs

Table A-8 lists the USR VSAs.

Table A-8 USR VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	USR-DTE-Data-Idle-Timeout	UINT32	0-0
2	USR-Default-DTE-Data-Rate	ENUM: 110_BPS 300_BPS 600_BPS 1200_BPS 2400_BPS 4800_BPS 7200_BPS 9600_BPS 12K_BPS 14.4K_BPS 16.8_BPS 19.2K_BPS 38.4K_BPS 75_BPS 450_BPS UNKNOWN_BPS 57.6K_BPS 21.6K_BPS 24K_BPS 26K_BPS 28K_BPS 115K_BPS 31K_BPS 33K_BPS 25333_BPS 110_BPS 300_BPS 600_BPS 1200_BPS 2400_BPS 26666_BPS 28000_BPS 29333_BPS 30666_BPS 32000_BPS	1-54

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
2	USR-Default-DTE-Data-Rate	33333_BPS 34666_BPS 36000_BPS 37333_BPS 38666_BPS 40000_BPS 41333_BPS 42666_BPS 44000_BPS 45333_BPS 46666_BPS 48000_BPS 49333_BPS 50666_BPS 52000_BPS 53333_BPS 54666_BPS 56000_BPS 57333_BPS 58666_BPS 60000_BPS 61333_BPS 62666_BPS 64000_BPS	
3	USR-Last-Number-Dialed-Out	String	1-253
4	USR-Sync-Async-Mode	ENUM: Asynchronous Synchronous	1-2
5	USR-Originate-Answer-Mode	ENUM: Originate_in_Originate_Mode Originate_in_Answer_Mode Answer_in_Originate_Mode Answer_in_Answer_Mode	1-4
6	USR-Failure-to-Connect-Reason	ENUM:	1-67

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
7	USR-Initial-Tx-Link-Data-Rate	ENUM: 110_BPS 14.4K_BPS 16.8_BPS 19.2K_BPS 38.4K_BPS 75_BPS 450_BPS UNKNOWN_BPS 57.6K_BPS 21.6K_BPS 24K_BPS 300_BPS 26K_BPS 28K_BPS 115K_BPS 31K_BPS 33K_BPS 25333_BPS 26666_BPS 28000_BPS 29333_BPS 30666_BPS 600_BPS 32000_BPS 33333_BPS 34666_BPS 36000_BPS 37333_BPS 38666_BPS 40000_BPS 41333_BPS 42666_BPS 44000_BPS 1200_BPS 45333_BPS 46666_BPS 48000_BPS 49333_BPS 50666_BPS 52000_BPS 53333_BPS 54666_BPS 56000_BPS 57333_BPS 2400_BPS 58666_BPS 60000_BPS	1-54

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
7	USR-Initial-Tx-Link-Data-Rate (continued)	61333_BPS 62666_BPS 64000_BPS 4800_BPS 7200_BPS 9600_BPS 12K_BPS	
8	USR-Final-Tx-Link-Data-Rate	ENUM: 110_BPS 14.4K_BPS 16.8_BPS 19.2K_BPS 38.4K_BPS 75_BPS 450_BPS UNKNOWN_BPS 57.6K_BPS 21.6K_BPS 24K_BPS 300_BPS 26K_BPS 28K_BPS 115K_BPS 31K_BPS 33K_BPS 25333_BPS 26666_BPS 28000_BPS 29333_BPS 30666_BPS 600_BPS	1-54
8	USR-Final-Tx-Link-Data-Rate	32000_BPS 33333_BPS 34666_BPS 36000_BPS 37333_BPS 38666_BPS 40000_BPS 41333_BPS 42666_BPS 44000_BPS 1200_BPS 45333_BPS 46666_BPS 48000_BPS 49333_BPS 50666_BPS 52000_BPS 53333_BPS	1-54

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
8	USR-Final-Tx-Link-Data-Rate	54666_BPS 56000_BPS 57333_BPS 2400_BPS 58666_BPS 60000_BPS 61333_BPS 62666_BPS 64000_BPS 4800_BPS 7200_BPS 9600_BPS	
9	USR-Modulation-Type	ENUM: usRoboticsHST bell208b v21FaxClass1 v27FaxClass1 v29FaxClass1 v17FaxClass1 v21FaxClass2 v27FaxClass2 v29FaxClass2 v17FaxClass2 v32Terbo ccittV32 v34 vFC v34plus x2 v110 v120 x75 ayncSyncPPP clearChannel ccittV22bis bell103 ccittV21 bell1212 ccittV32bis ccittV23 negotiationFailed	1-28
9	USR-Modulation-Type	ENUM:	
10	USR-Equalization-Type	ENUM: Long Short	1-2
112	USR-Characters-Sent	UINT32	0-0
13	USR-Characters-Received	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
14	USR-Blocks-Sent	UINT32	0-0
15	USR-Blocks-Received 0	UINT32	0-0
16	USR-Blocks-Resent	UINT32	0-0
17	USR-Retrains-Requested	UINT32	0-0
18	USR-Retrains-Granted	UINT32	
19	USR-Line-Reversals	UINT32	
20	USR-Number-Of-Characters-Lost0	UINT32	0-0
21	USR-Back-Channel-Data-Rate	ENUM : 450BPS 300BPS None	1-3
22	USR-Number-of-Blers	UINT32	0-0
23	USR-Number-of-Link-Timeouts	UINT32	0-0
24	USR-Number-of-Fallbacks	UINT32	0-0
25	USR-Number-of-Upshifts	UINT32	0-0
26	USR-Number-of-Link-NAKs	UINT32	0-0
27	USR-Simplified-MNP-Levels	ENUM: Unknown NON_ARQ MNP10ec LAPMAC V42ETC2 V42SREJ PIAFS V120 X75 MNP3 MNP4 V42 HST synchronous MNP2 MNP10(Cellular) V42ETC	0-16

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
28	USR-Connect-Term-Reason	ENUM: dtrDrop retransmitLimit linkDisconnectMsgReceived noLoopCurrent invalidSpeed unableToRetrain managementCommand noDialTone keyAbort lineBusy noAnswer escapeSequence voice noAnswerTone noCarrier undetermined v42SabmeTimeout v42BreakTimeout v42DisconnectCmd v42IdExchangeFail v42BadSetup v42InvalidCodeWord athCommand v42StringTooLong v42InvalidCommand none v32Cleardown dialSecurity	1-67

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
28	USR-Connect-Term-Reason	remoteAccessDenied loopLoss ds0Teardown promptNotEnabled noPromptingInSync carrierLoss nonArqMode modeIncompatible noPromptInNonARQ dialBackLink linkAbort autopassFailed pbGenericError pbLinkErrTxPreAck pbLinkErrTxTardyACK pbTransmitBusTimeout inactivityTimeout pbReceiveBusTimeout pbLinkErrTxTAL pbLinkErrRxTAL pbTransmitMasterTimeout pbClockMissing pbReceivedLsWhileLinkUp pbOutOfSequenceFrame pbBadFrame pbAckWaitTimeout pbReceivedAckSeqErr mnpIncompatible pbReceiveOvrflwRNRFail pbReceiveMsgBufOvrflw rcvdGatewayDiscCmd tokenPassingTimeout dspInterruptTimeout mnpProtocolViolation	
28	USR-Connect-Term-Reason	class2FaxHangupCmd hstSpeedSwitchTimeout undefined remotePassword linkPassword	
29	USR-DTR-False-Timeout	UINT32	0-0
30	USR-Fallback-Limit	UINT32	0-0
31	USR-Block-Error-Count-Limit	UINT32	0-0
32	USR-Simplified-V42bis-Usage	ENUM: None ccittV42bis mnpLevel5	1-3
33	USR-DTR-True-Timeou	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
34	USR-Last-Number-Dialed-In-DNIS	String	1-253
35	USR-Last-Callers-Number-ANI	String	1-253
36	USR-Mbi-Ct-PRI-Card-Slot	UINT32	0-0
37	USR-Mbi-Ct-TDM-Time-Slot	UINT32	0-0
38	USR-Mbi-Ct-PRI-Card-Span-Line	UINT32	0-0
39	USR-Mbi-Ct-BChannel-Used	UINT32	0-0
40	USR-IP-Input-Filter	String	1-253
41	USR-IPX-Input-Filter	String	1-253
42	USR-IP-Output-Filter	String	1-253
43	USR-IPX-Output-Filter	String	1-253
44	USR-SAP-Output-Filter	String	1-253
45	USR-VPN-ID	UINT32	0-0
46	USR-VPN-Name	String	1-253
47	USR-VPN-Neighbor	String	1-253
48	USR-Framed-Routing-V2	ENUM: RIP-V2-Off RIP-V2-On	1-2
49	USR-VPN-Gateway	String	1-253
50	USR-Tunnel-Authenticato	String	1-253
51	USR-Packet-Index	String	1-253
52	USR-Cutoff	String	1-253
53	USR-Access-Accept-Packet	String	1-253
54	USR-Primary-DNS-Server	String	1-253
55	USR-Secondary-DNS-Server	String	1-253
56	USR-Primary-NBNS-Server	String	1-253
57	USR-Secondary-NBNS-Server	String	1-253
58	USR-Syslog-Tap	UINT32	0-0
59	USR-Chassis-Call-Slot	UINT32	0-0
60	USR-Chassis-Call-Span	UINT32	0-0
61	-Chassis-Call-Channel	UINT32	0-0
62	USR-Keypress-Timeout	UINT32	0-0
63	USR-Unauthenticated-Time	UINT32	0-0
64	USR-Bearer-Capabilities	UINT32	0-0
65	USR-Speed-Of-Connection	UINT32	0-0
66	USR-Max-Channels	UINT32	0-0
67	USR-Channel-Expansion	UINT32	0-0
68	USR-Channel-Decrement	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
69	USR-Expansion-Algorithm	UINT32	0-0
70	USR-Compression-Algorithm	UINT32	0-0
71	USR-Receive-Acc-Map	UINT32	0-0
72	USR-Transmit-Acc-Map	UINT32	0-0
73	USR-Compression-Reset-Mode	UINT32	0-0
74	USR-Min-Compression-Size	UINT32	0-0
75	USR-IP	UINT32	0-0
76	USR-IPX	UINT32	0-0
77	USR-Filter-Zones	UINT32	0-0
78	USR-Appletalk	UINT32	0-0
79	USR-Bridging	UINT32	0-0
80	USR-Spoofing	UINT32	0-0
81	USR-Host-Type	String	1-253
82	USR-Send-Name	UINT32	0-0
83	USR-Send-Password	String	1-253
84	USR-Start-Time	UINT32	0-0
85	USR-End-Time	UINT32	0-0
86	USR-Send-Script1	String	1-253
87	USR-Reply-Script1	String	1-253
88	USR-Send-Script2	String	1-253
89	USR-Reply-Script2	String	1-253
90	USR-Send-Script3	String	1-253
91	USR-Send-Script3 USR-Reply-Script3	String	1-253
92	USR-Send-Script4	String	1-253
93	USR-Reply-Script4	String	1-253
94	USR-Send-Script5	String	1-253
95	USR-Reply-Script5	String	1-253
96	USR-Send-Script6	String	1-253
97	USR-Reply-Script6	String	1-253
98	USR-Terminal-Type	String	1-253
99	USR-Appletalk-Network-Range	UINT32	0-0
100	USR-Local-IP-Address	String	1-253
101	USR-Routing-Protocol	UINT32	0-0
102	USR-Modem-Group	UINT32	0-0
103	USR-IPX-Routing	UINT32	0-0
104	USR-IPX-Wan	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
105	USR-IP-RIP-Policies	UINT32	0-0
106	USR-IP-RIP-Simple-Auth-Password	String	0-253
107	USR-IDS0-Call-Type	UINT32	0-0
108	USR-Call-Terminate-in-GMT	UINT32	0-0
109	USR-Call-Connect-in-GMT	UINT32	0-0
110	USR-Call-Arrival-in-GMT	UINT32	0-0
111	USR-Channel-Connected-To	UINT32	0-0
112	USR-Slot-Connected-To	UINT32	0-0
113	USR-Device-Connected-To	ENUM: None isdnGateway quadModem	1-3
114	USR-NFAS-ID	UINT32	0-0
115	USR-Q931-Call-Reference-Value	UINT32	0-0
116	USR-Call-Event-Code	ENUM: notSupported noFreeIGW igwRejectCall igwSetupTimeout noFreeTdmTs bcReject ieReject chidReject progReject callingPartyReject calledPartyReject setup blocked analogBlocked digitalBlocked outOfService busy congestion protocolError noFreeBchannel inOutCallCollision usrSetup telcoDisconnect usrDisconnect noFreeModem modemsNotAllowed modemsRejectCall modemSetupTimeout	1-28
117	USR-DS0	UINT32	0-0
118	USR-DS0s	String	1-253

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
119	USR-Gateway-IP-Address	IP Address	0-0
120	USR-Physical-State	UINT32	0-0
121	USR-Chassis-Temp-Threshold	UINT32	0-0
122	USR-Card-Type	ENUM: SlotEmpty QuadV32DigitalModemNAC DualT1NIC DualAlogMdmNIC QuadDgtlMdmNIC QuadAlogDgtlMdmNIC TokenRingNIC SingleT1NIC EthernetNIC ShortHaulDualT1NIC DualAlogMgdIntlMdmNIC X25NIC	
122	USR-Card-Type (continued)	ENUM: QuadAlogNonMgdMdmNIC QuadAlogMgdIntlMdmNIC QuadAlogNonMgdIntlMdmNIC QuadLsdLiMgdMdmNIC QuadLsdLiNonMgdMdmNIC QuadLsdLiMgdIntlMdmNIC QuadLsdLiNonMgdIntlMdmNIC EthernetWithV35NIC HSEthernetWithoutV35NIC DualHighSpeedV35NIC QuadV35RS232LowSpeedNIC DualE1NIC ShortHaulDualE1NIC BellcoreLongHaulDualT1NIC BellcoreShrtHaulDualT1NIC SCSIEdgeServerNIC QuadV32AnalogModemNAC QuadV32DigAnlModemNAC QuadV34DigModemNAC QuadV34AnlModemNAC QuadV34DigAnlModemNAC SingleT1NAC EthernetGatewayNAC AccessServer 486TrGatewayNAC SlotUnknown	

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
122	USR-Card-Type (continued)	ENUM: 486EthernetGatewayNAC DualRS232NAC 486X25GatewayNAC ApplicationServerNAC ISDNGatewayNAC ISDNpriT1NAC ClkedNetMgtCard ModemPoolManagementNAC NetwMgtCard ModemPoolNetserverNAC (continued)	1-1027
122	USR-Card-Type (continued)	ModemPoolV34ModemNAC ModemPoolISDNNAC NTServerNAC QuadV34DigitalG2NAC QuadV34AnalogG2NAC QuadV34DigAnlgG2NAC NETServerFrameRelayNAC NETServerTokenRingNAC X2524ChannelNAC DualT1NAC WirelessGatewayNac EnhancedAccessServer EnhancedISDNGatewayNAC DualModemNAC QuadModemNAC TrGatewayNAC X25GatewayNAC DualV34ModemNAC	
123	USR-Security-Login-Limit	UINT32	0-0
124	USR-Security-Resp-Limit	UINT32	0-0
125	USR-Packet-Bus-Session	UINT32	0-0
126	USR-DTE-Ring-No-Answer-Limit	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
127	USR-Final-Rx-Link-Data-Rate	ENUM: 110_BPS 14.4K_BPS 16.8_BPS 19.2K_BPS 38.4K_BPS 75_BPS 450_BPS UNKNOWN_BPS 57.6K_BPS 21.6K_BPS 24K_BPS 300_BPS 6K_BPS 28K_BPS 115K_BPS 31K_BPS 33K_BPS 25333_BPS 26666_BPS 28000_BPS 62666_BPS 9333_BPS 30666_BPS 600_BPS (continued)	1-54

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
127	USR-Final-Rx-Link-Data-Rate (continued)	32000_BPS 33333_BPS 34666_BPS 36000_BPS 37333_BPS 38666_BPS 40000_BPS 41333_BPS 42666_BPS 44000_BPS 1200_BPS 45333_BPS 46666_BPS 48000_BPS 49333_BPS 50666_BPS 52000_BPS 53333_BPS 54666_BPS 56000_BPS 57333_BPS 2400_BPS 58666_BPS 60000_BPS 61333_BPS 64000_BPS 800_BPS 7200_BPS 9600_BPS 12K_BPS	

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
128	USR-Initial-Rx-Link-Data-Rate	ENUM: 110_BPS 14.4K_BPS 16.8_BPS 19.2K_BPS 38.4K_BPS 75_BPS 450_BPS UNKNOWN_BPS 57.6K_BPS 21.6K_BPS 24K_BPS 300_BPS 26K_BPS 28K_BPS 115K_BPS 31K_BPS 33K_BPS 25333_BPS 26666_BPS	1-54
128	USR-Initial-Rx-Link-Data-Rate	28000_BPS 29333_BPS 30666_BPS 600_BPS 32000_BPS 33333_BPS 34666_BPS 36000_BPS 37333_BPS 38666_BPS 40000_BPS 41333_BPS 42666_BPS 44000_BPS 1200_BPS 45333_BPS 46666_BPS 48000_BPS 49333_BPS 50666_BPS 52000_BPS 53333_BPS	

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
128	USR-Initial-Rx-Link-Data-Rate	54666_BPS 56000_BPS 57333_BPS 2400_XBPS 58666_BPS 60000_BPS 61333_BPS 62666_BPS 64000_BPS 4800_BPS 7200_BPS 9600_BPS 12K_BPS	
129	USR-Event-Date-Time	UINT32	0-0
130	USR-Chassis-Temperature	UINT32	0-0
131	USR-Actual-Voltage	UINT32	0-0
132	USR-Expected-Voltage	UINT32	0-0
133	USR-Power-Supply-Number	UINT32	0-0
134	USR-Channel	UINT32	0-0
135	USR-Chassis-Slot	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
136	USR-Event-Id	ENUM: HUB_Temp_Out_of_Range Fan_Failed Watchdog_Timeout Mgmt_Bus_Failure In_Connection_Est Out_Connection_Est In_Connection_Term Out_Connection_Term Connection_Failed Connection_Timeout DTE_Transmit_Idle DTR_True DTR_False Block_Error_at_Threshold Fallbacks_at_Threshold No_Dial_Tone_Detected No_Loop_Current_Detected Yellow_Alarm Red_Alarm Loss_Of_Signal Rcv_Alrm_Ind_Signal Timing_Source_Switch Modem_Reset_by_DTE Modem_Ring_No_Answer DTE_Ring_No_Answer Pkt_Bus_Session_Active Pkt_Bus_Session_Congestion Pkt_Bus_Session_Lost Pkt_Bus_Session_Inactive User_Interface_Reset Gateway_Port_Out_of_Service Gateway_Port_Link_Active Dial_Out_Login_Failure Dial_In_Login_Failure Dial_Out_Restricted_Number Dial_Back_Restricted_Number User_Blacklisted Attempted_Login_Blacklisted Response_Attempt_Limit_Exceed Login_Attempt_Limit_Exceeded Dial_Out_Call_Duration Dial_In_Call_Duration Pkt_Bus_Session_Err_Status NMC_AutoRespns Trap Acct_Server_Contact_Loss Yellow_Alarm_Clear Red_Alarm_Clear Loss_Of_Signal_Clear (Continued)	

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
136	USR-Event-Id (<i>Continued</i>)	Rcv_Alm_Ind_Signal_Clear Incoming_Connection_Establish Module_Inserted Outgoing_Connection_Establish Incoming_Connection_Terminate Outgoing_Connection_Terminate Connection_Attempt_Failure Continuous_CRC_Alarm Continuous_CRC_Alarm_Clear Physical_State_Change Module_Removed Gateway_Network_Failed Gateway_Network_Restored Packet_Bus_Clock_Lost Packet_Bus_Clock_Restored D_Channel_In_Service D_Channel_Out_of_Service DS0s_In_Service DS0s_Out_of_Service T1/T1PRI/E1PRI_Call_Event PSU_Voltage_Alarm Psu_Incompatible T1,T1-E1/PRI-Call-Arrive-Even T1,T1-E1/PRI-Call-Connect-Eve T1,T1-E1/PRI-Call-Termina-Eve T1,T1-E1/PRI-Call-Failed-Even	6-84
137	USR-Number-of-Rings-Limit	UINT32	0-0
138	USR-Connect-Time-Limit	UINT32	0-0
139	USR-Call-End-Date-Time	UINT32	0-0
140	USR-Call-Start-Date-Time	UINT32	0-0
141	USR-Server-Time	UINT32	0-0
142	USR-Request-Type	ENUM: Access-Request Access-Challenge Status-Server Status-Client Access-Accept Reserved Access-Reject Accounting-Request Accounting-Response Access-Password-Change Access-Password-Ack Access-Password-Reject	1-255
143	USR-Old-Password	String	0-253
144	USR-Expiration	UINT32	0-0

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
145	USR-Prompt	UINT32	0-1
146	USR-Char-Noecho	UINT32	0-0
147	USR-User-Group-Name	String	0-253
148	148 USR-Call-Reference-Number	UINT32	0-253
149	USR-Dial-In-Sec-Mode	UNIT32	0-0
150	USR-Req-Db-Mdm-Sel	UINT32	0-0
151	USR-Req-Db-Login-Valid	UINT32	0-0
152	USR-Dialback-Group-Names	String	0-253
153	USR-Dial-In-Call-Rest	String	0-253
154	USR-Dial-Out-Call-Rest	String	0-253
155	USR-Logins-Before-Blacklist	UINT32	0-0
156	USR-Failed-Logins	UINT32	0-0
157	USR-Allowed-DB-Modems	String	0-253
158	USR-VPN-Encrypter	String	0-253
159	USR-Acct-VPN-Gateway	String	0-253
160	USR-Re-CHAP-Timeout	UINT32	0-0
161	USR-RMMIE-Manufacture-ID	String	0-253
162	USR-RMMIE-Product-Code	String	0-253
163	USR-RMMIE-Serial-Number	String	0-253
164	USR-RMMIE-Firmware-Version	String	0-253
165	USR-RMMIE-Firmware-Build-Date	String	0-253
166	USR-RMMIE-Status	ENUM: notEnabledInLocalModem notDetectedInRemoteModem ok	1-3
170	USR-RMMIE-Last-Update-Time	UINT32	0-253
171	USR-RMMIE-Last-Update-Event	ENUM: None initialConnection retrain speedShift plannedDisconnect	1-5
172	USR-RMMIE-Rcv-Tot-PwrLvl	UNIT32	0-253
173	USR-RMMIE-Rcv-PwrLvl-3300Hz	UNIT32	0-253
174	USR-RMMIE-Rcv-PwrLvl-3750Hz	UNIT32	0-253
175	USR-RMMIE-PwrLvl-NearEcho-Canc	UNIT32	0-253
176	USR-RMMIE-PwrLvl-FarEcho-Canc	UNIT32	0-253
177	USR-RMMIE-PwrLvl-Noise-Lvl	UNIT32	0-253
178	USR-RMMIE-PwrLvl-Xmit-Lvl	UNIT32	0-253

Table A-8 USR VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
179	USR-IPX-SAP	String	0-253
180	USR-MIC	UNIT32	0-253
181	USR-Call-Tracking-ID	UNIT32	0-253
182	USR-Log-Filter-Packet	UNIT32	0-253
183	USR-CCP-Algorithm	UNIT32	0-253
184	USR-ACCM-Type	UNIT32	0-253
185	USR-Connect-Speed	UNIT32	0-253
186	USR-Framed-IP-Address-Pool-Name	UNIT32	0-253
187	USR-MP-EDO	String	0-253
188	USR-Local-Framed-IP-Addr	UNIT32	0-253
189	USR-IP-RIP-Input-Filter	String	0-253
190	USR-IP-Call-Input-Filter	String	0-253
191	USR-IPX-Call-Input-Filter	String	0-253
192	USR-AT-Input-Filter	String	0-253
193	USR-AT-RTMP-Input-Filter	String	0-253
194	USR-AT-Zip-Input-Filter	String	0-253
195	USR-AT-Call-Input-Filter	String	0-253
196	USR-ET-Bridge-Input-Filter	String	0-253
197	USR-IP-RIP-Output-Filter	String	0-253
198	USR-IP-Call-Output-Filter	String	0-253
199	USR-IPX-RIP-Output-Filter	String	0-253
200	USR-IPX-Call-Output-Filter	String	0-253
201	USR-AT-Output-Filter	String	0-253
202	USR-ET-RTMP-Output-Filter	String	0-253
203	USR-AT-Zip-Output-Filter	String	0-253
204	USR-AT-Call-Output-Filter	String	0-253
205	USR-ET-Bridge-Output-Filter	String	0-253
206	USR-ET-Bridge-Call-Output-Filter	String	0-253
207	USR-IP-Default-Route-Option	UINT32	0-253
208	USR-MP-EDO-HIPER	String	0-253
209	USR-MP-MRRU	UINT32	0-253

Telebit VSAs

Table A-9 lists the Telebit VSAs.

Table A-9 Telebit VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	Telebit-Login-Command	String	0-253
2	Telebit-Port-Name	String	0-253
3	Telebit-Activate-Command	String	0-253
4	Telebit-Accounting-Info	String	0-253
5	Telebit-Login-Option	String	0-253

Bay Networks VSAs

Table A-10 Lists the Bay Networks VSAs.

Table A-10 Bay Networks VSAs

SubAttr	VSA Name	Type	Min-Max Value
28	Annex-Filter	String	1-253
29	Annex-CLI-Command	String	1-253
30	Annex-CLI-Filter	String	1-253
31	Annex-Host-Restrict	String	1-253
32	Annex-Host-Allow	String	1-253
33	Annex-Product-Name	String	1-253
34	Annex-SW-Version	String	1-253
35	Annex-Local-IP-Address	IPADDR	1-253
36	Annex-Callback-Portlist	UINT32	0-0
44	Annex-System-Disc-Reason	UINT32	0-0
45	Annex-Modem-Disc-Reason	UINT32	0-0
46	Annex-Disconnect-Reason	UINT32	0-0
50	Annex-Transmit-Speed	UINT32	0-0
51	Annex-Receive-Speed	UINT32	0-0

3GPP2 VSAs

Table A-11 lists the 3GPP2 VSAs.

Table A-11 3GPP2 VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	CDMA-Security-Status	UINT32	0-253
2	CDMA-Security-Level	UINT32	0-253
3	CDMA-Pre-Shared-Secret	String	0-253
4	CDMA-Reverse-Tunnel-Spec	UINT32	0-253
5	CDMA-Diff-Svc-Class-Opt	UINT32	0-253
6	CDMA-Container	String	0-253
9	CDMA-PCF-IP-Addr	IPADDR	0-253
10	CDMA-BS-MS-Addr	String	0-253
11	CDMA-User-ID	UINT32	0-253
12	CDMA-Forward-MUX	UINT32	0-253
13	CDMA-Reverse-MUX	UINT32	0-253
14	CDMA-Forward-Rate	UINT32	0-253
15	CDMA-Reverse-Rate	UINT32	0-253
16	CDMA-Service-Option	UINT32	0-253
17	CDMA-Forward-Type	UINT32	0-253
18	CDMA-Reverse-Type	UINT32	0-253
19	CDMA-Frame-Size	UINT32	0-253
20	CDMA-Forward-RC	UINT32	0-253
21	CDMA-Reverse-RC	UINT32	0-253
22	CDMA-IP-Technology	UINT32	0-253
23	CDMA-Comp-Flag	UINT32	0-253
24	CDMA-Release-Ind	ENUM: Unknown MS-Release PDSN-Release PPP-Timeout Handoff PPP-Failure Unknown-Failuer Time-Of-Day RN-Failure	0-8
25	CDMA-Dropped-Octets	UINT32	0-253
26	CDMA-Start-Date	String	0-253
27	CDMA-Start-Time	String	0-253
28	CDMA-Stop-Date	String	0-253

Table A-11 3GPP2 VSAs

SubAttr	VSA Name	Type	Min-Max Value
29	CDMA-Stop-Time	String	0-253
30	CDMA-Num-Active	UINT32	0-253
31	CDMA-SDB-Input-Octets	UINT32	0-253
32	CDMA-SDB-Output-Octets	UINT32	0-253
33	CDMA-NumSDB-Input	UINT32	0-253
34	CDMA-NumSDB-Output	UINT32	0-253
35	CDMA-Alt-Billing	UINT32	0-253
36	CDMA-IP-QoS	UINT32	0-253
37	CDMA-Interconnect-IP	UINT32	0-253
38	CDMA-Interconnect-QoS	UINT32	0-253
39	CDMA-Air-QoS	UINT32	0-253
40	CDMA-Airlink-Record-Type	UNIT32	0-253
41	CDMA-R-P-Link-ID	UNIT32	0-253
42	CDMA-Airlink-Record-Type	UNIT32	0-253
43	CDMA-PPP-Bytes-Received	UNIT32	0-253
44	CDMA-Correlation-ID	UNIT32	0-253
45	CDMA-Mobile-Terminate-Originated	UNIT32	0-253
48	CDMA-Session-Continue	UNIT32	0-1

ACC VSAs

Table A-12 lists the ACC VSAs.

Table A-12 ACC VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	Acc-Reason-Code	ENUM: no reason given/no failure resource shortage protocol error invalid attribute invalid service type invalid framed protocol invalid attribute value invalid user information invalid IP address invalid integer syntax invalid NAS port	
1	Acc-Reason-Code (<i>Contionued</i>)	ENUM: requested by user session already open network disconnect service interruption physical port error idle timeout session timeout administrative reset NAS reload or reset NAS error NAS request	0-56
1	Acc-Reason-Code (<i>Contionued</i>)	ENUM: undefined reason given too many RADIUS users conflicting attributes port limit exceeded facility not available internal configuration error bad route specification	0-56

Table A-12 ACC VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
1	Acc-Reason-Code (Continued)	Access Partition bind failure security violation request type conflict configuration disallowed missing attribute no authentication server invalid request missing parameter invalid parameter call cleared with cause inopportune config request invalid config parameter missing config parameter incompatible service profile administrative reset	
1	(Continued)	administrative reload no authentication response port unneeded port preempted port suspended service unavailable callback user error host request no accounting server no accounting response access denied temporary buffer shortage	
2	Acc-Ccp-Option	ENUM: Disabled Enabled	1-2
3	Acc-Input-Errors	UINT32	0-253
4	Acc-Output-Errors	UINT32	0-253
5	Acc-Access-Partition	String	0-253
6	Acc-Customer-Id	String	0-253
8	Acc-Ip-Gateway-Sec	IPADDR	0-253
9	Acc-Route-Policy	ENUM : Funnel Direct	1-2
10	Acc-ML-MLX-Admin-State	ENUM: Enabled Disabled	1-2
11	Acc-ML-Call-Threshold	UINT32	0-253
12	Acc-ML-Clear-Threshold	UINT32	0-253
13	Acc-ML-Damping-Factor	UINT32	0-253

Table A-12 ACC VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
14	Acc-Tunnel-Secret	String	0-253
15	Acc-Clearing-Cause	ENUM: cause unspecified unassigned number invalid information element c message incompatible with sta recovery on timer expiration mandatory information element protocol error interworking normal clearing user busy no user responding user alerted no answer	0-127
15	Acc-Clearing-Cause (Continued)	ENUM: no route to transit network call rejected number changed non selected user clearing destination out of order invalid or incomplete number facility rejected no route to destination response to status inquiry normal unspecified cause no circuit or channel availab network out of order	0-127
15	Acc-Clearing-Cause (Continued)	ENUM: temporary failure switching equipment congestio access information discarded circuit or channel unavailabl circuit or channel preempted resources unavailable quality of service unavailabl facility not subscribed outgoing calls barred incoming calls barred bearer capability unauthorize bearer capability not availab	0-127

Table A-12 ACC VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
15	Acc-Clearing-Cause (Continued)	ENUM: channel unacceptable service not available bearer capability not impleme channel type not implemented facility not implemented call awarded being delivered restricted digital informatio service not implemented invalid call reference identified channel does not e call identity does not exist call identity in use no call suspended	0-127
15	Acc-Clearing-Cause (Continued)	ENUM: suspended call cleared incompatible destination invalid transit network selec invalid message mandatory information element message not implemented inopportune message information element not imple	0-127
16	Acc-Clearing-Location	ENUM: local or remote user private network serving local beyond interworking point public network serving local transit network private network serving remot public network serving remote international network	0-10
17	Acc-Service-Profile	String	0-253
18	Acc-Request-Type	ENUM: Ring Indication Dial Request User Authentication Tunnel Authentication User Accounting Tunnel Accounting	1-6
19	Acc-Framed-Bridge	ENUM : Disabled Enabled	0-1
20	Acc-Vpsm-Oversubscribed	ENUM : False True	1-2

Table A-12 ACC VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
21	Acc-Acct-On-Off-Reason	ENUM : NAS Reset NAS Reload Configuration Reset Configuration Reload Enabled Disabled	0-5
22	Acc-Tunnel-Port	UINT32	0-253
24	Acc-Dns-Server-Sec	IPADDR	0-253
26	Acc-Nbns-Server-Sec	IPADDR	0-253
27	Acc-Dial-Port-Index		
28	Acc-Ip-Compression	ENUM: Disabled Enabled	0-1
29	Acc-Ipx-Compression	ENUM: Disabled Enabled	0-1
30	Acc-Connect-Tx-Speed	UINT32	0-253
31	Acc-Connect-Rx-Speed	UINT32	0-253
32	Acc-Modem-Modulation-Type	String	0-253
33	Acc-Modem-Error-Protocol	String	0-253
34	Acc-Callback-Delay	UINT32	0-253
35	Acc-Callback-Num-Valid	String	0-253
36	Acc-Callback-Mode	ENUM: User-Auth User-Specified-E-164 CBCP-Callback CLI-Callback	0-7
37	Acc-Callback-CBCP-Type	ENUM: CBCP-None CBCP-User-Specified CBCP-Pre-Specified	1-3
38	Acc-Dialout-Auth-Mode	ENUM: PAP CHAP CHAP-PAP NONE	1-4
39	Acc-Dialout-Auth-Password	String	0-253
40	Acc-Dialout-Auth-UserName	String	0-253
42	Acc-Access-Community	ENUM: PUBLIC NETMAN	1-2

Table A-12 ACC VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
43	Acc-Vpsm-Reject-Cause	ENUM: No-Access-Partition Access-Partition-Disabled Partition-Portlimit-Exceeded License-Portlimit-Exceeded Home-Server-Down Rejected-By-Home-Server NAS-Administratively-Disabled	1-7
44	Acc-Ace-Token	String	0-253
45	Acc-Ace-Token-Ttl	UINT	0-253
46	Acc-IP-Pool-Name	String	0-253
47	Acc-Igmp-Admin-State	ENUM : Enabled Disabled	1-2
48	Acc-Igmp-Version	ENUM : V1 V2	1-2

Altiga VSAs

Table A-13 lists the Altiga VSAs.

Table A-13 Altiga VSAs

SubAttr	VSA Name	Type	Min-Max Value
1	Altiga-General-Access-Hours	String	0-253
2	Altiga-General-Simultaneous-Logic	UINT32	0-253
3	Altiga-General-Minimum-Password-	UINT32	0-253
4	Altiga-General-All-Alphabetic-On	ENUM	0-1
6	Altiga-General-Secondary-DNS	IP Address	0-253
8	Altiga-General-Secondary-WINS	IP Address	0-253
9	Altiga-General-SEP-Card-Assignment	UINT32	0-253
10	Altiga-General-Priority-On-SEP	UINT32	0-253
11	Altiga-General-Tunneling-Protoco	UNIT32	0-253
12	Altiga-IPSec-Security-Associatio	String	0-253
13	Altiga-IPSec-Authentication	ENUM: None RADIUS LDAP NT Domain SDI Internal	0-5

Table A-13 Altiga VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
15	Altiga-IPSec-Banner	String	0-253
16	Altiga-IPSec-Allow-Password-Stor	ENUM: False True	0-1
17	Altiga-PPTP-L2TP-Use-Client-Spec	ENUM: False True	0-1
18	Altiga-PPTP-Minimal-Authentication	UINT32	0-253
19	Altiga-L2TP-Minimal-Authentication	UINT32	0-253
20	Altiga-PPTP-Encryption	UINT32	0-253
21	Altiga-L2TP-Encryption	UINT32	0-253
22	Altiga-Argument-Authentication-	ENUM: First Active Server RADIUS LDAP NT SDI Internal	0-5
23	Altiga-Argument-Authentication-	String	0-253
24	Altiga-Argument-Request-Authenti	String	0-253
25	Altiga-IPSec-LTL-Keepalives	ENUM: False True	0-1
26	Altiga-Argument-IPSec-Group-Name	String	0-253
27	Altiga-IPSec-Split-Tunneling	String	0-253
28	Altiga-IPSec-Default-Domain	String	0-253
28	Altiga-IPSec-Secondary-Domain-List	String	0-253
30	Altiga-IPSec-Tunnel-Type	ENUM: LAN to LAN Remote Access	1-2
31	Altiga-IPSec-Mode-Configuration	ENUM: False True	0-1
32	Altiga-Argument-Authentication-	UINT32	0-253
33	Altiga-IPSec-Group-Lock-Of-User	ENUM: False True	0-1
34	Altiga-IPSec-IPSec-Over-UDP	ENUM: False True	0-1
35	Altiga-IPSec-UDP-Port-For-IPSec	UINT32	0-253
129	Altiga-Partitioning-Secondary-DHCP	IP Address	0-253

Table A-13 Altiga VSAs (continued)

SubAttr	VSA Name	Type	Min-Max Value
131	Altiga-Partitioning-Premise-Rout	IP Address	0-253
133	Altiga-Partitioning-Mobile-IP-Ke	String	0-253
134	Altiga-Partitioning-Mobile-IP-Address	IP Address	0-253
136	Altiga-Partitioning-Strip-Realm	ENUM: False True	0-1
137	Altiga-Partitioning-Group-ID	UINT32	0-253
250	Altiga-Group-Name	String	0-253