



## CHAPTER 8

# License Manager Class Constructor

---

This chapter provides information about the License Manager Class Constructor.

## new

### Synopsis

```
new([callback_port])
```

### Description

The input parameter *callback\_port* is optional. If no value is specified for *callback\_port*, TCP/IP port 1198 is used for client-side callback function to receive results of asynchronous calls. If port 1198 is not available, the next available port in the range from 1198 to 1297 is used.

If the input parameter *callback\_port* is specified, it is used for the client-side callback function to receive results of asynchronous calls. If port *callback\_port* is not available, the next available port from *callback\_port* and (*callback\_port* + 99) is used.

### Input Parameters

Parameter	Type	Range	Description
<i>callback_port</i>	Integer, optional	Range from 1024 to 65535	The port on which the client-side callback function receives results of asynchronous calls.

### Return

None.

### Error and Exception

If a system error prevents the operation from completing, a `RemoteException` is thrown.

new