



H Commands

This chapter describes the Cisco NX-OS PIM commands that begin with H.

Review Draft -- Cisco Confidential

hardware profile multicast max-limit

To set the maximum number of entries in the multicast routing table, use the **hardware profile multicast max-limit** command.

hardware profile multicast max-limit *max-entries*

Syntax Description	<i>max-entries</i>	Maximum number of entries in the multicast routing table. The range is from 0 to 16000.
--------------------	--------------------	---

Command Default	None
-----------------	------

Command Modes	Global configuration mode
---------------	---------------------------

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples	This example shows how to set the maximum number of entries in the multicast routing table to 3000: <pre>switch(config)# hardware profile multicast max-limit 3000 Warning!!: The multicast and /32 unicast route limits have been changed. Any route exceeding the limit may get dropped. switch(config)#</pre>
----------	---

Related Commands	Command	Description
	show hardware profile status	Displays information about the multicast routing table limits.