



P Commands

This chapter describes the Cisco NX-OS Border Gateway Protocol (BGP) commands that begin with P.

Review Draft -- Cisco Confidential

password (BGP)

To configure Border Gateway Protocol (BGP) to use MD5 authentication, use the **password** command. To disable this function, use the **no** form of this command.

password [*auth-key string* | *string*]

no password [*auth-key string* | *string*]

Syntax Description	<i>auth-key</i> (Optional) MD5 authentication key. You can enter an unencrypted (cleartext) key, or one of these values followed by a space and the MD5 authentication key: 0—Specifies an unencrypted (cleartext) key 3—Specifies a 3-DES encrypted key 7—Specifies a Cisco Type 7 encrypted key The key can be from 1 to 16 characters. <i>string</i> (Optional) Neighbor password.				
Command Default	None				
Command Modes	BGP neighbor configuration mode				
Command History	<table> <tr> <th>Release</th><th>Modification</th></tr> <tr> <td>6.0(2)N1(1)</td><td>This command was introduced.</td></tr> </table>	Release	Modification	6.0(2)N1(1)	This command was introduced.
Release	Modification				
6.0(2)N1(1)	This command was introduced.				
Usage Guidelines	This command requires the LAN Enterprise Services license.				
Examples	This example shows how to enable an unencrypted key for a BGP neighbor: <pre>switch(config)# router bgp 101 switch(config-router)# neighbor 192.0.2.1 remote-as 1.2 switch(config-route-neighbor)# password 0 myauthkey switch(config-route-neighbor)#</pre> This example shows how to disable an unencrypted authentication key for a BGP neighbor: <pre>switch(config)# router bgp 101 switch(config-router)# neighbor 192.0.2.1 remote-as 1.2 switch(config-route-neighbor)# no password 0 myauthkey switch(config-route-neighbor)#</pre>				

Review Draft -- Cisco Confidential**Related Commands**

Command	Description
show ip bgp	Displays information about BGP routes.

Review Draft -- Cisco Confidential