



Recommended Cisco ATA Tone Parameter Values by Country

This section provides tables of recommended tone parameters for the followings countries, listed alphabetically:



Note

The extended tone format used by some countries is available only with Cisco ATA software version 3.0 or later. For more information about tone parameter syntax and formats, see the [“Tone Configuration Parameters”](#) section on page 5-26.



Note

The *SIT*Tone parameter applies only to the SIP protocol

- [Argentina](#)
- [Australia](#)
- [Austria](#)
- [Belgium](#)
- [Brazil](#)
- [Canada](#)
- [China](#)
- [Columbia](#)
- [Czech Republic](#)
- [Denmark](#)
- [Egypt](#)
- [Finland](#)
- [France](#)
- [Germany](#)
- [Greece](#)
- [Hong Kong](#)
- [Hungary](#)
- [Iceland](#)

- India
- Indonesia
- Ireland
- Israel
- Italy
- Japan
- Korea
- Luxembourg
- Malaysia
- Mexico
- Netherlands
- New Zealand
- Norway
- Pakistan
- Panama
- Peru
- Philippines
- Poland
- Portugal
- Russia
- Saudi Arabia
- Singapore
- Slovakia
- Slovenia
- South Africa
- Spain
- Sweden
- Switzerland
- Taiwan
- Thailand
- Turkey
- United Kingdom
- United States
- Venezuela

Table E-1 Argentina

| Parameter | Recommended Values |
|--------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2400,1600,0 |
| ReorderTone | 1,30958,0,1757,0,0,2400,3200,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2400,1600,0 |

Table E-2 Australia

| Parameter | Recommended Values |
|--------------|--|
| DialTone | 2,31163,30958,1477,1566,1,0,0,0 |
| BusyTone | 1,30958,0,2212,0,0,3000,3000,0 |
| ReorderTone | 1,31163,0,2086,0,0,3000,3000,0 |
| RingbackTone | 102,31163,1477,30742,1654,2,3200,1600,3200,16000,0 |
| SITtone | 1,30958,0,2212,0,0,20000,4000,0 |

Table E-3 Austria

| Parameter | Recommended Values |
|--------------|---|
| DialTone | 1,31000,0,3089,0,1,0,0,0 |
| BusyTone | 1,31000,0,1737,0,0,3200,3200,0 |
| ReorderTone | 1,31000,0,1737,0,0,1600,1600,0 |
| RingbackTone | 1,31000,0,1949,0,0,8000,40000,0 |
| SITtone | 101,3,24062,3640,14876,4778,5126,5297,3,2664,0,2664,0,2664,8000,0,0 |

Table E-4 Belgium

| Parameter | Recommended Values |
|--------------|---------------------------------|
| DialTone | 1,30958,0,4952,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,1336,1336,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,24000,0 |
| SITtone | 1,30958,0,1757,0,0,1336,1336,0 |

Table E-5 Brazil

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 100,1,30958,1757,0,0,0,2,6000,2000,2000,2000,0,0,0,0 |

Table E-6 Canada

| Parameter | Recommended Values |
|------------------|---------------------------------------|
| DialTone | 2,31537,30830,1490,1859,1,0,0,0 |
| BusyTone | 2,30466,28958,1246,1583,0,4000,4000,0 |
| ReorderTone | 2,30466,28958,1246,1583,0,2000,2000,0 |
| RingbackTone | 2,30830,30466,793,862,0,8000,24000,0 |
| SITtone | 2,30466,28958,1246,1583,0,2000,2000,0 |

Table E-7 China

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30742,0,5870,0,1,0,0,0 |
| BusyTone | 1,30742,0,5870,0,0,2800,2800,0 |
| ReorderTone | 1,30742,0,5870,0,0,5600,5600,0 |
| RingbackTone | 1,30742,0,5870,0,0,8000,32000,0 |
| SITtone | 100,1,30742,1856,0,0,0,2,800,800,3200,3200,0,0,2,0 |

Table E-8 Columbia

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-9 Czech Republic

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2664,2664,0 |
| ReorderTone | 1,30958,0,1757,0,0,1336,1336,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,1336,1336,0 |

Table E-10 Denmark

| Parameter | Recommended Values |
|------------------|---|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1757,0,0,8000,32000,0 |
| SITtone | 101,3,24062,3640,14876,4778,5126,5297,3,2664,0,2664,0,2664,8000,0,0 |

Table E-11 Egypt

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 2,31356,30513,1102,1384,0,8000,32000,0 |
| ReorderTone | 1,30742,0,1856,0,0,4000,4000,0 |
| RingbackTone | 2,31356,31356,1237,1237,0,16000,8000,0 |
| SITtone | 1,30742,0,1856,0,0,4000,4000,0 |

Table E-12 Finland

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,4952,0,1,0,0,0 |
| BusyTone | 1,30958,0,4952,0,0,2400,2400,0 |
| ReorderTone | 1,30958,0,5556,0,0,1600,2000,0 |
| RingbackTone | 1,30958,0,9545,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,1600,1600,0 |

Table E-13 France

| Parameter | Recommended Values |
|------------------|----------------------------------|
| DialTone | 1,30830,0,3231,0,1,0,0,0 |
| BusyTone | 1,30830,0,1817,0,0,4000,4000,0 |
| ReorderTone | 1,30830,0,1817,0,0,4000,4000,0 |
| RingbackTone | 1,30830,0,2038,0,0,12000,28000,0 |
| SITtone | 1,30830,0,1817,0,0,4000,4000,0 |

Table E-14 Germany

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,3840,3840,0 |
| ReorderTone | 1,30958,0,1757,0,0,1920,1920,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,1920,1920,0 |

Table E-15 Greece

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 101,30958,3587,0,0,2,1600,2400,5600,6400,0 |
| BusyTone | 1,30958,0,1757,0,0,2400,2400,0 |
| ReorderTone | 1,30958,0,1757,0,0,2400,2400,0 |
| RingbackTone | 1,30958,0,3426,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2400,2400,0 |

Table E-16 Hong Kong

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 2,31537,30830,1833,2287,1,0,0,0 |
| BusyTone | 2,30466,28958,2215,2816,0,4000,4000,0 |
| ReorderTone | 2,30466,28958,2215,2816,0,2000,2000,0 |
| RingbackTone | 102,30830,2038,30466,2215,2,3200,1600,3200,24000,0 |
| SITtone | 2,30466,28958,1398,1777,1,0,0,0 |

Table E-17 Hungary

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3197,0,1,0,0,0 |
| BusyTone | 1,30958,0,1737,0,0,2400,2400,0 |
| ReorderTone | 1,30958,0,1737,0,0,2400,2400,0 |
| RingbackTone | 1,30958,0,1927,0,0,9600,29600,0 |
| SITtone | 1,30958,0,1737,0,0,2400,2400,0 |

Table E-18 Iceland

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,9600,37600,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-19 India

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 2,31356,30958,5336,6023,1,0,0,0 |
| BusyTone | 1,31163,0,9003,0,0,6000,6000,0 |
| ReorderTone | 1,31163,0,1657,0,0,2000,4000,0 |
| RingbackTone | 102,31356,3485,30958,3934,2,3200,1600,3200,16000,0 |
| SITtone | 1,31163,0,1657,0,0,20000,4000,0 |

Table E-20 Indonesia

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,20000,4000,0 |

Table E-21 Ireland

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30958,0,7582,0,1,0,0,0 |
| BusyTone | 1,30958,0,6758,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,48000,8000,0 |
| RingbackTone | 102,31163,3194,30742,3578,2,3200,1600,3200,16000,0 |
| SITtone | 1,30958,0,1757,0,0,48000,8000,0 |

Table E-22 Israel

| Parameter | Recommended Values |
|------------------|---|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,31163,0,1859,0,0,8000,24000,0 |
| SITtone | 101,3,23620,3717,14876,4778,5126,5297,3,2664,0,2664,0,2664,8000,0,0 |

Table E-23 Italy

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 101,30958,3125,0,0,2,1600,1600,4800,8000,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,1600,1600,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,4000,4000,0 |

Table E-24 Japan

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,31163,0,1657,0,1,0,0,0 |
| BusyTone | 1,31163,0,1859,0,0,4000,4000,0 |
| ReorderTone | 1,31163,0,1859,0,0,4000,4000,0 |
| RingbackTone | 2,31318,31000,1769,1949,0,8000,16000,0 |
| SITtone | 1,31163,0,1859,0,0,4000,4000,0 |

Table E-25 Korea

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 2,31537,30830,1833,2287,1,0,0,0 |
| BusyTone | 2,30466,28958,1398,1777,0,4000,4000,0 |
| ReorderTone | 2,30466,28958,1398,1777,0,2400,1600,0 |
| RingbackTone | 2,30830,30466,1443,1568,0,8000,16000,0 |
| SITtone | 100,1,30742,1856,0,0,0,0,2,1600,800,1600,12000,0,0,0,0 |

Table E-26 Luxembourg

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-27 Malaysia

| Parameter | Recommended Values |
|------------------|---|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,3840,3840,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 101,30958,1971,0,0,2,3200,1600,3200,16000,0 |
| SITtone | 1,30958,0,1757,0,0,20000,4000,0 |

Table E-28 Mexico

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-29 Netherlands

| Parameter | Recommended Values |
|--------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,4839,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-30 New Zealand

| Parameter | Recommended Values |
|--------------|---|
| DialTone | 1,31163,0,3307,0,1,0,0,0 |
| BusyTone | 1,31163,0,1657,0,0,4000,4000,0 |
| ReorderTone | 1,24916,0,3483,0,0,4000,4000,0 |
| RingbackTone | 102,31163,1316,30742,1474,2,3200,1600,3200,16000,0 |
| SITtone | 100,1,31163,1657,0,0,0,2,6000,800,6000,3200,0,0,2,0 |

Table E-31 Norway

| Parameter | Recommended Values |
|--------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,3053,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-32 Pakistan

| Parameter | Recommended Values |
|--------------|---------------------------------|
| DialTone | 1,31163,0,2947,0,1,0,0,0 |
| BusyTone | 1,31163,0,1657,0,0,6000,6000,0 |
| ReorderTone | 1,31163,0,1657,0,0,6000,6000,0 |
| RingbackTone | 1,30742,0,2083,0,0,8000,32000,0 |
| SITtone | 1,31163,0,1657,0,0,6000,6000,0 |

Table E-33 Panama

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2560,37200,0 |
| ReorderTone | 1,30958,0,1757,0,0,2560,37200,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,37200,0 |
| SITtone | 100,1,30958,3125,0,0,0,0,2,1440,1440,4000,1440,0,0,0,0 |

Table E-34 Peru

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

Table E-35 Phillipines

| Parameter | Recommended Values |
|------------------|---------------------------------------|
| DialTone | 1,30958,0,3125,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 2,30466,28958,1398,1777,0,2000,2000,0 |
| RingbackTone | 1,30742,0,2083,0,0,8000,32000,0 |
| SITtone | 2,30466,27666,1398,2034,0,2000,2000,0 |

Table E-36 Poland

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3889,0,1,0,0,0 |
| BusyTone | 1,30958,0,5368,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1697,0,0,4000,4000,0 |
| RingbackTone | 1,30742,0,8010,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1697,0,0,4000,4000,0 |

Table E-37 Portugal

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3889,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,1600,1600,0 |
| RingbackTone | 1,30742,0,2083,0,0,8000,40000,0 |
| SITtone | 1,30958,0,1757,0,0,1600,1600,0 |

Table E-38 Russia

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3889,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,3200,3200,0 |
| ReorderTone | 1,30958,0,1757,0,0,1600,1600,0 |
| RingbackTone | 1,30742,0,2083,0,0,6400,25600,0 |
| SITtone | 1,30958,0,1757,0,0,1600,1600,0 |

Table E-39 Saudi Arabia

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3889,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,4000,4000,0 |
| RingbackTone | 1,30958,0,1971,0,0,9600,36800,0 |
| SITtone | 1,30958,0,1757,0,0,4000,4000,0 |

Table E-40 Singapore

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30958,0,3506,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,6000,6000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 102,31163,3710,30742,4156,2,3200,1600,3200,16000,0 |
| SITtone | 1,30958,0,1757,0,0,20000,4000,0 |

Table E-41 Slovakia

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3889,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2640,2640,0 |
| ReorderTone | 1,30958,0,1757,0,0,1320,1320,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,1320,1320,0 |

Table E-42 Slovenia

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 101,30958,3125,0,0,2,1600,2400,5600,6400,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,1600,1600,0 |
| RingbackTone | 1,30958,0,1971,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,1600,1600,0 |

Table E-43 South Africa

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 2,31415,30890,1919,2252,1,0,0,0 |
| BusyTone | 1,31163,0,1657,0,0,4000,4000,0 |
| ReorderTone | 1,31163,0,1657,0,0,2000,2000,0 |
| RingbackTone | 102,31415,1079,30890,1266,2,3200,1600,3200,16000,0 |
| SITtone | 1,31163,0,1657,0,0,2000,4000,0 |

Table E-44 Spain

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30958,0,4895,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,1600,1600,0 |
| ReorderTone | 100,1,30958,1757,0,0,0,2,1600,1600,1600,4800,0,0,1,0 |
| RingbackTone | 1,30958,0,1757,0,0,12000,24000,0 |
| SITtone | 100,1,30958,1757,0,0,0,2,1600,1600,1600,4800,0,0,0,0 |

Table E-45 Sweden

| Parameter | Recommended Values |
|------------------|---|
| DialTone | 1,30958,0,3889,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,6000,0 |
| RingbackTone | 1,30958,0,1927,0,0,8000,40000,0 |
| SITtone | 101,3,24062,3640,14876,4778,5126,5297,3,2664,0,2664,0,2664,8000,0,0 |
| CallWaitTone | 1,30958,0,1757,0,0,1600,4000,11200 |
| AlertTone | 1,30467,0,4385,0,0,480,480,1920 |

Table E-46 Switzerland

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3506,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,4000,4000,0 |
| ReorderTone | 1,30958,0,1757,0,0,1600,1600,0 |
| RingbackTone | 1,30958,0,1927,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,1600,1600,0 |

Table E-47 Taiwan

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 2,31537,30830,1833,2287,1,0,0,0 |
| BusyTone | 2,30466,28958,1398,1777,0,4000,4000,0 |
| ReorderTone | 2,30466,28958,1398,1777,0,2000,2000,0 |
| RingbackTone | 102,30830,1443,30466,1568,2,3200,1600,3200,16000,0 |
| SITtone | 2,30466,28958,1398,1777,0,2000,2000,0 |

Table E-48 Thailand

| Parameter | Recommended Values |
|------------------|---|
| DialTone | 1,31163,0,2947,0,1,0,0,0 |
| BusyTone | 1,31163,0,1657,0,0,4000,4000,0 |
| ReorderTone | 1,30742,0,1856,0,0,2640,2640,0 |
| RingbackTone | 1,31163,0,1657,0,0,8000,32000,0 |
| SITtone | 100,1,31163,1657,0,0,0,2,800,7200,2400,5600,0,0,5,0 |

Table E-49 Turkey

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 1,30742,0,3301,0,1,0,0,0 |
| BusyTone | 1,30742,0,1856,0,0,4000,4000,0 |
| ReorderTone | 100,1,30742,1856,0,0,0,0,2,1600,1600,4800,1600,0,0,2,0 |
| RingbackTone | 1,30742,0,2083,0,0,16000,32000,0 |
| SITtone | 1,30742,0,1856,0,0,1600,1600,0 |

Table E-50 United Kingdom

| Parameter | Recommended Values |
|------------------|--|
| DialTone | 2,31537,30830,1833,2287,1,0,0,0 |
| BusyTone | 1,31163,0,1657,0,0,3000,3000,0 |
| ReorderTone | 100,1,31163,1657,0,0,0,0,2,3200,2800,1800,4200,0,0,0,0 |
| RingbackTone | 102,31163,1173,30742,1314,2,3200,1600,3200,16000,0 |
| SITtone | 1,31163,0,2947,0,1,0,0,0 |

Table E-51 United States

| Parameter | Recommended Values |
|------------------|---------------------------------------|
| DialTone | 2,31537,30830,1490,1859,1,0,0,0 |
| BusyTone | 2,30466,28958,1246,1583,0,4000,4000,0 |
| ReorderTone | 2,30466,28958,1246,1583,0,2000,2000,0 |
| RingbackTone | 2,30830,30466,793,862,0,8000,24000,0 |
| SITtone | 2,30466,28958,1246,1583,0,2000,2000,0 |

Table E-52 Venezuela

| Parameter | Recommended Values |
|------------------|---------------------------------|
| DialTone | 1,30958,0,3506,0,1,0,0,0 |
| BusyTone | 1,30958,0,1757,0,0,2000,2000,0 |
| ReorderTone | 1,30958,0,1757,0,0,2000,2000,0 |
| RingbackTone | 1,30958,0,1757,0,0,8000,32000,0 |
| SITtone | 1,30958,0,1757,0,0,2000,2000,0 |

