



Route List Configuration

Route groups consisting of a list of resources (gateways) make up route lists. A route list associates a set of route groups with a route pattern and determines the order in which those route groups are accessed. The order controls the progress of the search for available trunk devices for outgoing calls.

A route list comprises a collection of resources (gateways, route groups) that route calls that match the defined route pattern. Once the Cisco CallManager determines a call that is to be routed through a defined route list, the Cisco CallManager finds the first available device based on the order of the route group(s) defined in a route list. Each route list should have at least one route group. Within each route group, at least one device, such as a gateway, is available. Cisco CallManager can select some, or all, ports as resources in each route group based on device type. Some devices, such as digital access, only allow you to select all ports.

Each route list can contain the same route groups that other route lists have already selected.

Use the following topics to add or remove route lists or to add, remove, or change the order of route groups in a route list:

- [Finding Route Lists, page 16-2](#)
- [Adding a Route List, page 16-3](#)
- [Adding Route Groups to a Route List, page 16-4](#)
- [Removing Route Groups from a Route List, page 16-6](#)
- [Changing the Order of Route Groups in a Route List, page 16-7](#)
- [Deleting a Route List, page 16-8](#)

Finding Route Lists

Because you might have several route filters in your network, Cisco CallManager lets you locate specific route filters based on specific criteria. Use the following procedure to locate route filters.

Procedure

Step 1 Choose **Route Plan > Route List**.

The Find and List Route Lists pane displays.

Step 2 From the drop-down list box, choose one of the following criteria:

- begins with
- contains
- ends with
- is exactly

Step 3 Specify the appropriate search text, if applicable and click **Find**. You can also specify how many items per page to display.



Note To find all route lists registered in the database, click **Find** without entering any search text.

A list of discovered route lists displays by:

- Route list name
- Description



Note You can delete multiple route lists from the Find and List Route Lists pane by checking the check boxes next to the appropriate route lists and clicking **Delete Selected**. You can delete all of the route lists on the pane by checking the check box in the matching records title bar and clicking **Delete Selected**.

- Step 4** Click the route list from the list of records that matches your search criteria. The pane displays the route list you choose.
-

Related Topics

- [Adding a Route List, page 16-3](#)
- [Adding Route Groups to a Route List, page 16-4](#)
- [Removing Route Groups from a Route List, page 16-6](#)
- [Changing the Order of Route Groups in a Route List, page 16-7](#)
- [Deleting a Route List, page 16-8](#)

Adding a Route List

The following procedure describes how to add a route list.

Procedure

- Step 1** Choose **Route Plan > Route List** in the menu bar.
- Step 2** Click **Add a New Route List**.
- Step 3** Enter a name in the Route List Name field. The name can comprise up to 50 alphanumeric characters and can contain any combination of spaces, periods (.), hyphens (-), and underscore characters (_). Ensure each route list name is unique to the route plan.



Timesaver

Use concise and descriptive names for your route lists. The CompanynameLocationCalltype format usually provides a sufficient level of detail and is short enough to enable you to quickly and easily identify a route list. For example, CiscoDallasMetro identifies a route list for toll-free, inter-local access transport area (LATA) calls from the Cisco office in Dallas.

Cisco CallManager automatically inserts a description in the Description field. You can, however, edit this field.

- Step 4** Click **Insert** to add this route list.
- Step 5** To add a route group to this list, click **Add Route Group** and perform Steps 4 through 8 of the “Adding Route Groups to a Route List” section on page 16-4 .



Note For called party and calling party transformation information, you can click on the **Route Details for Route Groups** link on the left side of the pane. This takes you to the Route Details Configuration pane.

Related Topics

- [Finding Route Lists, page 16-2](#)
- [Adding Route Groups to a Route List, page 16-4](#)
- [Changing the Order of Route Groups in a Route List, page 16-7](#)
- [Removing Route Groups from a Route List, page 16-6](#)
- [Deleting a Route List, page 16-8](#)
- [Understanding Route Plans, Cisco CallManager System Guide](#)

Adding Route Groups to a Route List

You can add route groups to a new route list or to an existing route list. The following procedure describes adding a route group to an existing route list.

Before You Begin

You must build one or more route groups and add a route list before performing this procedure.

Procedure

- Step 1** Choose **Route Plan > Route List** in the menu bar.
- Step 2** Locate the route list to which you want to add a route group. See the “[Finding Route Lists](#)” section on page 16-2.
- Step 3** Click **Add Route Group**.

Step 4 From the Select Route Group drop-down list box, choose a route group to add to the list.

Step 5 Click **Add**.

Step 6 If you need to manipulate the calling party number on calls routed through this route group, set up the calling party transformations in the appropriate fields.



Note For more information on calling party transform, see [“Calling Party Transformations Settings” section on page 20-19](#).

Step 7 If you need to manipulate the dialed digits on calls routed through this route group, set up the called party transformations in the appropriate fields.



Note For more information on calling party transform, see [“Called Party Transformations Settings” section on page 20-21](#).

Step 8 Click **Insert** to add the route group.

The route details information appears in the Route Details for Route Groups list on the left side of the pane.

Step 9 To add more route groups to this list, click **Add Route Group to the Current Route List** and repeat Steps 4 through 8.

Related Topics

- [Adding a Route List, page 16-3](#)
- [Removing Route Groups from a Route List, page 16-6](#)
- [Changing the Order of Route Groups in a Route List, page 16-7](#)
- [Deleting a Route List, page 16-8](#)
- [Understanding Route Plans, Cisco CallManager System Guide](#)

Removing Route Groups from a Route List

You can remove route groups from a new route list or from an existing route list. The following procedure describes removing a route group from an existing route list.

Procedure

- Step 1** Choose **Route Plan > Route List** in the menu bar.
- Step 2** Locate the route list from which you want to remove a route group. See the [“Finding Route Lists”](#) section on page 16-2.
- Step 3** From the Selected Route Groups list, choose one or more route group names.



Note To select multiple route groups from the list, press the **Shift** key and click on the desired route groups.

- Step 4** Click **Remove Route Groups**.
- A dialog box appears warning you that you cannot undo removing route groups from a route list.
- Step 5** Click **OK** to remove the route group or click **Cancel** to cancel the action. If you click **OK**, when the pane refreshes, the route group no longer appears in the route list, and the message “Status: Update Completed” displays.
-

Related Topics

- [Finding Route Lists](#), page 16-2
- [Adding a Route List](#), page 16-3
- [Adding Route Groups to a Route List](#), page 16-4
- [Changing the Order of Route Groups in a Route List](#), page 16-7
- [Deleting a Route List](#), page 16-8
- [Understanding Route Plans](#), *Cisco CallManager System Guide*

Changing the Order of Route Groups in a Route List

Cisco CallManager accesses route groups in the order in which they appear in the route list. The following procedure allows you to change the access order of route groups.

Procedure

- Step 1** Choose **Route Plan > Route List** in the menu bar.
- Step 2** Locate the route list in which you want to change the order of a route group. See the [Finding Route Lists, page 16-2](#).
- Step 3** From the Selected Route Groups list, choose a route group name.
- Step 4** Click the up or down arrows on the right side of the list box to move the route group up or down in the list.
- Step 5** Click **Update**.



Note For called party and calling party transformation information, you can click on the **Route Details for ...** link in the Route Details for Route Groups list. This takes you to the Route Details Configuration pane.

Related Topics

- [Finding Route Lists, page 16-2](#)
- [Adding a Route List, page 16-3](#)
- [Adding Route Groups to a Route List, page 16-4](#)
- [Removing Route Groups from a Route List, page 16-6](#)
- [Deleting a Route List, page 16-8](#)
- [Understanding Route Plans, Cisco CallManager System Guide](#)

Deleting a Route List

Cisco CallManager associates route lists with both route groups and route patterns; however, deletion of route groups and route patterns does not occur when the route list is deleted.

The following procedure describes how to delete a route list.

Procedure

-
- Step 1** Choose **Route Plan > Route List** in the menu bar.
- Step 2** Locate the route list you want to delete. See the [“Finding Route Lists” section on page 16-2](#).
- Step 3** Click **Delete**.
- A dialog box appears warning you that you cannot undo removing a route list.
- Step 4** Click **OK** to remove the route list or click **Cancel** to cancel the action.



Caution

A route list cannot be deleted if it is associated with one or more route patterns.

Related Topics

- [Finding Route Lists, page 16-2](#)
- [Adding a Route List, page 16-3](#)
- [Adding Route Groups to a Route List, page 16-4](#)
- [Changing the Order of Route Groups in a Route List, page 16-7](#)
- [Removing Route Groups from a Route List, page 16-6](#)
- [Understanding Route Plans, *Cisco CallManager System Guide*](#)