



## CHAPTER 23

# Unity Server

---

Use Cisco Unity Server settings to configure settings that are related to Cisco Unity. You can use this window to search for specific servers and change individual settings.

## Finding a Cisco Unity Server

Because you might have several Cisco Unity Servers in your network, Cisco Unified Presence lets you locate specific Cisco Unity servers on the basis of specific criteria.

Use the following procedure to locate specific Cisco Unity servers.



### Note

During your work in a browser session, the cookies on the client machine store your find/list search preferences. If you navigate to other menu items and return to this menu item, or if you close the browser and then open a new browser window, the system retains your Cisco Unified Presence search preferences until you modify your search.

---

### Procedure

---

**Step 1** Choose **Application > Cisco Unified Personal Communicator > Unity Server**.

The Find and List Unity Hosts window displays. Records from an active (prior) query may also display in the window.

**Step 2** To find all records in the database, ensure the dialog box is empty; go to [Step 3](#).

To filter or search records

- From the first drop-down list box, choose a search parameter.
- From the second drop-down list box, choose a search pattern.
- Specify the appropriate search text, if applicable.



### Note

To add additional search criteria, click the + button. When you add criteria, the system searches for a record that matches all criteria that you specify. To remove criteria, click the – button to remove the last added criterion or click the **Clear Filter** button to remove all added search criteria.

---

**Step 3** Click **Find**.

All matching records display. You can change the number of items that display on each window by choosing a different value from the Rows per Page drop-down list box.



---

**Note** You can delete multiple records from the database by checking the check boxes next to the appropriate record and clicking **Delete Selected**. You can delete all configurable records for this selection by clicking **Select All** and then clicking **Delete Selected**.

---

**Step 4** From the list of records that display, click the link for the record that you want to view.

---

**Note** To reverse the sort order, click the up or down arrow, if available, in the list header.

---

The window displays the item that you choose.

---

**Additional Information**

See the [“Related Topics” section on page 23-3](#).

## Configuring a Cisco Unity Host

This section describes how to add or update a Cisco Unity host in the Cisco Unified Presence database.

**Procedure****Step 1** Perform one of the following tasks:

- To add a host, choose **Application > Cisco Unified Personal Communicator > Unity Server** and click **Add New**.
- To update a Cisco Unity host, find the host by using the procedure in the [“Finding a Cisco Unity Server” section on page 23-1](#).

The Unity Host Configuration window displays.

**Step 2** Enter the appropriate settings as described in [Table 23-1](#).**Step 3** To save the data and to add the Cisco Unity host to the database, click the **Save** icon that displays in the tool bar in the upper, left corner of the window (or click the **Save button** that displays at the bottom of the window).**Additional Information**

See the [“Related Topics” section on page 23-3](#).

## Cisco Unity Server Configuration Settings

[Table 23-1](#) describes the Unity Server configuration parameters. For related procedures, see the [“Related Topics” section on page 23-3](#).

**Table 23-1** Cisco Unity Server Configuration Parameters

Field	Description
Name	This parameter specifies the name of the Cisco Unity host. Maximum characters: 128
Description	This parameter provides a general description of the Cisco Unity server.
Hostname/IP Address	This parameter specifies the host name or IP Address of the Cisco Unity server.
Port	This parameter specifies the port number that is configured for the Cisco Unity server. Default: 143
Protocol Type	This parameter specifies the protocol to use when contacting the Cisco Unity server. Choose one of the following values: <ul style="list-style-type: none"> <li>• TCP</li> <li>• UDP</li> <li>• TLS</li> <li>• SSL</li> </ul> Default: UDP

## Deleting a Cisco Unity Server

This section describes how to delete a Cisco Unity server.

### Procedure

- 
- Step 1** Find the server by using the procedure in the [“Finding a Cisco Unity Server”](#) section on page 23-1.
- Step 2** From list of matching records, choose the Cisco Unity server that you want to delete.
- Step 3** To delete the Cisco Unity server, click the **Delete Selected Item** icon that displays in the tool bar in the upper, left corner of the window (or click the **Delete Selected** button that displays at the bottom of the window).

If the Cisco Unity server is not in use, Cisco Unified Presence deletes it. If it is in use, a message displays.

---

### Additional Information

See the [“Related Topics”](#) section on page 23-3.

## Related Topics

- [Finding a Cisco Unity Server, page 23-1](#)
- [Configuring a Cisco Unity Host, page 23-2](#)

- [Deleting a Cisco Unity Server, page 23-3](#)