

Cisco 1-Port Channelized OC-12/STM-4 Shared Port Adapter

The Cisco® I-Flex design combines shared port adapters (SPAs) and SPA interface processors (SIPs) using an extensible design that enables service prioritization for voice, video, and data services. Enterprise and service provider customers can use the improved slot economics resulting from modular port adapters that are interchangeable across Cisco routing platforms. The I-Flex design maximizes connectivity options and offers superior service intelligence through programmable interface processors that deliver line-rate performance. I-Flex enhances speed-to-service revenue and provides a rich set of quality-of-service (QoS) features for premium service delivery while effectively reducing the overall cost of ownership. This data sheet contains the specifications for the Cisco 1-Port Channelized OC12/STM-4 SPA (refer to Figure 1).

Figure 1. Cisco 1-Port Channelized OC-12/STM-4 Shared Port Adapter



Product Overview

The Cisco 1-Port Channelized OC-12/STM-4 SPA is available on high-end Cisco routing platforms offering the benefits of network scalability with lower initial costs and ease of upgrades. The Cisco SPA/SIP portfolio continues the Cisco focus on investment protection along with consistent feature support, broad interface availability, and the latest technology. The Cisco SPA/SIP portfolio allows different interfaces (Packet over SONET/SDH [POS], ATM, Ethernet, etc.) to be deployed on the same interface processor.

Applications

Internet traffic continues to grow at an explosive rate – with the number of users doubling each year. This unsurpassed growth is increasing the demand for higher-capacity interfaces from OC-3/STM-1 to OC-48/STM-16. In addition, POS enables efficient transport of IP traffic and uses SONET/SDH concatenated payloads (that is, STS-3c/VC-4, STS-12c/VC-4-4c, or STS-48c/VC-4-16c) to achieve a higher order of statistical multiplexing. At present, concatenated services at VC-4 rates are available only in some parts of the world (for example, Europe), with higher rates not yet readily available. The new Channelized OC-12/STM-4 SPA provides customers in these areas with an STM-4 POS interface that can be provisioned through the traditional network. The Channelized OC12/STM-4 SPA builds on the SONET/SDH channelization capability.

Features at a Glance

- 1-port Channelized OC-12/STM-4 port per SPA
- SONET VT 1.5 mapping: STS-1<>VTG<>VT1.5<>DS1<>
- SONET PDH-DS-3 (M13 and C-bit) mapping: STS-1<>DS3<>DS1<>nxD50
- SDH VC-12 mapping (AU-4<>TUG3<>TUG2<>VC-12<>E1<>nxE0)
- SDH VC-11 mapping (AU-3<>TUG2<>VC-11<>DS1<>nxD50)
- SONET DS-3 mapping: STS-1<>DS3 (clear channel)
- SDH DS-3 mapping: AU-4<>TUG3<>VC-3<>DS3 or AU-3<>VC-3<>DS3
- SDH E3 mapping: AU-4<>TUG3<>VC-3<>E3 or AU-3<>VC-3<>E3
- Bit Error Rate Test (BERT) support for T3/E3 channels
- Channelization support for 4 OC-3 or 12 DS-3 or 336 DS-1 or 2K DS-0 or n x DS-0 channels, or any combination of these
- Multilink bundling on T1/E1 channels as per RFC 1990
- Subrate DS-3
- BERT support for T1/E1 channels

Product Specifications

Table 1 shows the hardware specifications for the Channelized OC-12/STM-4 SPA.

Table 1. Hardware Specifications for the Cisco 1-Port Channelized OC-12 SPA

Features	Descriptions
Product compatibility	Cisco 12000 Routers
Port density per SPA	1-port Channelized OC-12/STM-4
Physical interface (Channelized OC-12)	OC-12c/STM-4 Small Form-Factor Pluggable (SFP) optics module (refer to optical parameters in Table 2) Visual status indicators (LEDs): <ul style="list-style-type: none"> • SPA status LED • Per-port LEDs <ul style="list-style-type: none"> ◦ Carrier and alarm ◦ Active and loopback
Protocols	IETF RFC 1490, Frame Relay Encapsulation RFC 1662, Point-to-Point Protocol (PPP) in High-Level Data Link Control (HDLC)-like framing Cisco HDLC Multilink PPP (RFC 1990) (as applicable for 1-port Channelized OC-12c/STM-4 (DS-1/E1)) FRF.12, link fragmentation and interleaving (LFI) PPP, HDLC, and Frame Relay User Network Interface (UNI) encapsulations

Features	Descriptions
Features and functions	<p>DS-3</p> <ul style="list-style-type: none"> • Full- and half-duplex connectivity at DS-3 rate (44.736 MHz) • Scrambling and subrate support of major data-service-unit (DSU) vendors • C-bit or M23 framing (software selectable) • MDL • Support for 16- and 32-bit cyclic redundancy check (CRC) (16-bit default) • 24-hour history maintained for error statistics and failure counts • DS-3 alarm and event detection (once-per-second polling) • Alarm indication signal (AIS) • Out of frame (OOF) • Far-end receive failure (FERF) <p>DS-1</p> <ul style="list-style-type: none"> • Superframe (SF) and Extended Superframe (ESF) support • ANSI T1.403 FDL support • Internal or line-derived (loop) clocking, independently selectable on each T1 tributary • Error and alarm detection: CRC errors, framing errors, loss of frame (red), AIS (blue), remote alarm indication (yellow) • Alarm reporting: 24-hour history maintained, 15-minute intervals on all errors • BERT at T1 level • Loopback capabilities: local, network line and network payload, remote network line, and remote network payload at the T1 level
SONET errors, alarms, and performance monitoring	<p>Synchronization</p> <ul style="list-style-type: none"> • Local (internal) or loop timed (recovered from network) • Pointer activity monitoring <p>Local (diagnostic) and line (network) loopback</p> <p>Payload mapping</p> <ul style="list-style-type: none"> • POS with 1 + X⁴³ self-synchronous scrambler <p>SONET/SDH compliance</p> <ul style="list-style-type: none"> • Telcordia (Bellcore) GR-253-CORE (as applicable) • ANSI T1.105, T1.231 • ITU-T G.707, G.957, G.825 (as applicable) <p>Supported SONET/SDH alarm and signal events</p> <ul style="list-style-type: none"> • Signal failure bit error rate (SF-ber) • Signal degrade bit error rate (SD-ber) • Signal label payload construction (C2) • Path trace byte (J1) • Section <ul style="list-style-type: none"> ◦ Loss of signal (LoS) ◦ Loss of frame (LoF) ◦ Error counts for B1 ◦ Threshold crossing alarms (TCA) for B1 • Line <ul style="list-style-type: none"> ◦ Line alarm indication signal (LAIS) ◦ Line remote defect indication (LRDI) ◦ Line remote error indication (LREI) ◦ Error counts for B2 ◦ TCA for B2 • Path <ul style="list-style-type: none"> ◦ Path alarm indication signal (PAIS) ◦ Path remote defect indication (PRDI) ◦ Path remote error indication (PREI) ◦ Error counts for B3 ◦ TCA for B3 ◦ Loss of pointer (LoP) ◦ Positive stuffing event (PSE) <p>Negative stuffing event (NSE)</p> <p>Path unequipped indication signal (PUNEQ)</p> <p>Path payload mismatch indication signal (PPLM)</p>

Features	Descriptions
Network management	SONET-MIB (RFC 3592) SONET/SDH-MIB (RFC 2558) CISCO-SONET-MIB DS-3/E3-MIB (RFC 3896) DS-1/E1-MIB (RFC 2496) Simple Network Management Protocol (SNMP)
Reliability and availability	Online insertion and removal (OIR) Field-replaceable SFP optical modules 1+1 SONET Automatic Protection Switching (APS) and SDH Linear Multiplexer Section Protection (MSP) protocols Single SPA software reset
Physical specifications	Weight: 1.27 lb (0.57 kg) Height: 1.56 in. (3.96 cm) (double height) Width: 6.75 in. (17.15 cm) Depth: 7.28 in. (18.49 cm)
Power	1-port Channelized OC-12/STM-4 = 41.3W (with optics)
Environmental specifications	Operating temperature: 41 to 104°F (5 to 40°C) Storage temperature: -38 to 150°F (-40 to 70°C) Operating humidity: 5 to 85% relative humidity Storage humidity: 5 to 95% relative humidity
Compliance and agency approvals	<p>Safety</p> <ul style="list-style-type: none"> • UL 60950 • CSA 22.2-No.60950 • EN60950 • IEC 60950 CB Scheme • ACA TS001 • AS/NZS 3260 • EN60825\IEC60825 laser safety (SR, IR-Class 1) (VSR-Class 1M)1 • 21CFR1040 -FDA Code of Federal Regulations (USA) laser safety (SR, IR-Class 1) (VSR-Class 1M)1 <p>EMC</p> <ul style="list-style-type: none"> • FCC Part 15 (CFR 47) • ICES 003 • EN55022 • CISPR 22 • AS/NZS CISPR22 • VCCI • EN55024 • EN50082-1 • EN61000-6-1 • EN61000-3-2 • EN61000-3-3 <p>Network Equipment Building Standards (NEBS)</p> <p>This product is designed to meet the following requirements (official qualification may be in progress):</p> <ul style="list-style-type: none"> • SR-3580 – NEBS: Criteria levels (Level 3 compliant) • GR-63-CORE – NEBS: Physical protection • GR-1089-CORE – NEBS: EMC and safety

Table 2. Optical Specifications for the Cisco 1-Port Channelized OC-12 SPA

SFP Optics	Maximum Distance
Multimode (MM)	Up to 0.25 mi (500m)
Single-mode (SM)	Up to 1.2 mi (2 km)
SM intermediate reach (IR-1)	Up to 9 mi (15 km)
SM long reach (LR-1)	Up to 25 mi (40 km)
SM extended reach (LR-2)	Up to 50 mi (80 km)

Power and Environmental Requirements

When installed in Cisco routers, these SPAs do not change the power or environmental requirements and standards of the router platform itself. Refer to the platform-specific data sheets for more information.

Ordering Information

To place an order, visit the [Cisco Ordering Homepage](#) and refer to Table 3.

Table 3. Ordering Information

Product Name	Part Number
Cisco 1-port Channelized OC12/STM-4 SPA	SPA-1xCHOC12/DS0
OC12/STM-4, OC12/STM-4 SFP, MM	SFP-OC12-MM
OC12/STM-4, OC12/STM-4 SFP, SM, SR	SFP-OC12-SR
OC12/STM-4, OC12/STM-4 SFP, SM, IR-1	SFP-OC12-IR1
OC12/STM-4, OC12/STM-4 SFP, SM, LR-1	SFP-OC12-LR1
OC12/STM-4, OC12/STM-4 SFP, SM, LR-2	SFP-OC12-LR2

Service and Support

Cisco offers a wide range of services programs to accelerate customer success. These innovative services programs are delivered through a unique combination of people, processes, tools, and partners, resulting in high levels of customer satisfaction. Cisco services help you protect your network investment, optimize network operations, and prepare your network for new applications to extend network intelligence and the power of your business. For more information about Cisco services, refer to [Cisco Technical Support Services](#) or [Cisco Advanced Services](#).

For More Information

For more information about the Cisco SPA/SIP portfolio, visit www.cisco.com/go/spa or contact your local Cisco account representative.



Americas Headquarters
Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
www.cisco.com
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

Asia Pacific Headquarters
Cisco Systems, Inc.
168 Robinson Road
#28-01 Capital Tower
Singapore 068912
www.cisco.com
Tel: +65 6317 7777
Fax: +65 6317 7799

Europe Headquarters
Cisco Systems International BV
Haarlerbergpark
Haarlerbergweg 13-19
1101 CH Amsterdam
The Netherlands
www-europe.cisco.com
Tel: +31 0 800 020 0791
Fax: +31 0 20 357 1100

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

©2007 Cisco Systems, Inc. All rights reserved. CVP, the Cisco logo, and the Cisco Square Bridge logo are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, BPX, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, Follow Me Browsing, FormShare, GigaDrive, GigaStack, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, iQuickStudy, LightStream, Linksys, MeetingPlace, MGX, Networking Academy, Network Registrar, Packet, PIX, ProConnect, RateMUX, ScriptShare, SlideCast, SMARTnet, StackWise, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0701R)