

Supported Devices Tables of RME, CM, DFM, and CV (LMS 3.1)

Updated: June 10, 2008.

The following tables list the devices supported by the LAN Management Solution (LMS) 3.1 Applications:

- Resource Manager Essentials (RME)
- Campus Manager (CM)
- Device Fault Manager (DFM)
- CiscoView (CV)

If a minor release of an application is required to support a device, it is noted in the table with a footnote. This document is updated every time a new device support is available for RME, CM, DFM, and CV.

You can download the device updates of LMS applications and their respective readmes from the following locations:

- RME: <http://www.cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>
- CM: <http://www.cisco.com/cgi-bin/tablebuild.pl/cw2000-campus>
- DFM: <http://www.cisco.com/cgi-bin/tablebuild.pl/cw2000-dfm>
- CV: <http://www.cisco.com/cgi-bin/Software/CiscoView/cvplanner.cgi>

To see a list of all packages installed on your CiscoWorks server, from the CiscoWorks LMS Portal or CiscoWorks home page, select **Common Services > Software Center > Software Update**.

Note:

- RME does not support End of Life (EoL) IOS image releases. For those devices that have EoL software images in them, upgrade to IOS supported software image versions which are not EoL images.
- For the CV Device Packages which have module support, links to the list of modules are provided.

Additional Supported Devices Tables for RME 4.2:

- [Supported Protocols for RME 4.2 Configuration Management](#)
- [Supported Image Distribution Features for RME 4.2 Software Management](#)
- [Supported Image Import Features for RME 4.2 Software Management](#)

Additional Supported Devices Table for DFM 3.1:

- [Supported Operating Systems for Cisco Switches in DFM 3.1](#)

Additional Supported Devices Table for CV:

- [Supported Modules Tables for CiscoView](#)

Installing LMS 3.1 will provide device support for all the devices listed in the following tables:

- [Devices Supported in RME, CM, DFM, and CV \(With LMS 3.0 December 2007 Update\)](#)
- [Devices Supported in RME, CM, DFM, and CV \(With LMS 3.0\)](#)

Note: The footnotes about the support for specific devices are not applicable as the devices are automatically supported when you install LMS 3.1.

Devices Supported in RME, CM, DFM, and CV (With LMS 3.0 December 2007 Update)

The following table lists the devices supported in LMS 3.0 December 2007 Update.

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-24-S Switch	1.3.6.1.4.1.9.1.929	12.2(37)EY	5.0.2	Yes	Yes	NA	NA	Yes ²	Yes	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-24TC-S Switch	1.3.6.1.4.1.9.1.928	12.2(37)EY	5.0.2	Yes	Yes	NA	NA	Yes ^{2,3}	Yes	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-48TC-S Switch	1.3.6.1.4.1.9.1.927	12.2(37)EY	5.0.2	Yes	Yes	NA	NA	Yes ²	Yes	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-24PC-L Switch	1.3.6.1.4.1.9.1.950	12.2(44)SE	5.0.3 ⁷	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ¹⁷	Switch	4.1.1 ⁵	Yes	Yes	Yes ⁴	Cat2960	5.0

Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-24LT-L Switch	1.3.6.1.4.1.9.1.951	12.2(44)SE	5.0.3 ²	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ¹⁷	Switch	4.1.1 ⁵	Yes	Yes	Yes	Cat2960	5.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960PD-8TT-L Compact Switch	1.3.6.1.4.1.9.1.952	12.2(44)SE	5.0.3 ²	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ¹⁷	Switch	4.1.1 ⁵	Yes	Yes	Yes	Cat2960	5.0
Cisco 2800 Series Integrated Services Routers	Cisco 2821 Integrated Services Router (NM-CUE Card Support)	1.3.6.1.4.1.9.1.577	—	Supported in 5.0	Yes	—	—	—	—	Yes	3.0.2	Router	4.1.1	Yes	—	—	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509 Switch (6582-2PA & WiSM - Card Support)	1.3.6.1.4.1.9.1.283	—	Supported in 5.0	Yes	Yes	NA	—	Yes ²	Yes	3.0.2	Switch	4.1.1	Yes	—	—	Cat6000IOS	29.0
Cisco Catalyst 6500 Series Switches	Cisco Virtual Switching System (WS-C6513)	1.3.6.1.4.1.9.1.896	12.2SXH	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509-V-E Switch	1.3.6.1.4.1.9.1.832	122-33.SXH[RME] 12.2(18)SXF10 [CM]	5.0.3 ²	Yes	Yes	NA	NA	Yes ^{2, 10}	Yes	3.0.3 ¹⁷	Switch	4.1.1 ⁵	Yes	Yes	Yes	Cat6000IOS	30.0
Cisco 7600 Series Routers	Cisco 7604 Router	1.3.6.1.4.1.9.1.658	12.2.17d.SXB11a [CM]	5.0.2	Yes	Yes	NA	NA	Yes ²	Yes	Not Supported	Not Supported	Supported in 4.1	Supported in 4.1	Supported in 4.1	Supported in 4.1	Cat6000IOS	29.0
Cisco 7600 Series Routers	Cisco 7609-S Router	1.3.6.1.4.1.9.1.864	12.2(33)SRB2 [RME] 12.2.33SRB1 [CM]	5.0.3 ²	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ¹⁷	Router	4.1.1 ⁵	Yes	Yes	Yes	Cat6000IOS	30.0
Cisco 7600 Series Routers	Cisco 7606-S Router	1.3.6.1.4.1.9.1.863	12.2(33)SRB2 [RME] 12.2.33SRB1 [CM]	5.0.3 ²	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ¹⁷	Router	4.1.1 ⁵	Yes	Yes	Yes	Cat6000IOS	30.0
Cisco 7600 Series Routers	Cisco 7603-S Router	1.3.6.1.4.1.9.1.862	12.2(33)SRB2 [RME] 12.2(33)SRB1 [CM]	5.0.2	Yes	Yes	NA	NA	Yes ²	Yes	3.0.2	Router	4.1.1	Yes	Yes	Yes	Cat6000IOS	30.0
Cisco 7200 Series Routers	Cisco 7201 Router	1.3.6.1.4.1.9.1.821	— [RME] 12.2.31SB5 [CM]	5.0.3 ²	Yes ¹¹	NA	NA	NA	Yes ^{2, 10}	Yes ⁹	3.0.3 ¹⁷	Router	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Fabric Switches	Cisco MDS 9513 Multilayer Director Switch	1.3.6.1.4.1.9.12.3.1.3.377	3.1.(2a)	5.0.2	Yes	NA	NA	NA	NA	Yes	3.0.2	Switch	4.1.1	Yes	Yes ¹	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Fabric Switches	Cisco MDS 9216i Multilayer Fabric Switch	1.3.6.1.4.1.9.12.3.1.3.472	2.0(1)	5.0.2	Yes	NA	NA	NA	NA	Yes	3.0.2	Switch	4.1.1	Yes	Yes ¹	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Fabric Switches	Cisco MDS 9124 Multilayer Fabric Switch	1.3.6.1.4.1.9.12.3.1.3.587	2.0(3) [RME] SAN-OS 2.0(3) [CM]	5.0.3 ²	Yes	NA	NA	NA	NA	Yes	3.0.3 ¹⁷	Switch	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Server Fabric Switches	Cisco SFS 3504 Multifabric Server Switch	1.3.6.1.4.1.6203.16	2.10.0	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
IBM Blade Center InfiniBand Switch	Cisco BladeCenterH (BCH)	1.3.6.1.4.1.6203.15	2.9.0	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-12D-S Switch	1.3.6.1.4.1.9.1.930	12.2(37)EX [RME] 12.2(0.0.63)EX [CM]	5.0.2	Yes	Yes	NA	NA	Yes ²	Yes	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-12E-S Switch	1.3.6.1.4.1.9.1.930	12.2(37)EX [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-12SD-E Switch	1.3.6.1.4.1.9.1.956	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ^{17, 18}	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Cat3560	5.0
Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-12SD-S Switch	1.3.6.1.4.1.9.1.956	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ^{17, 18}	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-12S Switch	1.3.6.1.4.1.9.1.530	12.2(25)SED1	5.0.2	Yes	Yes	NA	NA	Yes ²	Yes	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-24PS Switch	1.3.6.1.4.1.9.1.536	12.2(25)SED1	5.0.2	Yes	Yes	NA	NA	Yes ^{2, 3}	Yes	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-48PS Switch	1.3.6.1.4.1.9.1.535	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ²	Yes	Supported in 3.0	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported

Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-24 Switch	1.3.6.1.4.1.9.1.511	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Not Supported	Not Supported	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-48 Switch	1.3.6.1.4.1.9.1.512	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Not Supported	Not Supported	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-24TS Switch	1.3.6.1.4.1.9.1.513	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Supported in 3.0	NA	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-24T Switch	1.3.6.1.4.1.9.1.514	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Not Supported	Not Supported	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-24PS Switch	1.3.6.1.4.1.9.1.602	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Supported in 3.0	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-48PS Switch	1.3.6.1.4.1.9.1.603	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Supported in 3.0	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-48TS Switch	1.3.6.1.4.1.9.1.604	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Supported in 3.0	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-24TS-1U Switch	1.3.6.1.4.1.9.1.624	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Supported in 3.0	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-24FS Switch	1.3.6.1.4.1.9.1.656	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	Supported in 3.0	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-24WS-S25 Switch	1.3.6.1.4.1.9.1.778	—	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17}	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-24WS-S50 Switch	1.3.6.1.4.1.9.1.779	—	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17}	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 4500 Series Switches	Cisco Catalyst 4506-E Switch	1.3.6.1.4.1.9.1.875	12.2(40)SG	5.0.3 ^{2}	Yes	Yes	NA	NA	Yes ^{2, 10}	Yes ^{9}	3.0.3 ^{17}	Switch	4.1.1 ^{5}	Yes	Yes	Yes ^{4}	Not Supported	Not Supported
Cisco Catalyst 4500 Series Switches	Cisco Catalyst 4510R-E Switch	1.3.6.1.4.1.9.1.877	12.2(40)SG	5.0.3 ^{2}	Yes	Yes	NA	NA	Yes ^{2, 10}	Yes ^{9}	3.0.3 ^{17}	Switch	4.1.1 ^{5}	Yes	Yes	Yes ^{4}	Not Supported	Not Supported
Cisco Catalyst 4500 Series Switches	Cisco Catalyst 4503-E Switch	1.3.6.1.4.1.9.1.874	12.2(40)SG	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	3.0.3 ^{17, 18}	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 4500 Series Switches	Cisco Catalyst 4507R-E Switch	1.3.6.1.4.1.9.1.876	12.2(40)SG	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	3.0.3 ^{17, 18}	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 4900 Series Switches	Cisco Catalyst 4900M Switch	1.3.6.1.4.1.9.1.917	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	NA	Yes	3.0.3 ^{17, 18}	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE-612 Wide Area Application Engine	1.3.6.1.4.1.9.1.761	5.5.1.7[RME] ACNS5.5.1[CM]	5.0.2	Yes	NA	NA	NA	NA	Yes	3.0.2	Host	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE-612 Wide Area Application Engine	1.3.6.1.4.1.9.1.777	WAAS 4.0.13.23 [RME] oe612-4.0.13.23 [CM]	5.0.3 ^{2}	Yes	NA	NA	NA	NA	Yes ^{9}	3.0.3 ^{17}	Host	4.1.1 ^{5}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE-512 Wide Area Application Engine	1.3.6.1.4.1.9.1.776	WAAS 4.0.13.23 [RME] oe512-4.0.13.23 [CM]	5.0.3 ^{2}	Yes	NA	NA	NA	NA	Yes ^{9}	3.0.3 ^{17}	Host	4.1.1 ^{5}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE-7326 Wide Area Application Engine	1.3.6.1.4.1.9.1.787	WAAS 4.0.13.23 [RME] oe7326-4.0.13.23 [CM]	5.0.3 ^{2}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17}	Host	4.1.1 ^{5}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE-611 Wide Area Application Engine	1.3.6.1.4.1.9.1.786	—	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17, 18}	Host	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 600 Series Content Engines	Cisco 611 Content Engine	1.3.6.1.4.1.9.1.708	—	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17, 18}	Host	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ME 3400 Series Ethernet Access Switches	Cisco ME 3400G-2CS-A Switch	1.3.6.1.4.1.9.1.825	—[RME] 12.2(35)SE1[CM]	5.0.2	Yes	Yes	NA	NA	Yes ^{2, 3}	Yes	3.0.2	Switch	4.1.1	Yes	Yes	Yes	Cisco3400ME	3.0
Cisco ME 3400 Series Ethernet Access Switches	Cisco ME 3400-24FS-A Switch	1.3.6.1.4.1.9.1.873	—	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ^{2}	Yes	3.0.3 ^{17, 18}	Switch	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported

Cisco Services Modules	Cisco ACE Application Control Engine Module (ACE10-6500-K9)	1.3.6.1.4.1.9.1.730	—	Supported in 5.0.1	Yes	NA	NA	NA	NA	NA	3.0.2	Router	Card Support in 4.1.1	Yes	NA	NA	Not Supported	Not Supported
Cisco Services Modules	Cisco Catalyst 6500, 7600 Series Wireless Services Module	1.3.6.1.4.1.14179.1.1.4.4	—	5.0.3 ^{7, 8}	Yes	NA	NA	NA	NA	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Service Modules	Cisco WS-SVC-SAMI-BB	1.3.6.1.4.1.9.1.744	12.4 HA4.0, 12.4 BWG1.0[RME] BWG 1.0, HA4.0 ¹⁶ [CM]	5.0.3 ²	Yes	NA	NA	NA	NA	Yes	Supported in 3.0.1	Router	4.1.1 ⁵	Yes	Yes	Yes ¹⁴	Cat6000IOS	30.0
Cisco Catalyst 6500 Series Service Modules	WS-SVC-WISM-1-K9	NA	SWISMK9-32 or later (Parentdevice:12.2 (18)SXF10a)[CM]	5.0.3 ²	Yes	NA	NA	NA	NA	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Network Modules	Cisco 2600,2800,3700,3800 Series 16-Port EtherSwitch Service Module (NME-16ES-1G)	1.3.6.1.4.1.9.1.702	12.2(25)[RME] 12.2(25)SEC[CM]	5.0.3 ²	Yes ¹¹	Yes ¹²	NA	NA	Yes ^{2, 10}	Yes ²	3.0.3 ¹⁷	Probe	4.1.1 ⁵	Yes	Yes ¹⁵	Yes ⁴	Not Supported	Not Supported
Cisco Network Modules	Cisco 2600,2800,3700,3800 Series 16-Port EtherSwitch Service Module (NME-16ES-1G-P)	1.3.6.1.4.1.9.1.663	12.2(25)[RME] 12.2(25)SEC[CM]	5.0.3 ²	Yes ¹¹	Yes ¹²	NA	NA	Yes ^{2, 10}	Yes ²	3.0.3 ¹⁷	Probe	4.1.1 ⁵	Yes	Yes ¹⁵	Yes ⁴	Not Supported	Not Supported
Cisco Network Modules	Cisco 2800,3800 Series 23-Port EtherSwitch Service Module (NME-X-23ES-1GP)	1.3.6.1.4.1.9.1.664	12.2(25)[RME] 12.2(25)SEC[CM]	5.0.3 ²	Yes	Yes	NA	NA	Yes ^{2, 10}	Yes	3.0.3 ^{17, 18}	Probe	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Network Modules	Cisco 2851,3800 Series 24-Port EtherSwitch (with Stackwise Connectors) Service Module (NME-X-24ES-1GP)	1.3.6.1.4.1.9.1.665	12.2(25)[RME] 12.2(25)SEC[CM]	5.0.3 ^{2, 8}	Yes	Yes	NA	NA	Yes ²	Yes	3.0.3 ^{17, 18}	Probe	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Network Modules	Cisco 2851,3800 Series 48-Port EtherSwitch Service Module (NME-XD-48ES-2S-P)	1.3.6.1.4.1.9.1.666	12.2(25)[RME] 12.2(25)SEC[CM]	5.0.3 ²	Yes	Yes	NA	NA	Yes ^{2, 13}	Yes	3.0.3 ^{17, 18}	Probe	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls	Cisco PIX 535 Firewall Security Context	1.3.6.1.4.1.9.1.675	7.2	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.3 ¹⁷	Firewall	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls	Cisco PIX 525 Firewall Security Context	1.3.6.1.4.1.9.1.676	7.2	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.3 ¹⁷	Firewall	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls	Cisco PIX 515 Firewall Security Context	1.3.6.1.4.1.9.1.678	7.2	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.3 ^{17, 18}	Firewall	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Interface Cards	Cisco 3205 Wireless Mobile Interface Card (WMIC)	1.3.6.1.4.1.9.1.819	123-2.JL[RME] 12.3[CM]	5.0.3 ²	Yes	NA	NA	NA	NA	Yes	3.0.3 ¹⁷	Router	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Interface Cards	Cisco 3202 Wireless Mobile Interface Card (WMIC)	1.3.6.1.4.1.9.1.667	123-2.JL[RME] —[CM]	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17, 18}	Router	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 3200 Series Mobile Access Routers	Cisco 3270 Rugged Router (C3271MARC-TP)	1.3.6.1.4.1.9.1.689	—	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17, 18}	Router	4.1.1 ^{5, 6}	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 2100 Series Wireless LAN Controllers	Cisco 2106 Wireless LAN Controller	1.3.6.1.4.1.9.1.828	4.2.103.0[CM]	5.0.3 ²	Yes	NA	NA	NA	NA	Yes	3.0.3 ¹⁷	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 4400 series Wireless LAN Controllers	Cisco 4402 Wireless LAN Controller	1.3.6.1.4.1.14179.1.1.4.3	4.1.171.0[CM]	5.0.3 ²	Yes ¹¹	NA	NA	NA	NA	Yes ²	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Other Switches and Hubs	Cisco Intelligent Gigabit Ethernet Switch Module for IBM eServer Blade Center	1.3.6.1.4.1.9.1.592	12.1(14)AY1[CM]	5.0.2	Yes	Yes	NA	NA	Yes ^{2, 3}	Yes	Supported in 3.0	Switch	Supported in 4.1	Supported in 4.1	Supported in 4.1	Supported in 4.1	Not Supported	Not Supported
Other Switches and Hubs	Cisco Fiber Intelligent Gigabit Ethernet Switch Module for IBM eServer Blade Center	1.3.6.1.4.1.9.1.660	12.1(22)EA10a [CM]	5.0.2	Yes	Yes	NA	NA	Yes ¹⁰	Yes	Supported in 3.0	Switch	Supported in 4.1	Supported in 4.1	Supported in 4.1	Supported in 4.1	CIGESM	2.0
Cisco XR 12000 Series Routers	Cisco XR 12406 Router	1.3.6.1.4.1.9.1.388	3.4.1	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Rtr12000	21.0

Cisco XR 12000 Series Routers	Cisco XR 12410 Router	1.3.6.1.4.1.9.1.394	3.4.1	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco XR 12000 Series Routers	Cisco XR 12810 Router	1.3.6.1.4.1.9.1.478	3.4.1	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 12000 Series Routers	Cisco 12016 Router	1.3.6.1.4.1.9.1.273	IOSXR3.4.1[RME] 3.5.2[CM]	5.0.3 ²⁷	Yes ¹¹	NA	NA	NA	NA	Yes ⁹	Not Supported	Not Supported	4.1.1 ⁵	Yes	Yes	Yes	Not Supported	Not Supported	
Cisco 1800 Series Routers	Cisco 1805 Integrated Services Router	1.3.6.1.4.1.9.1.981	12.4(15)XY	5.0.3 ²⁷	Yes	NA	NA	NA	NA	Yes	3.0.3 ¹⁷	Router	4.1.1 ⁵	Yes	Yes	Yes	Rtr1800	7.0	
Cisco 800 Series Routers	Cisco 815 Router	1.3.6.1.4.1.9.1.733	12.4(6)XE1	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1.1	Yes	Yes	Yes	Not Supported	Not Supported	
Cisco 800 Series Routers	Cisco 861,861W Integrated Services Router	1.3.6.1.4.1.9.1.834	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr800	12.0	
Cisco 800 Series Routers	Cisco 881 Integrated Services Router	1.3.6.1.4.1.9.1.837	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr800	12.0	
Cisco 800 Series Routers	Cisco 888, 888W Integrated Services Router	1.3.6.1.4.1.9.1.852	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr800	12.0	
Cisco ASR 1000 Series Aggregation Services Routers	Cisco ASR 1006 Router	1.3.6.1.4.1.9.1.925	IOS XE (2.1)[CM]	5.0.3 ²⁷	Yes ¹¹	NA	NA	NA	NA	Yes ⁹	3.0.3 ^{17, 18}	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	
Cisco ASR 1000 Series Aggregation Services Routers	Cisco ASR 1004 Router	1.3.6.1.4.1.9.1.924	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.3 ^{17, 18}	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	
Cisco ASR 1000 Series Aggregation Services Routers	Cisco ASR 1002 Router	1.3.6.1.4.1.9.1.923	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.3 ^{17, 18}	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	
Cisco Wireless LAN Controller Modules	Integrated service router series 2800,3800 with Wireless LAN Controller Network Module	1.3.6.1.4.1.9.1.818	—	5.0.3 ^{2, 8}	Yes	NA	NA	NA	NA	Yes	3.0.3 ^{17, 18}	Probe	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Switch Module 3110G-S for IBM BladeCenter	1.3.6.1.4.1.9.1.909	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Switch Module 3110G-S-I for IBM BladeCenter	1.3.6.1.4.1.9.1.910	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Switch Module 3110X-S for IBM BladeCenter	1.3.6.1.4.1.9.1.911	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Switch Module 3110X -S-I for IBM BladeCenter	1.3.6.1.4.1.9.1.912	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3120G-S for HP	1.3.6.1.4.1.9.1.918	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3120X-S for HP	1.3.6.1.4.1.9.1.919	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3032 for Dell M1000E	1.3.6.1.4.1.9.1.920	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3130G-S for Dell M1000E	1.3.6.1.4.1.9.1.921	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3130X-S for Dell M1000E	1.3.6.1.4.1.9.1.922	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Switch Module 3110X Stack for IBM BladeCenter	1.3.6.1.4.1.9.1.947	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3120X Stack for HP	1.3.6.1.4.1.9.1.948	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	
Cisco Catalyst Blade Switch 3000 Series	Cisco Catalyst Blade Switch 3130X Stack for Dell M1000E	1.3.6.1.4.1.9.1.949	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CBS31x0	2.0	

1. Netconfig of Configuration, Management, is not supported by Cisco MDS 9513 Multilayer Director Switch and Cisco MDS 9216i Multilayer Fabric Switch.

2. IP Phones are supported.

3. Dynamic User Tracking is supported.
4. SWIM support for the device is untested. Support of this device category has already been tested in the earlier releases.
5. RME support for this specific device is available at <http://cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>.
6. RME support for the device is untested. Support of this device category has already been tested in the earlier releases.
7. CM support for this specific device is available at <http://www.cisco.com/cgi-bin/tablebuild.pl/cw2000-campus>.
8. CM support for the device is untested. Support of this device category has already been tested in the earlier releases.
9. Path Analysis for the device is untested. Support of this device category has already been tested in the earlier releases.
10. User Tracking for the device is untested. Support of this device category has already been tested in the earlier releases.
11. Topology Services for the device is untested. Support of this device category has already been tested in the earlier releases.
12. VLAN Management for the device is untested. Support of this device category has already been tested in the earlier releases.
13. IP Phone Tracking for the device is untested. Support of this device category has already been tested in the earlier releases.
14. Software Management: Support for the module requires IP address of the parent Catalyst 6000 or 7600 device with proper Telnet credentials.
15. Config Management support for the device is untested. Support of this device category has already been tested in the earlier releases.
16. Path Analysis for the device is untested in this software. Support of this device category has already been tested in the earlier releases.
17. DFM support for this specific device is available at: <http://www.cisco.com/cgi-bin/tablebuild.pl/cw2000-dfm>
18. DFM support for the device is untested. Support of this device category has already been tested in the earlier releases.

Devices Supported in RME, CM, DFM, and CV (With LMS 3.0)

The following tables list the devices supported in LMS 3.0.

- [Table 1: Access Servers](#)
- [Table 2: Cable Products](#)
- [Table 3: Content Networking Devices](#)
- [Table 4: Interfaces and Modules](#)
- [Table 5: Optical Platforms](#)
- [Table 6: Routers](#)
- [Table 7: Security and VPN Devices](#)
- [Table 8: Switches](#)
- [Table 9: Universal Gateways](#)
- [Table 10: Voice Gateways](#)
- [Table 11: Wireless LAN Products](#)
- [Table 12: Hubs](#)

Table 1: Access Servers

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco AS5200 Series Universal Access Servers	Cisco AS5200 Universal Access Server	1.3.6.1.4.1.9.1.109	Cisco IOS 12.1(T) [RME] IOS 11.0 [CM]	5.0	Yes	—	—	—	Yes ³	Yes	3.0	Router	4.1	Yes	Yes	Yes ¹	Not Supported	Not Supported
Cisco 2500 Series Access Servers	Cisco 2509RJ Access Server	1.3.6.1.4.1.9.1.153	—[RME] IOS 11.0 [CM]	5.0	Yes	—	—	—	Yes ³	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Access Servers	Cisco 2510 Access Server	1.3.6.1.4.1.9.1.126	—[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Access Servers	Cisco 2511RJ Access Server	1.3.6.1.4.1.9.1.154	Cisco IOS 12.0(17a) [RME] IOS 11.0 [CM]	5.0	Yes	—	—	—	Yes ³	Yes	3.0	Router	4.1	Yes	Yes	Yes ²	Rtr2500	2.0
Cisco 2500 Series Access Servers	Cisco 2512 Access Server	1.3.6.1.4.1.9.1.128	Cisco IOS 12.0(17a) [RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0

1. Software Management: Dual Flash bank and Single Flash bank on AS5200 supported; MICA modem upgrades on AS5200 supported; Microcom 56K firmware upgrade on AS5200 supported.

2. Software Management: Dual Flash bank and Single Flash bank supported.

3. Cisco routers supply the User Tracking application with ARP Table information.

Table 2: Cable Products

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco uBR900 Series Cable Access Routers	Cisco uBR904 Cable Access Router	1.3.6.1.4.1.9.1.191	Cisco IOS 11.3 [RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr900	5.0
Cisco uBR900 Series Cable Access Routers	Cisco uBR905 Cable Access Router	1.3.6.1.4.1.9.1.351	Cisco IOS 11.3 [RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr900	5.0
Cisco uBR900 Series Cable Access Routers	Cisco uBR924 Cable Access Router	1.3.6.1.4.1.9.1.255	Cisco IOS 11.3 [RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr900	5.0
Cisco uBR900 Series Cable Access Routers	Cisco uBR925 Cable Access Router	1.3.6.1.4.1.9.1.316	—[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	ubr900	5.0
Cisco uBR7100 Series Universal Broadband Routers	Cisco uBR 7111 Universal Broadband Router	1.3.6.1.4.1.9.1.344	12.1(5) EC1[RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Cisco uBR7100 Series Universal Broadband Routers	Cisco uBR 7111E Universal Broadband Router	1.3.6.1.4.1.9.1.345	12.1(7) EC [RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Cisco uBR7100 Series Universal Broadband Routers	Cisco uBR 7114 Universal Broadband Router	1.3.6.1.4.1.9.1.346	12.1(5)EC1 [RME]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Cisco uBR7100 Series Universal Broadband Routers	Cisco uBR 7114E Universal Broadband Router	1.3.6.1.4.1.9.1.347	12.1(7) EC [RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Universal Broadband Routers (uBR) 7200 Series	Cisco uBR 7223 Universal Broadband Router	1.3.6.1.4.1.9.1.210	Cisco IOS 11.3 [RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Universal Broadband Routers (uBR) 7200 Series	Cisco uBR 7246 Universal Broadband Router	1.3.6.1.4.1.9.1.179	Cisco IOS 11.3 [RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Universal Broadband Routers (uBR) 7200 Series	Cisco uBR 7246VXR Universal Broadband Router	1.3.6.1.4.1.9.1.271	Cisco IOS 11.3 [RME] IOS 11.1.[CM]	5.0	Yes	—	Yes	Yes	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Universal Broadband Routers (uBR) 10000 Series	Cisco uBR 10012 Universal Broadband Router	1.3.6.1.4.1.9.1.317	Cisco IOS 12.2.1 XF[RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	ubr7200	11.0
Cisco uBR 7100 Series Universal Broadband Routers	Cisco uBR7100 Universal Broadband Router	1.3.6.1.4.1.9.1.309	—[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco CVA120 Series Cable Voice Adapters	Cisco CVA122E Cable Voice Adapter	1.3.6.1.4.1.9.1.371	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	ubr900	5.0
Cisco uBR900 Series Cable Access Routers	Cisco uBR914 Cable Data Service Unit	1.3.6.1.4.1.9.1.294	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	ubr900	5.0

1. Cisco Routers provide User Tracking application with ARP Table information.

Table 3: Content Networking Devices

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)

Cisco CSS 11000 Series Content Services Switches	Cisco CSS11050 Content Services Switch	1.3.6.1.4.1.2467.4.4	5.0 build 2s[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	CSS11000	9.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11800 Content Services Switch	1.3.6.1.4.1.2467.4.2	5.0 build 2s[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	CSS11000	9.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11150 Content Services Switch	1.3.6.1.4.1.2467.4.3	5.0 build 2s[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	CSS11000	9.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11100 Content Services Switch	1.3.6.1.4.1.2467.4.1	5.0 build 2s[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11501 Content Services Switch	1.3.6.1.4.1.9.9.368.4.7 [RME] 1.3.6.1.4.1.2467.4.7 [CM]	7.50.0.04[RME] 7.20[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	CSS11000	9.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11501R Content Services Switch	1.3.6.1.4.1.9.9.368.4.7	7.4[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	CSS11500	1.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11503 Content Services Switch	1.3.6.1.4.1.2467.4.5	5.20B1[RME] —[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	CSS11000	9.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11503 Content Services Switch CSS11503R[CM]	1.3.6.1.4.1.9.9.368.4.5	7.50.0.04[RME] 8.10[CM]	5.0	Yes	—	—	—	—	No	3.0	Switch	4.1	Yes	Yes	Yes	CSS11500	1.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11506 Content Services Switch	1.3.6.1.4.1.2467.4.6	5.20B1[RME] —[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	CSS11000	9.0
Cisco CSS 11000 Series Content Services Switches	Cisco CSS11506 Content Services Switch CSS11506R[CM]	1.3.6.1.4.1.9.9.368.4.6	7.50.0.04[RME] 8.10[CM]	5.0	Yes	—	—	—	—	No	3.0	Switch	4.1	Yes	Yes	Yes	CSS11500	1.0
Cisco500 Series Content Engines	Cisco 507 Content Engine	1.3.6.1.4.1.9.1.409	ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco500 Series Content Engines	Cisco 507AV Content Engine	1.3.6.1.4.1.9.1.432	ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco500 Series Content Engines	Cisco 510 Content Engine	1.3.6.1.4.1.9.1.505	ACNS 4.2.0[RME] ACNS 5.1.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	4.1	Yes	Yes	Yes	CE500	5.0
Cisco500 Series Content Engines	CE511 ²	1.3.6.1.4.1.9.1.595	5.2.1.5[RME] ACNS 5.2.1.5[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE- 511 Wide Area Application Engines ¹	1.3.6.1.4.1.9.1.595	5.3.7.8[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	CE500	5.0
Cisco500 Series Content Engines	Cisco560 Content Engine	1.3.6.1.4.1.9.1.410	ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported

Cisco500 Series Content Engines	Cisco560AV- CDN (Running in CDM mode)	1.3.6.1.4.1.9.1.433		ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco500 Series Content Engines	Cisco 565 Content Engine	1.3.6.1.4.1.9.1.491		ACNS 5.0[RME] ACNS 5.1.0[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	4.1	Yes	Yes	Yes	CE500	5.0
Cisco500 Series Content Engines	Cisco590 Content Engine	1.3.6.1.4.1.9.1.411		ACNS 4.2.0[RME] ACNS 4.2[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco500 Series Content Engines	Cisco566 Content Engine ^{1, 2}	1.3.6.1.4.1.9.1.596		5.3.7.8[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	CE500	5.0
Cisco Wide Area Application Engine (WAE) Appliances	Cisco WAE- 512 Wide Area Application Engines ^{1, 2}	1.3.6.1.4.1.9.1.759		5.5.1[RME] 5.5.1[CM]	5.0	Yes	NA	NA	—	NA	Yes	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco7000 Series Content Engines	Cisco7305 Content Engine	1.3.6.1.4.1.9.1.504		ACNS 5.0[RME] ACNS 5.0[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	4.1	Yes	Yes	Yes	CE7300	4.0
Cisco7000 Series Content Engines	Cisco 7320 Content Engine (Running in CR mode)	1.3.6.1.4.1.9.1.412		ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco7000 Series Content Engines	Cisco7325 Content Engine	1.3.6.1.4.1.9.1.492		ACNS 5.0[RME] ACNS 5.0[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	4.1	Yes	Yes	Yes	CE7300	4.0
Cisco 2600, 3600, 3700 Series Content Engine Modules	NM-1CE, NM-2CE CE-2636[DFM]	1.3.6.1.4.1.9.1.454		ACNS 4.2.3[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	No	Not Supported	Not Supported
Cisco 4600 Series Content Distribution Manager	Cisco 4630 Content Distribution Manager	1.3.6.1.4.1.9.1.486		ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	No	Not Supported	Not Supported
Cisco 4600 Series Content Distribution Manager	Cisco 4650 Content Distribution Manager	1.3.6.1.4.1.9.1.487		ACNS 4.2.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	4.1	Yes	Yes	No	Not Supported	Not Supported
CiscoWorks Hosting Solution Engines	Cisco 1105 for Hosting Solution Engine	1.3.6.1.4.1.9.1.405		—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Global Site Selector Platforms	Cisco GSS 4490 Global Site Selector	1.3.6.1.4.1.9.1.517		—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 500 Series Cache Engines	Cisco 500 Cache Engine	1.3.6.1.4.1.9.1.9		—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

Network Analysis Modules	6380 - NAM	1.3.6.1.4.1.9.5.1.3.1.1.2.223	2.2[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Probe	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Network Analysis Modules	WS-SVC-NAM-1	1.3.6.1.4.1.9.5.1.3.1.1.2.914	2.2[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Probe	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Network Analysis Modules	WS-SVC-NAM-2	1.3.6.1.4.1.9.5.1.3.1.1.2.291	2.2[RME] —[CM]	5.0	Yes	—	—	—	—	—	3.0	Probe	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Network Analysis Module for Cisco 2600 Series	Cisco Branch Routers Series Network Analysis Module (NME-NAM for Cisco 2821)	1.3.6.1.4.1.9.1.826(RME) NA [Card Support (CM)]	3.6(1)	5.0.1	Yes	NA	NA	NA	NA	NA	3.0.1	Router	4.1 ⁸	Yes	Yes	No	Not Supported	Not Supported
Cisco 2600 Series MultiService Platforms	Cisco 2611 MultiService Platform	1.3.6.1.4.1.9.1.467	3.2(1A)[CM]	5.0	Yes ⁷	—	—	—	—	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr2600	27.0
Network Analysis Modules	Cisco 2600,3600,3700 Series NAM	1.3.6.1.4.1.9.1.562	3.2(1A)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Probe	4.1	Yes	Yes	No	Not Supported	Not Supported
Catalyst 6000 Modules	WS-SVC-IPSEC-1	—	12.2(9)YO[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Multiprocessor WAN Application Module (MWAM) for Cisco Catalyst 7600 Series Switches and Cisco 7600 Series Internet Routers	Cisco MWAM	1.3.6.1.4.1.9.12.3.1.9.17.39	12.3(2)XB[RME] 1.2(1.0)[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes ¹	Not Supported	Not Supported
Cisco Services Modules	Cisco 7600/Catalyst 6500 IPSec VPN Services Module	1.3.6.1.4.1.9.5.44	12.2(9)Y04[CM]	5.0	Yes	—	—	—	—	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Services Modules	SAMI (WS-SVC-SAMI-BB)	1.3.6.1.4.1.9.1.744 [RME] 1.3.6.1.4.1.9.5.44[CM]	12.4(11)CSG3.1(3)C4 (8) [RME] 3.1(3)C4[CM]	5.0	Yes	—	—	—	—	—	Not Supported	Not Supported	4.1	Yes	Yes	Yes ¹	Not Supported	Not Supported
Cisco 7000 Series Routers	Cisco Service Application Module for IP (WS-SVC-SAMI-BB)	1.3.6.1.4.1.9.1.744	12.4(11)	5.0.1	Yes	NA	NA	NA	NA	Yes	3.0.1	Router	4.1 ¹³	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Services Modules	SUP 720 ³	1.3.6.1.4.1.9.5.44[CM]	IOS 12.2.14-SX [CM]	5.0	Yes	Yes	—	—	Yes	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Services Modules	SUP 720 ³	1.3.6.1.4.1.9.5.44[CM]	CatOS 8.1(0.71)[RME]	5.0	Yes	Yes	—	—	Yes	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Services Modules	CSM	—	3.1(2)[RME] 3.1(3)[CM]	5.0	Yes	—	—	—	—	—	Not Supported	Not Supported	4.1	Yes	Yes	Yes ¹	Not Supported	Not Supported
Cisco Services Modules	Cisco Catalyst 6500 Series Firewall Services Module	1.3.6.1.4.1.9.1.522	1.1(2)[RME] 1.1(2)[CM]	5.0	Yes	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported

Cisco Catalyst 6500 Series Service Modules	Cisco ACE Application Control Engine Module (ACE10-6500-K9)	—	3.0(0)A1(2)	5.0.1	Yes	NA	NA	NA	NA	NA	3.0.1	Switch	4.1 ⁸	Yes	NA	Yes	Not Supported	Not Supported
Cisco Services Modules	WS-SUP720-3B	NA	12.2(18)SXE[CM]	5.0	Yes	Yes	NA	—	Yes ²	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Services Modules	WS-SUP-32	NA	12.2(18)SXF[CM]	5.0	Yes	Yes	NA	—	Yes ²	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Services Modules	Cisco Catalyst 6500 Series SSL Services Module	—	1.1(2)[CM]	5.0	Yes	—	—	—	—	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Network Modules	Cisco Catalyst 6000 Multilayer Switch Feature Card MSFC3 WS-SUP 720	1.3.6.1.4.1.9.1.557	12.2[CM]	5.0	Yes	—	—	—	Yes ⁴	Yes	3.0	MSFC	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 4500 Series Service Modules	4516	NA	12.2(25)EW[CM]	5.0	Yes	Yes	NA	—	Yes ²	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 4500 Series Service Modules	4516-10GE	NA	12.2(25)EWA6 [CM]	5.0	Yes	Yes	NA	—	Yes ²	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 4000 Series Modules	SUP-III, SUP-IV	1.3.6.1.4.1.9.5.59	12.1(13)EW1[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 4000 Series Supervisor Module	SUP II-Plus	1.3.6.1.4.1.9.5.59	12.1(19)EW1[CM]	5.0	Yes	Yes	—	—	Yes ²	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3201 Wireless Mobile Interface Card	Cisco 3201 Wireless Mobile Interface Card	1.3.6.1.4.1.9.1.581	12.2(15)JK[CM] 12.2(15)JK[RME]	5.0	Yes	—	—	—	Yes	Yes	3.0	Router	4.1	Yes	Yes	Yes	MAR3200	7.0
Cisco Catalyst 6500 and Cisco 7600 Series Communications Media Module (CMM)	WS-SVC-CMM	1.3.6.1.4.1.9.1.573	12.4(3)b[RME] 12.1(20)E ⁵ , 12.2(17) SX ⁶ [CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Intelligent Gigabit Ethernet Switch Module (IGESM) for IBM eServer BladeCenter	CIGESM	1.3.6.1.4.1.9.1.592	12.1(14)AY1 [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	CIGESM	2.0
Cisco Systems Intelligent Gigabit Ethernet Switch Module (IGESM) for IBM eServer BladeCenter	OS-CIGESM-18SFP-1	1.3.6.1.4.1.9.1.660	12.1(22)AY1 [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco IGX Universal Router Modules	Cisco IGX Universal Router Module 2FE	1.3.6.1.4.1.9.1.374		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco IGX Universal Router Module	Cisco IGX Universal Router Module 2FE-2V	1.3.6.1.4.1.9.1.375		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Gigabit Ethernet Switching Modules	Cisco Gigabit Ethernet Switch Module (371098-001)	1.3.6.1.4.1.11.2.3.7.11.33.3.1.1	12.2(25)SE [RME] 12.2(25)SE[CM]	5.0	Yes	—	—	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	CGESM	1.0

1. Software Management: Support for the module requires IP address of the parent Catalyst 6000 or 7600 device with proper Telnet credentials.

2. Support for IP Phones is also provided.

3. Supports Cisco IOS and CatOS.

4. Cisco Routers provide User Tracking application with ARP Table information.

5. Minimum supported version for SUP I and SUP II.

6. Minimum supported version for SUP III.

7. NAM is supported as a module on Cisco 2600 series routers rather than as an individual device, due to lack of CDP MIB support.

8. Support for this specific device is available at: <http://cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>

Table 5: Optical Platforms

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco ONS 15500 Series	Cisco ONS-15501-AC	1.3.6.1.4.1.1869.11.11.5.3	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	ONS15501	4.0
Cisco ONS 15500 Series	Cisco ONS-15501-DC	1.3.6.1.4.1.1869.11.11.5.1	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	ONS15501	4.0
Cisco ONS 15500 Series	Cisco ONS 15530 DWDM Multiservice Aggregation Platform	1.3.6.1.4.1.9.1.462	12.1(10) EV[RME] 12.1(10) EV1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	ONS15530	2.5
Cisco ONS 15500 Series	Cisco ONS 15530 DWDM Multiservice Aggregation Platform	1.3.6.1.4.1.9.1.461	12.1(10) EV[RME] 12.1(10) EV1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	ONS15530	2.5
Cisco ONS 15500 Series	Cisco ONS 15530 DWDM Multiservice Aggregation Platform	1.3.6.1.4.1.9.1.460	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	ONS15530	2.5
Cisco ONS 15500 Series	Cisco ONS 15540 (ESP) Extended Services Platform	1.3.6.1.4.1.9.1.406	Cisco IOS 12.1[RME] 12.1(10) EV1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	ONS15540	3.2
Cisco ONS 15500 Series	Cisco ONS 15540 (ESPx) Extended Services Platform	1.3.6.1.4.1.9.1.481	12.1(10) EV[RME] 12.1(10) EV1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	ONS15540	3.2
Cisco ONS 15500 Series	Cisco ONS15454ETSI/AN SI/HD	1.3.6.1.4.1.3607.1.20.10. 10	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	NA	NA	Not Supported	Not Supported
Cisco ONS 15500 Series	Cisco ONS-RAN-SVC	1.3.6.1.4.1.9.1.772	12.2[RME] 12.2[CM]	5.0	Yes	NA	NA	—	NA	Yes	3.0	Switch	4.1	Yes	Yes	NA	Not Supported	Not Supported
Metro Core	Cisco Metro 1500 Series (MAN DWDM)	1.3.6.1.4.1.2544.1.3	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Metro1500	3.0

Table 6: Routers

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco 12000 Series Routers	Cisco 12008 Router (GSR8/40)	1.3.6.1.4.1.9.1.182	Cisco IOS 11.3[RME] IOS 11.3[CM]	5.0	Yes	—	No	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 12000 Series Routers	Cisco 12010 Router	1.3.6.1.4.1.9.1.348	12.0(27)S1[RME] 12.0(27)S1[CM]	5.0	Yes	—	No	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0

Cisco 12000 Series Routers	Cisco 12012 Router (GSR12/60)	1.3.6.1.4.1.9.1.173	Cisco IOS 11.3[RME] IOS 11.3[CM]	5.0	Yes	—	No	Yes	Yes ⁵	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 12000 Series Routers	Cisco 12016 Router (GSR16/80-AC-8R)	1.3.6.1.4.1.9.1.273	Cisco IOS 11.3[RME] IOS 11.3[CM]	5.0	Yes	—	No	Yes	Yes ⁵	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 12000 Series Routers	Cisco 12004 Router	1.3.6.1.4.1.9.1.181	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco 12000 Router PRP	Same as Gigabit Switch Router (GSR) 12000 Series sysObjectIDs.	12.0(22)S[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco 12816 Router	1.3.6.1.4.1.9.1.477	12.0(31)S[RME] 12.0(32)S1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 12000 Series Routers	Cisco12816 Router PRP with SIP 400	1.3.6.1.4.1.9.1.477	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco12816 Router PRP with SIP600	1.3.6.1.4.1.9.1.477	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco 12810 Router with SIP601	1.3.6.1.4.1.9.1.478	12.0(31)S6, 12.0(32)S4 ¹ [RME] 12.0(32)S4[CM]	5.0	Yes	NA	NA	—	NA	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco 12404 Router (GSR4/80-AC)	1.3.6.1.4.1.9.1.423	Cisco IOS 12.0.8 S [RME] —[CM]	5.0	Yes	—	—	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 12000 Series Routers	Cisco 12406 Router (GSR6/120-AC)	1.3.6.1.4.1.9.1.388	Cisco IOS 12.0.8 S [RME] —[CM]	5.0	Yes	—	—	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco 12410 Router (GSR10/200-AC)	1.3.6.1.4.1.9.1.394	Cisco IOS 12.0.8 S [RME] —[CM]	5.0	Yes	—	—	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 12000 Series Routers	Cisco 12416 Router (GSR16/320-AC)	1.3.6.1.4.1.9.1.385	Cisco IOS 12.0.8 S [RME] —[CM]	5.0	Yes	—	—	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr12000	21.0
Cisco 10700 Series Routers	Cisco 10720-AC-A Router	1.3.6.1.4.1.9.1.397	12.0(19) SP[RME] 12.0(19)SP[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr10700	8.0
Cisco AGSplus Routers	Cisco AGSplus Router	1.3.6.1.4.1.9.1.11	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Other Routers	Cisco 10000 Series C 10400	1.3.6.1.4.1.9.1.272	—[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Rtr10000	10.0
Other Routers	Cisco Gateway Server	1.3.6.1.4.1.9.1.1	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported		
Other Routers	Cisco Optical Regenerator	1.3.6.1.4.1.9.1.254	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr12000	21.0
Cisco 10000 Series Routers	Cisco 10005 Router	1.3.6.1.4.1.9.1.437	Cisco IOS 12.0(9) SL1 [RME] 12.3(7)X16[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr10000	10.0
Cisco 10000 Series Routers	Cisco 10008 Router	1.3.6.1.4.1.9.1.438	Cisco IOS 12.0(9) SL1 [RME] 12.2(28)SB[CM]	5.0	Yes	NA	NA	—	NA	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr10000	10.0
Cisco 7000 Series Routers	Cisco 7000 Router	1.3.6.1.4.1.9.1.8	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7000 Series Routers	Cisco 7010 Router	1.3.6.1.4.1.9.1.12	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco7120 QuadT1 Router	1.3.6.1.4.1.9.1.259	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7120T3 Router	1.3.6.1.4.1.9.1.260	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0

Cisco 7100 Series VPN Routers	Cisco 7120E3 Router	1.3.6.1.4.1.9.1.261	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7120AT3 Router	1.3.6.1.4.1.9.1.262	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7120AE3 Router	1.3.6.1.4.1.9.1.263	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7120SMI3 Router	1.3.6.1.4.1.9.1.264	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140DualT3 Router	1.3.6.1.4.1.9.1.265	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140DualE3 Router	1.3.6.1.4.1.9.1.266	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140DualAT3 Router	1.3.6.1.4.1.9.1.267	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140DualAE3 Router	1.3.6.1.4.1.9.1.268	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140DualMM3 Router	1.3.6.1.4.1.9.1.269	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140-2FE Router	1.3.6.1.4.1.9.1.277	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7140-8T Router	1.3.6.1.4.1.9.1.276	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7100 Series VPN Routers	Cisco 7160 VPN Router	1.3.6.1.4.1.9.1.358	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7000 Series Routers	Cisco 7150-2FE Router	1.3.6.1.4.1.9.1.355	—[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7000 Series Routers	Cisco 7150-8T Router	1.3.6.1.4.1.9.1.356	—[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7000 Series Routers	Cisco 7150-8T1 Router	1.3.6.1.4.1.9.1.356	—[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7000 Series Routers	Cisco 7150-2T3 Router	1.3.6.1.4.1.9.1.357	—[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7600 Series Routers	Cisco 7604 Router with S1P400	1.3.6.1.4.1.9.1.658	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7600 Series Routers	Cisco 7604 Router with SUP32	1.3.6.1.4.1.9.1.658	12.2.18-SXF[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7600 Series Routers	Cisco 7604 Router with SUP720	1.3.6.1.4.1.9.1.658	12.2.18SXE[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7600 Series Routers	Cisco 7609 with WS-X6748-GE-TX	1.3.6.1.4.1.9.1.509	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7600 Series Routers	6748-GE-TX	1.3.6.1.4.1.9.1.509	—[CM]	5.0	Yes	Yes	—	—	Yes ¹²	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7600 Series Routers	SIP 200 on Cisco 7609	— 1.3.6.1.4.1.9.1.509 [DFM]	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	4.1	NA	Yes	Yes	Not Supported	Not Supported
Cisco 7600 Series Routers ^{7, 8}	Cisco OSR 7609 Router	1.3.6.1.4.1.9.1.509	Cisco IOS 12.1[RME] 12.2 (14) SX1[CM]	5.0	Yes	Yes	—	—	No	Yes	3.0	Router	4.1	Yes	Yes	Yes	Catt6000IOS	29.0

Cisco 7200 Series Routers	Cisco 7202 Router	1.3.6.1.4.1.9.1.194	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7200 Series Routers	Cisco 7204 Router	1.3.6.1.4.1.9.1.125	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7200 Series Routers	Cisco 7204VXR Router	1.3.6.1.4.1.9.1.223	Cisco IOS 11.1[RME] —[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7200 Series Routers	Cisco 7206 Router	1.3.6.1.4.1.9.1.108	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7200 Series Routers	Cisco 7206VXR Router with cevCpu7200Npeg2 and cevC7200CCPA	1.3.6.1.4.1.9.1.222	12.4.4-XD2[RME] —[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco Network Processor Modules (for Cisco 7206VSR)	NPE-G2	1.3.6.1.4.1.9.1.222	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Service Modules	Router RPM-XF	1.3.6.1.4.1.9.1.440	12.3(11)25[RME] 12.3(11)T4[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Service Modules	Router RPM	1.3.6.1.4.1.9.1.457	Cisco IOS 12.1(1)[RME] 12.2(15)MC1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	No	Not Supported	Not Supported
Cisco Service Modules	Router RPM-PR	1.3.6.1.4.1.9.1.199	—[RME] 12.1[RME]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	No	Not Supported	Not Supported
Cisco 7300 Series Routers	Cisco 7301 Router	1.3.6.1.4.1.9.1.476	12.2(11)YZ[RME] 12.2(15)B[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7300 Series Routers	Cisco 7304 Router	1.3.6.1.4.1.9.1.439	Cisco IOS 12.1[RME] —[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7300 Series Routers	Cisco Shared Port Adapter-2p-ge-7304 Router	—	12.2(25)S3[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes ²	Not Supported	Not Supported
Cisco 7300 Series Routers	Cisco Shared Port Adapter-4p-fe-7304 Router	—	12.2(25)S3[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes ²	Not Supported	Not Supported
Cisco 7400 Series Routers	Cisco 7401 Application Specific Router	1.3.6.1.4.1.9.1.403	Cisco IOS 12.2[RME] —[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7505 Router	1.3.6.1.4.1.9.1.48	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7506 Router	1.3.6.1.4.1.9.1.47	Cisco IOS 11.1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	NA	Yes	Yes	Not Supported	Not Supported
Cisco 7500 Series Routers	Cisco 7507 Router	1.3.6.1.4.1.9.1.45	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7507/4 Router	1.3.6.1.4.1.9.1.45	Cisco IOS 11.1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7500 Series Routers	Cisco 7507/4X2 Router	1.3.6.1.4.1.9.1.45	Cisco IOS 11.1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7500 Series Routers	Cisco 7507/8-MX Router	1.3.6.1.4.1.9.1.290	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7507/8X2-MX Router	1.3.6.1.4.1.9.1.290	Cisco IOS 11.1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	NA	Yes	Yes	Not Supported	Not Supported
Cisco 7500 Series Routers	Cisco 7513 Router	1.3.6.1.4.1.9.1.46	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0

Cisco 7500 Series Routers	Cisco 7513/4 Router	1.3.6.1.4.1.9.1.46	Cisco IOS 11.1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 7500 Series Routers	Cisco 7513/8-MX Router	1.3.6.1.4.1.9.1.289	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7513/8X2-MX Router	1.3.6.1.4.1.9.1.291	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7576 Router	1.3.6.1.4.1.9.1.204	Cisco IOS 11.1[RME] —[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	NA	Yes	Yes	Rtr7000	21.0
Cisco 7500 Series Routers	Cisco 7507 Router	1.3.6.1.4.1.9.1.288	Cisco IOS 11.1[RME] IOS 11.1[CM]	5.0	Yes	—	Yes	Yes	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr7000	21.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7603 Router	1.3.6.1.4.1.9.1.401	Cisco IOS 12.1[RME] —[CM]	5.0	Yes	Yes	Yes	Yes	Yes ⁶	Yes ⁶	3.0	Router	4.1	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7606 Router	1.3.6.1.4.1.9.1.402	Cisco IOS 12.1[RME] —[CM]	5.0	Yes	Yes	Yes	Yes	Yes ⁶	Yes ⁶	3.0	Router	4.1	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7613 IOS Router	1.3.6.1.4.1.9.1.528	Cisco IOS 12.1[RME] 12.2(17b) SXA2[CM]	5.0	Yes	Yes	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7603 Router	1.3.6.1.4.1.9.5.53	—[CM]	5.0	Yes	Yes	Yes	Yes	Yes ⁶	Yes ⁶	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000	9.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7606 Router	1.3.6.1.4.1.9.5.54	—[CM]	5.0	Yes	Yes	Yes	Yes	Yes ⁶	Yes ⁶	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000	9.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7609 Router	1.3.6.1.4.1.9.5.55	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000	9.0
Cisco 7600 Series Routers ^{7, 8}	Cisco 7609	1.3.6.1.4.1.9.5.44	—[CM]	5.0	Yes	Yes	Yes	Yes	Yes ⁶	Yes ⁶	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7600 Series Routers ^{7, 8}	Cisco 7613 Router	1.3.6.1.4.1.9.5.60	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000	9.0
Cisco 6400 Series Broadband Aggregators	Cisco 6400-NSP Broadband Aggregator	1.3.6.1.4.1.9.1.464 1.3.6.1.4.1.9.1.180 [DFM]	Cisco IOS 12.2(4)B5 [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 6400 Series Broadband Aggregators	Cisco 6400-NRP Broadband Aggregator	1.3.6.1.4.1.9.1.211	12.2 (2) B5[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 6400 Series Broadband Aggregators	Cisco 6400-NRP1 Broadband Aggregator	1.3.6.1.4.1.9.1.211	12.2 (2) B5[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 6400 Series Broadband Aggregators	Cisco 6400-NRP2 Broadband Aggregator	1.3.6.1.4.1.9.1.211	12.2 (4) B5 ⁴ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes ³	Not Supported	Not Supported
Cisco Catalyst 4000 Series Switches	Cisco Catalyst 4000 Switch	1.3.6.1.4.1.9.1.7	Cisco IOS 11.2(25)a [RME] IOS 11.0[CM]	5.0	Yes	—	Yes ⁹	Yes ⁵	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 4000 Series Switches	Cisco Catalyst 4000-M Switch	1.3.6.1.4.1.9.1.7	IOS 11.0[CM]	5.0	Yes	—	Yes ⁹	Yes ⁵	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Other Routers	Cisco 4500 Router	1.3.6.1.4.1.9.1.14	Cisco IOS 11.2(25)a [RME] IOS 11.0[CM]	5.0	Yes	—	Yes ⁹	Yes ⁵	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Other Routers	Cisco 4500-M Router	1.3.6.1.4.1.9.1.14	IOS 11.0[CM]	5.0	Yes	—	Yes ⁹	Yes ⁵	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Pro Series	Cisco Pro 761	1.3.6.1.4.1.9.1.88	—[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Pro Series	Cisco Pro751	1.3.6.1.4.1.9.1.76		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

[illegible]

Cisco Pro Series	Cisco Pro 2525	1.3.6.1.4.1.9.1.141	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3600 Series Multiservice Platforms	Cisco 3620 Multiservice Platform	1.3.6.1.4.1.9.1.123	__[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
CPA 3600 Series Routers	CPA 3640	1.3.6.1.4.1.9.1.124	__[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Pro Series	Cisco Pro 4500	1.3.6.1.4.1.9.1.66	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Pro Series	Cisco Pro 4700	1.3.6.1.4.1.9.1.142	Cisco IOS 11.2(25)a [RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Distributed Director	Cisco Distributed Director 4700M	1.3.6.1.4.1.9.1.50	Cisco IOS 11.2(25)a [RME] IOS 11.0[CM]	5.0	Yes	—	Yes ⁹	Yes ⁵	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MC3810 Multiservice Access Concentrators	Cisco MC3810-V Access Concentrator	1.3.6.1.4.1.9.1.157	Cisco IOS 11.0[RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MC3810 Multiservice Access Concentrators	Cisco MC3810-V3 Access Concentrator	1.3.6.1.4.1.9.1.286	Cisco IOS 12.1(4.0) [RME] __[CM]	5.0	Yes	—	—	—	Yes	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 3800 Series Integrated Services Routers	Cisco 3825 Integrated Services Router	1.3.6.1.4.1.9.1.543	12.3(11)T[RME] 12.3(11)T[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3800	8.0
Cisco 3800 Series Integrated Services Routers	Cisco 3845 Integrated Services Router	1.3.6.1.4.1.9.1.544	12.3(11)T[RME] 12.3(11)T[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3800	8.0
Cisco 3800 Series Integrated Services Routers	WIC-CABLE-D	—	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	NA	NA	Not Supported	Not Supported
Cisco 3700 Series MultiService Access Routers	Cisco 3725 MultiService Access Router	1.3.6.1.4.1.9.1.414	Cisco IOS 12.2(8) T [RME] __[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes ¹⁰	3.0	Router	4.1	Yes	Yes	Yes	Rtr3700	14.0
Cisco 3700 Series MultiService Access Routers	Cisco 3745 MultiService Access Router	1.3.6.1.4.1.9.1.436	Cisco IOS 12.2(8) T [RME] __[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes ¹⁰	3.0	Router	4.1	Yes	Yes	Yes	Rtr3700	14.0
Cisco 3600 Series MultiService Platforms	Cisco 3620-DC MultiService Platform	1.3.6.1.4.1.9.1.122	Cisco IOS 11.3[RME] IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3631-DC Central Office Access Router	1.3.6.1.4.1.9.1.425	Cisco IOS 12.2[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3640-DC MultiService Platform	1.3.6.1.4.1.9.1.110	Cisco IOS 12.2[RME] IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3640-RPS MultiService Platform	1.3.6.1.4.1.9.1.189	Cisco IOS 11.3[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3660 MultiService Platform	1.3.6.1.4.1.9.1.205	Cisco IOS 11.3[RME] IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3661-AC MultiService Platform	1.3.6.1.4.1.9.1.338	Cisco IOS 12.2[RME] __[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3661-DC MultiService Platform	1.3.6.1.4.1.9.1.339	Cisco IOS 12.2[RME] __[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3662-AC Telco Versatile DCN Access Platform	1.3.6.1.4.1.9.1.343	Cisco IOS 12.2[RME] __[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3662-AC-CO Telco Versatile DCN Access Platform	1.3.6.1.4.1.9.1.342	Cisco IOS 12.2 Telco [RME] __[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0

Cisco 3600 Series MultiService Platforms	Cisco 3662-DC Telco Versatile DCN Access Platform	1.3.6.1.4.1.9.1.340	Cisco IOS 12.2[RME]__[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3600 Series MultiService Platforms	Cisco 3662-DC-CO Telco Versatile DCN Access Platform	1.3.6.1.4.1.9.1.341	Cisco IOS 12.2 Telco [RME]__[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr3600	24.0
Cisco 3000 Series Mobile Access Routers	Cisco 3251 Mobile Access Router Card	1.3.6.1.4.1.9.1.479	12.2(11) YR[RME]__[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	MAR3200	7.0
Cisco 3000 Series Mobile Access Routers	Cisco 3220 Mobile Access Router Card	1.3.6.1.4.1.9.1.553	12.3.2 (XA)[RME]12.3(2) XA1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	MAR3200	7.0
Cisco 3000 Series Routers	Cisco 3000 Router	1.3.6.1.4.1.9.1.6	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3100 Series Routers	Cisco 3101 Router	1.3.6.1.4.1.9.1.32	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3100 Series Routers	Cisco 3102 Router	1.3.6.1.4.1.9.1.33	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3100 Series Routers	Cisco 3103 Router	1.3.6.1.4.1.9.1.34	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3000 Series Routers	Cisco 3104 Router	1.3.6.1.4.1.9.1.35	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3000 Series Routers	Cisco 3202 Router	1.3.6.1.4.1.9.1.36	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 3000 Series Routers	Cisco 3204 Router	1.3.6.1.4.1.9.1.37	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 2800 Series Integrated Services Routers	Cisco 2801 Integrated Services Router	1.3.6.1.4.1.9.1.619	12.3(8)T4[RME]12.3(8)T4[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2800	8.0
High-Speed WAN Interface Card for 1800/2800/3800 Series	WIC-CABLE1-D	—	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 2800 Series Integrated Services Routers	Cisco 2811 Integrated Services Router	1.3.6.1.4.1.9.1.576	12.3(8)T4[RME]12.3(8)T4[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2800	8.0
Cisco 2800 Series Integrated Services	Cisco 2821 Integrated Services Router	1.3.6.1.4.1.9.1.577	12.3(8)T4[RME]12.3(8)T4[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2800	8.0
Cisco 2800 Series Integrated Services	Cisco 2851 Integrated Services Router	1.3.6.1.4.1.9.1.578	12.3(8)T4[RME]12.3(8)T4[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2800	8.0
Cisco 2800 Series Integrated Services	WIC-CABLE-D	—	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	NA	NA	Not Supported	Not Supported
Cisco 2600 Series MultiService Platforms	Cisco 2610 MultiService Platform	1.3.6.1.4.1.9.1.185	Cisco IOS 11.3[RME]IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2611 MultiService Platform	1.3.6.1.4.1.9.1.186	Cisco IOS 11.3[RME]IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2612 MultiService Platform	1.3.6.1.4.1.9.1.187	Cisco IOS 11.3[RME]IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2613 MultiService Platform	1.3.6.1.4.1.9.1.195	Cisco IOS 11.3[RME]IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2620 MultiService Platform	1.3.6.1.4.1.9.1.208	Cisco IOS 11.3[RME]IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2621 MultiService Platform	1.3.6.1.4.1.9.1.209	Cisco IOS 11.3[RME]IOS 11.3[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2650 MultiService Platform	1.3.6.1.4.1.9.1.319	Cisco IOS 11.3[RME]__[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0
Cisco 2600 Series MultiService Platforms	Cisco 2651 MultiService Platform	1.3.6.1.4.1.9.1.320	Cisco IOS 11.3[RME]__[CM]	5.0	Yes	—	—	No	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2600	27.0

[illegible]

Cisco 2600 Series MultiService Platforms	Cisco 2651XM-RPS MultiService Platform	1.3.6.1.4.1.9.1.471	Cisco IOS 12.1 (14), 12.2(8)T1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco IAD2400 Series Integrated Access Devices	Cisco IAD2420 Integrated Access Device	1.3.6.1.4.1.9.1.362	Cisco IOS 12.15 [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	IAD2400	6.0
Cisco IAD2400 Series Integrated Access Devices	Cisco IAD2430 Integrated Access Device	1.3.6.1.4.1.9.1.545	122-15.ZJ[RME] 12.2(15)ZJ3[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	IAD2400	6.0
Cisco IAD2400 Series Integrated Access Devices	Cisco IAD2431-8FXS Integrated Access Device	1.3.6.1.4.1.9.1.546	12.2(15)ZJ3[RME] 12.3(7)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	IAD2400	6.0
Cisco IAD2400 Series Integrated Access Devices	Cisco IAD2431-16FXS Integrated Access Device	1.3.6.1.4.1.9.1.547	12.2(15)ZJ3[RME] 12.3(7)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	IAD2400	6.0
Cisco IAD2400 Series Integrated Access Devices	Cisco IAD2431-1T1E1 Integrated Access Device	1.3.6.1.4.1.9.1.548	12.2(15)ZJ3[RME] 12.3(7)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	IAD2400	6.0
Cisco IAD2400 Series Integrated Access Devices	Cisco IAD2431-24FXS Integrated Access Device	1.3.6.1.4.1.9.1.549	12.2(15)ZJ3[RME] 12.3(7)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	IAD2400	6.0
Cisco 2500 Series Routers	Cisco 2500 Router	1.3.6.1.4.1.9.1.13	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco 2501 Router	1.3.6.1.4.1.9.1.17	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	2500-2525	—	IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco Access ProEC	1.3.6.1.4.1.9.1.39	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco 2501CF Router	1.3.6.1.4.1.9.1.165	Cisco IOS 11.0[RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2501LF Router	1.3.6.1.4.1.9.1.166	Cisco IOS 11.0[RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2502 Router	1.3.6.1.4.1.9.1.18	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2502LF Router	1.3.6.1.4.1.9.1.167	Cisco IOS 11.0[RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2503 Router	1.3.6.1.4.1.9.1.19	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2504 Router	1.3.6.1.4.1.9.1.20	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2505 Router	1.3.6.1.4.1.9.1.21	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2506 Router	1.3.6.1.4.1.9.1.22	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco 2507 Router	1.3.6.1.4.1.9.1.23	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2508 Router	1.3.6.1.4.1.9.1.24	Cisco IOS 11.0[RME] —[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported

Cisco 2500 Series Routers	Cisco 2509 Router	1.3.6.1.4.1.9.1.25	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2511 Router	1.3.6.1.4.1.9.1.27	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2513 Router	1.3.6.1.4.1.9.1.29	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2514 Router	1.3.6.1.4.1.9.1.30	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2515 Router	1.3.6.1.4.1.9.1.31	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2516 Router	1.3.6.1.4.1.9.1.42	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2517 Router	1.3.6.1.4.1.9.1.67	Cisco IOS 11.0[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco 2518 Router	1.3.6.1.4.1.9.1.68	Cisco IOS 11.0[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco 2519 Router	1.3.6.1.4.1.9.1.69	Cisco IOS 11.0[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 2500 Series Routers	Cisco 2520 Router	1.3.6.1.4.1.9.1.70	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2521 Router	1.3.6.1.4.1.9.1.71	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2522 Router	1.3.6.1.4.1.9.1.72	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2523 Router	1.3.6.1.4.1.9.1.73	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2524 Router	1.3.6.1.4.1.9.1.74	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2500 Series Routers	Cisco 2525 Router	1.3.6.1.4.1.9.1.75	Cisco IOS 11.0[RME] __[CM]	5.0	—	—	—	—	—	—	3.0	Router	4.1	Yes	Yes	Yes	Rtr2500	2.0
Cisco 2000 Series Routers	Cisco 2000 Router	1.3.6.1.4.1.9.1.10		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 2000 Series Routers	Cisco 2102 Router	1.3.6.1.4.1.9.1.15	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 2000 Series Routers	Cisco 2202 Router	1.3.6.1.4.1.9.1.16	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco MWR1900 Mobile Wireless Routers	Cisco MWR1900 Mobile Wireless Edge Router	1.3.6.1.4.1.9.1.398	Cisco IOS 12.2[RME] 12.2(15)MC1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Mwr1900	5.0
Cisco MWR1900 Mobile Wireless Routers	Cisco MWR1941-DC Mobile Wireless Edge Router	1.3.6.1.4.1.9.1.520	12.2(8)MC2c[RME] 12.2(15)MC1a[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Mwr1900	5.0
Cisco MWR1900 Mobile Wireless Routers	Cisco MWR 1941-DC-A Mobile Wireless Edge Router	1.3.6.1.4.1.9.1.732	12.4(9)MR	5.0.1	Yes	NA	NA	NA	NA	Yes	3.0.1	Router	4.1 ¹³	Yes	Yes	Yes	Mwr1900	5.0

Cisco 1800 Series Routers	Cisco 1801 Integrated Services Router	1.3.6.1.4.1.9.1.638	12.3(14)YT[RME] 12.3(14)YT[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1802 Integrated Services Router	1.3.6.1.4.1.9.1.639	12.3(14)YT[RME] 12.3(14)YT[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1803 Integrated Services Router	1.3.6.1.4.1.9.1.640	12.3(14)YT[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1811 Integrated Services Router	1.3.6.1.4.1.9.1.641	12.3(8)YH[RME] 12.3(8)YH[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1812 Integrated Services Router	1.3.6.1.4.1.9.1.642	12.3(8)YH[RME] 12.3(8)YH[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1841 Integrated Services Router	1.3.6.1.4.1.9.1.620	12.3(8)T4 [RME] 12.3(8)T4[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1861 Integrated Services Router	1.3.6.1.4.1.9.1.902	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1861 Integrated Services Router	1.3.6.1.4.1.9.1.903	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1861 Integrated Services Router	1.3.6.1.4.1.9.1.904	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr1800	6.0
Cisco 1800 Series Routers	Cisco 1861 Integrated Services Router	1.3.6.1.4.1.9.1.905	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Rtr1800	6.0
Cisco 1800 Series Routers	WIC-CABLE-D	—	NA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	NA	NA	Not Supported	Not Supported
Cisco 1700 Series Modular Access Routers	Cisco 1701 ADSL Security Access Router	1.3.6.1.4.1.9.1.550	Cisco IOS 12.0[RME] 12.2(7r) XM1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1710 Security Access Router	1.3.6.1.4.1.9.1.200	12.2(8)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1711 Security Access Router	1.3.6.1.4.1.9.1.538	Cisco IOS 12.0[RME] 12.2(7r) XM1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1712 Security Access Router	1.3.6.1.4.1.9.1.539	Cisco IOS 12.0[RME] 12.2(7r) XM1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1750 Modular Access Router	1.3.6.1.4.1.9.1.216	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1751 Modular Access Router	1.3.6.1.4.1.9.1.326	Cisco IOS 12.0[RME] 12.2(8)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	1751—Digital voice capable Cisco 1700 platform with 2 WIC/ VIC slots and 1 VIC-only slot	1.3.6.1.4.1.9.1.326	Cisco IOS 12.0[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 1700 Series Modular Access Routers	Cisco 1720-VPN Modular Access Router	1.3.6.1.4.1.9.1.201	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1721 Modular Access Router	1.3.6.1.4.1.9.1.444	Cisco IOS 12.2(8) T [RME] 12.2(8)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1700 Series Modular Access Routers	Cisco 1760-ADSL Modular Access Router	1.3.6.1.4.1.9.1.416	Cisco IOS 11.2[RME] 12.2(8)T[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1700	10.2
Cisco 1400 Series Routers	Cisco 1401 Router	1.3.6.1.4.1.9.1.206	Cisco IOS 12.0[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1400	2.0
Cisco 1400 Series Routers	Cisco 1407 Router	1.3.6.1.4.1.9.1.249	__[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

Cisco 1400 Series Routers	Cisco 1417 Router	1.3.6.1.4.1.9.1.250	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Rtr1400	2.0
Cisco 1600 Series Routers	Cisco 1601 Router	1.3.6.1.4.1.9.1.113	Cisco IOS 11.2[RME] IOS 11.2[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1600	2.0
Cisco 1600 Series Routers	Cisco 1602 Router	1.3.6.1.4.1.9.1.114	Cisco IOS 11.2[RME] IOS 11.2[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1600	2.0
Cisco 1600 Series Routers	Cisco 1603 Router	1.3.6.1.4.1.9.1.115	Cisco IOS 11.2[RME] IOS 11.2[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1600	2.0
Cisco 1600 Series Routers	Cisco 1604 Router	1.3.6.1.4.1.9.1.116	Cisco IOS 11.2[RME] IOS 11.2[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1600	2.0
Cisco 1600 Series Routers	Cisco 1605 Router	1.3.6.1.4.1.9.1.172	Cisco IOS 11.2[RME] IOS 11.2[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr1600	2.0
Cisco 1000 Series Routers	Cisco 1000 Router	1.3.6.1.4.1.9.1.40	IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1000 Series Routers	Cisco 1003 Router	1.3.6.1.4.1.9.1.41	IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1000 Series Routers	Cisco 1004 Router	1.3.6.1.4.1.9.1.44	IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1000 Series Routers	Cisco 1005 Router	1.3.6.1.4.1.9.1.49	IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1000 Series Routers	Cisco 1020 Router	1.3.6.1.4.1.9.1.43	IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 800 Series Routers ¹¹	Cisco 801 ISDN Router	1.3.6.1.4.1.9.1.212	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 802 ISDN Router	1.3.6.1.4.1.9.1.213	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 803 ISDN Router	1.3.6.1.4.1.9.1.214	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 804 ISDN Router	1.3.6.1.4.1.9.1.215	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 804J ISDN Router	1.3.6.1.4.1.9.1.296	12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 800 Series Routers ¹¹	Cisco 805 Serial Router	1.3.6.1.4.1.9.1.245	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	No	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 811 ISDN Router	1.3.6.1.4.1.9.1.395	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 811 Router	1.3.6.1.4.1.9.1.295	12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 800 Series Routers ¹¹	Cisco 813 ISDN Router	1.3.6.1.4.1.9.1.396	12.2.11T [RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 811 ISDN Router	—	12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 800 Series Routers ¹¹	Cisco 815 Integrated Services Router	1.3.6.1.4.1.9.1.733	12.4.6-XE[CM]	5.0	Yes	NA	NA	—	NA	Yes	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 826 ADSL Router	1.3.6.1.4.1.9.1.321	Cisco IOS 12.0[RME] __[CM]	5.0	Yes	—	—	—	Yes	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 800 Series Routers ¹¹	Cisco 826 ADSL Router	1.3.6.1.4.1.9.1.322	12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Rtr800	11.0

Cisco 800 Series Routers ¹¹	Cisco 827-4V ADSL Router	1.3.6.1.4.1.9.1.270	Cisco IOS 12.0[RME] __[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 827 ADSL Router	1.3.6.1.4.1.9.1.284	__[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 827-H ADSL Router	1.3.6.1.4.1.9.1.446	12.2(4)YA[RME] 12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 806 Broadband Router	1.3.6.1.4.1.9.1.384	12.2 (1) XE2[RME] 12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 828 G.SHDSL Router	1.3.6.1.4.1.9.1.382	12.2 (1) XE2[RME] 12.2(4)YA[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 831 Ethernet Broadband Router	1.3.6.1.4.1.9.1.497	12.2(8)YN[RME] 12.2(8r)YN[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 836 ADSL over ISDN Broadband Router	1.3.6.1.4.1.9.1.499	12.2(11)YV[RME] 12.2(11) YV[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 837 ADSL Broadband Router	1.3.6.1.4.1.9.1.495	12.2(8)YN[RME] 12.2(8r)YN[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 857 Integrated Services Router	1.3.6.1.4.1.9.1.567	12.3(8)Y11[RME] 12.3(8)Y11[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 877 Integrated Services Router	1.3.6.1.4.1.9.1.569	12.3(8)Y11[RME] 12.3(8)Y11[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 851 Integrated Services Router	1.3.6.1.4.1.9.1.566	12.3(8)Y11[RME] 12.4(4)T[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 871 Integrated Services Router	1.3.6.1.4.1.9.1.571	12.3(8)Y11[RME] 12.3(8)[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 876 Integrated Services Router	1.3.6.1.4.1.9.1.568	12.3(8)Y11[RME] 12.3(14)YT1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Cisco 800 Series Routers ¹¹	Cisco 878 Integrated Services Router	1.3.6.1.4.1.9.1.570	12.3(8)Y11[RME] 12.3(8)Y12[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Rtr800	11.0
Other Routers	Cisco IGS-L, IGS-R	1.3.6.1.4.1.9.1.5	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Other Routers	Cisco Trouter	1.3.6.1.4.1.9.1.3	__[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco SOHO 70 Series Routers	Cisco SOHO 71 Broadband Router	1.3.6.1.4.1.9.1.463	—[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco SOHO 70 Series Routers	Cisco SOHO 76 ADSL Router	1.3.6.1.4.1.9.1.354	—[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	SOHO70	2.0
Cisco SOHO 70 Series Routers	Cisco SOHO 77 ADSL Router	1.3.6.1.4.1.9.1.353	—[RME] __[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco SOHO 70 Series Routers	Cisco SOHO 77H ADSL Router	1.3.6.1.4.1.9.1.447	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco SOHO 70 Series Routers	Cisco SOHO 78 G. SHDSL Router	1.3.6.1.4.1.9.1.383	12.2.1-XE2[RME] 12.2.1-XE2[CM]	5.0	Yes ¹¹	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	SOHO70	2.0
Cisco SOHO 90 Series Secure Broadband Routers	Cisco SOHO 91 Ethernet Broadband Router	1.3.6.1.4.1.9.1.498	12.2.8 YN[RME] 12.2(8) YN[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	SOHO	3.0
Cisco SOHO 90 Series Secure Broadband Routers	Cisco SOHO 96 ADSL over ISDN Secure Broadband Routers	1.3.6.1.4.1.9.1.500	12.2.11 YV[RME] 12.2(11) YV[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	SOHO	3.0
Cisco SOHO 90 Series Secure Broadband Routers	Cisco SOHO 97 ADSL Broadband Router	1.3.6.1.4.1.9.1.496	12.2.8 YN[RME] 12.2(8) YN[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	4.1	Yes	Yes	Yes	SOHO	3.0

Cisco Small Business 100 Series Routers	Cisco Small Business 101 Series Routers	1.3.6.1.4.1.9.1.627	12.3(8)YG[RME] 12.3(8)YG[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Small Business 100 Series Routers	Cisco Small Business 106 Series Routers	1.3.6.1.4.1.9.1.628	12.3(8)YG[RME] 12.3(8)YG[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Small Business 100 Series Routers	Cisco Small Business 107 Series Routers	1.3.6.1.4.1.9.1.629	12.3(8)YG[RME] 12.3(8)YG[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 3200 Series Mobile Access Routers	Cisco 3270 Rugged Router	1.3.6.1.4.1.9.1.690	12.4.6-XE[RME] 12.4[CM]	5.0	Yes	NA	NA	—	NA	Yes	3.0	Router	4.1	Yes	Yes	Yes	MAR3200	7.0
Cisco 700 Series ISDN Access Routers	Cisco 751 ISDN Access Router	1.3.6.1.4.1.9.1.81	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 752 ISDN Access Router	1.3.6.1.4.1.9.1.82	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 753 ISDN Access Router	1.3.6.1.4.1.9.1.83	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 761 ISDN Access Router	1.3.6.1.4.1.9.1.98	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 762 ISDN Access Router	1.3.6.1.4.1.9.1.99	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 765 ISDN Access Router	1.3.6.1.4.1.9.1.102	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 766 ISDN Access Router	1.3.6.1.4.1.9.1.103	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 771 ISDN Access Router	1.3.6.1.4.1.9.1.126	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 772 ISDN Access Router	1.3.6.1.4.1.9.1.127	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 775 ISDN Access Router	1.3.6.1.4.1.9.1.128	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 700 Series ISDN Access Routers	Cisco 766 ISDN Access Router	1.3.6.1.4.1.9.1.129	4.1[CM]	5.0	Yes	—	—	—	Yes ⁵	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Carrier Routing System	Cisco CRS-18-Slot Single-Shelf System	1.3.6.1.4.1.9.1.643	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

1. SIP601 card support is tested in this version only.
2. Supported through parent device.
3. Software Management: Support for NRP2 requires IP address of the parent NSP with proper Telnet credentials.
4. Software Management: Image library import from device, baseline, and synchronize not supported.
5. Cisco routers supply the User Tracking application with ARP Table information.
6. Support for Analog Voice Gateway (FXS/FXO port) provided.
7. Supports Cisco IOS and CatIOS.
8. All Optical Services Routers.
9. Provided only on the 4500 and 4700 series.
10. Support for Analog Voice Gateway (FXS/FXO port) provided.
11. Since this device (for Campus Manager) does not support CDP MIB, Topology is partially supported. However, because of this, the device cannot be used as a seed device and cannot discover other devices that are further behind this device.
12. Support for IP Phones is also provided.
13. Support for this specific device is available at: <http://cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>

Table 7: Security and VPN Devices

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
-------------	-------------	-------------	------------------	------------------------	---------------	----------------	----------------	---------------	--------------------	--------------------	-------------------------	--------------------	-------------------------	-----------------	-------------------	---------------------	-------------------	----------------------

Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall	1.3.6.1.4.1.9.1.227	6.1(1) ³ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 501 Firewall	1.3.6.1.4.1.9.1.417	6.1(1) ⁴ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall501 Proxy	1.3.6.1.4.1.9.1.417	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 506 Firewall	1.3.6.1.4.1.9.1.389	6.1(1) ⁴ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 515 Firewall	1.3.6.1.4.1.9.1.390	6.1(1) ³ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall515 Proxy	1.3.6.1.4.1.9.1.390	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 520 Firewall	1.3.6.1.4.1.9.1.391	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 525 Firewall	1.3.6.1.4.1.9.1.392	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall535 Proxy	1.3.6.1.4.1.9.1.393	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 535 Firewall ⁴	1.3.6.1.4.1.9.1.393	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 506E Firewall	1.3.6.1.4.1.9.1.450	6.1(1) ³ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall506E Proxy	1.3.6.1.4.1.9.1.450	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX 515E Firewall	1.3.6.1.4.1.9.1.451	6.1(1) ⁴ [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Pix	5.1
Cisco PIX 500 Series Firewalls ^{1, 2}	Cisco PIX515E	1.3.6.1.4.1.9.1.451	7.2(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall515E Proxy	1.3.6.1.4.1.9.1.451	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall Proxy	1.3.6.1.4.1.9.1.227	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall520 Proxy	1.3.6.1.4.1.9.1.39	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Firewalls ^{1, 2}	PIX Firewall525 Proxy	1.3.6.1.4.1.9.1.392	6.1(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco PIX 500 Series Security Appliances	Cisco PIX 515E Firewall (Multiple Security Contexts) ⁶	1.3.6.1.4.1.9.1.677	7.0(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ⁷	Yes	Yes	Yes	Not Supported	Not Supported
Other Switches and Hubs	CPW1220i	1.3.6.1.4.1.9.5.30	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco VPN 3000 Series Concentrators	Cisco VPN 30xx Concentrator	1.3.6.1.4.1.3076.1.2.1.1.2.1	—[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes ⁸	Yes	VPN3000	5.0

Cisco VPN 3000 Series Concentrators	C3015 C3030 C3060 C3080	1.3.6.1.4.1.3076.1.2.1.1.1.2	__[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes ⁵	Yes	Not Supported	Not Supported
Cisco VPN 3000 Series Concentrators	Cisco VPN 3000 Concentrator	1.3.6.1.4.1.3076.1.2.1.1.1.2	__	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	VPN3000	5.0
Cisco VPN 3000 Series Concentrators	C3015 C3030 C3060 C3080	1.3.6.1.4.1.3076.1.2.1.1.1.1	__[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes ⁵	Yes	VPN3000	5.0
Cisco VPN 3000 Series Concentrators	VPN 3002 Hardware Client	1.3.6.1.4.1.3076.1.2.1.1.3.1	3.0.2[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes ⁵	Yes	Not Supported	Not Supported
Cisco VPN 3000 Series Concentrators	Cisco VPN 3002 Concentrator	1.3.6.1.4.1.3076.1.2.1.1.3.1	__	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	VPN3000	5.0
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA 5520 Adaptive Security Appliance	1.3.6.1.4.1.9.1.670	7.2(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA 5520 Adaptive Security Appliance Security Context ⁶	1.3.6.1.4.1.9.1.671	7.2(1)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5510 Adaptive Security Appliance (Multiple Security Contexts) ⁶	1.3.6.1.4.1.9.1.773	7.2(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5510 Adaptive Security Appliance	1.3.6.1.4.1.9.1.669	7.2(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5505 Adaptive Security Appliance	1.3.6.1.4.1.9.1.745	7.2(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5540 Adaptive Security Appliance (Multiple Security Contexts) ⁶	1.3.6.1.4.1.9.1.673	7.0(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5540 Adaptive Security Appliance	1.3.6.1.4.1.9.1.672	7.0(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5550 Adaptive Security Appliance (Multiple Security Contexts) ⁶	1.3.6.1.4.1.9.1.763	7.2(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported
Cisco ASA 5500 Series Adaptive Security Appliances	Cisco ASA-5550 Adaptive Security Appliance	1.3.6.1.4.1.9.1.753	7.2(1)	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0.1	Firewall	4.1 ²	Yes	Yes	Yes	Not Supported	Not Supported

1. These devices can also be managed through an Auto Update Server.

2. NetConfig support is not available if the software version 7.0 or above is running on PIX Firewall devices.

3. Check product documentation of individual PIX Firewall device for supported software versions.

4. PIX Firewall 535 is not supported by NetConfig.

5. Cisco VPN 3000 and Cisco VPN 3002 are not supported by NetConfig.

6. In case of RME, after adding the device into the DCR, and whenever the device is switched between the Single and Multi Security Context Modes, the device should be deleted and added again into the DCR. This is due to change in the sysobjid and also because the number of configurations for the device varies when there is switching between the modes.

7. Support for this specific device is available at: <http://cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>

Table 8: Switches

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco SN 5400 Series Storage Routers	Cisco SN 5428 Storage Router	1.3.6.1.4.1.9.1.475	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	SN5420	4.0
Cisco SN 5400 Series Storage Routers	Cisco SN 5420 Storage Router	1.3.6.1.4.1.9.1.407	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	SN5420	4.0
Cisco Catalyst Blade Switch 3000 Series	Cisco Blade Switch WS-3030 for Dell	1.3.6.1.4.1.9.1.749	12.2(25)SEE[RME] —[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	CBS30x0	2.0
Cisco Catalyst Blade Switch 3000 Series	Cisco Blade Switch WS-3040 for FSC	1.3.6.1.4.1.9.1.784	12.2(25)SEF2[RME] 12.2(25)[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	CBS30x0	2.0
Cisco Catalyst Blade Switch 3000 Series	Cisco Blade Switch WS-3020 for HPQ	1.3.6.1.4.1.9.1.748	12.2(25)SEF1[RME] —[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	NA	4.1	Yes	Yes	Yes	CBS30x0	2.0
Cisco MDS 9000 Series Multilayer Switches	Cisco DS-X9124 with MDS 9509 Multilayer Director Switch	1.3.6.1.4.1.9.12.3.1.3.376	1.0.1[RME] SAN OS 1.2.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Switches	Cisco MDS 9509 Multilayer Director Switch	1.3.6.1.4.1.9.12.3.1.3.376	3.0.1[RME] SAN OS 1.2.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Switches	Cisco MDS 9120 Multilayer Fabric Switch	1.3.6.1.4.1.9.12.3.1.3.414	1.2[RME] SAN-OS 1.2[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Switches	Cisco MDS 9140 Multilayer Fabric Switch	1.3.6.1.4.1.9.12.3.1.3.411	1.2[RME] SAN-OS 1.2[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Switches	Cisco MDS 9216 Multilayer Fabric Switch	1.3.6.1.4.1.9.12.3.1.3.380	1.0.1[RME] SAN-OS 1.0.5[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Switches	Cisco MDS 9216A Multilayer Fabric Switch	1.3.6.1.4.1.9.12.3.1.3.442	2.0(2b)[RME] 3.0[CM]	5.0	Yes	—	—	—	—	Yes	3.0	NA	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco MDS 9000 Series Multilayer Switches	Cisco MDS 9506 Multilayer Director Switch	1.3.6.1.4.1.9.12.3.1.3.375	1.1[RME] 1.1[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 8500 Series Multiservice Switch Routers (MSR)	Cisco Catalyst 8510 MSR Switch	1.3.6.1.4.1.9.1.230	Cisco IOS 11.2 (8.0.1) FWA4.1[RME] IOS 11.2 (8.0.1) FWA4.1[CM]	5.0	Yes	—	Yes	Yes	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco Catalyst 8500 Series Multiservice Switch Routers (MSR)	Cisco Catalyst 8515 MSR Switch	1.3.6.1.4.1.9.1.231	Cisco IOS 11.2 (8.0.1) FWA4.1[RME]	5.0	Yes	—	Yes	Yes	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco Catalyst 8500 Series Multiservice Switch Routers (MSR)	Cisco Catalyst 8540 MSR Switch	1.3.6.1.4.1.9.1.202	Cisco IOS 11.2 (8.0.1) FWA4.1[RME] IOS 11.2 (8.0.1) FWA4.1[CM]	5.0	Yes	—	Yes	Yes	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2

Cisco Catalyst 8500 Series Campus Switch Routers (CSR)	Cisco Catalyst 8510 CSR Switch	1.3.6.1.4.1.9.1.190	Cisco IOS 11.3[RME] IOS 11.3[CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco Catalyst 8500 Series Campus Switch Routers (CSR)	Cisco Catalyst 8515 CSR Switch	1.3.6.1.4.1.9.1.196	Cisco IOS 11.3[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco Catalyst 8500 Series Campus Switch Routers (CSR)	Cisco Catalyst 8540 CSR Switch	1.3.6.1.4.1.9.1.203	Cisco IOS 11.3[RME] IOS11.3[CM]	3.0	Yes	—	—	—	Yes ²	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco BPX 8600 Series Switches	Cisco BPX 8620 Switch	1.3.6.1.4.1.9.1.237	8.4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco BPX 8600 Series Switches	Cisco BPX 8650 Switch	1.3.6.1.4.1.9.1.238	8.4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco IGX 8600 Series Switches	Cisco IGX 8410 Multiservice Switch	1.3.6.1.4.1.9.1.232	8.4[RME] —[CM]	5.0	Yes	—	—	No	—	No	3.0	Switch	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco IGX 8600 Series Switches	Cisco IGX 8420 Multiservice Switch	1.3.6.1.4.1.9.1.233	8.4[RME] —[CM]	5.0	Yes	—	—	No	—	No	3.0	Switch	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco IGX 8600 Series Switches	Cisco IGX 8430 Multiservice Switch	1.3.6.1.4.1.9.1.234	8.4[RME] —[CM]	5.0	Yes	—	—	No	—	No	3.0	Switch	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco MGX 8200 Series Edge Concentrators	Cisco MGX 8220 Edge Concentrator	1.3.6.1.4.1.351.110	8.4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco MGX 8800 Series Switches	Cisco MGX 8850 Voice Gateway	1.3.6.1.4.1.351.130	8.4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco MGX 8800 Series Switches	Cisco MGX 8850 Multiservice Switch	1.3.6.1.4.1.9.1.228	8.4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco MGX 8800 Series Switches	Cisco MGX 8830 ATM Multiservice Switch	1.3.6.1.4.1.9.1.229	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco BPX 8600 Series Switches	Cisco BPX 8680IP,ATM Multiservice Switch	1.3.6.1.4.1.9.1.239	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco BPX 8600 Series Switches	Cisco IPX 8xxx (IPX/IGX/BPX) Switch	1.3.6.1.4.1.351.100	8.4[RME] —[CM]	5.0	Yes	—	—	No	—	No	Not Supported	Not Supported	4.1	Yes	No	Yes	Not Supported	Not Supported
Cisco Catalyst 6000 Series Switches	Cisco Catalyst 6000 Switch	1.3.6.1.4.1.9.1.241		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 6000 Series Switches	Cisco Catalyst 6200 Switch	1.3.6.1.4.1.9.1.192		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 6000 Series IP DSL Switches	Cisco 6015 IP DSL Switch	1.3.6.1.4.1.9.1.299	12.1 (4) DA[RME] 12.2 (12) DA5[CM]	5.0	Yes	—	—	—	No	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported

Cisco 6000 Series IP DSL Switches	Cisco 6160 IP DSL Switch	1.3.6.1.4.1.9.1.297	12.1 (4) DA[RME] 12.2 (12) DA5[CM]	5.0	Yes	—	—	—	No	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco 6000 Series IP DSL Switches	Cisco 6260 IP DSL Switch	1.3.6.1.4.1.9.1.253	12.1 (4) DA[RME] 12.2 (12) DA5[CM]	5.0	Yes	—	—	—	No	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst WS-C6513 Switch	1.3.6.1.4.1.9.5.50	6.2(2)[RME] _ [CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6000 Series Switches	Cisco Catalyst 6006 Switch	1.3.6.1.4.1.9.5.38	5.1(1) CSX[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6000 Series Switches	Cisco Catalyst 6006IOS Switch	1.3.6.1.4.1.9.1.280	5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000IOS	29.0
Cisco Catalyst 6000 Series Switches	Cisco Catalyst 6009 Switch	1.3.6.1.4.1.9.5.39	5.1(1) CSX[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst WS-C6503 Switch	1.3.6.1.4.1.9.5.56	7.4(3)[RME] CatOS 7.5(1)[CM]	5.0	Yes	Yes	—	—	Yes ⁸	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst WS-C6506 Switch	1.3.6.1.4.1.9.5.45	5.1(1) CSX[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst SUP32-10GE-3B with WS-6506-E Switch	1.3.6.1.4.1.9.5.45	8.4.1[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6506 Switch with 6 slots	1.3.6.1.4.1.9.1.282	5.1(1) CSX[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6506 Switch	1.3.6.1.4.1.9.1.282	12.0.17.SR[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509-NEB Switch	1.3.6.1.4.1.9.1.310	Cisco IOS 12.0[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Router	4.1	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509-NEB Switch	1.3.6.1.4.1.9.5.47	5.1(1)[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509-NEB-A Switch	1.3.6.1.4.1.9.5.61	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509 Switch	1.3.6.1.4.1.9.5.44	8.1(1)[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509 Switch with 9 slots	1.3.6.1.4.1.9.1.283	Cisco IOS 12.0[RME] 5.1(1)CSX[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst SUP32-10GE-3B with WS-C6509 Switch	1.3.6.1.4.1.9.1.283	12.2.18-SXF[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509-E Switch	1.3.6.1.4.1.9.1.283	12.2(17d)SXB[RME] 12.2(17d)SXB[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6000 Series Switches	Cisco Catalyst 6009-IOS Switch	1.3.6.1.4.1.9.1.281	_ [CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Cat6000IOS	29.0

Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6513 Switch (SUP 720)	1.3.6.1.4.1.9.1.400	Cisco IOS 12.1[RME] _ [CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Network Modules	Cisco Catalyst 6000 Series Switches MSM	1.3.6.1.4.1.9.1.256	_ [RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	MSFC	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6503 Switch ⁸	1.3.6.1.4.1.9.1.449	IOS 12.1(11b)E[CM] Cisco IOS 12.1(11b)E [RME]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Network Modules	Cisco Catalyst 6000 Series Supervisor Module with MSFC	1.3.6.1.4.1.9.1.258	Cisco IOS 12.0[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	MSFC	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Network Modules	Cisco Catalyst 6000 Multilayer Switch Feature Card MSFC2	1.3.6.1.4.1.9.1.301	Cisco IOS 12.0[RME] _ [CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	MSFC	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Network Modules	Cisco Catalyst 6506 and 6504-E with MSFC2A	1.3.6.1.4.1.9.1.301	12.2.17d-SXB10[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	MSFC	4.1	Yes	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Network Modules	Cisco Catalyst 6000 Multilayer Switch Feature Card MSFC3	1.3.6.1.4.1.9.1.557	12.2(14)SX2[RME] _ [CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	MSFC	4.1	Yes	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Services Modules	Cisco Catalyst 6500 Series SSL Services Module	1.3.6.1.4.1.9.1.554	2.1(0.38)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst 6509-NEB-A Switch	1.3.6.1.4.1.9.1.534	12.1(20) E3[RME] 12.1(20) E3[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Services Modules	Cisco Catalyst 6500 Series Wireless LAN Services Module	1.3.6.1.4.1.9.1.599	c6svc-wlan-k9w7.2.1(1) [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500 Series Switches	Cisco Catalyst SUP32-8GE with WS-6504-E Switch	1.3.6.1.4.1.9.5.64	8.4.1[RME] 8.4(1)[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat6000	9.0
Cisco Catalyst 6500 Series Switches	Cisco Catalyst SUP720-3B, WS-SUP32-GE-3B with 6504-E Switch	1.3.6.1.4.1.9.1.657	12.2(18)SXF[RME] 12.2(18)[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco Services Modules	Cisco Catalyst 6500 Series Firewall Services Module Security Context ³	1.3.6.1.4.1.9.1.674	3.1(3)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Firewall	4.1	Yes	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 6500/7600 Series Supervisor Modules	SUP 720-3BXL	—	12.2(17a)SXA[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 5000 Series Switches	Cisco Catalyst 5000 Switch	1.3.6.1.4.1.9.5.7	2.4.3[RME] 2.4.3[CM]	5.0	Yes ⁴	Yes ⁴	Yes	Yes ⁴	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat5000	2.0
Cisco Catalyst 5000 Series Switches	Cisco Catalyst 5002 Switch	1.3.6.1.4.1.9.5.29	2.4.3[RME] 2.4.3[CM]	5.0	Yes ⁴	Yes ⁴	Yes	Yes ⁴	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat5000	2.0
Cisco Catalyst 5500 Series Switches	Cisco Catalyst 5500 Switch	1.3.6.1.4.1.9.5.17	2.4.3[RME] 2.4.3[CM]	5.0	Yes ⁴	Yes ⁴	Yes	Yes ⁴	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat5500	2.0
Cisco Catalyst 5500 Series Switches	Cisco Catalyst 5505 Switch	1.3.6.1.4.1.9.5.34	2.4.3[RME] 2.4.3[CM]	5.0	Yes ⁴	Yes ⁴	Yes	Yes ⁴	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat5500	2.0
Cisco Catalyst 5500 Series Switches	Cisco Catalyst 5509 Switch	1.3.6.1.4.1.9.5.36	2.4.3[RME] 2.4.3[CM]	5.0	Yes ⁴	Yes ⁴	Yes	Yes ⁴	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Yes	Cat5500	2.0
Cisco Network Modules	Cisco Catalyst 5000 RSM	1.3.6.1.4.1.9.1.168	2.4.3[RME] IOS 12.0[CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	RSM	4.1	Yes	Yes	Yes	Yes	Cat5000	2.0

Cisco Network Module Supervisor Engine V 1000BASE-T GBIC (for Cisco Catalyst 4000/4500 Series Switches)	Cisco Catalyst G5483 Switch	1.3.6.1.4.1.9.1.537		Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 4500 Series Switches	Cisco catalyst 4507R Switch ^{9, 18}	1.3.6.1.4.1.9.1.501	12.2(25)SG[RME] _ [CM]	5.0	Yes	Yes ⁵	—	—	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat4000IOS	14.0
Cisco Catalyst 4500 Series Switches	Cisco Catalyst 4507 Switch (SUP IV)	1.3.6.1.4.1.9.1.501	12.1(12c) EW[RME] _ [CM]	5.0	Yes	Yes ⁵	—	—	Yes	Yes	Yes	3.0	NA	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 4500 Series Switches	Cisco Catalyst X4516-10GE on WS-C4507 Switch	1.3.6.1.4.1.9.1.501	12.2(25)EW[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 4900 Series Switches	Cisco Catalyst 4948 Switch	1.3.6.1.4.1.9.1.626	12.2(25)SG[RME] 12.2(20)EWA[CM]	5.0	Yes	Yes	Yes	—	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat4000IOS	14.0
Cisco Catalyst 4900 Series Switches	Cisco Catalyst 4948 10 Gigabit Ethernet Switch	1.3.6.1.4.1.9.1.659	12.2(25)SG[RME] 12.2(25)SG[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	Yes	3.0	NA	4.1	Yes	Yes	Yes	Cat4000IOS	14.0
Cisco Catalyst 4200 Series Switches	Cisco Catalyst 4224 Access Gateway Switch	1.3.6.1.4.1.9.1.399	Cisco IOS 12.1.5 YE1 [RME] _ [CM]	5.0	Yes	Yes	—	—	No	Yes	Yes	3.0	Router	4.1	Yes	Yes	Yes	Cat4200	3.0
Cisco Catalyst 2900 Series Switches	Cisco Catalyst 2948G-L2 Switch	1.3.6.1.4.1.9.5.42	[2948G 4.4(1)], [2980G 5.4(1)] [RME] 5.4(2)[CM]	5.0	Yes	Yes	—	—	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat4000	6.0
Cisco Catalyst 2900 Series Switches	Cisco Catalyst 2980G-A Switch	1.3.6.1.4.1.9.5.49	[2948G 4.4(1)], [2980G 5.4(1)] [RME] 2.4.3[CM]	5.0	Yes	Yes	—	—	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat4000	6.0
Cisco Catalyst 3900 Series Switches	Cisco Catalyst 3900 Switch	1.3.6.1.4.1.9.5.33	3.0(2)[CM]	5.0	Yes	Yes	No	Yes	Yes	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3900 Series Switches	Cisco Catalyst 3920 Switch	1.3.6.1.4.1.9.5.37	3.0(2)[CM]	5.0	Yes	Yes	No	Yes	Yes	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco catalyst 3750G-24PS Switch	1.3.6.1.4.1.9.1.602	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst3750G-24TS-1U Switch	1.3.6.1.4.1.9.1.624	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-48PS Switch	1.3.6.1.4.1.9.1.603	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750G-48TS Switch	1.3.6.1.4.1.9.1.604	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst G-L3 Series Switches	Cisco Catalyst 3750-24TS Switch	1.3.6.1.4.1.9.1.513	12.1(11)AX[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst G-L3 Series Switches	Cisco Catalyst 3750-24 Switch	1.3.6.1.4.1.9.1.511	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

Cisco Catalyst G-L3 Series Switches	Cisco Catalyst 3750-48 Switch	1.3.6.1.4.1.9.1.512	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst G-L3 Series Switches	Cisco Catalyst 3750G-24T Switch	1.3.6.1.4.1.9.1.514	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	NA	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750 Stack Switch	1.3.6.1.4.1.9.1.516	12.2(25)SEC[RME] 12.2(20)SE3[CM]	5.0	Yes	Yes ¹⁰	—	—	Yes ^{1, 10}	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat3750	8.0
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-24FS Switch	1.3.6.1.4.1.9.1.656	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-24PS Switch	1.3.6.1.4.1.9.1.536	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco Catalyst 3750-48PS Switch	1.3.6.1.4.1.9.1.535	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3750 Metro Series Switches	Cisco Catalyst 3750 metro 24-DC Switch	1.3.6.1.4.1.9.1.574	12.1(14)AX1[RME] 12.1(14)AX1[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3750	8.0
Cisco Catalyst 3750-E Series Switches	Cisco Catalyst 3750E-24TD-E Switch	1.3.6.1.4.1.9.1.789	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750-E Series Switches	Cisco Catalyst 3750E-48TD-E Switch	1.3.6.1.4.1.9.1.790	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750-E Series Switches	Cisco Catalyst 3750E-24PD-E Switch	1.3.6.1.4.1.9.1.792	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750-E Series Switches	Cisco Catalyst 3750E-48PD-E Switch	1.3.6.1.4.1.9.1.791	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco catalyst 3750G-12S-SD Switch	1.3.6.1.4.1.9.1.688	12.2(25)SEE[RME] 12.2(25)SEE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 3750 Series Switches	Cisco 2600,2800,3700,3800 Series 16-Port EtherSwitch Service Module	1.3.6.1.4.1.9.1.663	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Cat3750	8.0
Cisco Catalyst 3500 Series XL Switches ^{12, 17}	Cisco Catalyst 3508G XL Switch	1.3.6.1.4.1.9.1.246	Cisco IOS 11.2(8)[RME] IOS 11.2(8)SA5 [3548XL 12.0(5)XP] [CM]	5.0	Yes	Yes	—	—	Yes ¹¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3500XL	4.1
Cisco Catalyst 3500 Series XL Switches ^{12, 17}	Cisco Catalyst 3512 XL Switch	1.3.6.1.4.1.9.1.247	Cisco IOS 11.2(8)[RME] IOS 11.2(8)SA5 [3548XL 12.0(5)XP] [CM]	5.0	Yes	Yes	—	—	Yes ¹¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3500XL	4.1
Cisco Catalyst 3500 Series XL Switches ^{12, 17}	Cisco Catalyst 3524 XL Switch	1.3.6.1.4.1.9.1.248	Cisco IOS 11.2(8)[RME] IOS 11.2(8)SA5 [3548XL 12.0(5)XP] [CM]	5.0	Yes	Yes	—	—	Yes ¹¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3500XL	4.1

Cisco Catalyst 3500 Series XL Switches 12 , 17	Cisco Catalyst 3548 XL Switch	1.3.6.1.4.1.9.1.278	Cisco IOS 11.2(8)[RME] IOS 11.2(8)SA5 [3548XL 12.0(5)XP] [CM]	5.0	Yes	Yes	—	—	Yes 11	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3500XL	4.1
Cisco Catalyst 3500 Series XL Switches 12 , 17	Cisco Catalyst 3524-PWR XL Switch	1.3.6.1.4.1.9.1.287	Cisco IOS 11.2(8)[RME] —[CM]	5.0	Yes	Yes	—	—	Yes 11	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3500XL	4.1
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550 12T Series Switch	1.3.6.1.4.1.9.1.368	12.1(19)EA1c[RME] —[CM]	5.0	Yes	Yes	—	—	Yes 11	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3550	8.0
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550 24 Switch	1.3.6.1.4.1.9.1.366	12.1(19)EA1c[RME] —[CM]	5.0	Yes	Yes	—	—	Yes 11	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3550	8.0
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550 48 Switch	1.3.6.1.4.1.9.1.367	12.1(19)EA1c[RME] —[CM]	5.0	Yes	Yes	—	—	Yes 11	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3550	8.0
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550 12G Switch	1.3.6.1.4.1.9.1.431	12.1(19)EA1c[RME] —[CM]	5.0	Yes	Yes	—	—	Yes 11	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3550	8.0
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550-24-DC Switch	1.3.6.1.4.1.9.1.452	12.1(19)EA1c[RME] —[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3550	8.0
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550-24-FX Switch	1.3.6.1.4.1.9.1.453	12.1(19)EA1c[RME] —[CM]	5.0	Yes	Yes	—	—	Yes	Yes 7	3.0	Switch	4.1	Yes	Yes	Yes	Cat3550	8.0
Cisco Catalyst 3550 Series Switches	Cisco Catalyst 3550 24PWR Switch	1.3.6.1.4.1.9.1.485	12.1(13)EA1[CM]	5.0	Yes	Yes	—	—	Yes 10	Yes 10	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Cat3550	8.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560-24PS Switch	1.3.6.1.4.1.9.1.563	12.1(19)EA1[RME] 12.1(19)EA1[CM]	5.0	Yes	Yes	—	—	Yes 1	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst IOS 3560-48PS Switch	1.3.6.1.4.1.9.1.564	12.1(19)EA1[RME] 12.1(19)EA1[CM]	5.0	Yes	Yes	—	—	Yes 1	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560G-24PS Switch	1.3.6.1.4.1.9.1.614	12.2(20)SE3[RME] 12.2(20)SE3[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560G-24TS Switch	1.3.6.1.4.1.9.1.615	12.2(20)SE3[RME] 12.2(20)SE3[CM]	5.0	Yes	Yes	—	—	Yes 1	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560G-48PS Switch	1.3.6.1.4.1.9.1.616	12.2(20)SE3[RME] 12.2(20)SE3[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560G-48TS Switch	1.3.6.1.4.1.9.1.617	12.2(20)SE3[RME] —[CM]	5.0	Yes	Yes	—	—	Yes 1	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560-24TS Switch	1.3.6.1.4.1.9.1.633	12.2(20)EX[RME] 12.2(25)SEB2[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560-48TS Switch	1.3.6.1.4.1.9.1.634	12.2(20)EX[RME] 12.2(25)SEB[CM]	5.0	Yes	Yes	—	—	Yes 1	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560 Series Switches	Cisco Catalyst 3560-8PC Compact Switch	1.3.6.1.4.1.9.1.797	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes 1	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0

Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-48PD-E Switch	1.3.6.1.4.1.9.1.796	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-24PD-E Switch	1.3.6.1.4.1.9.1.795	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560-E Series Switches	Cisco Catalyst 3560E-48TD-E Switch	1.3.6.1.4.1.9.1.794	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3560-E Switches	Cisco Catalyst 3560E-24TD-E Switch	1.3.6.1.4.1.9.1.793	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat3560	4.0
Cisco Catalyst 3000 Series Switches	Cisco Catalyst 3000 Switch	1.3.6.1.4.1.9.5.10	2.2(2)[RME] 2.2.2[CM]	5.0	Yes	Yes	Yes	Yes	Yes ¹	Yes	3.0	Switch	4.1	Yes	No	No	Not Supported	Not Supported
Other Switches and Hubs	Catalyst WSC3001	1.3.6.1.4.1.9.5.26	2.2.2[CM]	5.0	Yes	Yes	Yes	Yes	Yes ¹	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3000 Series Switches	Cisco Catalyst 3000 Switch	1.3.6.1.4.1.197.2.5	2.2(2)[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	No	No	Not Supported	Not Supported
Cisco Catalyst 3011 Series Switches	WSX3011	1.3.6.1.4.1.9.1.112	—[CM]	5.0	Yes	—	—	—	—	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 3000 Series Switches	Cisco Catalyst 3100 Switch	1.3.6.1.4.1.9.5.23	2.2(2)[RME] 2.2.2[CM]	5.0	Yes	Yes	Yes	Yes	Yes ¹	Yes	3.0	Switch	4.1	Yes	No	No	Not Supported	Not Supported
Cisco Catalyst 3000 Series Switches	Cisco Catalyst 3200 Switch	1.3.6.1.4.1.9.5.15	2.2(2)[RME] 2.2.2[CM]	5.0	Yes	Yes	Yes	Yes	Yes ¹	Yes	3.0	Switch	4.1	Yes	No	No	Not Supported	Not Supported
Cisco Catalyst 2900 Series Switches	Cisco Catalyst 2926 Switch	1.3.6.1.4.1.9.5.35	4.3(0.31)[RME] 2.4.3[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Other Switches and Hubs	Catalyst WSC2900	1.3.6.1.4.1.9.5.12	—[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 2900 Series Switches	Cisco Catalyst 2980G-A Switch	1.3.6.1.4.1.9.5.51	4.3(0.31)[RME] —[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat4000	6.0
Cisco Catalyst 2900 Series Switches	Cisco Catalyst 2948G-GE-TX Switch	1.3.6.1.4.1.9.5.62	8.2(1)GLX[RME] 8.2 (1) GLX[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat4000	6.0
Cisco Catalyst 2900 Series Switches	Cisco Catalyst 2960G-48TC Switch	1.3.6.1.4.1.9.1.697	12.2.25-SSE[RME] 12.2(25)SEE[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2900 Series LRE XL Switches	Cisco Catalyst 2908 XL Switch	1.3.6.1.4.1.9.1.170	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2(8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2916M XL Switch	1.3.6.1.4.1.9.1.171	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2924 XL Switch	1.3.6.1.4.1.9.1.217	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0

Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2924 XL Switch	1.3.6.1.4.1.9.1.183	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series LRE XL Switches	Cisco Catalyst 2924-XL-LRE witch	1.3.6.1.4.1.9.1.183	12.0(5) WC6[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes ¹	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2912 XL Switch	1.3.6.1.4.1.9.1.219	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series LRE XL Switches	Cisco Catalyst 2912-XL-LRE witch	1.3.6.1.4.1.9.1.219	12.0(5) WC6[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes ¹	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2924M XL Switch	1.3.6.1.4.1.9.1.220	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2912MF XL Switch	1.3.6.1.4.1.9.1.221	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2924C XL Switch	1.3.6.1.4.1.9.1.184	Cisco IOS 11.2(8) SA5 [RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series XL Switches	Cisco Catalyst 2924C-XL V Switch	1.3.6.1.4.1.9.1.218	12.0(5) WC11[RME] IOS 11.2 (8) SA5[CM]	5.0	Yes	Yes ¹³	Yes (only on LEC)	—	Yes ¹⁴	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series LRE XL Switches	Cisco Catalyst 2924 LRE XL Switch	1.3.6.1.4.1.9.1.369	12.0(5) WC4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2900 Series LRE XL Switches	Cisco Catalyst 2912 LRE XL Switch	1.3.6.1.4.1.9.1.370	12.0(5) WC4[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Cat2900XL	4.0
Cisco Catalyst 2970 Series Switches	Cisco Catalyst 2970G-24T Switch	1.3.6.1.4.1.9.1.527	12.1(11)AX [RME] 12.1(11) EA1[CM]	5.0	Yes	Yes	—	—	Yes ¹⁰	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat2970	2.0
Cisco Catalyst 2970 Series Switches	Cisco Catalyst 2970G-24TS Switch	1.3.6.1.4.1.9.1.561	12.1(14)EA1[RME] 12.1(14) EA1[CM]	5.0	Yes	Yes ¹⁰	—	—	Yes ¹⁰	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2970	2.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950 12 Switch	1.3.6.1.4.1.9.1.323	12.1(11)EA1[RME] __[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950 24 Switch	1.3.6.1.4.1.9.1.324	12.1(11)EA1[RME] __[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950C 24 Switch	1.3.6.1.4.1.9.1.325	12.1(11)EA1[RME] __[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950G 12 E1 Switch	1.3.6.1.4.1.9.1.427	Cisco IOS 12.1.(11) EA1 [RME] __[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950G 24 E1 Switch	1.3.6.1.4.1.9.1.428	Cisco IOS 12.1.(11) EA1 [RME] __[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0

Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950G 48 E1 Switch	1.3.6.1.4.1.9.1.429	Cisco IOS 12.1.(11) EA1 [RME] _ [CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950T 24 Switch	1.3.6.1.4.1.9.1.359	Cisco IOS 12.1.(11) EA1 [RME] _ [CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950G 24 E1 DC Switch	1.3.6.1.4.1.9.1.472	Cisco IOS 12.1.(11) EA1 [RME] _ [CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950SX 24 Switch	1.3.6.1.4.1.9.1.480	Cisco IOS 12.1.(11) EA1 [RME] _ [CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950SX 48 SI Switch	1.3.6.1.4.1.9.1.560	12.1(14)A2 [RME] 12.1(19)[CM]	5.0	Yes	Yes ¹⁰	—	—	Yes ¹⁰	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2950T 48 SI Switch	1.3.6.1.4.1.9.1.559	12.1(14)A2 [RME] 12.1(19)[CM]	5.0	Yes	Yes ¹⁰	—	—	Yes ¹⁰	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2955C 12 Switch	1.3.6.1.4.1.9.1.489	Cisco IOS 12.1(12c) [RME] 12.1(13)EA1[CM]	5.0	Yes	Yes	—	—	Yes ¹⁰	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat2955	2.0
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2955S 12 Switch	1.3.6.1.4.1.9.1.508	Cisco IOS 12.1(12c) [RME] 12.1(13)EA1[CM]	5.0	Yes	Yes	—	—	Yes ¹⁰	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat2955	2.0
Cisco Catalyst 2950 Series XL Switches	Cisco Catalyst 2955 Switch	1.3.6.1.4.1.9.1.508	Cisco IOS 12.1(12c) [RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco Catalyst 2950 Series Switches	Cisco Catalyst 2955T 12 Switch	1.3.6.1.4.1.9.1.488	Cisco IOS 12.1(12c) [RME] 12.1(13)EA1[CM]	5.0	Yes	Yes	—	—	Yes ¹⁰	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat2955	2.0
Cisco Catalyst 2950 LRE Series Switches	Cisco Catalyst 2950 24 LRE Switch	1.3.6.1.4.1.9.1.482	Cisco IOS 12.1(11)YJ [RME] 12.(11)YJ[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes ¹	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2950 LRE Series Switches	Cisco Catalyst 2950S 8 LRE Switch	1.3.6.1.4.1.9.1.483	Cisco IOS 12.1(11)YJ [RME] 12.(11)YJ[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes ¹	3.0	Switch	4.1	Yes	Yes	Yes	Cat2950	6.0
Cisco Catalyst 2940 Series Switches	Cisco Catalyst 2940-8TF Switch	1.3.6.1.4.1.9.1.542	12.1(13)AY[RME] 12.1(13) AY[CM]	5.0	Yes	Yes	—	—	Yes ¹⁰	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat2940	2.0
Cisco Catalyst 2940 Series Switches	Cisco Catalyst 2940-8TT Switch	1.3.6.1.4.1.9.1.540	12.1(13)AY[RME] 12.1(13) AY[CM]	5.0	Yes	Yes	—	—	Yes ¹⁰	Yes ¹⁰	3.0	Switch	4.1	Yes	Yes	Yes	Cat2940	2.0
Cisco Catalyst G-L3 Series Switches	Cisco Catalyst C2948G-L3 Ethernet Switch	1.3.6.1.4.1.9.1.275	Cisco IOS 12.0(7) [RME] 2.4.3[CM]	5.0	Yes	—	—	—	Yes ²	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2948GL3	3.0
Cisco Catalyst G-L3 Series Switches	Cisco Catalyst C2948G-L3 Ethernet Switch	1.3.6.1.4.1.9.1.386	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Cat2948GL3	3.0
Cisco Lightstream ATM Switches	Cisco Lightstream 1010 ATM Switches	1.3.6.1.4.1.9.1.107	Cisco IOS 11.2 (8.0.1) FWA4.1[RME] _ [CM]	5.0	Yes	—	Yes	Yes	—	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco Lightstream ATM Switches	Cisco Lightstream 1010 ATM Switches	1.3.6.1.4.1.9.5.11	IOS 11.2 (8.0.1) FWA4.1[CM]	5.0	Yes	—	Yes	Yes	—	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Lightstream ATM Switches	Cisco Lightstream 1015 ATM Switches	1.3.6.1.4.1.9.1.164	_ [RME] _ [CM]	5.0	—	—	—	—	—	—	3.0	Switch	4.1	Yes	Yes	Yes	Cat8500	10.2
Cisco Pro Series	Cisco Pro Workgroup Switch 1420	1.3.6.1.4.1.9.5.21	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

Cisco Pro Series	Cisco Pro Workgroup Switch 1601	1.3.6.1.4.1.9.5.25	—[CM]	5.0	Yes	—	—	—	—	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 1600 Series Switches	Cisco Catalyst 1600 Switch	1.3.6.1.4.1.9.5.9	—[CM]	5.0	Yes	—	—	—	—	—	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 1600 Series Switches	Cisco Catalyst 1600 Switch	1.3.6.1.4.1.9.5.8	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 2800 Series Switches	Cisco Catalyst 2820 Modular Ethernet Switch	1.3.6.1.4.1.9.5.20	9.00.07[RME] 8.0(Enterprise)[CM]	5.0	Yes	Yes	Yes	Yes	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat2820	3.0
Cisco Catalyst 1900 Series Switches	Cisco Catalyst 1900 L	1.3.6.1.4.1.9.5.31	8.00.00[RME] 8.0(Enterprise)[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat1900	3.0
Cisco Catalyst 1900 Series Switches	Cisco Catalyst 1924 A Switch	1.3.6.1.4.1.9.5.16	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 1900 Series Switches	Cisco Catalyst 1924 A Switch	1.3.6.1.4.1.9.5.18	9.00.07[RME] 8.0(Enterprise)[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat1900	3.0
Cisco Catalyst 1900 Series Switches	Cisco Catalyst 1900 C	1.3.6.1.4.1.9.5.28	8.00.00[RME] 8.0(Enterprise)[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	4.1	Yes	Yes	Yes	Cat1900	3.0
Cisco Catalyst 1900 Series Switches	Cisco Catalyst 1912 C A Switch	1.3.6.1.4.1.9.5.175	8.0(Enterprise)[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 1900 Series Switches	wsc1900LiteFx	1.3.6.1.4.1.9.5.175	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Cat1900	3.0
Cisco Catalyst 1200 Series Switches	1200	1.3.6.1.4.1.9.5.5	4.29[CM]	5.0	Yes	No	—	—	No	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1220 EtherSwitch Series	Cisco 1220 EtherSwitch	1.3.6.1.4.1.9.5.19	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 1200 Series Switches	1220	1.3.6.1.4.1.9.5.27	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Pro Series	Cisco Pro Workgroup Switch 2200	1.3.6.1.4.1.9.5.13	—[CM]	5.0	Yes	Yes	—	—	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-24TC Switch	1.3.6.1.4.1.9.1.694	12.2(25)FX[RME] 12.2(25)FX[CM]	5.0	Yes	Yes	—	—	Yes	Yes ¹	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-48TC Switch	1.3.6.1.4.1.9.1.695	12.2(25)FX[RME] 12.2(25)FX[CM]	5.0	Yes	Yes	—	—	Yes	Yes ¹	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960G 24TC Switch	1.3.6.1.4.1.9.1.696	12.2(25)FX[RME] 12.2(25)FX[CM]	5.0	Yes	Yes	—	—	Yes	Yes ¹	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-24TT Switch	1.3.6.1.4.1.9.1.716	12.2(25)FX[RME] 12.2(25)FX[CM]	5.0	Yes	Yes	—	—	Yes	Yes ¹	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-48TT Switch	1.3.6.1.4.1.9.1.717	12.2(25)FX[RME] 12.2(25)FX[CM]	5.0	Yes	Yes	—	—	Yes	Yes ¹	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960-8TC Compact Switch	1.3.6.1.4.1.9.1.798	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0

Cisco Catalyst 2960 Series Switches	Cisco Catalyst 2960G-8TC Compact Switch	1.3.6.1.4.1.9.1.799	12.2(35.1)SE[RME] 12.2(35.1)SE[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	3.0	NA	4.1	Yes	Yes	Yes	Cat2960	4.0
Cisco ME 2400 Series Ethernet Access Switches	Cisco ME 2440-24TS-A Switch	1.3.6.1.4.1.9.1.734	12.2(25)EX[RME] 12.2(25)EX[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	NA	4.1	Yes	Yes	Yes	Cisco2400ME	1.0
Cisco ME 3400 Series Ethernet Access Switches	Cisco ME 3440-24TS-A Switch	1.3.6.1.4.1.9.1.736	12.2(25)EX[RME] 12.2(25)EX[CM]	5.0	Yes	Yes	—	—	Yes ¹	Yes	3.0	NA	4.1	Yes	Yes	Yes	Cisco3400ME	3.0
Cisco ME 3400 Series Ethernet Access Switches	Cisco ME 3440-24TS-D Switch	1.3.6.1.4.1.9.1.737	12.2(25)EX[RME] 12.2(25)EX[CM]	5.0	Yes	Yes	NA	—	Yes ¹	Yes	Not Supported	Not Supported	4.1	Yes	Yes	Yes	Cisco3400ME	3.0
Cisco ME 3400 Series Ethernet Access Switches	Cisco ME 3400G-12CS-D Switch	1.3.6.1.4.1.9.1.781	12.2(35)SE1	5.0.1	Yes	Yes	NA	NA	Yes ^{1, 21}	Yes	3.0.1	Switch	4.1 ²⁰	Yes	Yes	Yes	Cisco3400ME	3.0
Cisco ME 3400 Series Ethernet Access Switches	Cisco ME 3400G-12CS-A Switch	1.3.6.1.4.1.9.1.780	12.2(35)SE1	5.0.1	Yes	Yes	NA	NA	Yes ^{1, 21}	Yes	3.0.1	Switch	4.1 ²⁰	Yes	Yes	Yes	Cisco3400ME	3.0
Cisco ME 6500 Series Ethernet Switches	Cisco ME 6524GS-8S Ethernet Switch	1.3.6.1.4.1.9.1.719	12.2(18)ZU	5.0.1	Yes	Yes	NA	NA	Yes ¹	Yes	3.0.1	Switch	4.1 ²⁰	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco ME 6500 Series Ethernet Switches	Cisco ME 6524GT-8S Ethernet Switch	1.3.6.1.4.1.9.1.720	12.2(18)ZU	5.0.1	Yes	Yes	NA	NA	Yes ¹	Yes	3.0.1	Switch	4.1 ²⁰	Yes	Yes	Yes	Cat6000IOS	29.0
Cisco SFS 7000 Series InfiniBand Server Switches	Cisco SFS 7008 Infiniband Server Switch ¹⁵	1.3.6.1.4.1.6203.18	2.5.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco SFS 7000 Series InfiniBand Server Switches	Cisco SFS 7000 Infiniband Server Switch ¹⁵	1.3.6.1.4.1.6203.17	2.5.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco SFS 7000 Series InfiniBand Server Switches	Cisco SFS 7000D Infiniband Server Switch ¹⁵	1.3.6.1.4.1.6203.19	2.9.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco SFS 3000 Series Multifabric Server Switches	Cisco SFS 3012 Multifabric Server Switch ¹⁵	1.3.6.1.4.1.6203.20 1.3.6.1.4.1.6203.3[DFM]	2.10.0[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	4.1	Yes	Yes	Yes	Not Supported	Not Supported

1. Support for IP Phones is also provided.

2. Cisco Routers provide User Tracking application with ARP Table information.

3. After adding the device into the DCR, and whenever the device is switched between the Single and Multi Security Context Modes, the device should be deleted and added again into the DCR. This is due to change in the sysobjid and also because the number of configurations for the device varies when there is switching between the modes.

4. IOS version 3.2(7), 3.2(9), 3.2(12), 3.2(13), and 3.2(15) are compatible code bases for Cisco Catalyst 5000 ATM interface.

5. Supported with CatOS only.

6. Supports Cisco IOS and CatOS in Campus Manager.

7. VLAN management supported in IOS 12.1(13)EW1.

8. User Tracking not supported in IOS 12.1(13)EW1.

9. Supports Cisco IOS only.

10. Support for VLAN Port Assignment not provided.

11. User Tracking will not discover end-hosts connected to Cisco Catalyst 2900XL or Cisco Catalyst 3500XL devices running IOS 12.0(5)XP.

12. 3500XL series is supported in IP Mode only [in Campus Manager]. Clustered devices not assigned an IP address are not supported.

14. IOS version 3.2(7), 3.2(9), 3.2(12), 3.2(13), and 3.2(15) are compatible code bases for Cisco Catalyst 5000 ATM interface.

15. Contact TAC (Technical Assistance Center) to access this support. You can also contact TAC at <http://www.cisco.com/public/support/tac/contacts.shtml>

16. On the Catalyst 4503 and 4506, DFM supports the Supervisor Engine I and II running the CatOS operating system, and the Supervisor Engine III and IV running the IOS operating system.

17. Clustering and stack are supported in the Catalyst 3500 series.

18. On the Catalyst 4507, DFM supports the Supervisor Engine IV running the IOS operating system.

19. On the Catalyst 4006, DFM supports the Supervisor Engine III and IV running the IOS operating system.

20. Support for this specific device is available at: <http://cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>

21. Dynamic User Tracking is supported.

Table 9: Universal Gateways

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco AS5300 Series Universal Gateways	Cisco AS5300 Access Server	1.3.6.1.4.1.9.1.162	Cisco IOS 11.0[RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	AS5300	6.0
Cisco AS5300 Series Universal Gateways	Cisco AS5350 Universal Gateway	1.3.6.1.4.1.9.1.313	Cisco IOS 11.0[RME] —[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	AS5350	12.0
Cisco AS5300 Series Universal Gateways	Cisco AS5350XM Universal Gateway	1.3.6.1.4.1.9.1.679	12.3(14)T	5.0.1	Yes	NA	NA	NA	NA	Yes	3.0.1	Router	4.1 ²	Yes	Yes	Yes	AS5350	12.0
Cisco AS5400 Series Universal Gateways	Cisco AS5400 Universal Gateway	1.3.6.1.4.1.9.1.274	12.2(3g)[RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	AS5400	8.0
Cisco AS 5400 Series Universal Gateways	Cisco AS5400 HPX Universal Gateway AS5400[CM]	1.3.6.1.4.1.9.1.274	Cisco IOS 12.3(3g)[RME] —[CM]	5.0	Yes	—	—	—	Yes ³	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco AS5400 Series Universal Gateways	Cisco AS5400XM Universal Gateway	1.3.6.1.4.1.9.1.668	12.3(14)T	5.0.1	Yes	NA	NA	NA	NA	Yes	3.0.1	Router	4.1 ²	Yes	Yes	Yes	AS5400	8.0
Cisco AS5800 Series Universal Gateways	Cisco AS5800 Access Server	1.3.6.1.4.1.9.1.188	Cisco IOS 11.0 [RME] IOS 11.0[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	AS5800	8.0
Cisco AS5800 Series Universal Gateways	Cisco AS5850 Universal Gateway	1.3.6.1.4.1.9.1.308	Cisco IOS 11.0 [RME] —[CM]	5.0	Yes	—	—	—	Yes ¹	Yes	3.0	Router	4.1	Yes	Yes	Yes	AS5850	10.0

1. Cisco routers supply the User Tracking application with ARP Table information.

2. Support for this specific device is available at: <http://cisco.com/cgi-bin/tablebuild.pl/cw2000-rme>

Table 10: Voice Gateways

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)

Cisco VG 200 Series Gateways	Cisco VG200 Voice Gateway	1.3.6.1.4.1.9.1.279	Cisco IOS 12.1(1)[RME] —[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Router	4.1	Yes	Yes	Yes	Not Supported	Not Supported
Cisco VG 200 Series Gateways	Cisco VG248 48-Port Analog Phone Gateway	1.3.6.1.4.1.9.1.404	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	VG248	2.0
Cisco VG 200 Series Gateways	Cisco VG 224 Voice Gateway	1.3.6.1.4.1.9.1.558	12.3(4)XD[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	4.1	Yes	Yes	No	VG224	1.0
Cisco Media Convergence Server	Cisco Media Convergence Server	1.3.6.1.4.1.311.1.1.3.1.1x	—[RME]	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	4.1	Yes	No	No	Not Supported	Not Supported
Cisco IP Phones	7902, 7905, 7910, 7912, 7960, 7940, 7936, 7970	—	—[CM]	5.0	—	—	—	—	Yes	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco IP Conference Station	7935	—	—[CM]	5.0	—	—	—	—	Yes	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco DPA 7600 Series Gateways	Cisco DPA 7630 Voice Mail Gateway	1.3.6.1.4.1.9.1.365	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco DPA 7600 Series Gateways	Cisco DPA 7610 Voice Mail Gateway	1.3.6.1.4.1.9.1.381	—[CM]	5.0	Yes	—	—	—	—	Yes	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco ICS 7700 Series Integrated Communication Systems	Cisco ICS 7750 Integrated Communication System	1.3.6.1.4.1.9.1.302	—[CM]	5.0	Yes	—	—	—	Yes	Yes	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco ICS 7700 Series Integrated Communication Systems	Cisco ICS 7750-MRP300 Integrated Communication System	1.3.6.1.4.1.9.1.456	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Router	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco ICS 7700 Series Integrated Communication Systems	Cisco ICS 7750SPE Integrated Communication System	1.3.6.1.4.1.9.1.314	—[CM]	5.0	Yes	—	—	—	Yes	Yes	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco ICS 7700 Series Integrated Communication Systems	Cisco ICS 7750SSP Integrated Communication System	1.3.6.1.4.1.9.1.303	—[CM]	5.0	Yes	—	—	—	Yes	Yes	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Call Control ²	Cisco Call Manager	1.3.6.1.4.1.311.1.1.3.1.3	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Application Server	Application Server	1.3.6.1.4.1.311.1.1.3.1.2	—[CM]	5.0	Yes	—	—	—	Yes	Yes	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Unity Servers ²	Windows Servers	1.3.6.1.4.1.311.1.1.3.1.2	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
IBM Media Server ³	x330, x340, x342	1.3.6.1.4.1.311.1.1.3.1.2	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Media Convergence Server (MCS) ^{1, 2}	MCS-7800 Series MCS 7820, MCS 7822, MCS 7825, MCS 7830, MCS 7835; IBM Media Server x330, x340, x342[DFM]	1.3.6.1.4.1.311.1.1.3.1.2	—[CM]	5.0	Yes	—	—	—	Yes	Yes	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7800 Series Media Convergence Servers ^{1, 2}	Cisco 7825H Media Convergence Server	1.3.6.1.4.1.9.1.583	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 7800 Series Media Convergence Servers ^{1, 2}	Cisco 7835H Media Convergence Server	1.3.6.1.4.1.9.1.584	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

Cisco 7800 Series Media Convergence Servers ^{1, 2}	Cisco 7845I Media Convergence Server	1.3.6.1.4.1.9.1.587	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco IP Contact Center Product Family	Cisco IPCC Enterprise Edition	1.3.6.1.4.1.9.1.693	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Voice Applications	Meeting Place Express	1.3.6.1.4.1.9.1.710	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Host	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported

Table 11: Wireless LAN Products

[illegible]

[illegible]

Device Type	Device Name	sysObjectID	Minimum Software	Supported Version (CM)	Topology (CM)	VLAN Mgmt (CM)	LANE Mgmt (CM)	ATM Mgmt (CM)	User Tracking (CM)	Path Analysis (CM)	Supported Version (DFM)	DFM1.x Class (DFM)	Supported Version (RME)	Inventory (RME)	Config Mgmt (RME)	Software Mgmt (RME)	Package Name (CV)	Package Version (CV)
Cisco Fast Hub 100 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.226	__[CM]	5.0	Yes	—	—	—	—	—	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub 100[CM, DFM]																	
Cisco Fast Hub 400 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.226	__[CM]	5.0	Yes	—	—	—	—	—	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
	FastHub 400[CM]																	
Cisco Fast Hub 300 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.147	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub316T[CM, DFM]																	
Cisco Fast Hub 300 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.148	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub316C[CM, DFM]																	
Cisco Fast Hub Series	__[RME]	1.3.6.1.4.1.9.1.149	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub3116[CM, DFM]																	
Cisco Fast Hub 100 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.150	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub116T[CM, DFM]																	
Cisco Fast Hub 100 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.151	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub116C[CM, DFM]																	
Cisco Fast Hub Series	__[RME]	1.3.6.1.4.1.9.1.152	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub1116[CM, DFM]																	
Cisco Fast Hub 200 Series Hubs	__[RME]	1.3.6.1.4.1.9.1.169	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	4.1	Yes	No	No	Not Supported	Not Supported
	FastHub216T[CM, DFM]																	
Cisco Fast Hub Series Hubs	FastHub BMMFX [CM, DFM]	1.3.6.1.4.1.9.1.178	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Fast Hub Series Hubs	FastHub BMMTX [CM, DFM]	1.3.6.1.4.1.9.1.177	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1500 Series Micro Hubs	MicroHub 1502	1.3.6.1.4.1.9.1.161	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1500 Series Micro Hubs	MicroHub 1503	1.3.6.1.4.1.9.1.160	__[CM]	5.0	Yes	—	—	—	—	Not tested	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1538 Series Micro Hubs	Cisco 1538M Micro Hub	1.3.6.1.4.1.9.1.224	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco 1548 Series Micro Switch	Cisco 1548M Micro Switch	1.3.6.1.4.1.9.1.225	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Workgroup Concentrators	Cisco 1000 Workgroup Concentrator	1.3.6.1.4.1.9.5.3	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Workgroup Concentrators	Cisco WS-C1100 CDDI, FDDI Workgroup Concentrator	1.3.6.1.4.1.9.5.4	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Switch	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported
Cisco Workgroup Concentrators	Cisco WS-C1400 Workgroup Concentrator	1.3.6.1.4.1.9.5.6	—	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	3.0	Hub	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported	Not Supported