

# اهحالص او طالتخملا ميوقتلا عاااخاً فاشكتسا ريغ اهنأ وأ رورملا ةملك ةيحالص تهتنا - ةحالص

## تايوتحمل

[ةمدقملا](#)

[ةيساسألا تابلطتملا](#)

[تابلطتملا](#)

[ةمدختسملا تانوكملا](#)

[ضرعلا](#)

[Expressway-C زارط \(GUI\) ةيموسرلا مدختسملا ةهجاو](#)

[Webex Control Hub مدختسم ةهجاو](#)

[اهحالص او عاااخألا فاشكتسا](#)

[لحلا](#)

[دوصقم ريغل كش ريغ تلالا قيبطتل Expressway مداخ ةيمت ةدعاب مق](#)

[Webex Control Hub مدختسم ةهجاو نم حوسملا هيبتتلا ةحص نم ققختلا](#)

[تاعومجم يلعة عيرس قرط](#)

[عجارملا](#)

## ةمدقملا

عقوم لوؤسم رورم ةملك ةيحالص اءهتنا عم Expressway Connector حالصا دننتملا اذه فصوي اءهتيحالص مدع وأ هبتملا WebEx تاعامتجا.

## ةيساسألا تابلطتملا

### تابلطتملا

ةيلتلا عيضاوملاب ةفرعم كيذل نوكت ناب Cisco يوصوت:

- [Webex Control Hub](#) ةمظنم.
- [Exchange](#) ةمدخ عم طالتخملا ميوقتلا.
- (ةديجال رشنلا تايلمعل ىندأ دحك 12.5 ددع) [Expressway](#) لوصوم.
- [ةطالتخملا Webex تامدختالصلوم Expressway نم ةمومدملا تارادصلا](#)

### ةمدختسملا تانوكملا

ةيلتلا ةيامل تانوكملا او جماربال تارادصا ىلا دننتملا اذه يف ةدراولا تامولعمل دننست:

- عم طالتخملا ميوقتلا مدختسا، ليلدلا اذه يف. طالتخملا ميوقتلا طيشنت مت

Exchange.

- Exchange Server 2019 Standard.
- Expressway-C X14. 0. 5.

ةصاخ ةي لمعم ةئيب يف ةدوجوملا ةزهجال نم دنتسمل اذف ةدراول تامولعمل عاشنإ م تناك اذإ. (يفضارتفا) حوسمم نيوكتب دنتسمل اذف يف ةمدختسمل ةزهجال عيمج تادب رملأ يال لمحتحمل ريثأتلل كمهف نم دكأتف ، ليعغشتلا ديق كتكبش

## ضرعلا

### Expressway-C زارط (GUI) ةيموسررلا مدختسمل ةهجاو

نم WebEx تاعامتجا عقوم لوؤسم رورم ةملك ةيحص تهتنا. تاهي بننتلا > ةلجال لىل لقتنا اهاتنا ببسب Cisco نم WebEx تاعامتجا عقوم لىل لوصول نكمي ال :ةحلص دعت مل وأ Cisco يف تاعامتجال ةجلال عم متت ال @webex. اهتيجال صمدع وأ لوؤسم رورم ةملك ةيحص Cisco WebEx عقوم مسانمضتي :ةيلصفت تامولعم. اهلح متي ىتح رثأتمل عقومل Meetings "[ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779]: sitename.webex.com".

The screenshot shows the Cisco Expressway-C GUI. At the top right, a red banner indicates "This system has 1 alarm". Below this, the "Alarms" section is active, showing a warning: "Warning: Your current hardware does not meet supported VM configuration requirements. For information on standard configuration for this version of Expressway, view [Virtualization for Cisco Expressway](#) page." Below the warning, a table lists the alarm details:

Alarm	Description	State	Severity	Peer	Action	First raised	Last raised	ID
<input type="checkbox"/> Cisco Webex Meetings site administrator password has expired or invalid	Cisco Webex Meetings site cannot be accessed due to expired or invalid administrator password. @webex meetings on affected site will not be processed until this is resolved. Detailed info: the Cisco Webex Meetings site name includes "[ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779]: jvizcain.webex.com"	Raised	Error	This system	Change the expired or invalid administrator password on affected Cisco Webex Meetings site	2022-08-18 11:34:58	2022-08-18 11:34:58	60162

Red arrows in the image point to the "Alarms" tab (1), the alarm description (2), and the "Raised" state (3).

### Webex Control Hub مدختسم ةهجاو

ةيحص تهتنا. ثادح > Exchange عم نيجه ميوقت > نيجه > admin.webex.com لىل لقتنا لىل لوصول نكمي ال :ةحلص دعت مل وأ Cisco نم WebEx تاعامتجا عقوم لوؤسم رورم ةملك ةيحص دعت مل وأ لوؤسم رورم ةملك ةيحص Cisco نم WebEx تاعامتجا عقوم مدع وأ لوؤسم رورم ةملك ةيحص اهاتنا ببسب Cisco نم WebEx تاعامتجا عقوم لىل لوصول نكمي ال @webex. اهتيجال صمدع وأ لوؤسم رورم ةملك ةيحص Cisco WebEx Meetings "[ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779]: sitename.webex.com".

The screenshot shows the Cisco Webex Control Hub interface. On the left, the 'Hybrid' menu item is highlighted with a red box and arrow labeled '1'. The main area displays the 'Hybrid Services Events History' table. One event is highlighted with a red box and arrow labeled '2':

Event	Severity	Type	Service
Cisco Webex Meetings site administrator passw...	Error	Alarm	Calendar Servi...

The 'Event Details' panel on the right shows the alarm description, which is highlighted with a red box and arrow labeled '3':

An alarm was raised on node ccnp-expressway-hybrid1.vizcainovich.com. The node provided the following alarm description: Cisco Webex Meetings site cannot be accessed due to expired or invalid administrator password. @webex meetings on affected site will not be processed until this is resolved. Detailed info: the Cisco Webex Meetings site name includes "[ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779]:jvizcain.webex.com"

## اهحال صاوا عا طخال افاشك تسا

ع قوم نيوكت > ميوقتلا ممدخ > ةطلتخم الم تامدخال > تاقي بطلتلا لىل لقتنا  
 ع قوم الم مسا ناوع قوف رقنا > Cisco WebEx Meetings

The screenshot shows the Cisco Expressway-C configuration page. The 'Applications' menu is highlighted with a red box and arrow labeled '1'. The 'Hybrid Services' sub-menu is highlighted with a red box and arrow labeled '2'. The 'Calendar Service' configuration is highlighted with a red box and arrow labeled '3'. The 'Cisco Webex Meetings site administrator password' field is highlighted with a red box and arrow labeled '4'. A warning message at the top right states: 'This system has 1 alarm'.

Cisco Expressway-C

This system has 5 alarms

Status > System > Applications > Users > Maintenance >

You are here: Applications > Hybrid Services > Calendar Service > Cisco Webex Meetings Site Configuration

**Cisco Webex Meetings Site Configuration**

Warning: Your current hardware does not meet supported VM configuration requirements. For information on standard configuration for this version of Expressway, view [Virtualization for Cisco Expressway](#) page.

Address	Username	UUID	Default Site?	Status	Actions
<input type="checkbox"/>	[redacted].com	ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779	Yes	-	<a href="#">View/Edit</a>

New

5

Related Tasks

- [Configure Microsoft Exchange Servers](#)
- [Configure Cisco Conferencing Services](#)
- [Check Calendar Connector Status](#)
- [Back to Calendar Connector configuration](#)
- [Back to Connector Management](#)

User: admin Access: Read-write System host name: ccnp-expressway-hybrid1 System time: 12:29 CDT Language: en\_US S/N: 0FD3D510 Version: X14.0.5

ةم لك ،مدختسملا مسا ،لمالك لاب لهؤملا عقوملا مسا ىل ع WebEx عامتجا عقوم نيوكت يوتحي رورملا.

Cisco Expressway-C

This system has 4 alarms

Status > System > Applications > Users > Maintenance >

You are here: Applications > Hybrid Services > Calendar Service > Cisco Webex Meetings Site Configuration

**Cisco Webex Meetings Site Configuration** ← 1

Warning: Your current hardware does not meet supported VM configuration requirements. For information on standard configuration for this version of Expressway, view [Virtualization for Cisco Expressway](#) page.

Configuration

Fully Qualified Site Name	* sname.webex.com	↓
Username	user@domain.com	↓ ← 2
Password	*****	↓
Default Site	Yes	↓
Cisco Webex Meetings Site UUID	ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779	

Information: Enter a test user's email address (WBS31.4 and later) or a read-only administrator username for earlier versions (input is mandatory in this case).

Save Cancel Delete Test Connection

## لحل

> VCS-C لصوصم ىل لقتنا .ةغراف لوقحلا كرتاو رورملا ةم لك/مدختسملا مسا ةلازاب مق  
عقوم > Cisco نم تارمتؤملا تامدخ نيوكت > ميوقتلا ةمدخ > ةطلتخملا تامدخلا > اتاقيبطت  
تاريغتلا قيبطت Webex.

This system has 4 alarms

Status > System > Applications > Users > Maintenance >

You are here: Applications > Hybrid Services > Calendar Service > Cisco Webex Meetings Site Configuration

**Warning** Your current hardware does not meet supported VM configuration requirements. For information on standard configuration for this version of Expressway, view [Virtualization for Cisco Expressway](#) page.

**Configuration**

Fully Qualified Site Name  ⓘ

Username  ⓘ

Password  ⓘ

Default Site  ⓘ

Cisco Webex Meetings Site UUID ad2f68c1-8f07-4c0a-96d6-dfa6c05c5779

**Information** ⓘ  
If required, enter the password for the read-only administrator account.

**Save** **Cancel** **Delete** **Test Connection**

دوصقم ريغ لكش ب ريغ تال قيبطتل Expressway مداخ ديهم تاداع اب مق  
ديهم تال اداع > ليغش تال اداع تاراخي > تايصل ال ل لقتنا

This system has 5 alarms

Status > System > Applications > Users > Maintenance >

You are here: Maintenance > Restart options

**Restart options**

**Warning** Your current hardware does not meet supported VM configuration requirements. For information on standard configuration for this version of Expressway, view [Virtualization for Cisco Expressway](#) page.

**System status**

Cluster status	This system is part of a cluster
Call status	There are 0 calls active
Registration status	There are 0 registrations active

**Information**

A restart is typically required in order for some configuration changes to take effect, or when the system is being added to, or removed from, a cluster.

A reboot is typically required when you want to apply new versions of software, or when you are trying to resolve unexpected system errors.

Note that a restart shuts down and restarts only the application software, whereas a reboot shuts down and restarts the application software, operating system and hardware.

A shutdown is typically required if you want to unplug your unit, prior to maintenance or relocation for example.

**Restart** **Reboot** **Shutdown**

ةعاس 24 دع ب هي بننتال حسم متي، ليغش تال اداع نكمم ال نم نكي مل اذا: تظحال م

Webex Control Hub مدختسم ةهجاو نم حوسم ال هي بننتال ةحص نم ققحتال  
لحل مت امك نال هي بننتال رهظي

The screenshot displays the Webex Control Hub interface. On the left, the navigation menu includes 'Overview', 'Alerts center', 'MONITORING', 'MANAGEMENT', and 'SERVICES'. The 'Hybrid' option under 'SERVICES' is highlighted with a red box and an arrow labeled '1'. The main content area shows the 'Hybrid Services Events History' table. The table has columns for 'Event', 'Severity', 'Type', and 'Service'. One event, 'Cisco Webex Meetings site administrator password has expired or invalid', is highlighted with a red box and an arrow labeled '2'. The 'Event Details' panel on the right shows the description of this event, which is also highlighted with a red box and an arrow labeled '3'. The description reads: 'The alarm titled Cisco Webex Meetings site administrator password has expired or invalid is resolved on node ccnp-expressway-hybrid1.vizcainovich.com.' The 'Technical Details' section below shows fields for Connector ID, Alarm ID, Timestamp, User ID, and Tracking ID.

## تاعومجم یل عة عیرس قرط

ةیساسألا ةدقعالا یف طوقف بولطم لیدبلا لجالا

## عجارملا

[میوقتلا لصلومل WebEx عقوم تادادعلا نیوکت](#)

[ةطلتخملال Webex تامدخال لصلومل Expressway نم ةم وعودملا تارادصلالا](#)

[ةطلتخملال تامدخال لمدختسملال لصلومل فیضمل Expressway ةیقرت](#)

[طلتخملال میوقتلا ةمدخال رادصال تاظالم](#)

[ةطلتخملال تامدخال دراومل ةیئاقلا تالال تایقرتلا](#)

ةمچرتل هذه لوج

ةللأل تاي نقتل نم ةومچم مادختساب دن تسمل اذه Cisco تچرت  
ملاعلاء انءمچ يف نيمدختسمل معدى وتحم مي دقتل ةيرشبلاو  
امك ةقيد نوك تنل ةللأل ةمچرت لصف أن ةظحال مچرئى. ةصاغل مهتغب  
Cisco يلخت. فرتحم مچرت مامدقي يتل ةيفارتحال ةمچرتل عم لالحل وه  
ىلإ أمئاد عوچرلاب يصوت وتامچرتل هذه ةقदन ةتيلوئسم Cisco  
Systems (رفوتم طبارلا) يلصلأل يزلچنلإل دن تسمل