

ةي عجرم ل رماوأل ا ةمئاق ااطأ فاشكتسأ ة دعاسمب ة صاخلا اءال صاوة عيرسل IOS-XR اءاومل

ا اءوءءملا

[ةمءملا](#)

[مءءءسالا](#)

[آكيسالاك - ASR9K](#)

[ASR9K - eXR](#)

[NCSxxxx، و Whitebox اءصنم](#)

[CRS](#)

[Cisco 8xxx](#)

ةمءملا

Cisco IOS®-XR اءاومل نم اءءمءء مءي يءلا رماوأل نم ةماعلا ةءومءملا ءنءسمل اءه فصي
TAC اءالء راءصا ءءب/ءقو يء

مءءءسالا

نوءءرءم وه امك امامء هءوملاب ة صاخلا (CLI) رماوأل رطس ةءءاو يءلا رماوأل ةمئاق قصل نكمي
قءاطءء يءلا اءزملا ءي فنء مءي مل اءا أء ةني عم رماوأل ءرءنا نكمي. اءريي ءء يا ءارء
ل.كاشم ةيا ببسء الو ةءقو ءم ةءءن هءو

نيكمء يوس كءل ع ام. كء صاخلا هءوملا يءل لمالكلاب ةمئاقلا هءه قصل/ءسن نكمي
ءروصل اءاقلال كءءل SSH/telnet لءم ع يءلا لوءءلا لءءسء

آكيسالاك - ASR9K

```
term length 0 show platform admin show platform show install active summary show version show
hw-module fpd location all show diag show logging show install log show running admin show
running show configuration failed show configuration commit changes all show configuration
history show configuration failed startup show history show cli history detail admin show
environment admin show led show pfm location all show processes show processes cpu show
processes blocked location all show watchdog memory-state show context location all show
controllers np counters all show drops show redundancy show redundancy summary show snmp mib
access show snmp interface show interfaces description show ospf neighbor show bgp sessions show
bgp summary show rib update-groups show tcp brief show l2vpn xconnect show mpls traffic-eng
tunnels show bfd session show virtual-service list
```

ASR9K - eXR

```
term length 0 show platform show install active summary show version show hw-module fpd show
diag show logging show install log show running admin show running show configuration failed
```

show configuration commit changes all show configuration history show configuration failed startup show history show cli history detail admin show environment admin show led show pfm location all show processes show processes cpu show processes blocked location all show watchdog memory-state show context location all show controllers np counters all show drops show redundancy show redundancy summary show snmp mib access show snmp interface show interfaces description show ospf neighbor show bgp sessions show bgp summary show rib update-groups show tcp brief show l2vpn xconnect show mpls traffic-eng tunnels show bfd session

NCSxxxx، و Whitebox تاصنم

نCS، ةصنم لك اذه NCS6K، NCS5K، NCS55xx، NCS540، و NCS560. لثام ل لبس ل ع، ل نكل، ل ع رصتقي ال نكل،

term length 0 show platform admin show platform show inventory show install active summary show version show hw-module fpd show diag show logging show install log show running admin show running show configuration failed show configuration commit changes all show configuration history show configuration failed startup show history show cli history detail show environment admin show environment show led admin show led show alarms brief system active show asic-errors all detail location 0/RP0/CPU0 show asic-errors all detail location 0/0/CPU0 show processes show processes cpu show processes blocked location all show watchdog memory-state show context location all show redundancy show redundancy summary show snmp mib access show snmp interface show interfaces description show ospf neighbor show bgp sessions show bgp summary show rib update-groups show tcp brief show l2vpn xconnect show mpls traffic-eng tunnels show bfd session

CRS

term length 0 show platform admin show platform show install active summary show version show hw-module fpd location all show diag show logging show install log show running admin show running show configuration failed show configuration commit changes all show configuration history show configuration failed startup show history show cli history detail admin show environment admin show led show processes show processes cpu show processes blocked location all show watchdog memory-state show context location all show redundancy show redundancy summary show snmp mib access show snmp interface show interfaces description show ospf neighbor show bgp sessions show bgp summary show rib update-groups show tcp brief show l2vpn xconnect show mpls traffic-eng tunnels show bfd session

Cisco 8xxx

term length 0 show platform show install active summary show version show hw-module fpd show diag show logging show install log show running show configuration failed show configuration commit changes all show configuration history show configuration failed startup show history show cli history detail show environment show led show processes show processes cpu show processes blocked location all show watchdog memory-state show context location all show reboot history show redundancy show redundancy summary show snmp mib access show snmp interface show interfaces description show ospf neighbor show bgp sessions show bgp summary show rib update-groups show tcp brief show l2vpn xconnect show mpls traffic-eng tunnels show bfd session

ةمچرتل هذه لوج

ةللأل تاي نقتل نم ةومچم مادختساب دن تسمل اذه Cisco تچرت
ملاعلاء انءمچ يف نيمدختسمل معدى وتحم مي دقتل ةيرشبلاو
امك ةقيد نوك تنل ةللأل ةمچرت لصف أن ةظحال مچرئى. ةصاغل مهتغب
Cisco يلخت. فرتحم مچرت مامدقي يتل ةيفارتحال ةمچرتل عم لالحل وه
ىلإ أمئاد عوچرلاب يصوت وتامچرتل هذه ةقد نع اهتيلوئسم Cisco
Systems (رفوتم طبارلا) يلصلأل يزيلچنلإل دن تسمل