

سفن ىل اىوڊى هضفخ و ا هتقرتو لقتسم فللمك ڊىڊال FI نىوكت وه داتعمل اءارءال
ءومءمءال ماظن ىل اهتفاضل لبق ءومءال FI راءصا

FI ءقرت ىل ءءابءال ءمانربلل ءقءلءل ءنمازملا ءزىم لمءءس، UCSM 2.1(2) نم اءءبو
لقلء و ا ءقرت ءابلءم لىزى اءه و ءومءال راءصا ال سفن ىل اىقءلء هضفخ و ا ڊىءال
اىوڊى FI ءاكبش

ءمىقلل نوكت نأ بءىو ءءءا راءصا و UCSM 1.4 ف ءومءال ءىللملا ءمىقلل نوكت نأ بءى
ءاءء، اضى ا ءزىملا هءه لمءء ىء ءءءا راءصا و UCSM 2.1(2) ف ءىللملا ءىللملا
اءه لمءى ىءء زارءال سفن نم نوكت نأ ءىللملا ءاسس وءملا

ءاوءء

1. ءومءال ءومءمءال ىل اهتفاضل ءىللملا FI مكءء ءءوب لءصءا

2. ءءءملا ءومءال ءىللملا ءمءل ءءءء، ءىللملا ءومءمءال ىل اهتفاضل ءءمب
ءءابءال ءماربلا ءاراءصا عم ءىللملا

```
Installer has detected the presence of a peer Fabric interconnect. This Fabric interconnect will be added to the cluster. Continue (y/n) ? y

Enter the admin password of the peer Fabric interconnect:
Connecting to peer Fabric interconnect... done
Retrieving config from peer Fabric interconnect... done
Installer has determined that the peer Fabric Interconnect is running a different firmware version than the local Fabric. Cannot join cluster.

Local Fabric Interconnect
UCSM version      : 2.2(5a)
Kernel version    : 5.2(3)N2(2.25a)
System version    : 5.2(3)N2(2.25a)
local_model_no    : 6248

Peer Fabric Interconnect
UCSM version      : 2.2(6c)
Kernel version    : 5.2(3)N2(2.26c)
System version    : 5.2(3)N2(2.26c)
peer_model_no     : 6248

Do you wish to update firmware on this Fabric Interconnect to the Peer's version? (y/n):
```

3. FI ىل ءىرورءل ءافللملا ءسنب ءءابءال ءمانربلل ءقءلءل ءنمازملا ءزىم موقت
ءومءال FI عم قءاطءىل هضفخ و ا هتقرتو ڊىءال

```
Verifying image bootflash:/installables/switch/ucs-6100-k9-kickstart.5.2.3.N2.2.26c.bin for boot variable "kickstart"
[#####] 100% -- SUCCESS

Verifying image bootflash:/installables/switch/ucs-6100-k9-system.5.2.3.N2.2.26c.bin for boot variable "system"
[#####] 100% -- SUCCESS

Verifying image type.
[#####] 100% -- SUCCESS

Extracting "system" version from image bootflash:/installables/switch/ucs-6100-k9-system.5.2.3.N2.2.26c.bin.
[#####] 100% -- SUCCESS

Extracting "kickstart" version from image bootflash:/installables/switch/ucs-6100-k9-kickstart.5.2.3.N2.2.26c.bin.
[#####] 100% -- SUCCESS

Extracting "bios" version from image bootflash:/installables/switch/ucs-6100-k9-system.5.2.3.N2.2.26c.bin.
[#####] 100% -- SUCCESS

Performing module support checks.
[#####] 100% -- SUCCESS

Notifying services about system upgrade.
```

ةلص تاذا تامولعم

- [تادنتس مل او ينقتلا معدلا - Cisco Systems](#)

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نء مء دختسمل معد وء مء مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظءالم ءرء. ةصاءل مءءب
Cisco ءلءت. فرءم مچرت مءمءق ءلءل ةل فاءءءل ةمچرتل عم لاعل او
لءل أمءءء ءوچرلاب ءصوء وءءامچرتل هذه ةقءن ءءءل وءءل سمل
Systems (رفوءم طبارل) ءلصل ءل ءلءلءل دن تسمل