

ةلسلس ىلع ديدجلا فيرعتلا فلم نيوكت نم (IP) تنرتنإلا لوكوتورب فتاوه نم 7800 8800 ةلسلس وأ Cisco

فدهلا

اهي مدختس مل تامدخلا ريفوتب اهل حامس لل اهزيهجتو ةكبش دادعإ ةيلمع وه دادمإلا وهو. ةكبشلا رصانع ىلإ ءالمعلا تامدخ دادمإ ىلإ صاخ لكش ب ةكبشلا دادمإ ريشي يزكرم مداخ نم هب ةصاخلا نيوكتلا تامولعم بحسب تنرتنإلا لوكوتورب فتاهل حمسي نم الءب دحاو يزكرم عقوم نم اعلم فتاوهلا ةئيهت نكمي، ةقيرطلا هذهبو. ايئاقلت يدرف لكش ب هدادعإو فتاه لك ىلإ باهذلا.

ةصاخلا "ريفوتلا" بيبوتلا ةمالع ي ف فيرعتلا فلم ةدعاق تاداعإ ةحفص حيتت فيرعت فلم عم IP فتاه ةنمازم ةداعإ مدختس ملل 8800 وأ 7800 ةلسلسلا نم IP فتاوهب يسايق نيوكت ىلإ ةيدرفل IP فتاوه ةنمازمل ةنمازمل ةداعإ رايخ مادختسا متي. ديعب دعب ن IP فتاه ي رفوتم.

فتاه ىلع فيرعتلا فلم دعاق نيوكت ةيفيكي لوح تاميلعت ةلاقملا هذه كل مدقت Cisco IP Phone 7800 Series IP Phone أو 8800 تنرتنإلا لوكوتورب.

لومخلا ةلاح ي ف نوكي ام دنع طقف فتاهلا طبض ةداعإ متت: ةطحال

قبيطتلل ةلباقلا ةزهجالا

- 7800 ةلسلسلا
- 8800 ةلسلسلا

جماربال رادصا

- 10.4

ديج فيصوت ليكشت

رتخاو بيولا ىلإ ةدنتسمل ةدعاسملا ةادألا ىلإ لوخدلا ليحستب مق 1. ةوطخلا ةمدقتم تاراخي > لوؤسملا لوخد ليحست

Admin Login basic | advanced

نيوكتلا فيرعت فلم > دادمإ > توصل رتخأ. 2. ةوطخلا

Info	Voice	Call History	Personal Directory							
System	SIP	Provisioning	Regional	Phone	User	Ext1	Ext2	Ext3	Ext4	Ext5

Configuration Profile	
Provision Enable:	Yes
Resync Random Delay:	2
Resync At Random Delay:	600
Resync Error Retry Delay:	3600
Resync From SIP:	Yes
Resync Trigger 1:	
Resync Trigger 2:	
Resync Fails On FNF:	Yes
Profile Rule:	/SPSN.xml
Profile Rule B:	
Profile Rule C:	
Profile Rule D:	
Resync DHCP Option To Use:	160,159,66,150
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR
User Configurable Resync:	Yes

في مكحلت كل حيتي اذهو. ريفوتل ني كمت ةلدسنملا ةمئاقلا نم معن رتخأ. 3 ةوطخل متي و. ةتباتل جماربل ةيقرت تاءارج نع لقتسم لكشب ةنمازملا ةداع تاءارج عيجم تافلما نيخشب دعب نع دادعلا حمسي. دعب نع دادعلا ني كمتل اضيأ اذه مادختسا معن يه ةيضارتفالا ةميقل. بيوم داخ ي اتقوم اهليغشت يراجلا

Configuration Profile	
Provision Enable:	Yes
Resync Random Delay:	Yes
Resync At Random Delay:	No
Resync Error Retry Delay:	3600
Resync From SIP:	Yes
Resync Trigger 1:	
Resync Trigger 2:	
Resync Fails On FNF:	Yes
Profile Rule:	/SPSN.xml
Profile Rule B:	
Profile Rule C:	
Profile Rule D:	
Resync DHCP Option To Use:	160,159,66,150
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR
User Configurable Resync:	Yes

ةلدسنملا ةمئاقلا ي "نييعة ةداع" ةلدسنملا ةمئاقلا نم معن رتخأ. 4 ةوطخل اناثتساب ليغشت ةداع ةي لمع لك دعب ليغشت ةداع ةي لمع ليغشت يلا اذه يدوي جماربل تايقرتو تامل عمل تاثير دحت اه ي ببستت ي تال ليغشتلا ةداع تاي لمع معن يه ةيضارتفالا ةميقل. ةتباتل

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	2	Resync At (HHmm):	Yes
Resync At Random Delay:	600	Resync Periodic:	No
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:			
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/\$PSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

ةرتفلا يه هذه ريخأتلا تقو لخدا، ةنمازما ةداعلا يئوشعلا ريخأتلا لقح ي 5 ةوطخلا مداخل دئازلا لمحلل عنمي امم، دادعلا مداخل لصت ي نأ لقب زاهجلا اهرطت ني يتلا ةينمزللا نيوكتللاب مايقلل او تقولا سفن ي ف زاهجلا ليغشت زهجالا عيمج ةلواحم دنع دادملا زاهجلا ليغشت دنع يلوألا نيوكتلل تقوي ف الا ريخأتلا اذه مادختسا نكمي الو. يلوألا 40 لى 2 ةيضارتفالا ةميقللا ريشت. ةيناث 20 يه ةملعملل هذه ةدحو. هنييعة ةداعلا وأ 0 لى ةملعملل هذه نييعة مت اذا ةزيملا هذه ليطعت متي. ةيناث

3. يه ةمدختسملل ةميقللا، لاثملا ليلبس لىع: ةظحالم

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	
Resync At Random Delay:	600	Resync Periodic:	3600
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:			
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/\$PSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

(hhmm) ةعاس 24 قيسنتب تقولا لخدا، (HHmm) نم ةنمازما ةداعلا لقحلا ي 6 ةوطخلا. ةنمازما ةداعلا IP فتاه ةعبتس يذلا تقولا وه اذه

1800 مادختسا متي، لاثملا ليلبس لىع: ةظحالم

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3601	Forced Resync Delay:	14401
Resync From SIP:	Yes		
Resync Trigger 1:			
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/SPSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

م تيس (ي ناو ث ل اب) اتقو ل خ دأ ، يئ اوش ع ل ري خ أ ت ل ا دن ع ن م ا ز م ل ا ة د ا ع ل ق ح ي ف 7 . ة و ط خ ل ا ت ا ب ل ط ن ي ب م د ا خ ل ا ي ف م د ا ص ت د ج و ي ال ي ت ح ة يئ اوش ع ة ق ي ر ط ب IP ف ت ا ه ن م ا ز م ة د ا ع ل (ق ئ ا ق د 10) ة ي ن ا ث 600 وه ي ض ا ر ت ف ا ل ل ا خ د ا ل ا . ة د د ع ت م ل ا IP ف ت ا وه ن م ن م ا ز م ل ا ة د ا ع ل

666 ي ه ة ل خ د م ل ا ة م ي ق ل ل ا ، ل ا ث م ل ا ل ي ب س ي ل ع : ة ط ح ا ل م

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3600
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:			
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/SPSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

ة د ا ع ل ب ز ا ه ج ل ا م و ق ي (ي ناو ث ل اب) اتقو ل خ دأ ، ة ي ر و د ل ا ن م ا ز م ل ا ة د ا ع ل ق ح ي ف 8 . ة و ط خ ل ا ل و ا د ع ب ط ق ف ا ط ش ن ا ذ ه ن م ا ز م ل ا ة د ا ع ل ق و م ن و ك ي . د ا د ع ل ا م د ا خ ع م ي ر و د ل ل ك ش ب ن م ا ز م ل ا 0 . ي ل ا ة م ل ع م ل ا ن ي ع ت ب م ق ، ة ي ر و د ل ا ن م ا ز م ل ا ة د ا ع ل ع ن م ل . م د ا خ ل ا ع م ح ج ا ن ن م ا ز م ل ا ة ي ن ا ث 3600 ي ه ي ض ا ر ت ف ا ل ا ة م ي ق ل ل ا

3665 ي ه ة ل خ د م ل ا ة م ي ق ل ل ا ، ل ا ث م ل ا ل ي ب س ي ل ع : ة ط ح ا ل م

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:			
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/SPSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

م تي (ين او ثل اب) اتقو لخدا، ةنما زملا ةداع| أ طخ ةل و احم ةداع| ريخأت لقح في 9. ةوطخل زاوجل او مداخلل نيب ةقبا سلا ةنما زملا ةداع| ةي لمع تلشف اذا ةنما زملا ةداع| ءارج ه دعب ةداع| ةقبا سلا ةل و احم ل لشف ةلا ح في ه ل يغش ت م تي أ طخ ةل و احم ةداع| تقوم دجوي لىل ع زاوجل ل و احم ل س ف، 0 لىل ع ةمي قلا هذه ني عت مت اذا . ري ف وتل م داخ عم ةنما زملا ةي ناث 3600 يه ةي ضار ت فال ةمي قلا . ةل شاف ةل و احم دعب م داخ ل عم ةنما زملا ةداع| روفل

3601 يه ةل خ دمل ةمي قلا ، ل ا ث م ل ا ذه في : ةظ ح الم

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3601	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:			
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/SPSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

ري شي . (ين او ثل اب) ريخأت تقو لخدا ، ري ر ا ب ج ا ل ةنما زملا ةداع| ريخأت لقح في 10. ةوطخل ةداع| ةل و احم ل بق ةي فتاهل IP ةم د خ زا ه ر ط ت ن ي ي ذل ري خأت ل ل ي ص ق ا ل د ح ل ا ل ا ذه ك ل ذل ، ة ط ش ن ف ت ا ه ل ط و ط خ ن م ي ا ت ن ا ك اذا ةنما زملا ةداع| ب زاوجل م و ق ي ن ل . ةنما زملا ةنما زملا ةداع| ةل و احم ل بق ةل م ا خ ف ت ا ه ل ط و ط خ ح ب ص ت ا ت ح تقو ل ا ذه زاوجل ر ط ت ن ي س تقو ل ا د ا د ع ف ق و ت ي . ع ا ط ق ن ا ي ا ن و د ت ا م ل ا ك م ل ا ء ا ر ج م د خ ت س م ل ا لىل ع ل ه س ي ا ذه و . م داخ ل عم لىل ع تقو م ل ف ق و ت ي ا ت ح ر ط ت ن ي و ةل م ا خ ف ت ا ه ل ط و ط خ ح ب ص ت ا م د ن ع زاوجل ا ي ف د و ج و م ل ا يه ةي ضار ت فال ةمي قلا . ن ي ح ل ا ك ل ذ ا ت ح ةنما زملا ةداع| ت ا ل و احم ل ل ي ج ا ت م تي . ر ف ص ل ا ةي ن ا ث 14400

14401 يه ةل خ دمل ةمي قلا ، ل ا ث م ل ا ل ي ب س لىل ع : ةظ ح الم

Info	Voice	Call History	Personal Directory
System	SIP	Provisioning	Regional
Phone	User	Ext1	Ext2
Ext3	Ext4	Ext5	

Configuration Profile	
Provision Enable:	Yes
Resync Random Delay:	3
Resync At Random Delay:	666
Resync Error Retry Delay:	3601
Resync From SIP:	Yes
Resync Trigger 1:	
Resync Trigger 2:	
Resync Fails On FNF:	Yes
Profile Rule:	/SPSN.xml
Profile Rule B:	
Profile Rule C:	
Profile Rule D:	
Resync DHCP Option To Use:	160,159,66,150
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR
User Configurable Resync:	Yes
Resync On Reset:	Yes
Resync At (HHmm):	1800
Resync Periodic:	3665
Forced Resync Delay:	14401

حما سي اذهو SIP نم ResetYnc ةلدسننملا ةمئاقلا نم Yesis راي تخا نم دكا ت 11 ةوطخلا م عن يه ةيضا رتفالا ةمي قلا SIP NOTIFY ةلاسر لالخ نم "ةنمازمل اءاعا" ليغشتب

Configuration Profile	
Provision Enable:	Yes
Resync Random Delay:	3
Resync At Random Delay:	666
Resync Error Retry Delay:	3601
Resync From SIP:	Yes
Resync Trigger 1:	Yes
Resync Trigger 2:	No
Resync Fails On FNF:	Yes
Profile Rule:	/SPSN.xml
Profile Rule B:	
Profile Rule C:	
Profile Rule D:	
Resync DHCP Option To Use:	160,159,66,150
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR
User Configurable Resync:	Yes
Resync On Reset:	Yes
Resync At (HHmm):	1800
Resync Periodic:	3665
Forced Resync Delay:	14401

هيف بجي يذلا تقولا نع يطرش ريبت لخدأ، Resync Trigger 1 لقح يف 12 ةوطخلا ةي قطنملا ةلءاعملا موقت امدنع ةنمازمل اءاعا ليغشت متي . ةنمازمل اءاعا ليغشت نوكتي نا بجي . ةغراف ةيضا رتفالا ةمي قلا TRUE ةمي ق سايقب تامل عمل اذه يف http://phone-ip-addr/admin/resync?protocol://server-name[:port]/profile-pathName ةيالاتل اءاعا صلا وا قيسنتلاب ةنمازمل اءاعا لغشم

هه ةغاي صلا نوكت ، لاثملا لابس يلع : ةظحالم
<http://10.74.121.56/admin/resync?tftp://10.74.121.56:69/8861conf.cfg>

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3601	Forced Resync Delay:	14401
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?ftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/\$PSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

يذلل تقولا نع اطورش م اري بعت لخدأ 2، ResetYnc ل غشم لقح يف (يراي تخا). 13 ةوطخلا ل داعم الم موقت ام دنع ةنمازم الم ةداع ل يغشت متي . ةنمازم الم ةداع ل يغشت هي ف بجي ة غراف ة يضارت فال ة ميق الل . TRUE ة ميق سايقب تامل عمل الم هذه يف ةي قطن الم

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3601	Forced Resync Delay:	14401
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?ftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	/\$PSN.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

ةلدسنم الم ةمئاقلا يف Resync نم هراي تخا مت يذلل Yesis لش ف نم دكأت . 14 ةوطخلا نم "هيلع روث عمل ريغ فللم" ةباجتسا تناك اذا مدختس الم الم اعلا اذله يدؤيس . FNF ةنمازم الم ةداع ل موق . ةلشاف وا ةحجان ةنمازم ةداع ل موق رفوت ري فوت الم مداخل م . م عن يه ة يضارت فال ة ميق الل . أطخلا ةنمازم ةداع ل تقوم طيشنتب ةلشاف الل

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3601	Forced Resync Delay:	14401
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?tftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	Yes		
Profile Rule B:	No		
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

يذلل في رعتال فلمل يصنللا جامانربلل لخدأ، في رعتال فلمل دعاق ل قحلال في 15 ةوطخلل فلمل دعاوقل ةوطخلل هذه ررك . ط بترملل في رعتال فلمل طبر ناونعو لوكوتوربلا فرعي وه بارعالل . /spa\$PSN.cfg يه ةيضا رتفالال ةم يقلا . D و C و B في رعتال protocol://server[:port]/profile_pathname.

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	3	Resync At (HHmm):	1800
Resync At Random Delay:	666	Resync Periodic:	3665
Resync Error Retry Delay:	3601	Forced Resync Delay:	14401
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?tftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

مظحال م: http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml مادختسا متي، لاثملا ليل بس يلعل . لوصحلل متي ويضا رتفالل TFTP ذخأ متي هنإف، رمالا اذه دي دحت متي مل اذإ . 66 (DHCP) فيض ملل كي ماني دلل نيوكتلل لوكوتورب رايخ نم TFTP مداخ ناونع يلعل (FQDN) لمكلا ل لهؤملا لاجملا مسا وإ IP ناونع يلعل اما ةراشلال نكمي، طبرلا ناونع في حمسي يذلل \$MA لثم وركام تادحو يلعل فلمل مسا يوتحي نا نكمي . مداخلاب صاخلا زاهجلاب صاخلا (MAC) طئاسولا يلعل لوصولا في مكحتل ناونع عيسوتب .

D لى B نم في رعتال فلمل دعاوقل في رعتال فلمل ةي صنللا جاماربلل ذي فننت متي ةي لمعل ليغشت ةلاحي في . يساساللا في رعتال فلمل دعاق ذي فننت مامت اذعب بي رتربلاب فلمل دعاوقل ذي فننتو باسح رمتسي، ةغراف في رعتال فلمل دعاق تناك و ةنمازم ةداعل D لى B نم ةي قبتملل في رعتال .

ةداعتسال ل قحلال مادختسا ل Resync DHCP رايخ في DHCP تاراخي لخدأ . 16 ةوطخلل 150 و 66 و 159 و 160 يه ةيضا رتفالال ميقلا . في رعتال فلمل و تباثللا جامانربلل

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	2	Resync At (HHmm):	1800
Resync At Random Delay:	600	Resync Periodic:	3600
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?://ftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

لاسرا م تي. لجسلا ةنمازم ةداع| بلط ةلاسرا لخدأ *msg* لجسلا بلط لقح في 17. ةوطخلا
 بلطي — \$pn\$mac ةمقلا. ةنمازما ةداع| ةلواجم ةيادب في syslog مداخل ةلاسرا ل هذه
 ةنمازم \$scheme://\$servip:\$port\$path.

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	2	Resync At (HHmm):	1800
Resync At Random Delay:	600	Resync Periodic:	3600
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?://ftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	SPN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	SPN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	SPN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

يقلت م تي. لجسلا طبض ةداع| حاجن ةلاسرا لخدأ *Log Success MSG* لقح في 18. ةوطخلا
 ةنمازم ةداع| — \$pn\$mac ةمقلا. حاجن ةنمازما ةداع| ةلواجم مامت دن ةلاسرا ل هذه
 ةنمازم \$scheme://\$servip:\$port\$path.

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	2	Resync At (HHmm):	1800
Resync At Random Delay:	600	Resync Periodic:	3600
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?://tftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

متي لجسلة نمازمة داعل لشف لاسرر لخدأ، *msg* لجسلة لشف لقح في 19 ةوطخل داعل ت لشف — \$pn\$mac ةميقلا. ةنمازمة داعل ةلواحم لشف دنع لاسرلة هذه يقلت ةنمازمة: \$err.

Configuration Profile			
Provision Enable:	Yes	Resync On Reset:	Yes
Resync Random Delay:	2	Resync At (HHmm):	1800
Resync At Random Delay:	600	Resync Periodic:	3600
Resync Error Retry Delay:	3600	Forced Resync Delay:	14400
Resync From SIP:	Yes		
Resync Trigger 1:	http://10.74.121.56/admin/resync?://tftp://10.74.121.56:69/8861conf.cfg		
Resync Trigger 2:			
Resync Fails On FNF:	Yes		
Profile Rule:	http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml		
Profile Rule B:			
Profile Rule C:			
Profile Rule D:			
Resync DHCP Option To Use:	160,159,66,150		
Log Request Msg:	\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH		
Log Success Msg:	\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR		
Log Failure Msg:	\$PN \$MAC -- %s failed: \$ERR		
User Configurable Resync:	Yes		

ةلباقلا ةنمازمة داعل ةلدسنملا ةمئاقلا نم مرن راي تخا نم دكأ 20 ةوطخل مرن يه ةيضارتفالا ةميقلا. مدختسملاب ةصاخلا نيوكتلل

Configuration Profile	
Provision Enable:	<input type="checkbox"/> Yes
Resync Random Delay:	<input type="text" value="2"/>
Resync At Random Delay:	<input type="text" value="600"/>
Resync Error Retry Delay:	<input type="text" value="3600"/>
Resync From SIP:	<input type="checkbox"/> Yes
Resync Trigger 1:	<input type="text" value="http://10.74.121.56/admin/resync?ftp://10.74.121.56:69/8861conf.cfg"/>
Resync Trigger 2:	<input type="text"/>
Resync Fails On FNF:	<input type="checkbox"/> Yes
Profile Rule:	<input type="text" value="http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml"/>
Profile Rule B:	<input type="text"/>
Profile Rule C:	<input type="text"/>
Profile Rule D:	<input type="text"/>
Resync DHCP Option To Use:	<input type="text" value="160,159,66,150"/>
Log Request Msg:	<input type="text" value="\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH"/>
Log Success Msg:	<input type="text" value="\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR"/>
Log Failure Msg:	<input type="text" value="\$PN \$MAC -- %s failed: \$ERR"/>
User Configurable Resync:	<input type="checkbox"/> Yes
Firmware Upgrade	
Upgrade Enable:	<input type="checkbox"/> Yes
Upgrade Error Retry Delay:	<input type="text" value="3600"/>

تاريي غتال نيوك ت م .تاريي غتال عي مج لاسرا قوف رقنا .21 ةوطخال

Resync At Random Delay:	<input type="text" value="000"/>	Resync Periodic:	<input type="text" value="0000"/>
Resync Error Retry Delay:	<input type="text" value="3600"/>	Forced Resync Delay:	<input type="text" value="14400"/>
Resync From SIP:	<input type="checkbox"/> Yes		
Resync Trigger 1:	<input type="text" value="http://10.74.121.56/admin/resync?ftp://10.74.121.56:69/8861conf.cfg"/>		
Resync Trigger 2:	<input type="text"/>		
Resync Fails On FNF:	<input type="checkbox"/> Yes		
Profile Rule:	<input type="text" value="http://10.74.121.56/dms/CP-8861-3PCC/8861-3PCC.xml"/>		
Profile Rule B:	<input type="text"/>		
Profile Rule C:	<input type="text"/>		
Profile Rule D:	<input type="text"/>		
Resync DHCP Option To Use:	<input type="text" value="160,159,66,150"/>		
Log Request Msg:	<input type="text" value="\$PN \$MAC -- Requesting %s \$SCHEME://\$SERVIP:\$PORT\$PATH"/>		
Log Success Msg:	<input type="text" value="\$PN \$MAC -- Successful %s \$SCHEME://\$SERVIP:\$PORT\$PATH -- \$ERR"/>		
Log Failure Msg:	<input type="text" value="\$PN \$MAC -- %s failed: \$ERR"/>		
User Configurable Resync:	<input type="checkbox"/> Yes		
Firmware Upgrade			
Upgrade Enable:	<input type="checkbox"/> Yes		
Upgrade Error Retry Delay:	<input type="text" value="3600"/>		
<input type="button" value="Undo All Changes"/> <input type="button" value="Submit All Changes"/>			

وأ Cisco IP 7800 فتاه ىلع ديدج فيرعت فلم نيوك ت م نألآ تي هت نا دق نوكت نأ بجي ة مظنألآ ددعت م 8800 Series .

ةمچرتل هذه ل و ح

ةلأل تاي نقتل ن م ة و مچ م ادخت ساب دن تسم ل ا اذ ه Cisco ت مچرت
م ل ا ل ا ا ن ا ع مچ ي ف ن ي م د خ ت س م ل ل م ع د ي و ت ح م م ي د ق ت ل ة ي ر ش ب ل و
ا م ك ة ق ي ق د ن و ك ت ن ل ة ل ا ة مچرت ل ض ف ا ن ا ة ظ ح ا ل م ي ج ر ي . ة ص ا خ ل ا م ه ت غ ل ب
Cisco ي ل خ ت . ف ر ت ح م مچرت م ا ه م د ق ي ي ت ل ا ة ي ف ا ر ت ح ا ل ا ة مچرت ل ا ع م ل ا ح ل ا و ه
ي ل ا م ا ة ا د ع و ج ر ل ا ب ي ص و ت و ت ا مچرت ل ا ه ذ ه ة ق د ن ع ا ه ت ي ل و ئ س م Cisco
Systems (ر ف و ت م ط ب ا ر ل ا) ي ل ص ا ل ا ي ز ي ل ج ن ا ل ا دن ت س م ل ا