

يكلسالاللا عيزوتاللا مازن نيوكت ةيفيك RV130W ىلع (WDS)

فدهلا

لوصولا طاقنل يكلسالاللا ليصوتاللا حيتي مازن وه (WDS) يكلسالاللا عيزوتاللا مازن لوصولا طاقن مادختساب ةيكلسالاللا ةكبشاللا عيسوتب WDS حمسي. ام ةكبش ي (AP) نيوكت بجي، WDS طابترلا عاشنال. اهلصول يكلسالاللا ساسا زاهج ىللا ةجالحا نود ةددعتم ةانقلاو ةيكلسالاللا ةكبشاللا عضو سفن ي ف دعب نع WDS ي ف نيخاللا عارظنلاو زاهجال ل تلحأ. (WEP وأ عيشال) ريفشتاللا عاونأو يكلسالاللا قاطنلا ديدحتو ةيكلسالاللا [RV130W ىلع دادعلا ةيلمع ساسا يكلسالاللا لكشي](#)، ةمولعم ريثك

عضو وأ Bridge عضو ي ف WDS نيوكت كنكمي، ةيجذومنلا ةريغصلاللا تاكشراللا ةئيبي ي ف ةراشا عيسوتب ىخاللا لوصولا طاقن موقت نأ ديرت تنك اذا رسجاللا عضو ديفي. رركم نأ ديرت تنك اذا اديفم رركم عضو نوكي. كرتشم طبارك لمعت يتلاو، كزاهجل ةكبشاللا ليصوت مادختساب ىخاللا لوصولا طاقنل ةكبشاللا ةراشا رركم كزاهج لمعي يكلسال.

RV130W ىلع يكلسالاللا عيزوتاللا مازن نيوكت ةيفيك حيصوت وه دنتسملا اذه نم فدهلا.

قيبطتلل ةلباقلا ةزهجالا

• RV130W

جماربلا رادصا

• v1.0.1.3

يكلسالاللا عيزوتاللا مازن نيوكت

رسجاللا عضو ي ف WDS نيوكت

م تي. WDS > يكلسالاللا رتخاو بيولا نيوكتل ةدعاسملا ةادألا ىللا لوخدلا لجس. 1. ةوطخلا WDS: ةحفص حتف

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode

WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1

(Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Show Available Networks

MAC

Save

Cancel

WDS. ل ق ح ي ف ر ا ي ت خ ا ل ا ة ن ا خ د د ح ، WDS ن ي ك م ت ل . 2 ة و ط خ ل ا

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☐ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☒ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save Cancel

نېوكت مې امدن ع. WDS Bridge يكلسال رزلا قوف رقا ، عضولا لقح ي ف. 3 ؤوطالا
 مې تال لوصول ؤطقن نې عې WDS نإف ، رسچال عضولا هجوملاب ؤصاخال WDS
 ؤدعتم لوصول طاقن نې ب كرتشم طابتراك اهنېوكت

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☒ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☐ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save Cancel

ةطقنل MAC ناوع ،ديعلل اكلسالل رسجلل MAC ناوع مسق ف 4. ةوطخ لخد فافاضا لوصو طاقن نيوكت اضيأ كنكم ف 1. MAC لقح ف رسجك مدختستل لوصو 4. MAC و، 3. MAC و، 2. Mac لوقح ف روسجك اهمادختسال

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☒ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☐ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

تاري غتال ظفحل ظفح قوف رقنا 5 ةوطخل

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☒ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☐ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

يكلسال رركم عضو في WDS نيوكت

م تي. WDS > يكلسال رتخاو بيول نيوكتل دءاسملا ءاأالا لى لوخذل لءس. 1 ءوطءلا
WDS ءءصءء

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode

WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1

(Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

WDS Repeater

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Show Available Networks

MAC

Save

Cancel

WDS. ل ق ح ي ف ر ا ي ت خ ا ل ا ة ن ا خ د د ح ، WDS ن ي ك م ت ل 2. ة و ط خ ل ا

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS

Mode

☒

☐

WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1

(Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☒

☐

WDS Repeater

☐

☒

Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒

☐

Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Show Available Networks

MAC

Save

Cancel

هجوم لاب ةصاخلا WDS نيوكت دنع .WDS رركم رز قوف رقنا ، عضولا لقح يف 3. ةوطخلا طاقنب ليصوتلل اهنوكت مت يتلا لوصولا ةطقن نيغي WDS ناف ،رركم عضو ىلا تاراشلا راركت لالخ نم (LAN) ةيلحمل اكبشلاب يكللس لاصتا نودب ةددعتم لوصو يكللساللا لاصتالا مادختساب

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☐ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☒ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

يلع ةحاتم ال تارايلخا دي دحت متي . WDS رركم عضول ب و غرم ال رايلخا رتخأ 4. ةوطخل ال
يلالات وحنل:

لوصو طاقن م ادختسإ متي — رركم ةطساوب ةيكلسلال ةراشإل راركتب حامسل .
ةيكلسلال زاهجلا ةراشإ راركتل ةنيعم

ةراشإل راركتل زاهجلا مدختسي — دعب نع لوصولا ةطقنل ةيكلسلال ةراشإل راركت .
يطختلاب مقف ،رايلخا اذه دي دحتب تمق اذا . يرخأ ةيكلسلال لوصو ةطقنل ةيكلسلال
6. ةوطخل ال

4، ةوطخل ال يف رركم ةطساوب ةيكلسلال ةراشإل راركتب حامسل الترتخأ اذا . 5. ةوطخل
طاقن نيوكت كنكمي . 1. MAC لقح يف رركمك مدختستل لوصو ةطقنل MAC ناو نع لخدأ
يطختل . 4. MAC و ، 3. MAC و ، 2. MAC لوقح يف راركت زهجاك اهم ادختسال ةيفاضل لوصو
9. ةوطخل ال

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☐ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☒ WDS Repeater

☒ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☐ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

Save Cancel

رقنا 4، ةوطخال ي ف دعب نع لوصو ةطقنل ةيكلسال ةراشا راركت ترتخأ اذا 6. ةوطخال
ةحاتملا ةيكلسال لوصولا طاقن ىلع روثلل ةحاتملا تاكبشل راهاظ قوف
اهب لاصتال

WDS

WDS MAC Address: 3C:CE:73:8E:04:1E

WDS ☒

Mode ☐ WDS Bridge

Remote Wireless Bridge's MAC Address

MAC 1 (Hint: 00:11:22:33:44:55 or 001122334455)

MAC 2

MAC 3

MAC 4

☒ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

MAC

قحاتملا تاكلشل لودج رهظي

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Available Networks Table

	Network Name (SSID)	Channel	Security	Signal	MAC Address
☐	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
☐	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
☐	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
☐	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
☐	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
☐	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
☐	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

Connect

Refresh

MAC

لوصول ةطقن ديدحتل ةكبشلل مسال ةبوغرملا رايتخال ةناخ ددح 7 ةوطخال
اهب ةصاخلا ةراشلا زاهجلا رركي نأ ديرت يتلا قحاتملا ةيكللل

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
☒	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
☐	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
☐	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
☐	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
☐	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
☐	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
☐	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

لقح إلى ددحمال لوصولاً ةطقنل MAC ناوع ةفاضل لاصتاً رزلا قوف رقنا .8 ةوطخل
MAC.

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
☒	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
☐	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
☐	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
☐	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
☐	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
☐	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
☐	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

ةددحمال ةكبشلل MAC ناوعب MAC لقح شي دحت متيس.

☒ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Hide Available Networks

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
☒	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
☐	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
☐	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
☐	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
☐	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
☐	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
☐	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

تادادعإل ظفحل ظفح قوف رقنا 9. ةوطخل

☒ WDS Repeater

☐ Allow wireless signal to be repeated by a repeater

MAC 1

MAC 2

MAC 3

MAC 4

☒ Repeat wireless signal of a remote access point

Remote Access Point's MAC Address (Select one from the site survey list or define your own):

Hide Available Networks

Available Networks Table					
	Network Name (SSID)	Channel	Security	Signal	MAC Address
☒	cisco-3C9B	6	WPA2-Personal	12%	00:01:36:11:3C:9D
☐	ciscosb1	6	Disabled	45%	B8:62:1F:50:07:33
☐	ciscosb1-KK	6	WPA2-Personal	43%	3C:CE:73:8E:00:2C
☐	linksys99	8	WPA2-Personal	48%	00:11:22:22:33:35
☐	1234567890	11	WPA2-Personal	42%	00:01:36:11:3C:9D
☐	SQA-1	10	WPA2-Personal	45%	00:90:A9:F0:23:D3
☐	52237	6	WPA-Personal	16%	00:0F:66:D9:00:7C

MAC

ةمچرتل هذه ل و ح

ةيلآل ا تاي ن ق ت ل ا ن م ة و م ج م ا د خ ت س ا ب د ن ت س م ل ا ا ذ ه Cisco ت م چ ر ت م ل ا ع ل ا ا ح ن ا ع م ج ي ف ن ي م د خ ت س م ل ل م ع د ي و ت ح م م ي د ق ت ل ة ي ر ش ب ل و ا م ك ة ق ي ق د ن و ك ت ن ل ة ي ل آ ة م چ ر ت ل ض ف ا ن ا ة ط ح ا ل م ي ج ر ي . ة ص ا خ ل ا م ه ت غ ل ب Cisco ي ل خ ت . ف ر ت ح م م چ ر ت م ا ه م د ق ي ي ت ل ا ة ي ف ا ر ت ح ا ل ا ة م چ ر ت ل ا ع م ل ا ح ل ا و ه ي ل ا ا م ا د ع و ج ر ل ا ب ي ص و ت و ت ا م چ ر ت ل ا ه ذ ه ة ق د ن ع ا ه ت ي ل و ئ س م Systems (ر ف و ت م ط ب ا ر ل ا) ي ل ص ا ل ا ي ز ي ل ج ن ا ل ا د ن ت س م ل ا