

# RV130W ىل ع SSID فر عمل MAC ةي ف صت

## فدهلا

اهض فر و ا ةي ك ل س ال ل ا ة ك ب ش ل ا ل ا ل و ص و ل ا ب ح ا م س ل ا ب MAC ةي ف صت ك ل ح م س ت ن م ر ث ك ا م ع د ي RV130W ن ا ل ا ر ط ن . ب و ل ط م ل ا ز ا ه ج ل ل ( ة ز ه ا ل ا ) MAC ن ا و ن ع ل ا ا د ا ن ت س ا ه ب ل ا ص ت ا ل ا ن ي ي ك ل س ال ل ا ا ل م ع ل ل ن ك م ي د ي ر ف فر ع م و ه و ، ( SSID ) ة م د خ ة و م ج م فر ع م ن ي و ا ن ع ل ا خ د ا ك ن ك م ي ، ل ا ث م ل ا ل ي ب س ل ع . SSID ل ك ل MAC ةي ف صت ن ي ي ع ت ك ن ك م ي ل ا ل و ص و ل ا ب ة ز ه ا ل ا ك ل ل ط ق ف ح ا م س ل ا و ر ت و ي ب م ك ل ا ة ز ه ا ن م ة و م ج م ل MAC ن ي و ك ت ك ن ك م ي . ل ا ع ف ل ك ش ب ك ت ك ب ش ا ض ع ا ة ر ا د ا ك ن ك م ي ، ك ل ل ذ ل ة ج ي ت ن و . ة ك ب ش ل ا RV130W ل ع ةي ك ل س ال ا ة ك ب ش ل ك ل MAC ةي ف صت

RV130W ل ع MAC ةي ف صت ت ا د ا ع ا ن ي و ك ت ةي ف ي ك ح ر ش و ه د ن ت س م ل ا ا ذ ه ن م ف د ه ل ا

## ق ي ب ط ت ل ل ة ل ب ا ق ل ا ة ز ه ا ل ا

RV130W ز ا ر ط ل ا

## ةي ئ ا ر ج ا ت ا و ط خ

> ي ك ل س ال ر ت خ ا و ب ي و ل ا ن ي و ك ت ل ة د ع ا س م ل ا ة ا د ا ل ا ل ا ل و خ د ل ا ل ي ج س ت ب م ق . 1 ة و ط خ ل ا ةي س ا س ا ل ا ت ا د ا ع ا ل ا ة ح ف ص ر ه ط ت . ةي س ا س ا T ا د ا ع ا :

Basic Settings

Radio:  Enable

Wireless Network Mode: B/G/N-Mixed

Wireless Band Selection:  20MHz  20/40MHz

Wireless Channel: Auto

AP Management VLAN: 1

U-APSD (WMM Power Save):  Enable

	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
											Portal Profile	Enable
<input type="checkbox"/>	<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

Edit Edit Security Mode Edit MAC Filtering Time of Day Access Edit WPS

Save Cancel

ق و ف ر ق ن ا . ه ر ي ر ح ت د ي ر ت ي ذ ل ا ( SSID ) ة م د خ ل ا ة و م ج م فر عمل ر ا ي ت خ ا ل ا ة ن ا خ د د ح . 2 ة و ط خ ل ا SSID فر عمل MAC ةي ف صت ن ي و ك ت ل MAC ةي ف صت ر ي ر ح ت ر ز ل ا

## Basic Settings

Radio:  Enable

Wireless Network Mode: B/G/N-Mixed

Wireless Band Selection:  20MHz  20/40MHz

Wireless Channel: Auto

AP Management VLAN: 1

U-APSD (WMM Power Save):  Enable

Wireless Table												
<input type="checkbox"/>	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	Max Associated clients	WPS	Captive Portal	
											Portal Profile	Enable
<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	SSIDName1	<input checked="" type="checkbox"/>	WPA2-Personal	Disabled	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	16	<input checked="" type="checkbox"/>	cisco1	<input checked="" type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	0	<input type="checkbox"/>	Please select a Profile	<input type="checkbox"/>

MAC: ةي فرصت ةحفص حتفت

## Wireless MAC Filter

SSID: SSIDName1

Wireless MAC Filter:  Enable

### Connection Control

- Prevent PCs listed below from accessing the wireless network.  
 Permit PCs listed below to access the wireless network.

Show Client List

### MAC Address Table

No.	MAC Address	No.	MAC Address	No.	MAC Address
01	<input type="text"/>	23	<input type="text"/>	45	<input type="text"/>
02	<input type="text"/>	24	<input type="text"/>	46	<input type="text"/>
03	<input type="text"/>	25	<input type="text"/>	47	<input type="text"/>
04	<input type="text"/>	26	<input type="text"/>	48	<input type="text"/>
05	<input type="text"/>	27	<input type="text"/>	49	<input type="text"/>
06	<input type="text"/>	28	<input type="text"/>	50	<input type="text"/>
07	<input type="text"/>	29	<input type="text"/>	51	<input type="text"/>
08	<input type="text"/>	30	<input type="text"/>	52	<input type="text"/>
09	<input type="text"/>	31	<input type="text"/>	53	<input type="text"/>
10	<input type="text"/>	32	<input type="text"/>	54	<input type="text"/>
11	<input type="text"/>	33	<input type="text"/>	55	<input type="text"/>
12	<input type="text"/>	34	<input type="text"/>	56	<input type="text"/>
13	<input type="text"/>	35	<input type="text"/>	57	<input type="text"/>
14	<input type="text"/>	36	<input type="text"/>	58	<input type="text"/>
15	<input type="text"/>	37	<input type="text"/>	59	<input type="text"/>
16	<input type="text"/>	38	<input type="text"/>	60	<input type="text"/>
17	<input type="text"/>	39	<input type="text"/>	61	<input type="text"/>
18	<input type="text"/>	40	<input type="text"/>	62	<input type="text"/>
19	<input type="text"/>	41	<input type="text"/>	63	<input type="text"/>
20	<input type="text"/>	42	<input type="text"/>	64	<input type="text"/>
21	<input type="text"/>	43	<input type="text"/>		
22	<input type="text"/>	44	<input type="text"/>		

Save

Cancel

Back

ةيفصت نيكمتل نيكمت رايتخالال ةناخ ددح، يكلسالل MAC حشرم لقق يف 3. ةوطخال  
ددحمل SSID فرعمل MAC.

SSID: SSIDName1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

يذلل لوصولل عونل قباطملا ويدرل رزلرأ، لوصولل في مكحلل لقل في 4. ةوطخلل ةيكلسللل ةكبشلل لىل ديرل.

SSID: SSIDName1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

يلائلل وحنلل لىل ةحاملل تارايخلل ديرل مئ:

لوصولل م MAC نيوانل لوجل في ةجرلمل MAC نيوانل اهل يئلل ةزحلل عئمى — عئم: في ةجرلم ريغ ةزحلل آل نكمي. يضارئل رايخلل وه عئملا. ةيكلسللل ةكبشلل لىل ةكبشلل لىل لوصولل MAC نيوانل لوجل.

MAC نيوانل لوجل في ةجرلمل MAC نيوانل ةدوزمل ةزحلل حمسى — حامسلل: نيوانل لوجل في ةجرلم ريغ ةزحلل آل نكمت نل. ةيكلسللل ةكبشلل لىل لوصولل ةكبشلل لىل لوصولل MAC.

لىل رقلنا، ةيكلسللل ةكبشلل لىل رخلل ةزحلل اورلويبمكلل ةزحلل راهظلل 5. ةوطخلل ةلملل ةمئاق راهظلل.

SSID: SSIDName1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

ءالملل ةمئاق لوجل رهظي:

SSID: SSIDName1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

**You must save before you can edit or delete.**

Client List Table				
Client Name	IP Address	MAC Address	Status	Save to MAC Address Filter List
		55:55:55:55:55:55	Connected	<input type="checkbox"/>
		55:55:55:55:55:5A	Connected	<input type="checkbox"/>

يتلى ؤزه ألى MAC ناونع حشرم ؤمئاق يف ظفح لقح يف راي تخال ؤناخ ددح. 6 ؤوطخال  
 ؤالمعلا ؤمئاق لودج يف اچردم كزاهج نكي مل اذا. MAC نينوانع لودج لى اهتفاضل ديرت  
 ؤيكلسالل ؤكبشلاب هليصوت نم دكأتف.

SSID: SSIDName1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

**You must save before you can edit or delete.**

Client List Table				
Client Name	IP Address	MAC Address	Status	Save to MAC Address Filter List
		55:55:55:55:55:55	Connected	<input checked="" type="checkbox"/>
		55:55:55:55:55:5A	Connected	<input type="checkbox"/>

عالمعلا ؤمئاق لودج يف ؤددحمال ؤزه ألى ؤفاضل MAC لى ؤفاضل قوف رقنا. 7 ؤوطخال  
 لى MAC نينوانع لودج لى

SSID: SSIDName1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

**You must save before you can edit or delete.**

Client List Table				
Client Name	IP Address	MAC Address	Status	Save to MAC Address Filter List
		55:55:55:55:55:55	Connected	<input checked="" type="checkbox"/>
		55:55:55:55:55:5A	Connected	<input type="checkbox"/>

MAC نينوانع لودج لى ؤزه ألى ؤفاضل مت

## Wireless MAC Filter

SSID: SSIDName1

Wireless MAC Filter:  Enable

### Connection Control

- Prevent PCs listed below from accessing the wireless network.  
 Permit PCs listed below to access the wireless network.

Hide Client List

You must save before you can edit or delete.

### Client List Table

Client Name	IP Address	MAC Address	Status	Save to MAC Address Filter List
		55:55:55:55:55	Connected	<input checked="" type="checkbox"/>
		55:55:55:55:55:5A	Connected	<input type="checkbox"/>

Add to MAC

### MAC Address Table

No.	MAC Address	No.	MAC Address	No.	MAC Address
01	55:55:55:55:55:55	23		45	
02		24		46	
03		25		47	
04		26		48	
05		27		49	

ناونع لخدأ، SSID ب ايلاح ةلصتم ريغ ةزهجأ ةفاضل ديتر تنك اذا (يراي تـ|). 8 ةوطخل  
MAC ناونع لودج يف زاهج لاب صاخل ال MAC.

كـتادادعـل ظفـحل ظفـحـلـع رـقـنـا. 9 ةوطخل

06		28		50	
07		29		51	
08		30		52	
09		31		53	
10		32		54	
11		33		55	
12		34		56	
13		35		57	
14		36		58	
15		37		59	
16		38		60	
17		39		61	
18		40		62	
19		41		63	
20		42		64	
21		43			
22		44			

Save

Cancel

Back

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت  
ملاعلاء انء مء مء نمة دختسمل معدى وتحم مء دقتل ةر شبل او  
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب  
Cisco ةللخت. فرتحم مچرت مءم دقء ةللأل ةفارتحال ةمچرتل عم لاعل او  
ىل إأمءءاد ءوچرلاب ةصوءو تامچرتل هذه ةقء نء اهءل ءوئس م Cisco  
Systems (رفوتم طبارل) ةلصلأل ةزىل ءن إل دن تسمل