

NFVIS-for-UC تي بڻت نيزخت ءدحو ودي دحت

تايوت حمل

[ءمدقم](#)

[ءلكشم](#)

[لحل](#)

ءمدقم

اي لاج ءت بڻم ل UC ل NFVIS نيزخت ل ءدحو ودي دحت ل ءبول طم ل تاوطل ل دن تسم ل اذ ءه فص ي اءل ع.

ءلكشم

اءل ع اي لاج ءت بڻم ل UC ل NFVIS نيزخت ل ءدحو ودي دحت مزلي.

لحل

ءصا ل CIMC ل باقم RedFish تا قيب طت ءم رب ءه او مال عت سا لي غش ت ب مق 1. ءوطل ل <https://<CIMC IP Address>/redfish/v1/systems/<CIMC Serial Number>/storage/mraid/Volume> رب ء ءو و م ل ءه اظ ل ص ارق ال تا كرم دء ودي دحت ل في ضم ل اب

جارال ل اثم

```
{
  "@odata.id": "/redfish/v1/Systems/SERIALNUMBER/Storage/MRAID/Volumes",
  "@odata.type": "#VolumeCollection.VolumeCollection",
  "@odata.context": "/redfish/v1/$metadata#VolumeCollection.VolumeCollection",
  "Description": "Collection of Volumes for this system",
  "Name": "Volume Collection",
  "Members@odata.count": 4,
  "Members": [
    {
      "@odata.id": "/redfish/v1/Systems/SERIALNUMBER/Storage/MRAID/Volumes/0"
    },
    {
      "@odata.id": "/redfish/v1/Systems/SERIALNUMBER/Storage/MRAID/Volumes/1"
    }
  ]
}
```



```

        "Cisco": {
            "VolumeAccessPolicy": "ReadWrite",
            "RequestedWriteCachePolicy": "WriteBack",
            "ConfiguredWriteCachePolicy": "WriteBack",
            "VolumeDriveCachePolicy": "NoChange",
            "VolumeReadAheadPolicy": "ReadAhead",
            "VolumeIoPolicy": "DirectIo",
            "VolumeState": "Optimal",
            "AvailableSizeMiBytes": 0,
            "Bootable": true,
            "FullDiskEncryptionCapable": false
        }
    }
}

```

UUID يهو دحاو لكل DurableName عميق، جارخاإلا طاقتل نم 3. ةوطخل

```

        "Identifiers": [
            {
                "DurableNameFormat": "UUID",
                "DurableName": "60027e370b077b003179502a9dc8b57a" <<- This is the UUID you copy
            }
        ]
    }
}

```

ضرع ةمئاق تادحو ذي فننتو NFVIs for-UC ب مكحتلا ةدحو لاصتا و SSH لاصتا 4. ةوطخل
نيزختلا ةدحو ل UUID نيمضت | معدلا

ماسقأ عم زاهجلا لىلع اهيلع NFVIs-for-UC تيبتت متي تلي نيزختلا ةدحو ويوتحت 5. ةوطخل
زاهجلا

اهيلع NFVIs-for-UC ليغشت ماظن تيبتت متي تلي نيزختلا ةدحو جارخا لاثم

```

BE7KH2-NFVIS# support show list-units | include 60027e370b077b003179502a9dc8b57a
dev-disk-by\x2did-scsi\x2d360027e370b077b003179502a9dc8b57a.device          loaded  active
dev-disk-by\x2did-scsi\x2d360027e370b077b003179502a9dc8b57a\x2dpart1.device  loaded  active
dev-disk-by\x2did-scsi\x2d360027e370b077b003179502a9dc8b57a\x2dpart2.device  loaded  active
dev-disk-by\x2did-scsi\x2d360027e370b077b003179502a9dc8b57a\x2dpart3.device  loaded  active
dev-disk-by\x2did-wnn\x2d0x60027e370b077b003179502a9dc8b57a.device          loaded  active
dev-disk-by\x2did-wnn\x2d0x60027e370b077b003179502a9dc8b57a\x2dpart1.device  loaded  active
dev-disk-by\x2did-wnn\x2d0x60027e370b077b003179502a9dc8b57a\x2dpart2.device  loaded  active
dev-disk-by\x2did-wnn\x2d0x60027e370b077b003179502a9dc8b57a\x2dpart3.device  loaded  active

```

NFVIs-for-UC ليغشت ماظن تيبتت متي مل تلي نيزختلا ةدحو جارخا لاثم

```

BE7KH2-NFVIS# support show list-units | include 60027e370b077b0031790987dc596ab8
dev-disk-by\x2did-scsi\x2d360027e370b077b0031790987dc596ab8.device          loaded  active  p1

```

dev-disk-by\x2did-wwn\x2d0x60027e370b077b0031790987dc596ab8.device

Loaded

active

p1

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةل صأل ةل ءل ءن إل دن تسمل