

مادختساب اءءال صءاو POD ءاطءاً فاشكءساً ل رماوأل Kubernetes و CEE OPS-center

ءاءوءءءال

ءمءءمءل

[ل رماوأل مادختساب اءءال صءاو POD ءاطءاً فاشكءساً
CEE OPS-center](#)

[1. k8s CLIs](#)

[2. k8s Log و Full Core](#)

[3. ءءع CEE ءءع TAC-Debug ءاشءا](#)

[4. ءاطءاً ءءءء لءءءء](#)

[5. SMF PODs ءءمءل CEE ءءءال ءءءل ءمء](#)

[6. ءءافارء ءءل لءءءل](#)

ءمءءمءل

CEE OPS-center و Kubernetes ل رماءم PODs ءءءء نأ فءك ءقءء اءه فءء.

ل رماوأل مادختساب اءءال صءاو POD ءاطءاً فاشكءساً Kubernetes و CEE OPS-center

1. k8s CLIs

مءءال ءءءم ءفاك ءرس 1.1

:

```
kubect1 get namespace
```

لءءم:

```
cisco@brusmi-master1:~$ kubect1 get namespace
```

NAME	STATUS	AGE
cee-cee	Active	6d
default	Active	6d
kube-node-lease	Active	6d

kube-public	Active	6d
kube-system	Active	6d
lfs	Active	6d
nginx-ingress	Active	6d
smf-data	Active	6d
smi-certs	Active	6d
smi-vips	Active	6d

1.2: نية عم مساة حاسمب ةصاخلا تامدخل ةفاك درس

:

```
kubectl get svc -n <namespace>
```

الاثم:

```
cisco@brusmi-master1:~$ kubectl get svc -n smf-data
```

NAME	TYPE	CLUSTER-IP	EXTERNAL-IP	PORT(S)
base-entitlement-smf	ClusterIP	10.97.93.253	<none>	8000/TCP
datastore-ep-session	ClusterIP	10.101.15.88	<none>	8882/TCP
datastore-notification-ep	ClusterIP	10.110.182.26	<none>	8890/TCP
datastore-tls-ep-session	ClusterIP	10.110.115.33	<none>	8883/TCP
documentation	ClusterIP	10.110.85.239	<none>	8080/TCP
etcd	ClusterIP	None	<none>	2379/TCP, 7070/TCP
etcd-smf-data-etcd-cluster-0	ClusterIP	10.103.194.229	<none>	2380/TCP, 2379/TCP
grafana-dashboard-app-infra	ClusterIP	10.98.161.155	<none>	9418/TCP
grafana-dashboard-cdl	ClusterIP	10.104.32.111	<none>	9418/TCP
grafana-dashboard-smf	ClusterIP	10.106.64.191	<none>	9418/TCP
gtpc-ep	ClusterIP	10.99.49.25	x.x.x.201	9003/TCP, 8080/TCP
helm-api-smf-data-ops-center	ClusterIP	10.109.206.198	<none>	3000/TCP
kafka	ClusterIP	None	<none>	9092/TCP, 7070/TCP

li-ep	ClusterIP	10.106.134.35	<none>	9003/TCP,8080/TCP
local-ldap-proxy-smf-data-ops-center	ClusterIP	10.99.160.226	<none>	636/TCP,369/TCP
oam-pod	ClusterIP	10.105.223.47	<none>	9008/TCP,7001/TCP,88
ops-center-smf-data-ops-center	ClusterIP	10.103.164.204	<none>	8008/TCP,8080/TCP,20
smart-agent-smf-data-ops-center	ClusterIP	10.97.143.81	<none>	8888/TCP
smf-n10-service	ClusterIP	10.102.197.22	10.10.10.205	8090/TCP
smf-n11-service	ClusterIP	10.108.109.186	10.10.10.203	8090/TCP
smf-n40-service	ClusterIP	10.111.170.158	10.10.10.206	8090/TCP
smf-n7-service	ClusterIP	10.102.140.179	10.10.10.204	8090/TCP
smf-nodemgr	ClusterIP	10.102.68.172	<none>	9003/TCP,8884/TCP,92
smf-protocol	ClusterIP	10.111.219.156	<none>	9003/TCP,8080/TCP
smf-rest-ep	ClusterIP	10.109.189.99	<none>	9003/TCP,8080/TCP,92
smf-sbi-service	ClusterIP	10.105.176.248	10.10.10.201	8090/TCP
smf-service	ClusterIP	10.100.143.237	<none>	9003/TCP,8080/TCP
swift-smf-data-ops-center	ClusterIP	10.98.196.46	<none>	9855/TCP,50055/TCP,5
zookeeper	ClusterIP	None	<none>	2888/TCP,3888/TCP
zookeeper-service	ClusterIP	10.109.109.102	<none>	2181/TCP,7070/TCP

ثمة: نية مساحات ملتاناي لى صوت تاعومجمة فاك درس 1.3

:

```
kubectl get pods -n <namespace>
```

الاثم:

```
cisco@brusmi-master1:~$ kubectl get pods -n smf-data
```

NAME	READY	STATUS	RESTARTS	AGE
api-smf-data-ops-center-57c8f6b4d7-wt66s	1/1	Running	0	6d
base-entitlement-smf-fcdb664d-fkgss	1/1	Running	0	6d
cache-pod-0	1/1	Running	0	6h53m
cache-pod-1	1/1	Running	0	6h53m

cdl-ep-session-c1-dbb5f7874-4gmfr	1/1	Running	0	6h53m
cdl-ep-session-c1-dbb5f7874-5zbqw	1/1	Running	0	6h53m
cdl-index-session-c1-m1-0	1/1	Running	0	6h53m
cdl-slot-session-c1-m1-0	1/1	Running	0	6h53m
documentation-5dc8d5d898-mv6kx	1/1	Running	0	6d
etcd-smf-data-etcd-cluster-0	1/1	Running	0	6h53m
grafana-dashboard-app-infra-5b8dd74bb6-xv1ln	1/1	Running	0	6h53m
grafana-dashboard-cdl-5df868c45c-vbr4r	1/1	Running	0	6h53m
grafana-dashboard-smf-657755b7c8-fvbdtd	1/1	Running	0	6h53m
gtpc-ep-n0-0	1/1	Running	0	6h53m
kafka-0	1/1	Running	0	6h53m
li-ep-n0-0	1/1	Running	0	6h53m
oam-pod-0	1/1	Running	0	6h53m
ops-center-smf-data-ops-center-7fbb97d9c9-tx7qd	5/5	Running	0	6d
smart-agent-smf-data-ops-center-6667dcdd65-2h7nr	0/1	Evicted	0	6d
smart-agent-smf-data-ops-center-6667dcdd65-6wfvq	1/1	Running	0	4d18h
smf-nodemgr-n0-0	1/1	Running	0	6h53m
smf-protocol-n0-0	1/1	Running	0	6h53m
smf-rest-ep-n0-0	1/1	Running	0	6h53m
smf-service-n0-0	1/1	Running	5	6h53m
smf-udp-proxy-0	1/1	Running	0	6h53m
swift-smf-data-ops-center-68bc75bbc7-4zdc7	1/1	Running	0	6d
zookeeper-0	1/1	Running	0	6h53m
zookeeper-1	1/1	Running	0	6h52m
zookeeper-2	1/1	Running	0	6h52m

نيزخالتا داحوو ذفانملاو روصلاو تاقصللملا (POD) ءامسأل ةلماكلا ليصافتلا درس 1.4 (كلذ ريغو ثادحألاو).

:

```
kubectl describe pods <pod_name> -n <namespace>
```

مثال:

```
cisco@brusmi-master1:~$ kubectl describe pods smf-service-n0-0 -n smf-data
```

```
smf-service-n0-0    <<< POD name
smf-data            <<< Namespace
```

2. k8s Log و Full Core

2.1 ددحم ذفنمل ةيواحل مسا ىلع لوصحل:

:

```
kubectl describe pods <pod_name> -n <namespace> | grep Containers -A1
```

مثال:

```
cisco@brusmi-master1:~$ kubectl describe pods smf-service-n0-0 -n smf-data | grep Containers -A1
```

تايواحل:

```
smf-service:
--
ContainersReady    True
PodScheduled       True
```

2.2 Kubernetes ىلع POD ي ف ل طع ة طحال م دنع تال جسلل نع شحبا

:

```
kubectġ get pods -n <namespace> | grep -v Running
```

الاثم:

```
cisco@brusmi-master1:~$ kubectġ get pods -n smf-data | grep -v Running
```

NAME	READY	STATUS	RESTARTS	AGE
smart-agent-smf-data-ops-center-6667dcdd65-2h7nr	0/1	Evicted	0	5d23h
smf-service-n0-0	0/1	CrashLoopBackOff	2	6h12m

:

```
kubectġ logs <pod_name> -c <container_name> -n <namespace>
```

الاثم:

```
cisco@brusmi-master1:~$ kubectġ logs smf-service-n0-0 -c smf-service -n smf-data
```

```
/opt/workspace
```

```
-rwxrwxrwx 1 root root 84180872 Mar 31 06:18 /opt/workspace/smf-service
```

```
Launching: /opt/workspace/tini /opt/workspace/smf-service
```

```
2020-06-09 20:26:16.341043 I | proto: duplicate proto type registered: internalmsg.SessionKey
```

```
2020-06-09 20:26:16.341098 I | proto: duplicate proto type registered: internalmsg.NInternalTxnMsg
```

```
2020-06-09 20:26:16.343170 I | smf-service [INFO] [main.go:18] [smfservice] #####M#####
```

```
2020-06-09 20:26:16.343197 I | smf-service [INFO] [main.go:19] [smfservice] #####
```

```
2020-06-09 20:26:16.343210 I | smf-service [INFO] [main.go:20] [smfservice] SMF-
```

```
2020-06-09 20:26:16.343221 I | smf-service [INFO] [main.go:21] [smfservice] #####
```

```
2020-06-09 20:26:16.343232 I | smf-service [INFO] [main.go:22] [smfservice] #####
```

#####

```
2020/06/09 20:26:16.343 smf-service [DEBUG] [Tracer.go:181] [unknown] Loaded initial tracing configuration
aegerTransportType: , TracerEndpoint: , ServiceName: smf-service, TracerServiceName: , EnableTracePercentage: 100
.
.
```

```
2020/06/09 20:44:28.157 smf-service [DEBUG] [RestRouter.go:24] [infra.rest_server.core] Rest message received
2020/06/09 20:44:28.158 smf-service [DEBUG] [RestRouter.go:43] [infra.rest_server.core] Set Ping as name
2020/06/09 20:44:28.159 smf-service [INFO] [ApplicationEndpoint.go:333] [infra.application.core] Ping successful
2020/06/09 20:44:30.468 smf-service [DEBUG] [MetricsServer_v1.go:305] [infra.application.core] Checkpoint
2020/06/09 20:44:31.158 smf-service [DEBUG] [RestRouter.go:24] [infra.rest_server.core] Rest message received
2020/06/09 20:44:31.158 smf-service [DEBUG] [RestRouter.go:43] [infra.rest_server.core] Set Ping as name
2020/06/09 20:44:31.158 smf-service [INFO] [ApplicationEndpoint.go:333] [infra.application.core] Ping successful
```

```
smf-service-n0-0    <<< POD name
smf-service         <<< Container Name
smf-data            <<< Namespace
```

2.3 زي مرت لا عاشن نم دكأت:

:

```
ls -lrt /var/lib/systemd/coredump/
```

الاثم:

```
cisco@brusmi-master1:~$ ls -lrt /var/lib/systemd/coredump/
```

```
total 0
```



صاخال VM في /var/lib/systemd/coredump/ راسملا في سياسال فلملا عاشن بجي: ةظحال
TAC. تامولعم ةحول لىل عاضيا سياسال رفوتي

3. CEE ىلع TAC-Debug ءاشنإ

3. 1 Master k8s: نم تنرثيإ ةكبش تايلىمع زكرم ىلإ لوخدلا ليحست 1 :

```
cisco@brusmi-master1:~$ kubectl get namespace
```

NAME	STATUS	AGE
cee-cee	Active	5d3h
default	Active	5d3h
kube-node-lease	Active	5d3h
kube-public	Active	5d3h
kube-system	Active	5d3h
lfs	Active	5d3h
nginx-ingress	Active	5d3h
smf-data	Active	5d3h
smi-certs	Active	5d3h
smi-vips	Active	5d3h

```
cisco@brusmi-master1:~$ ssh -p 2024 admin@$(kubectl get svc -n cee-cee | grep ^ops-center | awk '{print
```

```
admin@10.102.44.219's password:
```

```
Welcome to the cee CLI on brusmi/cee
```

```
admin connected from 192.x.0.1 using ssh on ops-center-cee-ops-center-79cf55b49b-6wrh9
```

```
[brusmi/cee] cee#
```



بجي "CEE-CEE" يه CEE مسا ةحاسم نوكت ،اقباس روكدمل لاثملا ي ف :ةطحال م
هبلط ةلاح ي ف مسالا اذه لادبتسإ

3.2 اهادارتسإ مت ي تللا ةيغجرملا عي مجتل ل تافلمل TAC ةمزح فرعم ءاشنإ :

:

```
tac-debug-pkg create from <Start_time> to <End_time>
```


للاام:

```
[brusmi/cee] cee# tac-debug-pkg create from 2020-06-08_14:00:00 to 2020-06-08_15:00:00
```

```
response : Tue Jun 9 00:22:17 UTC 2020 tac-debug pkg ID : 1592948929
```

: pod_name امك وأمسالا ءحاسم لثم ءيفاضا ءيفصت لم اوع نيمضت اضيأ كنكمي

:

```
tac-debug-pkg create from <Start_time> to <End_time> logs-filter { namespace <namespace> pod_name <pod_name>
```

للاام:

```
[brusmi/cee] cee# tac-debug-pkg create from 2020-06-08_14:00:00 to 2020-06-08_15:00:00 logs-filter { namespace <namespace> pod_name <pod_name>
```

```
response : Tue Jun 9 00:28:49 UTC 2020 tac-debug pkg ID : 1591662529
```



وأءعاس) اءاءءال نم ءينمز ءرءل TAC ءمزء فرعم ءاشناب ي صوي: ءظءالم
(ي صقاء ءك نيءعاس).

ءمءء لك ءلاء ضرع 3.3:

```
[brusmi/cee] cee# tac-debug-pkg status
```

```
response : Tue Jun 9 00:28:51 UTC 2020
```

```
Tac id: 1591662529
```

```
Gather core: completed!
```

```
Gather logs: in progress
```

```
Gather metrics: in progress
```

```
Gather stats: completed!
```

```
Gather config: completed!
```

```
[brusmi/cee] cee#
```

```
[brusmi/cee] cee# tac-debug-pkg status
```

```
response : Tue Jun 9 00:43:45 UTC 2020
```

```
No active tac debug session <<< If none active tac debug session is displayed, it means that
```



ءاطخألل احيحصت تافل م ةلازا ءاچرلا ، صرقلا ىلع ةحاسم رفوت مدع ةلاح يف : ةطخال م ةميدقلا.

```
[brusmi/cee] cee# tac-debug-pkg create from 2020-06-08_09:00:00 to 2020-06-08_10:00:00 logs-filter { na
```

```
response : Tue Jun 9 00:45:48 UTC 2020
```

```
Available disk space on node is less than 20 %. Please remove old debug files and retry.
```

```
[brusmi/cee] cee# tac-debug-pkg delete tac-id 1591662529
```

طوق سيسي اقمل احيحصت ل TAC ءاطخألل احيحصت فرعم ءاشن | 3.4 :

```
[nyucs504-cnat/global] cee# tac-debug-pkg create from 2021-02-24_12:30:00 to 2021-02-24_14:30:00 cores  
response : Wed Feb 24 19:39:49 UTC 2021 tac-debug pkg ID : 1614195589
```

4. TAC ءاطخألل احيحصت ليزنت

CEE نم TAC ءاطخألل احيحصت ليزنت ل ةفلتخم تاراخي ةثالث كانه ، ايلاح :

4. 1 SFTP ةمهملا ةيصخشلا نم (ةيسيئرلا ةمهملا ةيصخشلا نم SFTP 1. اتقو قرغتسي كلذ نأ رابتعإل نيعب ذخال عم) (الايوط).

4. 1. 1 tac package ID : ةمجملا تالچسلا ليزنت ل URL ناوع ىلع لصح

:

```
kubectl get ingress -n <namespace> | grep show-tac
```

النتيجة:

```
cisco@brusmi-master1:~$ kubectl get ingress -n cee-cee | grep show-tac
show-tac-manager-ingress          show-tac-manager.cee-cee-smi-show-tac.192.168.208.10.xxx.x
```

4.1.2 show-tac-manager pod نم tac-debug فلم ىلع لصح او طغضا:

أ. Show-tac pod فرعم ىلع لوصح لا.

:

```
kubectl get pods -n <namespace> | grep show-tac
```

النتيجة:

```
cisco@brusmi-master1:~$ kubectl get pods -n cee-cee | grep show-tac
show-tac-manager-85985946f6-bflrc 2/2 Running 0 12d
```

ب. تالجس لا هذه طغضا او show-tac pod، TAC ءاطخأ حي حصت تالجس ي ف EXEC رمأ لي غشت ب مق.

:

```
kubectl exec -it -n <namespace> <pod_name> bash
```

النتيجة:

```
cisco@brusmi-master1:~$ kubectl exec -it -n cee-cee show-tac-manager-85985946f6-bflrc bash
```

Defaulting container name to show-tac-manager.

Use 'kubectl describe pod/show-tac-manager-85985946f6-bflrc -n cee-cee' to see all of the containers in

groups: cannot find name for group ID 101

groups: cannot find name for group ID 190

groups: cannot find name for group ID 303

```
I have no name!@show-tac-manager-85985946f6-bflrc:/show-tac-manager/bin$ cd /home/tac/
```

```

I have no name!@show-tac-manager-85985946f6-bf1rc:/home/tac$ tar -zcvf tac-debug_1591662529.tar.gz 1591
1591662529/
1591662529/config/
1591662529/config/192.x.1.14_configuration.tar.gz.base64
1591662529/stats/
1591662529/stats/Stats_2020-06-08_14-00-00_2020-06-08_15-00-00.tar.gz
1591662529/manifest.json
1591662529/metrics/
1591662529/metrics/Metrics_2020-06-08_14-00-00_2020-06-08_15-00-00.tar.gz
1591662529/web/
1591662529/web/index.html
1591662529/logs/
1591662529/logs/brusmi-master1/
1591662529/logs/brusmi-master1/brusmi-master1_Logs_2020-06-08_14-00-00_2020-06-08_15-00-00.tar.gz
I have no name!@show-tac-manager-85985946f6-bf1rc:/home/tac$ ls
1591662490 1591662529 1592265088 tac-debug_1591662529.tar.gz

```

4.1.3 ةسيئرلا ةمهملا تايصخشلاب tmp صاخلا ليلدلا ىلا فلملا خسن:

:

```
kubectl cp <namespace>/<show-tac_pod_name>:/home/tac/<file_name.tar.gz> /tmp/<file_name.tar.gz>
```

الاثم:

```

cisco@brusmi-master1:~$ kubectl cp cee-cee/show-tac-manager-85985946f6-bf1rc:/home/tac/tac-debug_1591662529.tar.gz /tmp/tee-tee
Defaulting container name to show-tac-manager.
tar: Removing leading `/' from member names
cisco@brusmi-master1:~$ cd /tmp
cisco@brusmi-master1:/tmp$ ls
cee.cfg
tac-debug_1591662529.tar.gz

```

tiller_service_acct.yaml

4. 1. 4 ةيسيئرلا ةمهملا ةيصوصخلا نم SFTP ربع فللم لقن 4.

4.2 wget (MacOS/Ubuntu) مادختساب TAC ءاطخأ حيحصت رمأ ليزنتب مق 4.2.

4.2.1 "k8s get ingress" جارخا نم show-tac طابترلا لعل لوصحلا 4.2.1:

```
cisco@brusmi-master1:~$ kubectl get ingress -n cee-cee | grep show-tac
```

```
show-tac-manager-ingress          show-tac-manager.cee-cee-smi-show-tac.192.168.208.10.xxx.x
```

4.2.2 كيدي لفرطال رتوي بمكلا زاهج نم wget رمالا لخدأ 4.2.2:

```
wget -r -np https://show-tac-manager.cee-cee-smi-show-tac.192.168.208.10.xxx.x/tac/  
<tac-id>/ --no-check-certificate --http-user=<NTID_username>  
--http-password=<NTID_password>
```

5. SMF PODs عيملج CEE نم تالجلسلا عمج 5.

5. 1 Master k8s نم smf-dataOPS زكرم ىلا لوخدلا ليجست 5.1:

```
cisco@brusmi-master1:~$ ssh -p 2024 admin@$(kubectl get svc -n smf-data | grep ^ops-center | awk '{prin
```

```
admin@10.103.164.204's password:
```

```
Welcome to the smf CLI on brusmi/data
```

```
admin connected from 192.x.0.1 using ssh on ops-center-smf-data-ops-center-7fbb97d9c9-tx7qd
```

5.2 "ليجستلا ىوتسم قيبطت" نيكم تديكتأ 5.2:

```
[brusmi/data] smf# show running-config | i logging
```

```
logging level application debug
```

```
logging level transaction debug
```

```
logging level tracing debug
```

```
logging name infra.config.core level application debug
```

```
logging name infra.config.core level transaction debug
logging name infra.config.core level tracing debug
logging name infra.message_log.core level application debug
logging name infra.message_log.core level transaction debug
logging name infra.resource_monitor.core level application off
logging name infra.rest_server.core level application debug
```

5. 3 Master k8s: نم تنرثي ةكبش تايلمع زكرم ىل لوخدلا ليچست

```
cisco@brusmi-master1:~$ ssh -p 2024 admin@$(kubectl get svc -n cee-cee | grep ^ops-center | awk '{print
admin@10.102.44.219's password:

Welcome to the cee CLI on brusmi/cee

admin connected from 192.x.0.1 using ssh on ops-center-cee-ops-center-79cf55b49b-6wrh9

[brusmi/cee] cee#
```



بجي "CEE-CEE" يه CEE مسا ةحاسم نوكت ،اقباس روكذمل لاثمل ي ف :ةطحال م
هبل ط ةلاح ي ف مسالا اذه لادبت سا .

5.4 SMF PODs تالچس عي مج ليذتب مق (smf-nodemgr , smf-protocol smf-rest , smf-service , smf-udp-proxy). تانايبل عي مجت فاقيل ال Ctrl+C مدختساو ،ناوٹ عضبل تالچسلا عي مجتب مق :

```
[brusmi/cee] cee# cluster logs ^smf- -n smf-data

error: current-context must exist in order to minify

Will tail 5 logs...

smf-nodemgr-n0-0
smf-protocol-n0-0
smf-rest-ep-n0-0
smf-service-n0-0
smf-udp-proxy-0

[smf-service-n0-0] 2020/06/08 17:04:57.331 smf-service [DEBUG] [RestRouter.go:24] [infra.rest_server.co
```

```
[smf-service-n0-0] 2020/06/08 17:04:57.331 smf-service [DEBUG] [RestRouter.go:43] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:04:57.331 smf-service [INFO] [ApplicationEndpoint.go:333] [infra.appli
[smf-service-n0-0] 2020/06/08 17:05:00.331 smf-service [DEBUG] [RestRouter.go:24] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:05:00.332 smf-service [DEBUG] [RestRouter.go:43] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:05:00.332 smf-service [INFO] [ApplicationEndpoint.go:333] [infra.appli
[smf-service-n0-0] 2020/06/08 17:05:01.658 smf-service [DEBUG] [MetricsServer_v1.go:305] [infra.applica
[smf-service-n0-0] 2020/06/08 17:05:03.330 smf-service [DEBUG] [RestRouter.go:24] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:05:03.330 smf-service [DEBUG] [RestRouter.go:43] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:05:03.330 smf-service [INFO] [ApplicationEndpoint.go:333] [infra.appli
[smf-service-n0-0] 2020/06/08 17:05:06.330 smf-service [DEBUG] [RestRouter.go:24] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:05:06.330 smf-service [DEBUG] [RestRouter.go:43] [infra.rest_server.co
[smf-service-n0-0] 2020/06/08 17:05:06.330 smf-service [INFO] [ApplicationEndpoint.go:333] [infra.appli
[smf-protocol-n0-0] 2020/06/08 17:04:58.441 smf-protocol [DEBUG] [RestRouter.go:24] [infra.rest_server.
[smf-service-n0-0] 2020/06/08 17:05:06.661 smf-service [DEBUG] [MetricsServer_v1.go:305] [infra.applica
[smf-protocol-n0-0] 2020/06/08 17:04:58.441 smf-protocol [DEBUG] [RestRouter.go:43] [infra.rest_server.
[smf-protocol-n0-0] 2020/06/08 17:04:58.441 smf-protocol [INFO] [ApplicationEndpoint.go:333] [infra.app
[smf-nodemgr-n0-0] 2020/06/08 17:04:57.329 smf-nodemgr [DEBUG] [CacheClient.go:118] [infra.cache_client
```



ةطقن نم تالچسلا عيمجت ىلإ كئجاج ةلاح يف اديدحت رثكأ نوكت نأ كنكمي :ةطحال
ة.ةنيعم لوصو طاقن ةدع وأ ةيواح وأ لوصو

Specific pod

```
[brusmi/cee] cee# cluster logs smf-nodemgr-n0-0 -n smf-data
```

```
[brusmi/cee] cee# cluster logs smf-rest-ep-n0-0 -n smf-data
```

Specific container

```
[brusmi/cee] cee# cluster logs smf-nodemgr -n smf-data
```

```
[brusmi/cee] cee# cluster logs smf-service -n smf-data
```

```
[brusmi/cee] cee# cluster logs zookeeper -n smf-data
```

```
[brusmi/cee] cee# cluster logs smf-rest-ep -n smf-data
```

Multiple pods

```
[brusmi/cee] cee# cluster logs "(smf-service.|smf-rest.|smf-nodemgr.|smf-protocol.|gtpc-ep.|smf-udp-pro
```

انافارغ ىلإ لوصولا - 6

6.1 Grafana ىلإ لوصولل URL ناونع ىل ع ل صحا :

```
cisco@brusmi-master1:~$ kubectl get ingress -n cee-cee | grep grafana
grafana-ingress grafana.192.168.168.208.10.xxx.x 80, 443 6d18h
```

6.2 ىل HTTPS اھب بېو ةحفص حتفا :

<https://grafana.192.168.208.10.xxx.x>

ةمچرتل هذه ل و ح

ةيلآل ا تاي ن ق ت ل ا ن م ة و م ج م ا د خ ت س ا ب د ن ت س م ل ا ا ذ ه Cisco ت م چ ر ت م ل ا ع ل ا ا ح ن ا ع م ج ي ف ن ي م د خ ت س م ل ل م ع د ي و ت ح م م ي د ق ت ل ة ي ر ش ب ل ا و ا م ك ة ق ي ق د ن و ك ت ن ل ة ي ل آ ة م چ ر ت ل ض ف ا ن ا ة ط ح ا ل م ي ج ر ي . ة ص ا خ ل ا م ه ت غ ل ب Cisco ي ل خ ت . ف ر ت ح م م چ ر ت م ا ه م د ق ي ي ت ل ا ة ي ف ا ر ت ح ا ل ا ة م چ ر ت ل ا ع م ل ا ح ل ا و ه ي ل ا ا م ا د ع و ج ر ل ا ب ي ص و ت و ت ا م چ ر ت ل ا ه ذ ه ة ق د ن ع ا ه ت ي ل و ئ س م Systems (ر ف و ت م ط ب ا ر ل ا) ي ل ص ا ل ا ي ز ي ل ج ن ا ل ا د ن ت س م ل ا